



(No Model.)

C. H. WILSON.

SIGNAL AND TEST CIRCUIT FOR TELEPHONE EXCHANGES.

No. 306,669.

Patented Oct. 14, 1884.



Witnesses

William S. Granger

William R. Patterson

Inventor

Charles H. Wilson

By George P. Barton
Attorney

UNITED STATES PATENT OFFICE.

CHARLES H. WILSON, OF CHICAGO, ILLINOIS.

SIGNAL AND TEST CIRCUIT FOR TELEPHONE-EXCHANGES.

SPECIFICATION forming part of Letters Patent No. 306,669, dated October 14, 1884.

Application filed June 20, 1881. (No model.)

To all whom it may concern:

Be it known that I, CHARLES H. WILSON, of Chicago, Illinois, have discovered a certain new and useful Improvement in Multiple Switch-Board Signal and Test Circuits, of which the following is a full, clear, concise, and exact description.

My improvement consists in connecting the testing-battery with points placed near the test-keys, so that when the key is depressed and the battery thrown to line for the purpose of testing, to see if a line wanted is in use at another board, the act of testing will call up the subscriber, provided his line is not in use.

In the drawings, Figure 1 is a front elevation of portions of three multiple switch-boards 1, 2, and 3, showing two subscribers' lines connected with the switches and test-keys and to ground. Figs. 2 and 3 are sections of a full-sized switch and test-key, respectively, upon lines X X and Z Z of Fig. 1.

The switch is of the usual form. The test-key consists of the spring *a*, to which the line of a subscriber is connected, and two contact-points, *b* and *c*. The telephone-line is normally closed through contact-points *b* of the test-keys of a line on the different boards to ground, as indicated in Fig. 1. One pole of the local battery is connected with the contact-points *c* of all the test or signal keys, and signaling-instruments *d* are provided, as shown. The calls are sent in from the subscribers' stations in any well-known way. I have shown annunciator-needles *e* in the telephone-lines for receiving the calls of the subscribers. I find it preferable, however, to

place the annunciators in the lines between the test-keys of the first board and the ground. Any two lines are connected by means of a conducting-cord provided with terminal plugs, which are inserted in the switches of the two lines upon one given board in the usual manner. By inserting a plug the lever or spring *f* is wedged away from contact with contact-point *g*, and thus the line-wire *h* is connected with the plug-point and cut off from the ground-wire *i* in the usual manner. In my system, when a call is sent in, the switchman at the board to which this call belongs at once presses against spring *a* of the test-key in the line of the subscriber called for. Contact is thus broken between the spring *a* and contact-point *b* and a new contact formed between said spring and the contact-point *c*. The battery is thus thrown to line, and the signaling-instrument *d* in the line between the contact-point *c* and the battery responds, provided the line is not in use, and by simply tapping upon the spring *a* the circuit of the line is closed and broken, thus calling up the subscriber.

I claim—

In a multiple switch-board system, the combination, with the calling-keys *a*, of the battery branching to contact-points *c* and the contact-points *b*, whereby any line may be disconnected from its normal ground and closed to said battery upon either of the boards, substantially as specified.

CHAS. H. WILSON.

Witnesses:

WM. S. GRANGER,
GEORGE P. BARTON.