

(19) United States

(12) Patent Application Publication (10) Pub. No.: US 2005/0270814 A1

Oh (43) Pub. Date: Dec. 8, 2005

(54) MODIFIED SINUSOIDAL PULSE WIDTH MODULATION FOR FULL DIGITAL POWER FACTOR CORRECTION

(52) U.S. Cl. 363/98

(76) Inventor: In-Hwan Oh, Cupertino, CA (US)

(57) ABSTRACT

Correspondence Address: SIDLEY AUSTIN BROWN & WOOD LLP Suite 5000 555 California Street San Francisco, CA 94104-1715 (US)


A converter-controller includes a feedback circuit, receiving a feedback voltage from an output stage and generating a current command signal according to the difference of a reference voltage and the feedback voltage. A duty cycle modulator generates a modified duty cycle utilizing the current command signal and a reference table. The controller further includes a counter producing a periodic signal, and a comparator, receiving the modified duty cycle and the periodic signal. The comparator generates a variable-duty-cycle output current corresponding to the difference of the periodic signal and the modified duty cycle.

(21) Appl. No.: 10/858,701

(22) Filed: Jun. 2, 2004

Publication Classification

(51) Int. Cl.⁷ H02M 1/00






FIG. 1




FIG. 2A




FIG. 2B




FIG. 2C




FIG. 3




FIG. 4




FIG. 5B




FIG. 5A




FIG. 6




FIG. 7




FIG. 8A




FIG. 8B




FIG. 8C




FIG. 9B




FIG. 9A

**MODIFIED SINUSOIDAL PULSE WIDTH
MODULATION FOR FULL DIGITAL POWER
FACTOR CORRECTION**

FIELD OF THE INVENTION

[0001] This invention relates in general to converter-controllers, and in particular to digital converter-controllers with an adjustable duty cycle.

BACKGROUND OF THE INVENTION

[0002] The power factor control method has been utilized in various power supplies. Certain popular methods use an analog controller with a Discontinuous Conduction Mode (DCM) such as the FAN7527B and FAN4812 integrated circuits from Fairchild Semiconductor. Recently there has been a lot of research of possible digital approaches for controlling the power factor of converters. One requirement is that the control speed of the digital controllers should be suitable to deliver a performance comparable to analog controllers. Since Digital Signal Processors (DSPs) have fast calculation speed, they can be used as digital controllers. However, price considerations are detrimental to DSPs.

[0003] A simple digital PFC method is to fix the switching frequency and adjust the duty ratio to control the output voltage. This method is easily realized by using a low speed/price digital controller. However, an unwanted third harmonic component of about 8~10% of the input signal typically appears in the output of these converters. It is difficult to eliminate this third harmonic component by using an EMI filter with a high cut-off frequency, since its frequency is close to the fundamental frequency. Furthermore, the third harmonic component in a full load condition is almost the same as in a light or no-load condition. Reducing or eliminating this third harmonic component is part of achieving low Total Harmonic Distortion (THD) in PFC controllers.

SUMMARY

[0004] Briefly and generally, according to embodiments of the invention, a converter-controller includes a feedback circuit, receiving a feedback voltage from an output stage and generating a current command signal according to the difference of a reference voltage and the feedback voltage. The controller further includes a duty cycle modulator, coupled to the feedback circuit to receive the current command signal, and configured to generate a modified duty cycle utilizing the current command signal and a reference table. Further, the controller includes a counter, configured to produce a periodic signal and a comparator, coupled to the duty cycle modulator to receive the modified duty cycle and coupled to the counter to receive the periodic signal. The comparator is configured to generate a variable-duty-cycle output current corresponding to the difference of the periodic signal and the modified duty cycle.

[0005] Other embodiments of the invention consist of a method of controlling a converter. The method includes receiving a feedback voltage by a feedback circuit from an output stage, and generating a current command signal by the feedback circuit, corresponding to the difference of a reference voltage and the feedback voltage. Further, the method includes modulating a duty cycle by a duty cycle modulator according to the current command signal and a

reference table, producing a periodic signal by a counter, and generating a variable-duty-cycle output signal by a comparator, corresponding to the difference of the modified duty cycle and the periodic signal.

DESCRIPTION OF THE DRAWINGS

[0006] For a more complete understanding of the present invention and for further features and advantages, reference is now made to the following description taken in conjunction with the accompanying drawings.

[0007] FIG. 1 is a block diagram of a converter, according to an embodiment of the invention.

[0008] FIGS. 2A-C illustrates various implementations of converters according to embodiments of the invention.

[0009] FIG. 3 illustrates the voltage and line current of converters with fixed duty cycles.

[0010] FIG. 4 illustrates details of the signal shape of the line current in converters.

[0011] FIGS. 5A and B illustrate timing diagrams of converters and the third harmonic component with fixed duty cycles, respectively.

[0012] FIG. 6 illustrates the voltage and line current of converters with modified duty cycles according to embodiments of the invention.

[0013] FIG. 7 illustrates the modification of the duty cycle in more detail.

[0014] FIGS. 8A-C illustrate various signal profiles of embodiments of the invention.

[0015] FIGS. 9 A and B illustrate a summary timing diagram and the third harmonic component in embodiments of the invention, respectively.

DETAILED DESCRIPTION

[0016] According to embodiments of the invention a converter-controller with an improved power factor conversion is described in relation to FIGS. 1-9.

[0017] FIG. 1 illustrates an embodiment of converter-controller 100, for controlling the operation of a converter 1. Converter-controller 100 includes a feedback circuit 110, which receives a feedback voltage V_{fb} from a resistor stepper 124 of output stage 120. Feedback circuit 110 generates a current command signal, which corresponds to the output of digital Proportional-Integral (PI) controller 119. The output of digital PI controller 119 is based on the difference of a reference voltage V^* and the feedback voltage V_{fb} .

[0018] Converter-controller 100 controls the power factor conversion of converter 1 digitally. Accordingly, feedback circuit 110 receives feedback voltage V_{fb} through an analog-digital converter 113 from output stage 120.

[0019] One embodiment of convert-controller 100 is microcontroller FMS7401 from Fairchild Semiconductor. Microcontroller FMS7401 includes analog-digital converter 113 at pin(3:AIN2/G2). Therefore, in this embodiment, feedback voltage V_{fb} is coupled into pin(3:AIN2/G2).

[0020] Analog-digital converter 113 converts the feedback voltage V_{fb} to a digital feedback voltage V_{dfb} and couples

V_{dfb} into feedback circuit **110**. In some embodiments, feedback circuit **110** is referred to as a software block.

[0021] Converter-controller **100** further includes a feedback comparator **116**, which receives reference voltage V^* and digital feedback voltage V_{dfb} . Feedback comparator **116** generates a digital control signal, which corresponds to the difference of reference voltage V^* and digital feedback voltage V_{dfb} .

[0022] The digital control signal of feedback comparator **116** is coupled into a digital proportional-integrator converter **119**. Digital PI controller **119** generates an intermediate current command signal i_i^* . One function of intermediate current command signal i_i^* is to keep the output DC voltage at an approximately constant level even if the corresponding output current changes due to variations in the electric load.

[0023] In some embodiments, feedback circuit **110** also includes a feed-forward control block **118**. Feed-forward control block **118** receives an input reference voltage V_i^* , which can be, for example, reference voltage V^* . Feed-forward control block **118** also receives a digital feed-forward input signal V_{dff} corresponding to a DC input voltage filtered through **R4**, **R5**, and **C4** to provide an averaged value through a feed-forward analog-digital converter **121**. Feed-forward control block **118** generates a feed-forward signal i_{ff} , which corresponds to the output of feed-forward control block **118** to provide a fast output voltage compensation, when AC input voltage is changed.

[0024] In embodiments with feed-forward circuits, the signals of feed-forward circuit **118** and digital proportional-integrator **119** are unified in a synthesizer **126**. Synthesizer **126** receives the intermediate current command signal i_i^* and the feed-forward signal i_{ff} , and generates a current command signal i^* by modifying intermediate current command signal i_i^* according to feed-forward signal i_{ff} .

[0025] The generated current command signal i^* is coupled from feedback circuit **110** into a duty cycle modulator **130**. Duty cycle modulator **130** modulates current command signal i^* according to a reference table. In some embodiments, the reference table is pre-programmed in a Read Only Memory (ROM). The modulation can be performed according to a periodic modulating signal. In some embodiment the periodic modulating signal is sinusoidal. The storing, or pre-programming, of the periodic modulating signal eliminates the need to sense the sinusoidal input voltage V_{in} . The modulation can be performed synchronously with an input voltage signal. The modulated current command signal translates to a modified duty cycle $D^*(k)$. The details of this modulation technique will be described in detail below.

[0026] Converter-controller **100** further includes a counter **140**. Counter, which can be for example, a free-running counter, produces a periodic signal. In some embodiments the periodic signal is a saw-tooth signal.

[0027] Converter-controller **100** further includes a comparator **150**. Comparator **150** is coupled to duty cycle modulator **130** and receives the modified duty cycle $D^*(k)$. Comparator **150** is also coupled to counter **140** and receives the periodic signal. One function of comparator **150** is to generate a variable-duty-cycle output signal, which corresponds to the difference of the periodic signal and modified

duty cycle $D^*(k)$. When this difference is positive, the output of comparator **150** is “high” and when the difference is negative, the output is “low”. In various embodiments, comparator **150** operates digitally.

[0028] In some embodiments, comparator **150** outputs the variable-duty-cycle output signal to a gate driver **160**. A function of gate driver **160** is to provide a gate-driving signal for a power device. The “high” output is such that it can make a corresponding power device conducting, whereas the “low” output can make the corresponding power device non-conducting.

[0029] In embodiments, where converter-controller **100** is microcontroller FMS7401 from Fairchild Semiconductor, gate driver **160** outputs the gate driving signal at pin(4:AIN3/G1). In some embodiments, the gate driver is FAN53418 from Fairchild Semiconductor.

[0030] Converter-controller **100** can be part of converter **1**. Converter **1** includes a DC link **5**. DC link **5** is energized by a rectified AC source **11**.

[0031] DC link **5** is coupled to converter-controller **100** to provide an operating voltage V_{cc} at pin(8). The operating-voltage-coupling between DC link **5** and converter-controller **100** may include a resistor **R2**, coupled to a capacitor **C1**, and a Zener diode **D3** in parallel to capacitor **C1**.

[0032] In embodiments including a feed-forward circuit **118**, DC link **5** is coupled to feed-forward circuit **118** to provide a feed forward signal. The feed-forward-coupling of DC link **5** to feed-forward circuit **118** can include a resistor **R4**, coupled to a capacitor **C4** and a resistor **R5** in parallel to capacitor **C4**. Resistor **R4** and capacitor **C4** form a low pass filter to extract an average value of V_{in} . In embodiments, where converter-controller **100** is microcontroller FMS7401 from Fairchild Semiconductor, DC link **5** is coupled to feed-forward circuit **118** at pin(1:AIN0/G4).

[0033] DC link **5** is further coupled to duty cycle modulator **130** through a synchronization coupling to provide a synchronizing signal for the modulation of current command signal i^* into modified duty cycle $D^*(k)$. The synchronization coupling can include a resistor **R1** and a diode **D1**, coupled to the ground. These synchronization-coupling senses when V_{in} crosses zero and thus can be used to synchronize duty cycle modulator **130** with the input voltage signal by a reset operation. Such embodiments maintain their sinusoidal output voltage even if V_{in} is distorted by higher harmonics. In embodiments, where converter-controller **100** is microcontroller FMS7401 from Fairchild Semiconductor, DC link **5** is coupled to duty cycle modulator **130** at pin (7:T1HS2/G5).

[0034] Converter **1** further includes power device **170**. Power device **170** can be a MOS-FET, a bipolar junction transistor, or an insulated gate bipolar transistor (IGBT). Power device **170** can be based on n-type conduction. In some embodiments, power device **170** is part of output stage **120**. A function of power device **170** is to control the line AC input current to be an essentially sinusoidal waveform as well as to regulate the output voltage of output stage **120** even if the load current is changed.

[0035] In some embodiments with a boost topology, output stage **120** includes a boost inductor L_b , coupled to DC link **5** at a first terminal. The second terminal of boost

inductor L_b is coupled to the anode of a boost diode Db , as well as to the drain of power device **170**. The cathode of boost diode Db is coupled to a first output terminal (+)Vo. Output stage **120** further includes a capacitor **C3**, coupled between first output terminal (+)Vo and a second output terminal (-)Vo. In parallel to capacitor **C3** is resistor stepper/bridge **124**, including resistors **R7** and **R8**. The midpoint of resistor stepper/bridge **124** is configured to generate feedback voltage V_{fb} by stepping down the output voltage V_o of output stage **120**.

[0036] FIGS. 2A-C illustrate various modifications of the embodiment of FIG. 1.

[0037] FIG. 2A includes a self-standing gate driver **U2**. Pin(4) of converter-controller **100** outputs the variable duty-cycle output signal, but instead of directly driving the gate of power device **170**, this signal is further controlled by gate driver **U2**. The operating voltage of gate driver **U2** is provided by the additional circuit of resistor **R3**, capacitor **C2**, and Zener diode **D4**, in parallel to capacitor **C2**. Gate driver **U2** can be, for example, Fairchild Semiconductor's integrated circuit FAN53418.

[0038] FIG. 2B illustrates another embodiment, where a voltage regulator is integrated in to converter-controller **100** so that the operating voltage for both converter-controller **100** and gate driver **U2** are provided through the same operating-voltage-coupling, including the capacitor **C1**—resistor **R2**—diode **D3** circuit.

[0039] FIG. 2C illustrates an embodiment, where the gate driver is integrated into converter-controller **100** as gate driver **160**.

[0040] Next, the principles of the operation of converter-controller **100** will be described. As described above, one function of converter-controller **100** is to reduce higher harmonics, specifically third harmonics, in the input line current.

[0041] To begin, we will consider a harmonic AC input voltage:

$$v_{ac}(t) = \sqrt{2} V_{rms} \sin \omega t, \text{ where } \omega = 2\pi f = \frac{2\pi}{T}. \quad (1)$$

[0042] The rectified DC rippled voltage is described as

$$v_{dc} = |v_{ac}(t)| = \sqrt{2} V_{rms} \sin \omega t. \quad (2)$$

[0043] In embodiments of the invention, a digital control system is utilized, in which power device **170** is turned on and off depending on a load requirement. This control system is sometimes referred to as a Switched Mode Power Supply (SMPS) system.

[0044] FIG. 3 illustrates that digital controllers generate sinusoidal currents by sampling the rectified voltage v_{dc} of Eq. (2), and converting it into a digitized signal. In some embodiments, the frequency of the input voltage or line voltage is about 50 Hz or 60 Hz, and this input voltage is sampled 10-10,000 times in a period. In general, in a pulse train with N pulses per half period, a sampling time t_s is given by

$$t_s = \frac{1}{2f(N+1)}, \quad (3)$$

[0045] where f is the above-introduced line frequency. The digitized DC voltage $V_a(k)$ is generated by sampling the rectified voltage v_{dc} at the k^{th} sampling time

$$V_a(k) = |V_{pk}| \sin\left(\frac{\pi k}{N+1}\right). \quad (4)$$

[0046] The voltage drop $v_L(k)$ across boost inductor L_b of output stage **120** is given by

$$v_L(k) = V_o - V_a(k), \quad (5)$$

[0047] where V_o is the above-defined output DC voltage. The ratio of on-time t_{on} , i.e. the time when the power device is on, and the total sampling time t_s defines with the duty ratio D as

$$D = \frac{t_{on}}{t_s} \Rightarrow t_{on} = t_s D. \quad (6)$$

[0048] By using above relation, the off-time t_{off} at the k^{th} sampling time can be written as

$$i_L(k) = \frac{t_{on}}{L} v_L(k) \rightarrow t_{off}(k) = L \frac{i_L(k)}{v_L(k)} = L \frac{i_L(k)}{V_o - V_a(k)} \quad (7)$$

[0049] FIG. 3 illustrates various aspects of the line current $I_a(k,t)$ with a peak value labeled $I_a(k)$, and the output current $I_o(t)$, appearing at the AC input terminal. In existing converters, comparator **150** outputs a "high" or "low" signal according to whether the difference of a fixed duty cycle and the periodic signal is positive or negative. This output signal controls the gate of power device **170**, resulting in a line current as shown. Within a sampling time t_s , the line current $I_a(k,t)$ rises for a period t_{on} , while power device **170** is on. Line current $I_a(k,t)$ decreases for a period of t_{off} while power device **170** is off. Finally, when the line current would cross zero, boost diode Db acquires a negative bias and the line current is kept essentially zero for a current discontinuity time t_{dc} . These three time intervals constitute the sampling time t_s . Therefore

$$t_{dc}(k) = t_s - t_{on} - t_{off}(k), \quad (8)$$

[0050] Since the voltage of an inductor is proportional to the time derivative of the current, to a good approximation the peak current $I_a(k)$ in the k^{th} sampling period can be written as

$$I_a(k) = \frac{V_a(k)}{L} t_{on}. \quad (9)$$

[0051] FIG. 4 illustrates that if the starting, center, and ending time instances of the k^{th} sampling time interval are denoted by $s(k)$, $c(k)$, and $e(k)$, respectively, the rising and falling slopes $A(k)$ and $B(k)$ of line current $I_a(k,t)$ are defined as

$$A(k) = \frac{I_a(k)}{c(k) - s(k)} \text{ and } B(k) = \frac{I_a(k)}{e(k) - c(k)}. \quad (10)$$

[0052] The full line current $I_a(t)$ (equal to the sum of line currents $I_a(k,t)$ in the sampling periods indexed by k) in a Fourier decomposition can be represented with the help of the Fourier coefficients a_n and b_n as follows

$$i_{in}(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos(n\omega t) + \sum_{n=1}^{\infty} b_n \sin(n\omega t), \quad (11)$$

$$a_n = \frac{2}{T} \int_{-T/2}^{T/2} f(t) \cos\left(\frac{2\pi}{T} nt\right) dt \text{ and} \quad (12)$$

$$b_n = \frac{2}{T} \int_{-T/2}^{T/2} f(t) \sin\left(\frac{2\pi}{T} nt\right) dt.$$

[0053] $a_0=0$ because the line current has no dc component. The a_n and b_n Fourier coefficients in Eq. (12) can be determined by straightforward application of the slopes introduced in Eq. (10). In the k^{th} sampling period one obtains

$$a_{k,n} = \frac{2}{T} \sum_{k=1}^N \left[\begin{aligned} & \int_{s(k)}^{c(k)} A(k)(t-s(k)) \cos(n\omega t) dt + \\ & \int_{c(k)}^{e(k)} [I_a(k) - B(k)(t-c(k))] \cos(n\omega t) dt - \\ & \int_{s(k)+T/2}^{c(k)+T/2} A(k)\left(t-s(k) - \frac{T}{2}\right) \cos(n\omega t) dt + \\ & \int_{c(k)+T/2}^{e(k)+T/2} (-I_a(k) + B(k)\left(t-c(k) - \frac{T}{2}\right)) \cos(n\omega t) dt \end{aligned} \right], \quad (13)$$

$$b_{k,n} = \frac{2}{T} \sum_{k=1}^N \left[\begin{aligned} & \int_{s(k)}^{c(k)} A(k)(t-s(k)) \sin(n\omega t) dt + \\ & \int_{c(k)}^{e(k)} [I_a(k) - B(k)(t-c(k))] \sin(n\omega t) dt - \\ & \int_{s(k)+T/2}^{c(k)+T/2} A(k)\left(t-s(k) - \frac{T}{2}\right) \sin(n\omega t) dt + \\ & \int_{c(k)+T/2}^{e(k)+T/2} (-I_a(k) + B(k)\left(t-c(k) - \frac{T}{2}\right)) \sin(n\omega t) dt \end{aligned} \right]. \quad (14)$$

[0054] The voltage drop across boost inductor L_b becomes high when the AC input voltage is low. Correspondingly, the inductor discharging time, t_{off} , becomes small. Conversely, the voltage drop across boost inductor L_b becomes low when the AC input voltage is high, making t_{off} low, as shown in FIG. 3.

[0055] The full line current, $i_{in}(t)$ is coupled into a low-pass filter of the input stage. This input stage low pass filter extracts the fundamental Fourier components of $i_{in}(t)$. It would be relatively difficult to eliminate the third harmonic

component by using a low pass filter (or EMI), which can extract the fundamental frequency component and suppress all other higher frequency components from $i_{in}(t)$. In contrast, embodiments of the present invention efficiently reduce the third harmonic component. Therefore, the fundamental frequency can be easily extracted from $i_{in}(t)$ by using a conventional low priced EMI filter.

[0056] FIG. 3 illustrates that in existing designs the desired line current deviates from the realistically expected line current. In particular, the desired line current is higher than the expected line current when the discontinuity time $t_{dc}(k)$ is sizeable compared to the sampling time t_s . This happens when the AC signal has a low value, as discussed above. The low value of the realistically expected line current compared to the desired line current generates a sizeable third harmonic component, resulting in a distortion of the original pure harmonic waveform.

[0057] The operation of existing converters is summarized in FIGS. 5A-B.

[0058] FIG. 5A illustrates that in fixed duty cycle converters the on-time t_{on} is constant throughout a cycle of the input voltage. The off-time $t_{\text{off}}(k)$ and correspondingly the discontinuity time $t_{dc}(k)$ still depend on the sampling index k , as the inductor's dynamics depend on the peak values $I_a(k)$ of the line current.

[0059] FIG. 5B illustrates that in fixed duty cycle converters the line current has sizeable discontinuity times, generating a third harmonic distortion of the fundamental current.

[0060] Embodiments of the invention reduce this third harmonic component by modifying the duty cycle of converter 1, resulting in a reduction or elimination of the discontinuity time $t_{dc}(k)$.

[0061] FIG. 6 shows the line current $I_a(k,t)$ according to embodiments of the invention. In this embodiment the on-time $t_{\text{on}}(k)$ varies from sampling period to sampling period as shown. In other words, $t_{\text{on}}(k)$ is now dependent on the sampling index k . The length of on-time $t_{\text{on}}(k)$ is adjusted so that the discontinuity time $t_{dc}(k)$ is reduced compared to fixed duty cycle converters, or, in some embodiments, essentially eliminated, as shown in FIG. 6.

[0062] FIG. 7 illustrates the modification of the duty cycle. Duty cycle $D^*(k)$ is modified according to a periodic modulating signal during the period T of the input voltage. In some embodiments, in the k^{th} sampling period modified duty cycle $D^*(k)$ takes the value

$$D^*(k) = i^* \left[1 - M_d \sin\left(\frac{\pi}{N+1} k\right) \right], \quad (15)$$

[0063] where M_d is a modified index and i^* is the current command signal, as shown in the upper panel. Modified duty cycle $D^*(k)$ is coupled into digital comparator 150, where its value is compared to the periodic saw tooth signal of counter 140, shown in the lower panel.

[0064] Embodiments can use low speed controller circuitry by including a ROM and programming the periodic

modulating signal into the ROM. The ROM access time is indicated as an update time by software and can be slower than the hardware digital pulse width modulator (PWM) signal period. In embodiments, where the frequency f of the input voltage is low, for example 50~60[Hz], the ROM access time does not need to be fast. For a digital PWM with period of about 10~15 microseconds, the ROM access time could be about few milliseconds.

[0065] FIGS. 8A-C illustrate various timing diagrams of some embodiments.

[0066] FIG. 8B illustrates the modified duty cycle and the saw-tooth periodic signal overlaid, both coupled into comparator 150.

[0067] FIG. 8C illustrates the output signal of comparator 150. When modified duty cycle $D^*(k)$ is greater than periodic saw-tooth signal, then the output gate signal of comparator 150 is "high". As described above, the output signal of comparator 150 serves as a gate signal for power device 170. As illustrated, the on-time t_{on} of the gate signal varies from sampling period to sampling period within a period of the input voltage.

[0068] FIG. 8A illustrates the resulting line peak current $I_a(k)$. In the illustrated embodiment, the discontinuity time $t_{dc}(k)$ is essentially modified.

[0069] FIGS. 9A-B summarize the operation of some embodiments.

[0070] FIG. 9A shows that, in contrast to FIG. 5A, $t_{on}(k)$ depends on the sampling index k .

[0071] FIG. 9B shows an embodiment where the discontinuity time $t_{dc}(k)$ has been modified. Correspondingly, the fundamental current is essentially indistinguishable from the current, which includes the generated third harmonic components. In particular, the line current value in the 0-30[Deg] interval is higher than in converters with fixed duty cycle, shown in FIG. 3 and FIG. 5B.

[0072] Since the described converter-controller utilizes digital control mechanism, in other embodiments, additional highly intelligent features can be implemented such as lowest standby power consumption, low total harmonic distortion, and high power factor correction from no-load to full load conditions.

[0073] Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions, and alterations can be made therein without departing from the spirit and scope of the invention as defined by the appended claims. That is, the discussion included in this application is intended to serve as a basic description. It should be understood that the specific discussion might not explicitly describe all embodiments possible; many alternatives are implicit. It also may not fully explain the generic nature of the invention and may not explicitly show how each feature or element can actually be representative of a broader function or of a great variety of alternative or equivalent elements. Again, these are implicitly included in this disclosure. Where the invention is described in device-oriented terminology, each element of the device implicitly performs a function. Neither the description nor the terminology is intended to limit the scope of the claims.

What is claimed is:

1. A converter-controller, comprising:
 - a feedback circuit, configured to receive a feedback voltage from an output stage and to generate a current command signal, corresponding to the difference of a reference voltage and the feedback voltage;
 - a duty cycle modulator, coupled to the feedback circuit to receive the current command signal, configured to generate a modified duty cycle utilizing the current command signal and a reference table;
 - a counter, configured to produce a periodic signal; and
 - a comparator, coupled to the duty cycle modulator to receive the modified duty cycle and coupled to the counter to receive the periodic signal, the comparator configured to generate a variable-duty-cycle output current corresponding to the difference of the periodic signal and the modified duty cycle.
2. The converter-controller of claim 1, wherein the converter-controller controls the power factor conversion digitally.
3. The converter-controller of claim 1, the converter-controller comprising:
 - a feedback analog-digital converter, configured to receive the feedback voltage from the output stage and to convert the feedback voltage to a digital feedback voltage.
4. The converter-controller of claim 3, the feedback circuit comprising:
 - a feedback comparator, configured to receive the reference voltage and the digital feedback voltage, and to generate a digital control signal, corresponding to the difference of the reference voltage and the digital feedback voltage.
5. The converter-controller of claim 4, the feedback circuit comprising:
 - a digital proportional-integrator converter, configured to receive the digital control signal of the feedback comparator and to generate an intermediate current command signal.
6. The converter-controller of claim 1, the feedback circuit further comprising:
 - a feed-forward circuit, configured to receive an input reference voltage and an input signal corresponding to an input voltage, and to generate a feed-forward signal, corresponding to the difference of the input reference voltage and the input signal.
7. The converter-controller of claim 6, the feedback circuit further comprising:
 - a synthesizer, configured to receive the intermediate current command signal and the feed-forward signal, and to generate the current command signal by modifying the intermediate current command signal according to the feed-forward signal.
8. The converter-controller of claim 7, wherein the duty cycle modulator is configured to receive the current command signal from the synthesizer.
9. The converter-controller of claim 8, wherein the variable-duty-cycle output current comprises a rising and falling current for a portion of a sampling period and a current discontinuity time for another portion of the sampling period.

10. The converter-controller of claim 9, wherein the duty cycle modulator modulates the duty cycle to reduce the discontinuity time of the variable-duty-cycle output current, compared to a corresponding fixed-duty-cycle output current.

11. The converter-controller of claim 9, wherein the duty cycle modulator modulates the duty cycle signal to essentially eliminate the discontinuity time of the variable-duty-cycle output current.

12. The converter-controller of claim 1, wherein the duty cycle modulator modulates the duty cycle to reduce a third harmonic Fourier component of the variable-duty-cycle output current, compared to a corresponding fixed-duty-cycle output current.

13. The converter-controller of claim 12, wherein the duty cycle modulator modulates the duty cycle to reduce a total harmonic distortion of the variable-duty-cycle output current.

14. The converter-controller of claim 1, wherein the reference table is pre-programmed into a Read Only Memory.

15. The converter-controller of claim 14, wherein a periodic modulating signal is stored in the reference table.

16. The converter-controller of claim 15, wherein the periodic modulating signal is utilized to generate the modified duty cycle utilizing the current command signal i^* and a reference table according to the formula:

$$D^*(k) = i^* \left[1 - M_d \sin\left(\frac{\pi}{N+1}k\right) \right],$$

k being the index of a sampling cycle within a period of an input voltage, N being the number of sampling cycles within the period of the input voltage, M_d being a modified index, and $D^*(k)$ being the modified duty cycle.

17. The converter-controller of claim 16, wherein the periodic signal of the counter is essentially a saw-tooth signal.

18. The converter-controller of claim 17, wherein the comparator is configured to receive the periodic signal of the counter and the modified duty cycle of the duty cycle modulator, and generate an output signal, corresponding to the difference of the periodic signal and the modified duty cycle.

19. The converter-controller of claim 18, wherein the output signal of the comparator is “high”, when the modified duty cycle is greater than the periodic signal, and the output signal is “low”, when the modified duty cycle is less than the periodic signal.

20. The converter-controller of claim 1, wherein the converter-controller is coupled to a DC link.

21. The converter-controller of claim 20, wherein the DC link is energized by one of a DC source and a rectified AC source.

22. The converter-controller of claim 20, wherein the DC link is coupled to the converter-controller to provide an operating voltage.

23. The converter-controller of claim 20, wherein the DC link is coupled to a feed-forward circuit in the feedback circuit, to provide a feed forward signal.

24. The converter-controller of claim 20, wherein the DC link is coupled to the duty cycle modulator to provide a synchronizing signal for the modified duty cycle.

25. The converter-controller of claim 20, further comprising:

a gate driver, coupled to the comparator to receive the variable-duty-cycle output signal, configured to control a gate of a power device.

26. The converter-controller of claim 25, wherein the power device is operable to control an output current of the output stage.

27. The converter-controller of claim 26, the output stage further comprising:

an inductor, wherein a first terminal of the inductor is coupled to the DC link;

a diode, wherein the anode of the diode is coupled to a second terminal of the inductor and the cathode of the diode is coupled to a first output terminal;

a capacitor, coupled between the first output terminal and a second output terminal; and

a resistor divider, coupled between the first and second output terminals, configured to generate the feedback voltage by stepping down an output voltage of the output stage.

28. The converter-controller of claim 27, wherein:

the power device is coupled to the second terminal of the inductor.

29. The converter-controller of claim 1, wherein the converter-controller senses a crossing point of two signals without fully sensing a line current.

30. The converter-controller of claim 1, wherein the operating speed of the converter-controller can be low compared to a conventional DSP based digital PFC controller.

31. A converter, including a converter-controller, which comprises:

a feedback circuit, configured to receive a feedback voltage from an output stage and to generate a current command signal, corresponding to the difference of a reference voltage and the feedback voltage;

a duty cycle modulator, coupled to the feedback circuit to receive the current command signal, configured to modify a duty cycle utilizing the current command signal and a reference table;

a counter, configured to produce a periodic signal; and

a comparator, coupled to the duty cycle modulator to receive the modified duty cycle and coupled to the counter to receive the periodic signal, the comparator configured to generate a variable-duty-cycle output signal, corresponding to the difference of the modified duty cycle and the periodic signal;

the converter further comprising:

a DC link to provide an operating voltage for the converter-controller, a feed forward signal for the feedback circuit, and a synchronizing signal for the duty cycle modulator; and

an output stage, including:

an inductor, wherein a first terminal of the inductor is coupled to the DC link;

a diode, wherein the anode of the diode is coupled to a second terminal of the inductor and the cathode of the diode is coupled to a first output terminal;

a capacitor, coupled between the first output terminal and a second output terminal;

a resistor divider, coupled between the first and second output terminals, configured to generate the feedback voltage corresponding to a stepped-down voltage of the output stage; and

a power device, controlled by receiving the variable-duty-cycle output signal at a gate, the power device being coupled to the second terminal of the inductor.

32. A method of controlling a converter, the method comprising:

receiving a feedback voltage by a feedback circuit from an output stage;

generating a current command signal by the feedback circuit, corresponding to the difference of a reference voltage and the feedback voltage without sensing a rectified input voltage and an inductor current;

modulating a duty cycle by a duty cycle modulator according to the current command signal and a reference table;

producing a periodic signal by a counter; and

generating a variable-duty-cycle output signal by a comparator, corresponding to the difference of the modified duty cycle and the periodic signal.

33. The method of claim 32, wherein generating a variable-duty-cycle output signal comprises:

outputting a “high” signal, when the modified duty cycle is greater than the periodic signal; and

outputting a “low” signal, when the modified duty cycle is less than the periodic signal.

34. The method of claim 32, the method further comprising:

modifying the duty cycle to reduce a current-discontinue-time of the variable-duty-cycle output current, compared to a corresponding fixed-duty-cycle output signal.

35. The method of claim 32, the method further comprising:

modifying the duty cycle to essentially eliminate a current-discontinue-time of the variable-duty-cycle output current.

36. The method of claim 32, the method further comprising:

modifying the duty cycle to reduce a third harmonic Fourier component of a current of the output stage, compared to a corresponding fixed-duty-cycle output current.

37. The method of claim 36, method further comprising:

modifying the duty cycle to reduce a total harmonic distortion of an output current of the output stage, compared to a corresponding fixed-duty-cycle output current.

38. The method of claim 32, the method further comprising:

pre-programming the reference table into a Read Only Memory.

39. The method of claim 38, the method further comprising:

storing a periodic modulating signal in the reference table.

40. The method of claim 39, the method further comprising:

utilizing the periodic modulating signal to modifying the duty cycle according to the formula:

$$D^*(k) = i^* \left[1 - M_d \sin\left(\frac{\pi}{N+1}k\right) \right],$$

k being the index of a sampling period within a period of an input voltage, N being the total number of sampling periods within the period of the output voltage, M_d being a modified index, and $D^*(k)$ being the modulated duty cycle.

41. The method of claim 32, the method further comprising:

controlling a power factor conversion digitally.

* * * * *