



US006130618A

# United States Patent [19]

[11] Patent Number: **6,130,618**

Burnett et al.

[45] Date of Patent: **Oct. 10, 2000**

[54] **PIEZOELECTRIC TRANSDUCER ASSEMBLY ADAPTED FOR ENHANCED FUNCTIONALITY**

5,475,368 12/1995 Collins ..... 340/391.1

### FOREIGN PATENT DOCUMENTS

[75] Inventors: **George A. Burnett**, Amo; **Brian S. Bush**, Indianapolis, both of Ind.

2544-530 10/1984 France .  
2736-089 2/1978 Germany .  
61-90600 5/1986 Japan .  
3-296098 12/1991 Japan .

[73] Assignee: **Yosemite Investment, Inc.**, Indianapolis, Ind.

*Primary Examiner*—Donnie L. Crosland  
*Attorney, Agent, or Firm*—Niro, Seavone, Haller & Niro

[21] Appl. No.: **09/007,596**

### [57] ABSTRACT

[22] Filed: **Jan. 15, 1998**

[51] Int. Cl.<sup>7</sup> ..... **G08B 5/22**; G08B 3/10

[52] U.S. Cl. .... **340/815.45**; 340/384.6;  
340/396.1; 340/391.1

[58] Field of Search ..... 340/815.45, 815.49,  
340/815.69–815.71, 384.6, 384.1, 384.7,  
391.1, 396.1, 474, 326, 330

A novel modular audible signaling device is provided capable of expanded functionality, such as the provision of visual signaling as well. A piezoelectric transducer audible alarm signaling device is provided with an assembly having a housing defining an interior holding a piezoelectric transducer, the housing having a first exterior portion for attachment to a surface and a second exterior portion extending beyond the surface, wherein the first exterior portion and the second exterior portion comprise at least one pair of communicating apertures whereby an electrical conductor may extend through the at least one pair of apertures to the surface. In another aspect, a piezoelectric transducer assembly is provided having a housing defining an interior and a surface, the housing holding a piezoelectric transducer, wherein the housing further comprises an illumination element associated the surface thereof, the illumination element having one or more conductors which extend through the interior of the housing, whereby the illumination element may be electrically inserted into the same electrical circuit as the piezoelectric transducer.

### [56] References Cited

#### U.S. PATENT DOCUMENTS

|           |         |                |       |           |
|-----------|---------|----------------|-------|-----------|
| 3,815,129 | 6/1974  | Sweany         | ..... | 340/384.6 |
| 3,879,726 | 4/1975  | Sweany         | ..... | 340/384.6 |
| 4,139,842 | 2/1979  | Fujita et al.  | ..... | 340/384.6 |
| 4,282,520 | 8/1981  | Shipp et al.   | ..... | 340/629   |
| 4,325,060 | 4/1982  | Purtell et al. | ..... | 340/384.6 |
| 4,374,377 | 2/1983  | Saito et al.   | ..... | 340/384.6 |
| 4,486,742 | 12/1984 | Kudo et al.    | ..... | 340/384.6 |
| 4,669,424 | 6/1987  | Bianco et al.  | ..... | 119/156   |
| 4,811,816 | 3/1989  | Lin            | ..... | 381/159   |
| 4,820,935 | 4/1989  | Gontowski      | ..... | 307/112   |
| 5,398,024 | 3/1995  | Knowles        | ..... | 340/384.6 |

**8 Claims, 2 Drawing Sheets**




FIG. 1




FIG. 2





FIG. 3



**PIEZOELECTRIC TRANSDUCER ASSEMBLY  
ADAPTED FOR ENHANCED  
FUNCTIONALITY**

**FIELD OF THE INVENTION**

The present invention relates to audible and visual alarm devices, and more specifically to the field of piezoelectric transducer audible and visual alarm devices.

**BACKGROUND OF THE INVENTION**

U.S. Pat. No. 3,815,129, issued to Sweany and hereby incorporated by reference, discloses an exemplary feedback type piezoelectric transducer. Piezoelectric transducers, such as those disclosed in the '129 patent, are typically disposed within a housing constructed to maximize transmission of sound into the ambient medium. As shown in FIGS. 1, 2 and 5 of the '129 patent, such transducers have a piezoelectric element mechanically coupled to a substrate, such as a brass disc. The piezoelectric element includes a piezoelectric crystal. The element also has electrode means carried on the crystal or the substrate. The electrode means are electrically connected to electrical terminals. In the '129 patent, these terminals are labeled  $T_1$ ,  $T_2$  and  $T_3$ .  $T_1$  and  $T_2$  are driving terminals for receiving oscillating driving potentials, and  $T_3$  is a feedback terminal that allows the transducer itself to cooperate with an electrical circuit as a reactive impedance.  $T_2$  is connected to the electrode means located on the substrate opposite  $T_1$  and  $T_3$ , a brass plate that forms a disc and acts as a diaphragm.

In typical use, all of the above parts are completely enclosed in a housing. The transducer is sealed with a silicon type of material between the brass side of the transducer and the nodal ring that defines the inner surface of the housing. The respective terminals extend outside the housing on one end. The end from which the terminals extend is attached onto a PC board, with the terminals attached to appropriate contacts via a solder connection. The PC board contains the components of the electrical circuit that, like in FIGS. 3 and 4 of the '129 disclosure, enable the noise making device to function.

Heretofore, it was not known to make any electrical connection extending outwardly from the PC board through the transducer housing and to the end of the housing opposite the PC board. Once the housing holding the transducer elements was attached to the PC board, electrical access to any electrical contacts on the PC board was extremely difficult to achieve. The transducer housing took up most of the surface of the PC board and blocked the way. This caused many disadvantages. Among the disadvantages, it was difficult to expand the circuit to include other electrical components that are not necessary to the sound generating function. This made it nearly impossible to add such electrical components to enhance the functionality of the noise making unit, such as light emitting devices or other actuator components. It was also unfeasible to dispose existing or new electrical components on the surface of the transducer housing. While placing such electrical components on the surface of the transducer housing was possible in principle, to do so would formerly require snaking a conductor such as a flying lead wire around the surface of the housing. This approach risks breakages and open circuits. Such an approach also would be expensive to manufacture. Furthermore, a problem to be overcome was how to extend an electrical contact to the PC board through the tight spaces inside the transducer housing without attenuating or degenerating the sound quality emitted by the brass disc diaphragm.

**SUMMARY OF THE INVENTION**

The present invention overcomes these disadvantages, problems and limitations. In the novel assembly of the present invention, the assembly has a housing defining an interior holding a piezoelectric transducer, the housing having a first exterior portion for attachment to a surface and a second exterior portion extending beyond the surface, wherein the first exterior portion and the second exterior portion comprise at least one pair of communicating apertures whereby an electrical conductor may extend through the at least one pair of apertures to the surface.

In another aspect, the present invention comprises a piezoelectric transducer assembly having a housing defining an interior and a surface, the housing holding a piezoelectric transducer, wherein the housing further comprises an illumination element associated the surface thereof, the illumination element having one or more conductors which extend through the interior of the housing, whereby the illumination element may be electrically inserted into the same electrical circuit as the piezoelectric transducer.

**BRIEF DESCRIPTION OF THE FIGURES**

FIG. 1 shows a side cut away cross section of the inside of the transducer assembly of a preferred embodiment of the present invention.

FIG. 2 shows the inside of the transducer assembly of FIG. 1, but from above.

FIG. 3 shows an the audible and visible oscillator circuit of a preferred embodiment of the present invention.

**DETAILED DESCRIPTION**

Turning to FIG. 1, in one embodiment, the assembly **5** has a housing **10** that includes an interior **15** and a surface **17**. The interior **15** of the housing **10** contains a piezoelectric transducer **70** as described in the Sweany '129 patent, particularly FIG. 5. The transducer **70** is connected to the interior surface of housing **10** with a room temperature vulcanized silicon bead **30** as shown. The surface **17** of housing **10** has a first exterior portion **32** that is on the end of the assembly designed for attachment to a PC board. Surface **17** also has a second exterior portion **34** that, in the preferred embodiment, is located opposite to the first exterior portion **32**. Along surface **17** near the second exterior portion **34** are a number of threads. This is so that the final assembly, along with any object to which it is attached, may be snugly secured to a matching set of threads, such as a threaded nut or any other threaded opening. In the case of a threaded opening in an otherwise solid object, the bulk of the assembly **5** and anything to which it is attached may remain hidden, with only second exterior portion **34** showing through.

In typical use, the Terminals **40**, **50** and **60** correspond respectively to terminals  $T_1$ ,  $T_2$  and  $T_3$  of the '129 patent. Terminals **40**, **50** and **60** extend from transducer **70** through first exterior portion **32** via block **20** which contains (not shown) a printed wiring board and ordinary potted material for sealing the housing. FIG. 2 illustrates the placement of the terminals **40**, **50** and **60** on transducer **70** inside the interior **15** of transducer assembly **5**. As shown in both FIGS. 1 and 2, a pair of holes, or apertures, **82** and **92** are placed through transducer **70**. Their placement is roughly symmetrical around the center, and empirically chosen so that attenuation of the sound quality emitted from the brass diaphragm is minimized. Ideally, such placement will be on nodes of the fundamental frequency of vibrations on the

brass disc. Aperture **82** cooperates with apertures **84** and **86** to allow conductor **80** to extend through all of them to reach from first external portion **32** through interior **15** and transducer **70** outward through second external portion **84**. Likewise, aperture **92** cooperates with apertures **94** and **87** to allow conductor **90** to extend through all of them to reach from first external portion **32** through interior **15** and transducer **70** outward through second external portion **94**. Where conductors **80** and **90** extend outwardly from the second external portion **34**, conductors **80** and **90** are connected to a light emitting diode, or LED **96**. In this way, when assembly **5** is attached to an appropriate PC board (not shown), the ends of conductors **80** and **90** that extend from first external portion **32** are connected to the rest of the electrical circuit (not shown) in a manner that the driving of transducer **70** through its terminals **40**, **50** and **60** simultaneously drives LED **96** in its forward biased mode. In the preferred embodiment, LED **96** is of the self-blinking variety. But constantly emitting LED's may be used with equal effectiveness.

It will be appreciated that in the preferred embodiment, construction of assembly **5** must occur in the proper sequence. This requires that apertures **82** and **92** and apertures **84** and **94** be punched or molded first, that conductors **80** and **90** be placed in their proper locations next, and finally that the potted material in block **20** seals the interior **15** last. In this respect, apertures **86** and **87** are formed by the sealing material surrounding the already-placed conductors **80** and **90**. Of course, in alternative embodiments, apertures **86** and **87** could just as easily be punched, molded or otherwise generated.

An advantage of the configuration shown in FIGS. **1** and **2** is that external circuitry (not limited to LED **96**) may now be coupled to any part of the electrical circuit located on the PC board (not shown). The resulting assembly **5** is modular and expandable. All of the frequencies, currents, potentials and impedances within the PC board (not shown) that were heretofore inaccessible may now be accessed and utilized in any way known in the art.

FIG. **3** shows a circuit of a preferred embodiment of the present invention. In general, FIG. **3** shows a variation on the electrical noise providing circuit of U.S. Pat. No. 3,815, 129 with a light producing illumination element **96** connected in parallel across  $+V$  and  $-V$ . LED **96** is the light producing element. LED **96** might be a self-blinking LED, or a standard LED. While an LED is preferred, any illumination device may be suitably used, such as incandescent bulbs, without departing from the scope of the disclosure. Resistors **270**, **272** and **274** are resistors that bias transistor **260**. These in general make up driving circuit **280**, contained within the dotted lines of the figure. Transistor **260** is connected to  $+V$ , and also to  $-V$  through emitter resistor **274**. Transducer **70** has three terminals, **40**, **50** and **60** as described above.

In operation, the circuit works as follows. When a positive potential (an electrical signal) is applied to  $+V$  with  $-V$  connected to ground, transducer **70** vibrates at a predetermined frequency, as determined by the impedances in the oscillator circuit **280** and transducer **70**, producing an audible signal. More specifically, initially transistor **260** is biased off. When the electrical signal appears at  $+V$ , the same potential appears at terminal **40**. This causes the crystal in transducer **70** to deform. Simultaneously, the substrate to which the crystal is mechanically attached also deforms. The deformation causes the potential at terminal **60** to begin to rise. Eventually, the potential at terminal **60** rises sufficiently to forward bias transistor **260** into its on state through base

resistor **272**. When this happens, the potential at terminal **50** quickly rises to that at  $+V$ , diminished by an amount equal to  $V_{CE}$  of transistor **260**. It is well known that  $V_{CE}$  of a bipolar junction transistor in saturation is approximately 0.3 volts; therefore, the potential at terminal **50** will now become  $(+V \text{ minus } 0.3)$  while the potential at terminal **40** remains  $(+V)$ . At this point, the deformation in the crystal of transducer **70** reverses. Consequently, the potential at terminal **60** now starts to decrease until transistor **260** is once again biased in the off position. The cycle repeats indefinitely. All the while, when a potential is applied to  $+V$ , LED **96** is excited and produces a visible signal. The signal may blink, as in the case where a blinking LED is used, or may be constant light, as in the case where a standard LED is used.

It will be appreciated that those skilled in the art may now make many uses and modifications of the specific embodiments described without departing from the inventive concepts. It is apparent that variations of the above embodiments may be easily performed. For example, LED **96** may be placed flush with the second external portion **34**, enabling an audible and visual signaling device having a streamlined and attractive form factor. LED **96** may also be placed in the interior **15** of housing **10**, as long as its visual signaling attributes are perceptible by an intended viewer, such as in an alarm situation. In this instance, housing **10** may be constructed from a clear material, such as LUCITE, glass or a transparent/translucent polymer. In another example, while a three terminal transducer has been shown, a two terminal transducer may be used without departing from the scope of the invention. In still another example, the modular features of the invention allow multiple audible and/or audible plus visual signaling devices to be chained together as a single apparatus. Other uses and modifications will be apparent.

We claim:

1. A piezoelectric transducer assembly comprising
  - a housing defining an interior holding a piezoelectric transducer, the housing having a first exterior portion for attachment to a surface and a second exterior portion extending beyond the surface,
  - wherein the first exterior portion and the second exterior portion comprise at least one pair of communicating apertures, and
  - wherein the piezoelectric transducer has a sound producing diaphragm having at least one aperture operatively communicating with the at least one pair of communicating apertures,
  - whereby an electrical conductor may extend through the at least one pair of apertures to the surface.
2. The assembly of claim **1** wherein the first and second exterior portions comprise a second pair of communicating apertures.
3. The assembly of claim **1** wherein a conductor extends through the at least one pair communicating apertures.
4. The assembly of claim **1** wherein a conductor extends through the at least one aperture and the at least one pair of communicating apertures.
5. The assembly of claims **3** or **4** wherein the conductor is attached at one end to an illumination element.
6. The assembly of claim **5** wherein the illumination element comprises an LED.

**5**

7. The assembly of claims **3** or **4** further comprising an electrical driving circuit for driving the piezoelectric transducer, the electrical circuit comprising a plurality of electrical components, wherein the conductor is attached at one end to one of the plurality of electrical components. 5

8. A piezoelectric transducer assembly having a housing defining an interior and a surface, the housing comprising at least one pair of communication apertures at its surface and holding a piezoelectric transducer disposed within an electrical circuit, 10

wherein the housing further comprises an illumination element associated with the surface thereof,

**6**

the illumination element electrically coupled to one or more conductors which extend through the interior of the housing, and

wherein the piezoelectric transducer has a sound producing diaphragm having at least one aperture operatively communicating with the at least one pair of communicating apertures,

whereby the illumination element may be electrically inserted into the same electrical circuit as the piezoelectric transducer.

\* \* \* \* \*