



US009210747B2

(12) **United States Patent**
Zhang

(10) **Patent No.:** **US 9,210,747 B2**
(45) **Date of Patent:** **Dec. 8, 2015**

(54) **DRIVER FOR DRIVING LED BACKLIGHT SOURCE, LED BACKLIGHT SOURCE AND LCD DEVICE**

(2013.01); *H05B 33/0824* (2013.01); *G09G 2320/043* (2013.01); *G09G 2330/02* (2013.01); *G09G 2330/021* (2013.01); *G09G 2330/028* (2013.01)

(71) Applicant: **Shenzhen China Star Optoelectronics Technology Co., Ltd.**, Shenzhen, Guangdong (CN)

(58) **Field of Classification Search**
CPC H05B 33/0815; H05B 33/0818; H05B 341/3927; H05B 41/3925
USPC 315/291, 185 R, 307, 362; 323/305
See application file for complete search history.

(72) Inventor: **Hua Zhang**, Shenzhen (CN)

(73) Assignee: **Shenzhen China Star Optoelectronics Technology Co., Ltd**, Shenzhen, Guangdong

(56) **References Cited**

U.S. PATENT DOCUMENTS

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 33 days.

8,035,315 B2 * 10/2011 Zhao et al. 315/299
8,947,407 B2 * 2/2015 Williams H05B 33/0827
315/122
9,030,459 B2 * 5/2015 Jang H05B 33/0815
315/192

(21) Appl. No.: **13/980,030**

(Continued)

(22) PCT Filed: **Jun. 26, 2013**

Primary Examiner — Douglas W Owens

Assistant Examiner — Syed M Kaiser

(86) PCT No.: **PCT/CN2013/077997**

(74) *Attorney, Agent, or Firm* — Andrew C. Cheng

§ 371 (c)(1),
(2) Date: **Jul. 16, 2013**

(87) PCT Pub. No.: **WO2014/205671**

PCT Pub. Date: **Dec. 31, 2014**

(65) **Prior Publication Data**

US 2014/0375930 A1 Dec. 25, 2014

(30) **Foreign Application Priority Data**

Jun. 24, 2013 (CN) 2013 1 0253835


(51) **Int. Cl.**
H05B 37/02 (2006.01)
H05B 33/08 (2006.01)
G09G 3/34 (2006.01)

(57) **ABSTRACT**

A driver for driving an LED backlight source is disclosed. The driver includes a boost converter for boosting inputted DC voltage and outputting boosted DC voltage to an LED series circuit having LEDs connected and a resistor in series, a feedback circuit for feeding back voltage across the resistor to a backlight driving circuit, and a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor for keeping current flowing through the LED series circuit in a constant current. The driver drives the LED series circuit with a constant current, thereby prolonging lifetime of each LED of the LED series circuit. Furthermore, since a time period which the current flowing through the LED series circuit approaches to constant value is shorter, the driver has advantages over lower power consumption, faster response time and better operating efficiency.

(52) **U.S. Cl.**
CPC *H05B 33/0815* (2013.01); *G09G 3/3413*

12 Claims, 2 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

9,035,566	B2 *	5/2015	Du	H05B 33/0818				
						315/291			
2006/0175986	A1 *	8/2006	Lee et al.		315/312			
2008/0198615	A1 *	8/2008	Klipstein		362/538			
2009/0262988	A1 *	10/2009	Karkanias et al.		382/118			
2010/0315019	A1 *	12/2010	Hoogzaad et al.		315/291			
2012/0206946	A1 *	8/2012	Sagneri et al.		363/68			
2012/0274228	A1 *	11/2012	Szczeszynski		315/224			
2012/0313536	A1 *	12/2012	Kim et al.		315/186			
2013/0026926	A1 *	1/2013	Oh et al.		315/122			
2013/0099684	A1 *	4/2013	Cheng et al.		315/186			
2013/0147358	A1 *	6/2013	Kotowski et al.		315/122			
2013/0147360	A1 *	6/2013	Kang		315/122			
2014/0339997	A1 *	11/2014	Tsuchida	H05B 33/0815				
						315/210			

* cited by examiner




Fig. 1




Fig. 2




Fig. 3

DRIVER FOR DRIVING LED BACKLIGHT SOURCE, LED BACKLIGHT SOURCE AND LCD DEVICE

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a liquid crystal display (LCD) field, more particularly, to a driver for rapidly adjusting current flowing through a light emitting diode (LED) series circuit of a LED backlight source to a constant current, an related LED backlight source using the driver and an LCD device using the LED backlight source.

2. Description of the Prior Art

As the progress of display technology, backlighting used in the LCD device has been developed. A cold cathode fluorescent lamp (CCFL) for use in a backlight source of a traditional LCD device presents disadvantages over poor color recovery, low lighting efficiency, high discharging voltage, poor discharging characteristic under low temperature and long time period to be heated to emit light with steady grey level. Nowadays, many LED backlight sources are developed.

The LED backlight source are disposed near the LCD panel in the LCD device, so that the LCD panel shows images by using light emitted by the LED backlight source. The LED backlight source includes an LED series circuit having multiple LEDs connected in serial. A specific driver is designed for supplying driving voltage to the LED series circuit. For prolonging lifetime of each LED, driving the LED series circuit with a constant current is required. However, the conventional driver needs a longer time period which the current flowing through the LED series circuit approaches to constant value, and causes higher power consumption, slower response time and worse operating efficiency.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention is to provide a driver for driving LED backlight source, an LED backlight source and an LCD device drives the LED series circuit with a constant current to solve the problem as presented in the prior art.

In one aspect of the present invention, a driver for driving a light emitting diode backlight source comprises a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage to a light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor in series, a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit, and a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current.

In another aspect of the present invention, an LED backlight source for use in an LCD device, comprises a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage, an light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor connected in series, a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit, and a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current.

In another aspect of the present invention, an LCD device comprising an LED backlight source and an LCD panel disposed near the LED backlight source to display image by

using light emitted from the LED backlight source is provided. The LED backlight source comprises a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage, an light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor connected in series, a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit, and a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current.

Furthermore, the backlight driving circuit comprise a control module, for adjusting a duty cycle of a driving signal fed to the boost converter based on voltage applied on a negative end of the LED series circuit, to control magnitude of the boosted DC voltage; and an operational amplifier having a negative end coupled to the feedback voltage of the voltage across the resistor through the feedback circuit and a positive end coupled to a reference voltage, for outputting different voltage level signals to control the control switch according to a comparison between the reference voltage and the feedback voltage of the voltage across the resistor through the feedback circuit.

Furthermore, the boosting converter comprises a diode comprising a positive and a negative end coupled to the LED series circuit, an inductor, coupled between the inputted DC voltage and the negative of the diode, a metal oxide semiconductor (MOS) transistor comprising a drain coupled the positive end of the diode, a source coupled to ground, and a gate coupled to the control module, and a capacitor coupled between the negative end of the diode and the ground.

Furthermore, the feedback circuit comprises a differential amplifier for feeding back the voltage across the resistor to the negative end of the operational amplifier.

Furthermore, the control switch is a bipolar junction transistor comprising a collector coupled to the resistor, an emitter coupled to the ground, and a base coupled to an output of the operational amplifier of the backlight driving circuit.

In contrast to the prior art, the driver for driving LED backlight source, the LED backlight source and the LCD device drives the LED series circuit with a constant current, thereby prolonging lifetime of each LED of the LED series circuit. Furthermore, since a time period which the current flowing through the LED series circuit approaches to constant value is shorter, the driver for driving the LED backlight source has advantages over lower power consumption, faster response time and better operating efficiency.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 shows an LED backlight source for use in an LCD device according to a preferred embodiment of the present invention.

FIG. 2 shows a boost converter, a feedback circuit, a control switch and a backlight driving circuit according to a preferred embodiment of the present invention.

FIG. 3 shows an LCD device according to a preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

The accompanying drawings are included to provide a further understanding of the invention, and are incorporated in and constitute a part of this specification. The drawings illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention.

Referring to FIG. 1, a light emitting diode (LED) backlight source for use in a liquid crystal display (LCD) device is shown according to a preferred embodiment of the present invention.

As shown in FIG. 1, the LED backlight source for use in the LCD device comprises a boost converter **110**, an LED series circuit **120**, a feedback circuit **130**, a control switch **140**, and a backlight driving circuit **150**.

The boost converter **110** is used for boosting inputted direct current (DC) voltage and outputting boosted DC voltage.

The LED series circuit **120** having a plurality of LEDs **121** connected and a resistor **122** in series is used to emit light to a LCD panel. The LED series circuit **120** receives the boosted DC voltage from the boost converter **110**.

A number N (N is a positive integer) of the LEDs **121** in the LED series circuit **120** is determined by a formula as follow:

$$N \times V_d \leq V_s,$$

Where V_d indicates driving voltage of each LED **121**, and V_s indicates an output voltage of the boost converter **110**.

For example, upon the condition that $V_d=6.5V$, and $V_s=48V$, $N \leq 7$.

The feedback circuit **130** is used for feeding back voltage across the resistor **122** to the backlight driving circuit **150**.

The control switch **140**, controlled by output of the backlight driving circuit **150** depending on feedback voltage of the voltage across the resistor **122**, is used for keeping current flowing through the LED series circuit **120** in a constant current. Since the control switch **140** present advantages over faster switching, shorter time period of adjusting current flowing through the LED series circuit in a constant current, and lower power consumption, the driver for use in the LED backlight source may drive the LED series circuit faster and upgrade efficiency accordingly.

The backlight driving circuit **150** can be integrated within a backlight driving IC chip. The backlight driving circuit **150** is used for adjusting a duty cycle of a driving signal fed to the boost converter **110**, and for controlling magnitude of the boosted DC voltage. The control switch **140** is controlled by output of the backlight driving circuit **150** depending on feedback voltage of the voltage across the resistor **122**, so that the control switch **140** is used for keeping current flowing through the LED series circuit **120** in a constant current.

Referring to FIG. 2, a LED backlight source comprises a boost converter, a feedback circuit, a control switch, and a backlight driving circuit according to a preferred embodiment of the present invention.

As shown in FIG. 2, the boost converter **110** comprises an inductor **111**, a metal oxide semiconductor (MOS) transistor **112**, a diode **113**, and a capacitor **114**.

The inductor **111** is coupled between the inputted DC voltage V_{in} and a positive end of the diode **112**. A negative end of the diode **112** is coupled a positive end of the LED series circuit **120**. A drain D, a source S, and a gate G of the MOS transistor **113** are coupled to a positive end of the diode **112**, ground, and control module **151** of the backlight driving circuit **150**, respectively. The capacitor **114** is coupled between a negative end of the diode **112** and the ground.

A control module **151** of the backlight driving module **150** can adjust a duty cycle of a driving signal fed to the gate G of the MOS transistor **113** based on voltage applied on a negative end of the LED series circuit **120**, so as to control magnitude of the boosted DC voltage. For example, when the driver used in the LED backlight source begins to work, a magnitude of the boosted DC voltage outputted from the boost converter **110** is insufficient to light up the LED series circuit **120**, causing that no current flows through the LED

series circuit **120**, voltage drop across each LED **121** is smaller, and voltage applied on the negative end of the LED series circuit **120** is greater. Upon detecting the greater voltage applied on the negative end of the LED series circuit **120**, the control module **151** outputs the driving signal with a greater duty cycle to the gate G of the MOS transistor **113** to raise the magnitude of the boosted DC voltage from the boost converter **110** until the LED series circuit **120** lights up normally. At this moment, the control module **151** outputs the driving signal with a constant duty cycle to steadily supply power to the LED series circuit **120**.

In another embodiment, the control switch **140** of the LED backlight source can be a Bipolar Junction Transistor (BJT). When the BJT turns on, a voltage drop between a base and a emitter is approximately 0.7V, and current flowing through the collector c is hundred times as much as current flowing through the base b (the hundred times indicates an amplifying number of the BJT). For example, when current flowing through the base b is one mA, the current flowing through the collector c is one hundred mA. Moreover, the BJT presents advantages over easy control, short response time period and low power consumption.

In this embodiment, the BJT is connected to the LED series circuit **120** in serial. A collector c of the BJT is coupled to the resistor **122**, an emitter e of the BJT is grounded, and a base b of the BJT is coupled to an output of the operational amplifier **152** of the backlight driving circuit **150**. In this way, the current flowing through the collector c of the BJT equals to that flowing through the LED series circuit **120**.

In this embodiment, the feedback circuit **130** of the LED backlight source comprises a differential amplifier **131** which is used for measuring a precise voltage across the resistor **122**. Additionally, the differential amplifier **131** may be replaced by other electrical elements capable of measuring precise voltage across the resistor **122**, such as a subtractor.

A positive end of the differential amplifier **131** is coupled between the negative end of the multiple LEDs **121** and the resistor **122**, and a negative end of the differential amplifier **131** is coupled between the collector c of the BJT and the resistor **122**, an output end of the differential amplifier **131** is coupled to a negative end of the operational amplifier **152** of the backlight driving circuit **150**.

The voltage across the resistor **122** is feedback to the negative end of the operational amplifier **152** through the differential amplifier **131**.

In this embodiment, the backlight driving circuit **150** comprises a control module **151** and the operational amplifier **152**.

The control module **151** is coupled between the gate G of MOS transistor **113** of the boost converter **110** and the negative end of the LED series circuit **120**.

In addition to the above function, the control module **151** protects the LED series circuit **120** from malfunction upon the LED series circuit **120** lights up and emits light. For example, when the LED series circuit **120** is open-circuited or short-circuited, the control module **151** detects abnormal voltage applied on the negative end of the LED series circuit **120** and thus stops outputting driving signal to the gate G of the MOS transistor **113** so as to shut down the driver.

The negative end of the operational amplifier **152** is coupled to the output of the differential amplifier **131** of the feedback circuit **130**, the positive end of the operational amplifier **152** is coupled to a reference voltage V_c generated by the backlight driving circuit **150**, and the output of the operational amplifier **152** is coupled to the base b of the BJT. The operational amplifier **152** having a negative end coupled to the feedback voltage of the voltage across the resistor **122** through the output of the differential amplifier **131** and a

5

positive end coupled to a reference voltage V_c . The operational amplifier **152** compares the feedback voltage of the voltage across the resistor **122** with the reference voltage V_c .

When the feedback voltage of the voltage across the resistor **122** is less than the reference voltage V_c , the operational amplifier **152** outputs high voltage level to raise the current flowing through the base b of the BJT. Since the current flowing through the base b is proportional to that flowing through the collector c , the current flowing through the LED series circuit **120** increases. When the feedback voltage of the voltage across the resistor **122** is greater than the reference voltage V_c , the operational amplifier **152** outputs low voltage level to reduce the current flowing through the base b of the BJT. Since the current flowing through the base b is proportional to that flowing through the collector c , the current flowing through the LED series circuit **120** decreases. Upon the condition that the feedback voltage of the voltage across the resistor **122** equals to the reference voltage V_c , the current flowing through the base b of the BJT becomes a constant current, as well as the current flowing through the LED series circuit **120** becomes a constant current.

In this embodiment, the control switch comprises but is not limited to the BJT. In another embodiment, the control switch may be other switches with short response time period and low power consumption.

In addition, the above LED backlight source can be applied in an LCD device, as depicted in FIG. 3.

FIG. 3 shows an LCD device according to a preferred embodiment of the present invention.

As shown in FIG. 3, the LCD device comprises an LED backlight source **310** and an LCD panel **320** disposed near the LED backlight source **310**. Since the LCD panel **320** does not emit light, the LCD panel **320** displays image by using light emitted from the LED backlight source **310**. Preferably, the LED backlight source **310** can be the LED backlight source as shown in FIG. 2.

According to the present invention, the driver for driving LED backlight source, the LED backlight source and the LCD device drives the LED series circuit with a constant current, thereby prolonging lifetime of each LED of the LED series circuit. Furthermore, since a time period which the current flowing through the LED series circuit approaches to constant value is shorter, the driver for driving the LED backlight source has advantages over lower power consumption, faster response time and better operating efficiency.

Those skilled in the art will readily observe that numerous modifications and alterations of the device may be made while retaining the teachings of the invention. Accordingly, the above disclosure should be construed as limited only by the metes and bounds of the appended claims.

What is claimed is:

1. A driver for driving a light emitting diode backlight source, comprising:

a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage to a light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor in series;

a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit; and

a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current,

wherein the backlight driving circuit comprises:

a control module, coupled to one end of the LED series, for adjusting a duty cycle of a driving signal fed to the boost

6

converter based on voltage applied on a negative end of the LED series circuit, to control magnitude of the boosted DC voltage; and

an operational amplifier having an output end directly connected to the control switch, a negative end coupled to the feedback voltage of the voltage across the resistor through the feedback circuit and a positive end coupled to a reference voltage, for outputting different voltage level signals to control the control switch according to a comparison between the reference voltage and the feedback voltage of the voltage across the resistor through the feedback circuit.

2. The driver as claimed in claim **1** wherein the boosting converter comprises:

a diode comprising a positive and a negative end coupled to the LED series circuit;

an inductor, coupled between the inputted DC voltage and the positive end of the diode;

a metal oxide semiconductor (MOS) transistor comprising a drain coupled the positive end of the diode, a source coupled to ground, and a gate coupled to the control module; and

a capacitor coupled between the negative end of the diode and the ground.

3. The driver as claimed in claim **1** wherein the feedback circuit comprises a differential amplifier for feeding back the voltage across the resistor to the negative end of the operational amplifier.

4. The driver as claimed in claim **1** wherein the control switch is a bipolar junction transistor comprising a collector coupled to the resistor, an emitter coupled to the ground, and a base coupled to an output of the operational amplifier of the backlight driving circuit.

5. A LED backlight source for use in a LCD device, comprising:

a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage;

a light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor connected in series;

a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit; and

a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current,

wherein the backlight driving circuit comprises:
a control module, coupled to one end of the LED series, for adjusting a duty cycle of a driving signal fed to the boost converter based on voltage applied on a negative end of the LED series circuit, to control magnitude of the boosted DC voltage; and

an operational amplifier having an output end directly connected to the control switch, a negative end coupled to the feedback voltage of the voltage across the resistor through the feedback circuit and a positive end coupled to a reference voltage, for outputting different voltage level signals to control the control switch according to a comparison between the reference voltage and the feedback voltage of the voltage across the resistor through the feedback circuit.

6. The LED backlight source as claimed in claim **5** wherein the boosting converter comprises:

a diode comprising a positive and a negative end coupled to the LED series circuit;

an inductor, coupled between the inputted DC voltage and the negative of the diode;

7

a metal oxide semiconductor (MOS) transistor comprising a drain coupled the positive end of the diode, a source coupled to ground, and a gate coupled to the control module; and

a capacitor coupled between the negative end of the diode and the ground.

7. The LED backlight source as claimed in claim 5 wherein the feedback circuit comprises a differential amplifier for feeding back the voltage across the resistor to the negative end of the operational amplifier.

8. The LED backlight source as claimed in claim 5 wherein the control switch is a bipolar junction transistor comprising a collector coupled to the resistor, an emitter coupled to the ground, and a base coupled to an output of the operational amplifier of the backlight driving circuit.

9. A LCD device comprising a LED backlight source and a LCD panel disposed near the LED backlight source to display image by using light emitted from the LED backlight source, the LED backlight source comprising:

a boost converter, for boosting inputted direct current (DC) voltage and outputting boosted DC voltage;

a light emitting diode (LED) series circuit having a plurality of LEDs connected and a resistor connected in series;

a feedback circuit, for feeding back voltage across the resistor to a backlight driving circuit; and

a control switch controlled by output of the backlight driving circuit depending on feedback voltage of the voltage across the resistor, for keeping current flowing through the LED series circuit in a constant current,

wherein the backlight driving circuit comprises:

a control module, coupled to one end of the LED series, for adjusting a duty cycle of a driving signal fed to the boost

8

converter based on voltage applied on a negative end of the LED series circuit, to control magnitude of the boosted DC voltage; and

an operational amplifier having an output end directly connected to the control switch, a negative end coupled to the feedback voltage of the voltage across the resistor through the feedback circuit and a positive end coupled to a reference voltage, for outputting different voltage level signals to control the control switch according to a comparison between the reference voltage and the feedback voltage of the voltage across the resistor through the feedback circuit.

10. The LCD device as claimed in claim 9 wherein the boosting converter comprises:

a diode comprising a positive and a negative end coupled to the LED series circuit;

an inductor, coupled between the inputted DC voltage and the negative of the diode;

a metal oxide semiconductor (MOS) transistor comprising a drain coupled the positive end of the diode, a source coupled to ground, and a gate coupled to the control module; and

a capacitor coupled between the negative end of the diode and the ground.

11. The LCD device as claimed in claim 9 wherein the feedback circuit comprises a differential amplifier for feeding back the voltage across the resistor to the negative end of the operational amplifier.

12. The LCD device as claimed in claim 9 wherein the control switch is a bipolar junction transistor comprising a collector coupled to the resistor, an emitter coupled to the ground, and a base coupled to an output of the operational amplifier of the backlight driving circuit.

* * * * *