



US009270512B2

(12) **United States Patent**
Eliaz et al.

(10) **Patent No.:** **US 9,270,512 B2**
(45) **Date of Patent:** **Feb. 23, 2016**

(54) **NONLINEARITY COMPENSATION FOR RECEPTION OF OFDM SIGNALS**

4,797,925 A 1/1989 Lin
5,111,484 A 5/1992 Karabinis
5,131,011 A 7/1992 Bergmans et al.
5,202,903 A 4/1993 Okanoue

(71) Applicant: **MagnaCom Ltd.**, Petach Tikva (IL)

(Continued)

(72) Inventors: **Amir Eliaz**, Moshav Ben Shemen (IL);
Ilan Reuven, Ganey Tikva (IL)

FOREIGN PATENT DOCUMENTS

(73) Assignee: **MagnaCom Ltd.** (IL)

WO 2007/000495 A1 1/2007
WO 2012/092647 A1 7/2012
WO 2013030815 A1 3/2013

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS

(21) Appl. No.: **14/541,312**

Equalization: The Correction and Analysis of Degraded Signals, White Paper, Agilent Technologies, Ransom Stephens V1.0, Aug. 15, 2005 (12 pages).

(22) Filed: **Nov. 14, 2014**

(Continued)

(65) **Prior Publication Data**

US 2015/0358191 A1 Dec. 10, 2015

Primary Examiner — Leon-Viet Nguyen

Related U.S. Application Data

(74) *Attorney, Agent, or Firm* — McAndrews, Held & Malloy, Ltd.

(63) Continuation of application No. 14/298,373, filed on Jun. 6, 2014, now Pat. No. 8,891,701.

(51) **Int. Cl.**

H04L 27/26 (2006.01)
H04B 1/10 (2006.01)
H04L 1/20 (2006.01)
H04W 16/14 (2009.01)

(57) **ABSTRACT**

An electronic receiver may comprise nonlinear distortion modeling circuitry, interference estimation circuitry, and sequence estimation circuitry. The receiver may receive an orthogonal frequency division multiplexing (OFDM) symbol in the form of an electromagnetic signal. The nonlinear distortion modeling circuitry may generate a nonlinear distortion model that models nonlinear distortion introduced to the received electromagnetic signal en route to the sequence estimation circuitry. The interference estimation circuitry may estimate inter-subcarrier interference present in the received OFDM symbol based on the generated nonlinear distortion model. The estimating of the inter-subcarrier interference may comprise applying the nonlinear distortion model to one or more candidate vectors generated by the sequence estimation circuitry. The sequence estimation circuitry may sequentially process a plurality of received virtual subcarrier values of the OFDM symbol using the estimated inter-subcarrier interference.

(52) **U.S. Cl.**

CPC **H04L 27/2647** (2013.01); **H04B 1/10** (2013.01); **H04L 1/20** (2013.01); **H04W 16/14** (2013.01)

(58) **Field of Classification Search**


None
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,109,101 A 8/1978 Mitani
4,135,057 A 1/1979 Bayless, Sr. et al.

32 Claims, 6 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

5,249,200 A	9/1993	Chen et al.	8,681,889 B2	3/2014	Eliaz
5,283,813 A	2/1994	Shalvi et al.	8,731,413 B1	5/2014	Dave et al.
5,291,516 A	3/1994	Dixon et al.	8,737,458 B2	5/2014	Eliaz
5,394,439 A	2/1995	Hemmati	8,744,003 B2	6/2014	Eliaz
5,432,822 A	7/1995	Kaewell, Jr.	8,781,008 B2	7/2014	Eliaz
5,459,762 A	10/1995	Wang et al.	8,804,879 B1	8/2014	Eliaz
5,590,121 A	12/1996	Geigel et al.	8,811,548 B2	8/2014	Eliaz
5,602,507 A	2/1997	Suzuki	8,824,572 B2	9/2014	Eliaz
5,757,855 A	5/1998	Strolle et al.	8,824,599 B1	9/2014	Eliaz
5,784,415 A	7/1998	Chevillat et al.	8,824,611 B2	9/2014	Eliaz
5,818,653 A	10/1998	Park et al.	8,831,124 B2	9/2014	Eliaz
5,886,748 A	3/1999	Lee	8,842,778 B2	9/2014	Eliaz
5,889,823 A	3/1999	Agazzi et al.	8,873,612 B1	10/2014	Eliaz
5,915,213 A	6/1999	Iwatsuki et al.	8,885,698 B2	11/2014	Eliaz
5,930,309 A	7/1999	Knutson et al.	8,885,786 B2	11/2014	Eliaz
6,009,120 A	12/1999	Nobakht	8,891,701 B1	11/2014	Eliaz
6,167,079 A	12/2000	Kinnunen et al.	8,897,387 B1	11/2014	Eliaz
6,233,709 B1	5/2001	Zhang et al.	8,897,405 B2	11/2014	Eliaz
6,272,173 B1	8/2001	Hatamian	8,948,321 B2	2/2015	Eliaz
6,335,954 B1	1/2002	Bottomley et al.	8,972,836 B2	3/2015	Eliaz
6,356,586 B1	3/2002	Krishnamoorthy et al.	8,976,853 B2	3/2015	Eliaz
6,516,025 B1	2/2003	Warke et al.	8,976,911 B2	3/2015	Eliaz
6,516,437 B1	2/2003	Van Stralen et al.	8,982,984 B2	3/2015	Eliaz
6,532,256 B2	3/2003	Miller	8,989,249 B2	3/2015	Zerbe et al.
6,535,549 B1	3/2003	Scott et al.	9,003,258 B2	4/2015	Eliaz
6,591,090 B1	7/2003	Vuorio et al.	2001/0008542 A1	7/2001	Wiebke et al.
6,675,184 B1 *	1/2004	Matsui 708/322	2002/0016938 A1	2/2002	Starr
6,690,754 B1	2/2004	Haratsch et al.	2002/0123318 A1	9/2002	Lagarrigue
6,697,441 B1	2/2004	Bottomley et al.	2002/0150065 A1	10/2002	Ponnekanti
6,785,342 B1	8/2004	Isaksen et al.	2002/0150184 A1	10/2002	Hafeez et al.
6,871,208 B1	3/2005	Guo et al.	2002/0172297 A1	11/2002	Ouchi et al.
6,968,021 B1	11/2005	White et al.	2003/0016741 A1	1/2003	Sasson et al.
6,985,709 B2	1/2006	Perets	2003/0132814 A1	7/2003	Nyberg
7,158,324 B2	1/2007	Stein et al.	2003/0135809 A1	7/2003	Kim
7,190,288 B2	3/2007	Robinson et al.	2003/0210352 A1	11/2003	Fitzsimmons et al.
7,190,721 B2	3/2007	Garrett	2004/0009783 A1	1/2004	Miyoshi
7,205,798 B1	4/2007	Agarwal et al.	2004/0037374 A1	2/2004	Gonikberg
7,206,363 B2	4/2007	Hegde et al.	2004/0081259 A1	4/2004	Ammer et al.
7,215,716 B1	5/2007	Smith	2004/0086276 A1	5/2004	Lenosky
7,269,205 B2	9/2007	Wang	2004/0120409 A1	6/2004	Yasotharan et al.
7,467,338 B2	12/2008	Saul	2004/0142666 A1	7/2004	Creigh et al.
7,830,854 B1	11/2010	Sarkar et al.	2004/0170228 A1	9/2004	Vadde
7,974,230 B1	7/2011	Talley et al.	2004/0174937 A1	9/2004	Ungerboeck
8,005,170 B2	8/2011	Lee et al.	2004/0203458 A1	10/2004	Nigra
8,059,737 B2	11/2011	Yang	2004/0227570 A1	11/2004	Jackson et al.
8,175,186 B1	5/2012	Wiss et al.	2004/0240578 A1	12/2004	Thesling
8,199,804 B1	6/2012	Cheong	2004/0257955 A1	12/2004	Yamanaka et al.
8,248,975 B2	8/2012	Fujita et al.	2005/0032472 A1	2/2005	Jiang et al.
8,265,561 B2 *	9/2012	Nakamura 455/63.1	2005/0047517 A1	3/2005	Georgios et al.
8,351,536 B2	1/2013	Mazet et al.	2005/0089125 A1 *	4/2005	Zhidkov 375/346
8,422,589 B2	4/2013	Golitschek Edler Von Elbwart et al.	2005/0123077 A1	6/2005	Kim
8,432,987 B2	4/2013	Siti et al.	2005/0135472 A1	6/2005	Higashino
8,498,591 B1	7/2013	Qian et al.	2005/0163252 A1	7/2005	McCallister et al.
8,526,523 B1	9/2013	Eliaz	2005/0193318 A1	9/2005	Okumura et al.
8,548,072 B1	10/2013	Eliaz	2005/0220218 A1	10/2005	Jensen et al.
8,548,089 B2	10/2013	Agazzi et al.	2005/0265470 A1	12/2005	Kishigami et al.
8,548,097 B1	10/2013	Eliaz	2005/0276317 A1	12/2005	Jeong et al.
8,553,821 B1	10/2013	Eliaz	2006/0067396 A1	3/2006	Christensen
8,559,494 B1	10/2013	Eliaz	2006/0109780 A1	5/2006	Fechtler
8,559,496 B1	10/2013	Eliaz	2006/0109935 A1	5/2006	McQueen et al.
8,559,498 B1	10/2013	Eliaz	2006/0171489 A1	8/2006	Ghosh et al.
8,565,363 B1	10/2013	Eliaz	2006/0203943 A1	9/2006	Scheim et al.
8,566,687 B1	10/2013	Eliaz	2006/0239339 A1	10/2006	Brown et al.
8,571,131 B1	10/2013	Eliaz	2006/0245765 A1	11/2006	Elahmadi et al.
8,571,146 B1	10/2013	Eliaz	2006/0280113 A1	12/2006	Huo
8,572,458 B1	10/2013	Eliaz	2007/0047121 A1	3/2007	Eleftheriou et al.
8,582,637 B1	11/2013	Eliaz	2007/0092017 A1	4/2007	Abedi
8,599,914 B1	12/2013	Eliaz	2007/0098059 A1	5/2007	Ives et al.
8,605,832 B1	12/2013	Eliaz	2007/0098090 A1	5/2007	Ma et al.
8,665,941 B1	3/2014	Eliaz	2007/0098116 A1	5/2007	Kim et al.
8,665,992 B1	3/2014	Eliaz	2007/0110177 A1	5/2007	Molander et al.
8,666,000 B2	3/2014	Eliaz	2007/0110191 A1	5/2007	Kim et al.
8,675,769 B1	3/2014	Eliaz	2007/0127608 A1	6/2007	Scheim et al.
8,675,782 B2	3/2014	Eliaz	2007/0140330 A1	6/2007	Allpress et al.
			2007/0189404 A1	8/2007	Baum et al.
			2007/0213087 A1	9/2007	Laroia et al.
			2007/0230593 A1	10/2007	Eliaz et al.
			2007/0258517 A1	11/2007	Rollings et al.
			2007/0291719 A1	12/2007	Demirhan et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2008/0002789 A1 1/2008 Jao et al.
 2008/0049598 A1 2/2008 Ma et al.
 2008/0080644 A1 4/2008 Batruni
 2008/0130716 A1 6/2008 Cho et al.
 2008/0130788 A1 6/2008 Copeland
 2008/0159377 A1 7/2008 Allpress et al.
 2008/0207143 A1 8/2008 Skarby et al.
 2008/0260985 A1 10/2008 Shirai et al.
 2009/0003425 A1 1/2009 Shen et al.
 2009/0028234 A1 1/2009 Zhu
 2009/0041105 A1* 2/2009 Okazaki 375/227
 2009/0058521 A1 3/2009 Fernandez
 2009/0075590 A1 3/2009 Sahinoglu et al.
 2009/0086808 A1 4/2009 Liu et al.
 2009/0115513 A1 5/2009 Hongo et al.
 2009/0122854 A1 5/2009 Zhu et al.
 2009/0137212 A1 5/2009 Belotserkovsky
 2009/0185612 A1 7/2009 McKown
 2009/0213908 A1 8/2009 Bottomley
 2009/0220034 A1 9/2009 Ramprasad et al.
 2009/0245226 A1 10/2009 Robinson et al.
 2009/0245401 A1 10/2009 Chrabieh et al.
 2009/0290620 A1 11/2009 Tzannes et al.
 2009/0323841 A1 12/2009 Clerckx et al.
 2010/0002692 A1 1/2010 Bims
 2010/0034253 A1 2/2010 Cohen
 2010/0039100 A1 2/2010 Sun et al.
 2010/0062705 A1 3/2010 Rajkotia et al.
 2010/0074349 A1 3/2010 Hyllander et al.
 2010/0158085 A1 6/2010 Khayrallah
 2010/0166050 A1 7/2010 Aue
 2010/0172309 A1 7/2010 Forenza et al.
 2010/0202505 A1 8/2010 Yu et al.
 2010/0202507 A1 8/2010 Allpress et al.
 2010/0203854 A1 8/2010 Yu et al.
 2010/0208774 A1 8/2010 Guess et al.
 2010/0208832 A1 8/2010 Lee et al.
 2010/0215107 A1 8/2010 Yang
 2010/0220825 A1 9/2010 Dubuc et al.
 2010/0278288 A1 11/2010 Panicker et al.
 2010/0283540 A1 11/2010 Davies
 2010/0284481 A1 11/2010 Murakami et al.
 2010/0309796 A1 12/2010 Khayrallah
 2010/0329325 A1 12/2010 Mobin et al.
 2011/0051864 A1 3/2011 Chalia et al.
 2011/0064171 A1 3/2011 Huang et al.
 2011/0069791 A1 3/2011 He
 2011/0074500 A1 3/2011 Bouillet et al.
 2011/0074506 A1 3/2011 Kleider et al.
 2011/0075745 A1* 3/2011 Kleider et al. 375/260
 2011/0090986 A1 4/2011 Kwon et al.
 2011/0103455 A1* 5/2011 Forrester et al. 375/232
 2011/0134899 A1 6/2011 Jones, IV et al.
 2011/0150064 A1 6/2011 Kim et al.
 2011/0164492 A1 7/2011 Ma et al.
 2011/0170630 A1 7/2011 Silverman et al.
 2011/0182329 A1 7/2011 Wehinger
 2011/0188550 A1 8/2011 Wajcer et al.
 2011/0228869 A1 9/2011 Barsoum et al.
 2011/0243266 A1 10/2011 Roh
 2011/0249709 A1 10/2011 Shiue et al.
 2011/0275338 A1 11/2011 Seshadri et al.
 2011/0310823 A1 12/2011 Nam et al.
 2011/0310978 A1 12/2011 Wu et al.
 2012/0025909 A1 2/2012 Jo et al.
 2012/0027132 A1 2/2012 Rouquette
 2012/0051464 A1 3/2012 Kamuf et al.
 2012/0106617 A1 5/2012 Jao et al.
 2012/0120990 A1* 5/2012 Koren et al. 375/219
 2012/0163489 A1 6/2012 Ramakrishnan
 2012/0177138 A1 7/2012 Chrabieh et al.
 2012/0207248 A1 8/2012 Ahmed et al.
 2013/0028299 A1 1/2013 Tsai
 2013/0044877 A1 2/2013 Liu et al.
 2013/0077563 A1 3/2013 Kim et al.

2013/0121257 A1 5/2013 He et al.
 2013/0343480 A1 12/2013 Eliaz
 2013/0343487 A1 12/2013 Eliaz
 2014/0036986 A1 2/2014 Eliaz
 2014/0056387 A1 2/2014 Asahina
 2014/0098841 A2 4/2014 Song et al.
 2014/0098907 A1 4/2014 Eliaz
 2014/0098915 A1 4/2014 Eliaz
 2014/0105267 A1 4/2014 Eliaz
 2014/0105268 A1 4/2014 Eliaz
 2014/0105332 A1 4/2014 Eliaz
 2014/0105334 A1 4/2014 Eliaz
 2014/0108892 A1 4/2014 Eliaz
 2014/0133540 A1 5/2014 Eliaz
 2014/0140388 A1 5/2014 Eliaz
 2014/0140446 A1 5/2014 Eliaz
 2014/0146911 A1 5/2014 Eliaz
 2014/0161158 A1 6/2014 Eliaz
 2014/0161170 A1 6/2014 Eliaz
 2014/0198255 A1 7/2014 Kegasawa
 2014/0241477 A1 8/2014 Eliaz
 2014/0247904 A1 9/2014 Eliaz
 2014/0269861 A1 9/2014 Eliaz
 2014/0286459 A1 9/2014 Eliaz
 2014/0301507 A1 10/2014 Eliaz
 2014/0321525 A1 10/2014 Eliaz
 2014/0328428 A1 11/2014 Eliaz
 2014/0376358 A1 12/2014 Eder et al.
 2015/0010108 A1 1/2015 Eliaz
 2015/0049843 A1 2/2015 Reuven et al.
 2015/0055722 A1 2/2015 Eliaz
 2015/0063499 A1 3/2015 Eliaz
 2015/0070089 A1 3/2015 Eliaz
 2015/0071389 A1 3/2015 Eliaz
 2015/0078491 A1 3/2015 Eliaz

OTHER PUBLICATIONS

Modulation and Coding for Linear Gaussian Channels, G. David Forney, Jr., and Gottfried Ungerboeck, IEEE Transactions of Information Theory, vol. 44, No. 6, Oct. 1998 pp. 2384-2415 (32 pages).
 Intuitive Guide to Principles of Communications, www.complextoreal.com, Inter Symbol Interference (ISI) and Root-raised Cosine (RRC) filtering, (2002), pp. 1-23 (23 pages).
 Chan, N., "Partial Response Signaling with a Maximum Likelihood Sequence Estimation Receiver" (1980). Open Access Dissertations and Theses. Paper 2855, (123 pages).
 The Viterbi Algorithm, Ryan, M.S. and Nudd, G.R., Department of Computer Science, Univ. of Warwick, Coventry, (1993) (17 pages).
 R. A. Gibby and J. W. Smith, "Some extensions of Nyquist's telegraph transmission theory," Bell Syst. Tech. J., vol. 44, pp. 1487-1510, Sep. 1965.
 J. E. Mazo and H. J. Landau, "On the minimum distance problem for faster-than-Nyquist signaling," IEEE Trans. Inform. Theory, vol. 34, pp. 1420-1427, Nov. 1988.
 D. Hajela, "On computing the minimum distance for faster than Nyquist signaling," IEEE Trans. Inform. Theory, vol. 36, pp. 289-295, Mar. 1990.
 G. Ungerboeck, "Adaptive maximum-likelihood receiver for carrier modulated data-transmission systems," IEEE Trans. Commun., vol. 22, No. 5, pp. 624-636, May 1974.
 G. D. Forney, Jr., "Maximum-likelihood sequence estimation of digital sequences in the presence of intersymbol interference," IEEE Trans. Inform. Theory, vol. 18, No. 2, pp. 363-378, May 1972.
 A. Duel-Hallen and C. Heegard, "Delayed decision-feedback sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989.
 M. V. Eyuboglu and S. U. Qureshi, "Reduced-state sequence estimation with set partitioning and decision feedback," IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988.
 W. H. Gerstaecker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep. 18-21, 2000.

(56)

References Cited

OTHER PUBLICATIONS

- W. H. Gerstaecker, F. Obernosterer, R. Meyer, and J. B. Huber, "On prefilter computation for reduced-state equalization," *IEEE Trans. Wireless Commun.*, vol. 1, No. 4, pp. 793-800, Oct. 2002.
- Joachim Hagenauer and Peter Hoeher, "A Viterbi algorithm with soft-decision outputs and its applications," in *Proc. IEEE Global Telecommunications Conference 1989*, Dallas, Texas, pp. 1680-1686, Nov. 1989.
- S. Mita, M. Izumita, N. Doi, and Y. Eto, "Automatic equalizer for digital magnetic recording systems" *IEEE Trans. Magn.*, vol. 25, pp. 3672-3674, 1987.
- E. Biglieri, E. Chiaberto, G. P. Maccone, and E. Viterbo, "Compensation of nonlinearities in high-density magnetic recording channels," *IEEE Trans. Magn.*, vol. 30, pp. 5079-5086, Nov. 1994.
- W. E. Ryan and A. Gutierrez, "Performance of adaptive Volterra equalizers on nonlinear magnetic recording channels," *IEEE Trans. Magn.*, vol. 31, pp. 3054-3056, Nov. 1995.
- X. Che, "Nonlinearity measurements and write precompensation studies for a PRML recording channel," *IEEE Trans. Magn.*, vol. 31, pp. 3021-3026, Nov. 1995.
- O. E. Agazzi and N. Sheshadri, "On the use of tentative decisions to cancel intersymbol interference and nonlinear distortion (with application to magnetic recording channels)," *IEEE Trans. Inform. Theory*, vol. 43, pp. 394-408, Mar. 1997.
- Miao, George J., *Signal Processing for Digital Communications*, 2006, Artech House, pp. 375-377.
- Xiong, Fuqin. *Digital Modulation Techniques*, Artech House, 2006, Chapter 9, pp. 447-483.
- Faulkner, Michael, "Low-Complex ICI Cancellation for Improving Doppler Performance in OFDM Systems", *Center for Telecommunication and Microelectronics*, 1-4244-0063-5/06/\$2000 (c) 2006 IEEE. (5 pgs).
- Stefano Tomasin, et al. "Iterative Interference Cancellation and Channel Estimation for Mobile OFDM", *IEEE Transactions on Wireless Communications*, vol. 4, No. 1, Jan. 2005, pp. 238-245.
- Int'l Search Report and Written Opinion for PCT/IB2013/01866 dated Mar. 21, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/001923 dated Mar. 21, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/001878 dated Mar. 21, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/002383 dated Mar. 21, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/01860 dated Mar. 21, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/01970 dated Mar. 27, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/01930 dated May 15, 2014.
- Int'l Search Report and Written Opinion for PCT/IB2013/02081 dated May 22, 2014.
- Ai-Dhahir, Naofal et al., "MMSE Decision-Feedback Equalizers: Finite-Length Results" *IEEE Transactions on Information Theory*, vol. 41, No. 4, Jul. 1995.
- Cioffi, John M. et al., "MMSE Decision-Feedback Equalizers and Coding—Part I: Equalization Results" *IEEE Transactions on Communications*, vol. 43, No. 10, Oct. 1995.
- Eyuboglu, M. Vedat et al., "Reduced-State Sequence Estimation with Set Partitioning and Decision Feedback" *IEEE Transactions on Communications*, vol. 36, No. 1, Jan. 1988.
- Khaled M. Gharaibeh, *Nonlinear Distortion in Wireless Systems*, 2011, John Wiley & Sons, 2nd Edition, chapter 3, pp. 59-81.
- Forney, G. David Jr., "Coset Codes—Part I: Introduction and Geometrical Classification" *IEEE Transactions on Information Theory*, vol. 34, No. 5, Sep. 1988.
- Prlja, Adnan et al., "Receivers for Faster-than-Nyquist Signaling with and Without Turbo Equalization".
- Int'l Search Report and Written Opinion for PCT/IB2014/002449 dated Mar. 12, 2015.
- Digital predistortion of power amplifiers for wireless applications (Doctoral dissertation, Georgia Institute of Technology). Retrieved from the internet <<http://http://202.28.199.34/multim/3126235.pdf>> Ding, L. Mar. 31, 2005.
- Digital predistortion for power amplifiers using separable functions. *Signal Processing*, *IEEE Transactions on*, 58(8), 4121-4130. Retrieved from the internet <<http://arxiv.org/ftp/arxiv/papers/1306/1306.0037.pdf>> Jiang, H., & Wilford, P.A. Aug. 8, 2010.
- Digital predistortion linearization methods for RF power amplifiers. *Teknillinen korkeakoulu*. Retrieved from the Internet <<http://lib.tkk.fi/Diss/2008/isbn9789512295463/isbn9789512295463.pdf>> Teikari I. Sep. 30, 2008.
- Kayhan, F., et al., *Joint Signal-Labeling Optimization for Pragmatic Capacity under Peak-Power Constraint*, 978-1-4244-5637, 2010.
- Kayhan, F., et al., *Constellation Design for Transmission over Non-linear Satellite Channels*, Oct. 5, 2012.
- Kayhan, F., et al., *Signal and Labeling Optimization for Non-Linear and Phase Noise Channels*, Department of Electronics and Telecommunications.

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4A




FIG. 4B




FIG. 6




FIG. 5




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 7D

NONLINEARITY COMPENSATION FOR RECEPTION OF OFDM SIGNALS

CLAIM OF PRIORITY

This application is a continuation of U.S. patent application Ser. No. 14/298,373, filed Jun. 6, 2014 (now patented as U.S. Pat. No. 8,891,701).

INCORPORATION BY REFERENCE

The entirety of U.S. Pat. No. 8,781,008 titled “Highly-Spectrally-Efficient Transmission Using Orthogonal Frequency Division Multiplexing” is hereby incorporated herein by reference.

BACKGROUND

Limitations and disadvantages of conventional approaches to reception of signals in the presence of nonlinear distortion will become apparent to one of skill in the art, through comparison of such approaches with some aspects of the present method and system set forth in the remainder of this disclosure with reference to the drawings.

BRIEF SUMMARY

Methods and systems are provided for nonlinearity compensation for reception of OFDM signals, substantially as illustrated by and/or described in connection with at least one of the figures, as set forth more completely in the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 shows an example transmitter operable to generate inter-carrier correlated (ICI) orthogonal frequency divisions multiplexed (OFDM) signals.

FIG. 2 shows an example receiver operable to recover information from received ICI OFDM signals.

FIG. 3 shows an example implementation of the reduced state sequence estimation (RSSE) circuitry of FIG. 2.

FIG. 4A shows a first example implementation of the nonlinear distortion model determination circuitry of FIG. 2.

FIG. 4B shows a second example implementation of the nonlinear distortion model determination circuitry of FIG. 2.

FIG. 5 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a generalized third-order nonlinear distortion model.

FIG. 6 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a digital clipping nonlinear distortion model.

FIGS. 7A-7D show an example implementation in which the receiver of FIG. 2 performs two or more iterations over the subcarriers of an OFDM symbol to recover the data of the OFDM symbol in the presence of nonlinear distortion.

DETAILED DESCRIPTION

As utilized herein the terms “circuits” and “circuitry” refer to physical electronic components (i.e. hardware) and any software and/or firmware (“code”) which may configure the hardware, be executed by the hardware, and or otherwise be associated with the hardware. As used herein, for example, a particular processor and memory may comprise a first “circuit” when executing a first one or more lines of code and may comprise a second “circuit” when executing a second one or more lines of code. As utilized herein, “and/or” means any

one or more of the items in the list joined by “and/or”. As an example, “x and/or y” means any element of the three-element set $\{(x), (y), (x, y)\}$. As another example, “x, y, and/or z” means any element of the seven-element set $\{(x), (y), (z), (x, y), (x, z), (y, z), (x, y, z)\}$. As utilized herein, the terms “e.g.,” and “for example” set off lists of one or more non-limiting examples, instances, or illustrations. As utilized herein, circuitry is “operable” to perform a function whenever the circuitry comprises the necessary hardware and code (if any is necessary) to perform the function, regardless of whether performance of the function is disabled, or not enabled, by some user-configurable setting.

FIG. 1 shows an example transmitter operable to generate inter-carrier correlated (ICI) orthogonal frequency divisions multiplexed (OFDM) signals. Shown is a transmitter that comprises encoder circuitry **102**, mapper circuitry **104**, inter-subcarrier interference (ICI) generation circuitry **106**, inverse fast Fourier transform (IFFT) circuit **108**, and analog front end (AFE) **110**.

The encoder circuitry **102** receives a vector of bits \underline{B}' which are the bits of a particular OFDM symbol. The encoder circuitry **102** converts the bits \underline{B}' , to a vector of bits \underline{B} , in accordance with a forward error correction (FEC) algorithm (e.g., Reed-Solomon, Low-Density Parity Check, Turbo, and/or the like).

The mapper circuit **104**, is operable to map the vector \underline{B} to a vector \underline{A} according to a selected modulation scheme. For example, for a quadrature amplitude modulation (QAM) scheme having an alphabet size of M (M-QAM), the mapper may map each $\log_2(M)$ bits of \underline{B} to a value represented as a complex number and/or as in-phase (I) and quadrature-phase (Q) components. Although M-QAM is used for illustration in this disclosure, aspects of this disclosure are applicable to any modulation scheme (e.g., pulse amplitude modulation (PAM), amplitude shift keying (ASK), phase shift keying (PSK), frequency shift keying (FSK), etc.). Additionally, points of the M-QAM constellation may be regularly spaced (“on-grid”) or irregularly spaced (“off-grid”). Furthermore, the constellation used by the mapper **104** may be optimized for best bit-error rate (BER) performance (or adjusted to achieve a target BER) that is related to log-likelihood ratio (LLR) and to optimizing mean mutual information bit (MMIB) (or achieving a target MMIB).

The ISC generation circuitry **106** is operable to process \underline{A} to generate a vector \underline{C} . The elements of \underline{A} are referred to herein as “virtual subcarrier values” of the particular OFDM symbol and the elements of \underline{C} are referred to herein as the corresponding “physical subcarrier values” of the particular OFDM symbol, where: the vector \underline{A} comprises N values, the vector \underline{C} comprises P values, N and P are positive integers, $N \geq 2$, and $N \geq P$. The N elements of \underline{A} are represented herein as $a_1 : a_N$, with any particular one of the values represented as a_n . The P elements of \underline{C} are represented herein as $c_1 : c_P$, with any particular one of the values represented as c_p . In an example implementation, the processing performed by the circuitry **106** may comprise cyclic filtering and/or decimation such that each of the ISC values of \underline{C} depends on a plurality (perhaps all) of the elements of \underline{A} . In an example implementation, the circuitry **106** may be similar to, or the same as, circuits **104** and **106** of the above incorporated United States Patent Application Publication US2013/0343473. In an example implementation, Δ (an integer) pilot symbols may be inserted at the IFFT and the total number of physical subcarriers may be $P + \Delta$, where P is thus the quantity of data-carrying subcarriers.

The inverse fast Fourier transform (IFFT) circuit **108** is operable to convert the physical subcarrier value vector \underline{C} (of

length P) to a corresponding vector of P time-domain samples (i.e., the time-domain representation of the particular OFDM symbol).

The analog front end (AFE) **110** is operable to convert the P time-domain values output by IFFT **108** to an analog representation, upconvert the resulting analog signal, and amplify the upconverted signal for transmission onto a channel **112**. Thus, the transmitter front-end **118** may comprise, for example, a digital-to-analog converter (DAC), mixer, and/or power amplifier. The front-end **118** may introduce nonlinear distortion and/or phase noise (and/or other non-idealities) to the transmitted signal **117**. The nonlinear distortion introduced by the circuit **118** may be represented as NL_{Tx} which may be, for example, a polynomial, or an exponential (e.g., Rapp model). The model of the nonlinear distortion may incorporate memory (e.g., Volterra series). The transmitted values \underline{C} , after being converted to the time domain, experiencing the nonlinear distortion introduced by the AFE **110**, and passing through the channel **112** (which may also introduce nonlinear distortion and/or noise), emerge as a signal **113**.

FIG. 2 shows an example receiver operable to recover information from received ICI OFDM signals. The receiver comprises an analog front-end **202**, time domain preprocessing circuitry **204**, a fast Fourier transform (FFT) circuit **208**, frequency domain preprocessing circuitry **206**, nonlinear distortion model determination circuitry **214**, interference estimation circuitry **210**, and reduced state sequence estimation (RSSE) circuitry **212**.

The AFE **202** is operable to process the signal **113** corresponding to a particular OFDM signal to a vector of \underline{S}' samples of the particular OFDM symbol. Such processing may comprise, amplification, downconversion (to IF or baseband), and analog-to-digital conversion. Thus, the receiver front-end **202** may comprise, for example, a low-noise amplifier, a mixer, and/or an analog-to-digital converter. The AFE **202** may, for example, sample the received signal **113** P times per OFDM symbol period resulting in a \underline{S}' of length P (where pilot symbols are used, the AFE **202** may sample P+ Δ times per OFDM symbol). Due to non-idealities, the receiver front-end **202** may introduce nonlinear distortion and/or phase noise to the signal \underline{S}' . The nonlinear distortion introduced by the front end **202** may be represented as NL_{Rx} which may be, for example, a polynomial, or an exponential (e.g., Rapp model). The model of the nonlinear distortion may incorporate memory (e.g., Volterra series).

The time domain preprocessing circuitry **204** is operable to perform time-domain processing of the samples \underline{S}' to generate received physical subcarrier value vector \underline{S} . Such processing may include, for example, timing acquisition, phase correction, frequency correction, decimation, DC removal, IQ mismatch correction, filtering, windowing, removal of pilot symbols, cyclic prefix removal, and/or the like.

The FFT **208** is operable to convert the time-domain physical subcarrier value vector \underline{S} (of length P) to a corresponding vector of P frequency-domain samples (i.e., convert the time-domain representation of \underline{S} to the frequency-domain representation of \underline{S}).

The frequency domain preprocessing circuitry **206** is operable to perform frequency domain processing of the output of the FFT **208** to generate a vector \underline{Y} , which is a vector of N received virtual subcarrier values. Such processing may include, for example, performing the inverse of the ICI generation circuitry **106** (FIG. 1), and performing per-subcarrier equalization. The elements of \underline{Y} are represented herein as $y_1:y_N$, with any particular one of the values represented as y_n .

The RSSE circuitry **212** is operable to perform reduced state sequence estimation on the vector \underline{Y} to generate a vector $\hat{\underline{A}}$ which is the receiver's decision vector ("best guess" as to the transmitted virtual subcarrier value vector \underline{A}). Details of an example implementation of RSSE circuitry **212** are described below with reference to FIG. 3.

The nonlinear distortion model determination circuitry **214** is operable to determine a model, NL, that represents/enables reproduction of (to a desired accuracy) the nonlinear distortion experienced by the signal \underline{S}' in the transmitter, the channel, and/or the receiver. In an example implementation, the nonlinear distortion introduced by the AFE **110** of the transmitter may be dominant and NL may be a representation of NL_{Tx} . The nonlinear distortion model, NL, may be, for example, a logical and/or mathematical expression, a look-up table, and/or any other suitable representation of the nonlinear distortion. Any one or more of a variety of model types may be used for NL, with each model type being characterized by one or more parameters. The model type and/or parameter values may be communicated directly by the transmitter (e.g., during handshaking) and/or may be learned by the receiver by processing signals received from the transmitter (e.g., selection of the model type and/or training of the parameter values may be based on preambles sent by the transmitter). In an example implementation, NL may comprise an AM/AM parameter whose value is dependent on transmitted signal strength, and an AM/PM parameter whose value is dependent on transmitted signal strength. In such an example implementation, received signal strength may be used as a proxy for transmitted signal strength and the received signal strength may be applied to the look-up table to determine appropriate values of the AM/AM and AM/PM parameters.

The interference estimation circuitry **210** is operable to estimate the interference, \underline{E} , present in the received virtual subcarrier values \underline{Y} , based on \underline{Y} and based on NL. Details of example implementations of **210** are described below with reference to FIGS. 5 and 6.

FIG. 3 shows an example implementation of the reduced state sequence estimation (RSSE) circuitry of FIG. 2. The example RSSE circuitry **212** shown in FIG. 3 comprises nonlinear distortion circuitry **302**, metric calculation circuitry **306**, survivor selection circuitry **308**, buffering circuitry **310**, successor generation circuitry **312**, and buffering circuitry **314**. FIG. 2 depicts the RSSE circuitry **212** processing received virtual subcarrier value having index n (where $1 \leq n \leq N$) of a particular OFDM symbol.

The buffer circuitry **310** is operable to, upon completion of processing a particular received virtual subcarrier value of the OFDM symbol being processed, latch the selected survivor vectors such that those survivors are available for processing the next received virtual subcarrier value of the OFDM symbol. Thus, in FIG. 3, which shows processing of received virtual subcarrier value having index n, the survivors selected upon completion of processing the received virtual subcarrier value having index n-1 ($\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$) are latched by the buffer **310** and output to the successor generation circuitry **312**. Each survivor $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ comprises up to n elements corresponding to one or more of subcarriers 0 through n-1. Elements of survivor $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ are represented herein as $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, where D is the memory depth of the RSSE circuitry.

The successor generation circuitry **312** is operable to extend each of the M survivors from the previous iteration, $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, to K successors, resulting in successors $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$. Elements of successor vector $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ are represented herein

as $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, where $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ is the element by which survivor $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ was extended to create successor $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$. The number of successors generated thus depends on the number of survivors, M, retained for each received virtual subcarrier value and the number of possible symbol transmitted virtual subcarrier values for which it is desired to search. Higher values of M and K may achieve improved results at the expense of increased size and complexity. In an example implementation, the value of K may be chosen to be the size of the constellation used by mapper 104 (FIG. 1) (e.g., for 64QAM K may be set to 64) such that each survivor is extended by each possible transmitted virtual subcarrier value.

The nonlinear distortion circuitry 302 is operable to, for each of the M×K successors $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, generate a candidate vector $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ by introducing nonlinear distortion to the successor $\underline{G}_n^{m,k}$. Elements of candidate vector $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ are represented herein as $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, where $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ is the estimated constellation symbol of the (m,k) candidate for subcarrier index n, $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ is the estimated constellation symbol of the (m,k) candidate for subcarrier index n-1, and so on (where n is less than D, D-n elements may be values from an initialization of the RSSE circuitry).

The nonlinear distortion introduced to each successor is determined based on NL from the nonlinear distortion model determination circuitry 214 (FIGS. 1, 4A, and 4B). In this manner, the circuitry 302 attempts to reproduce (to desired/necessary accuracy) the nonlinear distortion experienced by the signal 113 (or \underline{S}' where nonlinear distortion of the AFE 202 is accounted for in NL)).

The metric calculation circuitry 306 is operable to calculate branch a path metric, $\text{PM}_n^{m,k}$ for each of the candidates $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, and output the path metrics to the survivor selection circuitry 308. The path metric for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ may be calculated as $\text{PM}_n^{m,k}=\text{BM}_n^{m,k}+\text{PM}_{n-1}^{m,k}$, where $\text{BM}_n^{m,k}$ is the branch metric for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$. The branch metric for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ may be calculated based on \underline{F} . The manner in which the branch metric is calculated varies for different implementations. Some example branch metric calculations are described below with reference to FIGS. 5, 6, 7B, 7C, and 7D.

The survivor selection circuitry 308 is operable to compare the path metrics for each of the candidates $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ and select the M best candidates (corresponding to the M best path metrics) as the survivors $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$.

The buffer circuitry 314 is operable to buffer samples of signal \underline{Y} and/or initialization samples and may shift the samples out as signal \underline{Y}_n . For example, the first n elements of \underline{Y}_n may be equal to the first n elements of \underline{Y} and the remaining (D-n) elements of \underline{Y}_n may be known values used for initialization of the RSSE circuitry.

FIG. 4A shows a first example implementation of the nonlinear distortion model determination circuitry of FIG. 2. The example implementation of nonlinear distortion model determination circuitry 214 shown in FIG. 4A comprises circuitry 402 operable to estimate the nonlinear distortion experienced by \underline{S} (the output of time-domain processing circuitry 204 in FIG. 2) in the time domain. The estimation of the nonlinear distortion may be based on, for example, preambles present in \underline{S}' , the received signal strength of 113, and/or based on control information (e.g., a model type best suited for the transmitter from which signal 113 originated, initial nonlinear distortion model parameters, power level at signal 113 was transmitted,

and/or the like) communicated to the receiver (e.g., during handshaking and/or in frame headers of \underline{S}). Once the time domain nonlinear distortion model, T, has been determined, it is passed to circuitry 404 which translates it to the frequency domain representation, NL. The frequency domain representation NL is then output by the circuitry 214.

FIG. 4B shows a second example implementation of the nonlinear distortion model determination circuitry of FIG. 2. In the example implementation of FIG. 4B, the frequency domain NL is determined in the frequency domain directly from \underline{Y} .

FIG. 5 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a generalized third-order nonlinear distortion model. The example implementation of the interference estimation circuitry 210 in FIG. 5 comprises interference calculation circuitry 502.

The notation $f_n^{m,k}$ represents an estimate of the aggregate interference present in the received virtual subcarrier value having index n for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$. The aggregate interference estimate may, for example, be a complex number representing the magnitude and phase of the interference. The notation \underline{F} represents the vector (of length M×K) of aggregate interference estimates for all of the candidates $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ (i.e., $\underline{F}=\underline{f}_n^{1,1}:\underline{f}_n^{M,K}$). In some instances, the estimated aggregate interference may depend only on n (the received virtual subcarrier index) and may be the same for all of the candidates $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ (i.e., each of the estimates $f_n^{1,1}:f_n^{M,K}$ takes on the same value), but in other instances, the interference estimates may differ among the candidates $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$.

In a first variation, the aggregate interference estimate for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ may be calculated exhaustively taking into account each of the other N-1 virtual subcarriers. This exhaustive calculation may comprise calculating $f_n^{m,k}=\alpha\sum_{i=0}^{N-1}\sum_{j=0}^{N-1}z_i\cdot z_j^*\cdot z_{n-i+j}$, where: α is a parameter (or vector of parameters) determined by nonlinear model determination block 208, $z_i=y_i$ for $i\geq n$; $z_i=g_i^{m,k}$ for $i<n$; $z_j=y_j$ for $j\geq n$, $z_j=g_j^{m,k}$ for $j<n$, y_i is a received virtual subcarrier value for subcarrier having index i, y_j is the received virtual subcarrier value for subcarrier having index j, $g_i^{m,k}$ is the decision for the subcarrier having index i for the (m,k) candidate, where $g_i^{m,k}$ is the decision the subcarrier having index j for the (m,k) candidate.

In a second variation, the aggregate interference estimate for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$ may be calculated taking into account only a selected subset of the other N-1 virtual subcarriers. This may reduce the amount of calculations necessary. This selective calculation may comprise calculating $f_n^{m,k}=\alpha\sum_{i\in Q}\sum_{j\in Q}z_i\cdot z_j^*\cdot z_{n-i+j}$, where α is a parameter (or vector of parameters) determined by nonlinear model determination block 208, Q is a subset of the set 1:N; $z_x=y_x$ for $x\geq n$, $z_x=g_x^{m,k}$ for $x<n$, and x is used as a generic for i and j. For example, only indexes of virtual subcarriers having power above a determined threshold may be included in the set Q (based on the assumption that low-energy virtual subcarriers will experience relatively little nonlinear distortion and thus not contribute a lot of interference). The smaller the size of Q relative to the size of N, the more this selective calculation will reduce computational complexity/overhead.

Thus, common to both variations above is that, when calculating the interference present in received virtual subcarrier having index n due to another virtual subcarrier having index x for candidate $\hat{\underline{A}}_{n-1}^1:\hat{\underline{A}}_{n-1}^M$, if a decision as to a transmitted virtual subcarrier having index x has already been generated by the RSSE circuitry (i.e., $x<n$), then the decided value of x

(i.e., $g_x^{m,k}$) is used in the calculation, but if a decision as to a transmitted virtual subcarrier having index x has not yet been generated by the RSSE circuitry (i.e., $x > n$), then the received virtual subcarrier value having index x (i.e., y_x) is used for the calculation (based on the assumption that the interference in that received signal is relatively small compared to the desired signal and, therefore, error introduced is tolerable).

Once the estimated aggregate interference $f_n^{m,k}$ has been determined, the branch metric (represented as $BM_n^{m,k}$) for candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ may be calculated. In an example implementation, the following expression may be used:

$$BM_n^{m,k} = |y_n - \hat{A}_{n-1}^1 : \hat{A}_{n-1}^M - f_n^{m,k}|^2.$$

FIG. 6 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a digital clipping nonlinear distortion model. In FIG. 6, the interference estimation circuitry 210 comprises clipped subcarrier determination circuit 602 and interference estimation circuit 604.

The clipped subcarrier determination circuit 602 is operable to determine which transmitted virtual subcarriers values were digitally clipped in the transmitter during the transmission that resulted in signal 113. The circuit 602 then outputs the indexes of the clipped subcarriers to the circuit 604 as vector \underline{I} . In an example implementation, the transmitter may directly send such information (e.g., in a header) and the circuit 602 may simply extract the information. In another example implementation, the circuit 602 may determine which transmitted virtual subcarrier values were digitally clipped based on the magnitude of the received virtual subcarrier values.

With a digital clipping model, the interference \underline{F} may be determined by NL and \underline{I} . Thus, once the circuitry 604 has been provided NL and \underline{I} for a particular OFDM symbol, calculation of \underline{F} may be straightforward (with much less computational complexity/overhead than for the implementation described with reference to FIG. 5). Once \underline{F} is determined, the branch metric for candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ may be calculated. The calculation of the interference may be simplified as compared to the calculation described with reference to FIG. 5. In an example implementation, it may be calculated using the following expression: $BM_n^{m,k} = \hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$, which is substantially similar to the branch metric expression presented above with reference to FIG. 5 but with the m and k superscripts left off of the interference term to indicate that the estimated aggregate interference present in the received virtual subcarrier having index n is the same for all candidates.

FIGS. 7A-7D show an example implementation in which the receiver of FIG. 2 performs two or more iterations over the OFDM symbol to generate decisions as to the transmitted virtual subcarrier values of the OFDM symbol in the presence of nonlinear distortion. Shown in FIG. 7A is another example implementation of interference estimation circuitry 210, which comprises nonlinear distortion circuitry 702 and combiner 704.

The nonlinear distortion circuitry 702 is operable to introduce nonlinear distortion to the received virtual subcarrier vector \underline{Y} to generate \underline{Y}' . The nonlinear distortion introduced is determined based on NL from the nonlinear distortion model determination circuitry 214 (FIGS. 1, 4A, and 4B). In this manner, the circuitry 702 attempts to reproduce (to desired/necessary accuracy) the nonlinear distortion experienced by the signal 113 (or the signal \underline{S}' where nonlinear distortion of the AFE 202 is accounted for in NL).

The combiner 704 combines \underline{Y} and \underline{Y}' such that the output is the difference between \underline{Y} and \underline{Y}' . In this example imple-

mentation, the output of combiner 704 is $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ — an initial approximation of the interference introduced by the nonlinear distortion experienced by \underline{Y} . It is acknowledged that, because there is interference present in \underline{Y} as a result of the nonlinear distortion that \underline{Y} experienced en route to the circuitry 210 (at least a portion of which NL is attempting to model), this $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ is not going to be an exact measure of the actual interference present in \underline{Y} . Nevertheless, if the strength of the interference present in \underline{Y} is relatively small compared to the desired signal strength, the amount of additional interference contributed by the existing interference during application of NL may be small enough that $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ is a suitable approximation.

Once $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ is calculated as in FIG. 7A, a first iteration of processing the particular OFDM symbol is carried out by the RSSE circuitry 212 as shown in FIG. 7B. As is shown, during the first iteration on the particular OFDM symbol, $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ is input to the metric calculation circuitry 306, and the N subcarriers are processed sequentially. For each subcarrier n , the sequential processing during the first iteration on the particular OFDM symbol comprises: extending, by successor generation circuitry 312, each of the M selected survivors ($\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$) from the previous subcarrier to K successors ($\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$); distorting, by nonlinear distortion circuitry 302, each of the $M \times K$ successors to generate candidates $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$; calculating, by metrics calculation circuitry 306, metrics for each candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ using $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$; and selecting, by survivor selection circuitry 308, the M best survivors $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$. Thus, the metrics for candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ during the first iteration on the particular OFDM symbol are based on $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ and $y_{n+1} : y_N$ (as a result of using $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$). Upon completing processing of all N subcarriers, the M selected survivors are $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$. In some instances, the accuracy of these survivors may be improved via one or more additional iterations over the particular OFDM symbol. FIGS. 7C and 7D illustrate an embodiment where a second iteration is performed in an attempt to improve the reliability of the estimates.

As is shown, in FIG. 7C, for the second iteration on the particular OFDM symbol, $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ (rather than \underline{Y} as was used in FIG. 7A) is used by circuitry 702 and 704 for calculating \underline{F} , which, as shown in FIG. 7D, is then input to metric calculation circuitry 306 for calculating metrics during the second iteration on the particular OFDM symbol.

During the second iteration on the particular OFDM symbol, the successors are processed similarly to the first iteration. For each subcarrier n , the sequential processing during the second iteration on the particular OFDM symbol comprises: extending, by successor generation circuitry 312, each of the M selected survivors ($\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$) from the previous subcarrier to K successors ($\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$); distorting, by nonlinear distortion circuitry 302, each of the $M \times K$ successors to generate candidates $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$; calculating, by metrics calculation circuitry 306, metrics for each candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ using $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$; and selecting, by survivor selection circuitry 308, the M best survivors $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$. Thus, the metrics for candidate $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ during the first iteration on the particular OFDM symbol are based on $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ and $\hat{A}_{n-1}^1 : \hat{A}_{n-1}^M$ (as a result of using \underline{F}). Upon completing processing of all N subcarriers,

the M selected survivors are $\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$, and the best of these ($\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$) is selected for output to downstream circuitry such as a FEC decoder. In other implementations, additional iterations may be performed to refine these survivors even further.

In accordance with an example implementation of this disclosure, an electronic receiver (e.g., 200) may comprise nonlinear distortion modeling circuitry (e.g., 214), interference estimation circuitry (e.g., 210), and sequence estimation circuitry (e.g., 212). The receiver may receive an orthogonal frequency division multiplexing (OFDM) symbol in the form of an electromagnetic signal (e.g., 113). The nonlinear distortion modeling circuitry may generate a nonlinear distortion model (e.g., NL) that models nonlinear distortion introduced to the received electromagnetic signal en route to the sequence estimation circuitry. The interference estimation circuitry may estimate inter-subcarrier interference present in the received OFDM symbol based on the generated nonlinear distortion model. The sequence estimation circuitry may sequentially process a plurality of received virtual subcarrier values (e.g., \mathbf{Y}) of the OFDM symbol using the estimated inter-subcarrier interference. The processing may result in decisions as to a plurality of transmitted virtual subcarrier values (e.g., $\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$) that correspond to the plurality of received virtual subcarrier values. The estimating of the inter-subcarrier interference may comprise applying the nonlinear distortion model to one or more candidate vectors (e.g., $\mathbf{G}_n^{m,k}$) generated by the sequence estimation circuitry. The estimating of the inter-subcarrier interference may comprise determining which one or more of the transmitted virtual subcarrier values were digitally clipped in a transmitter from which the received electromagnetic signal originated. The estimating of the inter-subcarrier interference may comprise calculating the inter-subcarrier interference based on which one or more of the plurality of transmitted virtual subcarrier values were digitally clipped in the transmitter and based on the generated nonlinear distortion model. The determining which one or more of the plurality of transmitted virtual subcarrier values were digitally clipped in the transmitter may comprise determining magnitude of each of the plurality of received virtual subcarrier values. The estimating of the inter-subcarrier interference may comprise applying the nonlinear distortion model to the received electromagnetic signal to generate an intermediate electromagnetic signal (e.g., \mathbf{Y}'). The estimating of the inter-subcarrier interference may comprise subtracting the received electromagnetic signal from the intermediate electromagnetic signal, a result of the subtraction being the estimate of the inter-subcarrier interference. The plurality of received virtual subcarrier values may comprise a first received virtual subcarrier value (e.g., y_0) and a second received virtual subcarrier value (e.g., y_1). The sequential processing may comprise processing the first received virtual subcarrier value to generate a decision as to a first one of the plurality of transmitted virtual subcarrier values (e.g., $\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$) using an estimate of interference present in the first received virtual subcarrier value (e.g., f_0) that is based on the second received virtual subcarrier value. The sequential processing may comprise processing the second received virtual subcarrier value to generate a decision as to a second one of the plurality of transmitted virtual subcarrier values (e.g., $\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$) using an estimate of interference present in the second received virtual subcarrier value (e.g., f_1) that is based on the generated decision as to the first one of the plurality of transmitted virtual subcarrier values. The plurality of received virtual subcarrier values may comprise a third received virtual subcarrier value (e.g., y_2). The estimate

of interference present in the second received virtual subcarrier value may be based on the third received virtual subcarrier value. The sequential processing may comprise processing the third received virtual subcarrier value to generate a decision as to a third one of the plurality of transmitted virtual subcarrier values (e.g., $\hat{\mathbf{A}}_{n-1}^1 : \hat{\mathbf{A}}_{n-1}^M$) using an estimate of interference present in the third received virtual subcarrier value (e.g., f_3) that is based on the generated decision as to the first one of the plurality of transmitted virtual subcarrier values and on the generated decision as to the second one of the plurality of transmitted virtual subcarrier values. The sequential processing may comprise generating a plurality of branch metrics (e.g., $\text{BM}_0^{1,1} : \text{BM}_{N-1}^{M,K}$), wherein each of the plurality of branch metrics is based on a corresponding one of the received virtual subcarrier values, a candidate vector generated by the sequence estimation circuitry, and the estimated inter-subcarrier interference. For each of the plurality of received virtual subcarrier values, the estimating of the inter-subcarrier interference may consider all others of the received virtual subcarrier values or only a subset of all others of the plurality of received virtual subcarrier values. The subset of all others of the plurality of received virtual subcarrier values may correspond to those of the plurality of received virtual subcarrier values having a magnitude above a determined threshold.

The present method and/or system may be realized in hardware, software, or a combination of hardware and software. The present methods and/or systems may be realized in a centralized fashion in at least one computing system, or in a distributed fashion where different elements are spread across several interconnected computing systems. Any kind of computing system or other apparatus adapted for carrying out the methods described herein is suited. A typical combination of hardware and software may be a general-purpose computing system with a program or other code that, when being loaded and executed, controls the computing system such that it carries out the methods described herein. Another typical implementation may comprise an application specific integrated circuit or chip. Some implementations may comprise a non-transitory machine-readable (e.g., computer readable) medium (e.g., FLASH drive, optical disk, magnetic storage disk, or the like) having stored thereon one or more lines of code executable by a machine, thereby causing the machine to perform processes as described herein.

While the present method and/or system has been described with reference to certain implementations, it will be understood by those skilled in the art that various changes may be made and equivalents may be substituted without departing from the scope of the present method and/or system. In addition, many modifications may be made to adapt a particular situation or material to the teachings of the present disclosure without departing from its scope. Therefore, it is intended that the present method and/or system not be limited to the particular implementations disclosed, but that the present method and/or system will include all implementations falling within the scope of the appended claims.

What is claimed is:

1. A receiver comprising:
 - an analog front end circuit operable to receive a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
 - nonlinear distortion modeling circuitry operable to generate a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:

11

a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol; and said model of said nonlinear distortion is a digital clipping model; and circuitry operable to:
 iteratively calculate metrics based on said received OFDM symbol and said model of nonlinear distortion; and
 determine values of said symbols based on said metrics.

2. The receiver of claim 1, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.

3. The receiver of claim 1, wherein said model of said nonlinear distortion is stored in memory of said receiver as a look-up table.

4. The receiver of claim 3, wherein said look-up table is indexed based on a transmitted signal power parameter.

5. The receiver of claim 1, wherein said generation of said model is based on control information received from a transmitter from which said OFDM symbol originated.

6. The receiver of claim 5, wherein said control information comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.

7. The receiver of claim 5, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.

8. The receiver of claim 5, wherein said control information is received during handshaking with said transmitter.

9. The receiver of claim 5, wherein said control information is received in a preamble of said OFDM symbol.

10. A method comprising:
 in a receiver:
 receiving, by an analog front end circuit, a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
 generating, by nonlinear distortion modeling circuitry, a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
 a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol; and
 said model of said nonlinear distortion is a digital clipping model;
 iteratively calculating, by circuitry of said receiver, metrics based on said received OFDM symbol and said model of nonlinear distortion; and
 determining, by circuitry of said receiver, values of said symbols based on said metrics.

11. The method of claim 10, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.

12. The method of claim 10, wherein said model of said nonlinear distortion is stored in memory of said receiver as a look-up table.

13. The method of claim 12, wherein said look-up table is indexed based on a transmitted signal power parameter.

14. The method of claim 10, wherein said generating said model is based on control information received from a transmitter from which said OFDM symbol originated.

15. The method of claim 14, wherein said control information comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.

16. The method of claim 14, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.

17. The method of claim 14, comprising receiving said control information during handshaking with said transmitter.

12

18. The method of claim 14, comprising receiving said control information in a preamble of said OFDM symbol.

19. A receiver comprising:
 an analog front end circuit operable to receive a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
 nonlinear distortion modeling circuitry operable to generate a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
 a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol;
 said model of said nonlinear distortion is stored in memory of said receiver as a look-up table; and
 said look-up table is indexed based on a transmitted signal power parameter; and
 circuitry operable to:
 iteratively calculate metrics based on said received OFDM symbol and said model of nonlinear distortion; and
 determine values of said symbols based on said metrics.

20. The receiver of claim 19, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.

21. The receiver of claim 19, wherein said generation of said model is based on control information received from a transmitter from which said OFDM symbol originated.

22. The receiver of claim 21, wherein said control information comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.

23. The receiver of claim 21, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.

24. The receiver of claim 21, wherein said control information is received during handshaking with said transmitter.

25. The receiver of claim 21, wherein said control information is received in a preamble of said OFDM symbol.

26. A method comprising:
 in a receiver:
 receiving, by an analog front end circuit, a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
 generating, by nonlinear distortion modeling circuitry, a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
 a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol;
 said model of said nonlinear distortion is stored in memory of said receiver as a look-up table; and
 said look-up table is indexed based on a transmitted signal power parameter; and
 iteratively calculating, by circuitry of said receiver, metrics based on said received OFDM symbol and said model of nonlinear distortion; and
 determining, by circuitry of said receiver, values of said symbols based on said metrics.

27. The method of claim 26, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.

28. The method of claim 26, wherein said generating said model is based on control information received from a transmitter from which said OFDM symbol originated.

29. The method of claim 28, wherein said control information comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.

30. The method of claim 28, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.

31. The method of claim 28, comprising receiving said control information during handshaking with said transmitter. 5

32. The method of claim 28, comprising receiving said control information in a preamble of said OFDM symbol.

* * * * *