

United States Patent [19] **Schilling**

[11] E

Patent Number: Re. 35,402

[45] **Reissued Date of Patent: *Dec. 17, 1996**

[54] **CDMA/TDMA SPREAD-SPECTRUM COMMUNICATIONS SYSTEM AND METHOD**

[75] Inventor: **Donald L. Schilling**, Sands Point, N.Y.

[73] Assignee: **InterDigital Technology Corporation**, Wilmington, Del.

[*] Notice: The portion of the term of this patent subsequent to Nov. 24, 2009, has been disclaimed.

[21] Appl. No.: **277,142**

[22] Filed: **Jul. 5, 1994**

Related U.S. Patent Documents

Reissue of:

[64] Patent No.: **5,260,967**
 Issued: **Nov. 9, 1993**
 Appl. No.: **819,906**
 Filed: **Jan. 13, 1992**

[51] Int. Cl.⁶ **H04B 7/216**

[52] U.S. Cl. **375/203**

[58] Field of Search 375/1, 203; 380/34, 380/49

[56] **References Cited**

U.S. PATENT DOCUMENTS

3,778,715	12/1973	Schmidt et al.	325/2
3,864,635	2/1975	Ewanus	375/1
4,121,159	10/1978	Lampert	375/1

(List continued on next page.)

OTHER PUBLICATIONS

Nettleton, Raymond W., Spectral Efficiency in Cellular Land-Mobile Communications: A Second-Spectrum Approach (1978) (unpublished Ph.D. dissertation, Purdue University).

Cooper, George R. and Nettleton, Ray W., "Cellular Mobile Technology: The Great Multiplier" *IEEE Spectrum*, Jun. 1983, pp. 36-37.

Blasbalg, H., "A Comparison of Pseudo-Noise and Conventional Modulation for Multiple-Access Satellite Communications," *IBM Journal of Research and Development*, vol. 9, No. 4, Jul. 1965, pp. 241-255.

Dixon, Robert C., *Spread Spectrum Systems* (John Wiley & Sons, Inc.: New York, 3d ed. 1984), pp. 412-413.

(List continued on next page.)


Primary Examiner—David C. Cain

Attorney, Agent, or Firm—David Newman & Associates, P.C.

[57] **ABSTRACT**

A spread-spectrum transmitter and receiver using code division multiple access with time division multiple access technology for spread-spectrum communications. At a base station, a spread-spectrum transmitter includes a multiplexer for time multiplexing a synchronization-code signal and a plurality of data signals, which may be encoded as a plurality-encoded data signals, to generate a time-multiplexed signal. A chip code generator generates a chip-code signal which is modulo added with the time-multiplexed signal by an EXCLUSIVE-OR gate to generate a spread-spectrum-time-multiplexed signal. A transmitter transmits the spread-spectrum-time-multiplexed signal over a communications channel. A spread-spectrum receiver at the base station processes a plurality of spread-spectrum signals, received from a plurality of remote units in as time division sequence of spread-spectrum signals, using a despreader circuit to generate a time-division signal. A demultiplexer demultiplexes the time-division signal as a plurality of data signals or as a plurality of privacy-encoded data signals. A remote unit, which may be a handset, includes a despreader circuit for despreading the spread-spectrum-time-multiplexed signal as a time-multiplexed signal. A synchronization-code matched filter detects the synchronization-code signal embedded in the time-multiplexed signal and thereby generates a timing signal. A controller uses the timing signal to generate a control signal. The control signal controls a transmit-receive switch for switching an antenna between the despreader circuit to the transmitter at the remote unit.

54 Claims, 7 Drawing Sheets



U.S. PATENT DOCUMENTS

4,193,031	3/1980	Cooper	455/38
4,392,220	7/1983	Hirosaki et al.	370/18
4,455,651	6/1984	Baran	370/104
4,470,138	9/1984	Gutleber	370/18
4,484,335	11/1984	Mosley et al.	375/1
4,494,228	1/1985	Gutleber	370/18
4,532,635	7/1985	Mangalis	375/1
4,549,303	10/1985	Gutleber	375/25
4,563,774	1/1986	Gloge	455/607
4,587,661	5/1986	Schiff	375/1
4,587,662	5/1986	Langewellpott	375/1
4,607,375	8/1986	Lee	375/2.2
4,672,658	6/1987	Kavehrad et al.	379/63
4,675,839	6/1987	Kerr	364/821
4,843,612	6/1989	Brusch et al.	375/1
4,901,307	2/1990	Gilhousen et al.	370/18
4,912,721	3/1990	Pidgeon, Jr. et al.	375/1

5,031,192	7/1991	Clark	375/1
5,085,900	1/1992	Taylor	375/1
5,138,631	8/1992	Taylor	375/1
5,166,951	11/1992	Schilling	375/1
5,177,765	1/1993	Halland et al.	375/1
5,265,119	11/1993	Gilhousen et al.	375/1

OTHER PUBLICATIONS

The International Dictionary of Physics and Electronics (D. Van Nostrand Co.: Princeton, NJ, 2d ed. 1961), pp. 612, 952.

Robinson, Vester, *Solid-State Circuit Analysis* (Reston Publishing Co.: Reston, VA, 1975), pp. 309-314.

Alavin, Hossein, *Power Control and Interference Management in a Spread-Spectrum Cellular Mobile Radio System* (1984) (unpublished Ph.D., dissertation, Michigan State University).





Fig. 1






Fig. 3




Fig. 4

Fig. 8





Fig. 10







Fig. 5






Fig. 7




Fig. 9

CDMA/TDMA SPREAD-SPECTRUM COMMUNICATIONS SYSTEM AND METHOD

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

RELATED PATENTS

This patent is a reissue of U.S. Pat. Ser. No. 5,260,967 entitled, CDMA/TDMA SPREAD-SPECTRUM COMMUNICATIONS SYSTEM AND METHOD, having Ser. No. 07/819,906, filing date Jan. 13, 1992, and issue date of Nov. 9, 1993.

BACKGROUND OF THE INVENTION

The present invention relates to spread-spectrum communications, and more particularly to a direct sequence code division multiple access, time division multiple access, spread-spectrum system.

DESCRIPTION OF THE RELEVANT ART

Spread-spectrum modulation has been, and still is used extensively in military communications systems both to permit communications which are not detectable by enemy jamming systems, and to resist jamming by an enemy desiring to disrupt communications. Signals which are not detectable by enemy intercept systems are called low probability of intercept signals.

For commercial applications using spread-spectrum modulation, full duplex operation is desirable, allowing a base station and a remote unit to communicate with each other simultaneously. One approach for full duplex is to assign a pair of chip codewords unique to the base station and the remote unit, and have them communicate simultaneously in time and at the same carrier frequency with each other. A problem with this approach is that the spread-spectrum signal radiated at the remote unit raises the noise level at the input to the spread-spectrum receiver at the remote unit.

Another approach for full duplex operation, which alleviates the problem of having the spread-spectrum transmitter raising the noise power level at the input to the spread-spectrum receiver at the remote unit or base station, is to assign different carrier frequencies for transmitting and receiving. Thus, the base station may communicate to a plurality of remote units at a first carrier frequency f_1 and the plurality of remote units may communicate to the base station at a second carrier frequency f_2 . Using two carrier frequencies requires filters at each remote unit and at the base station to prevent leakage of signal energy from the respective spread-spectrum transmitter to the spread-spectrum receiver at each remote unit and at the base station. Additionally, different and long chip codewords are required with multiple remote units, which require complicated acquisition and tracking circuits. Using filters and long chip codewords adds to increased circuit complexity and cost.

OBJECTS OF THE INVENTION

A general object of the invention is a mobile cellular communications system, which allows full duplex operation without the need for complex filters for separating transmit-

ter and receiver frequencies and complex tracking and acquisition circuits.

Another object of the invention is an inexpensive personal communications network, mobile cellular communications system.

An additional object of the invention is a spread-spectrum communications system which has little or no interference between users.

A still further object of the invention is a spread-spectrum system in which the system performance is thermal noise power limited rather than interference limited.

SUMMARY OF THE INVENTION

The present invention provides a system and method which transmit a code division multiple access (CDMA), time division multiple access (TDMA), spread-spectrum communications signal between a base station and a plurality of remote units. The base station time multiplexes a synchronization-code signal and a first plurality of data signals, or a tint plurality of privacy-encoded data signals, to generate a time-multiplexed signal, and then spread-spectrum processes the time-multiplexed signal with a first chip-code signal to generate a spread-spectrum-time-multiplexed signal. The spread-spectrum-time-multiplexed signal is defined herein to include a time-multiplexed signal which is spread-spectrum processed with a chip-code signal.

Each remote unit receives and despreads the spread-spectrum-time-multiplexed signal, and demultiplexes a respective data signal being sent to the remote unit embedded in the time-multiplexed signal as a function of the synchronization-code signal. At a specified time, the remote unit sends a remote-data signal, or a remote-privacy-encoded data signal, to the base station by spread-spectrum processing the remote-data signal, or remote-privacy-encoded data signal, and transmitting the spread-spectrum signal over the communications channel. Since the remote unit is not transmitting and receiving at the same time, a transmit-receive switch can be employed to switch an antenna between the despreader circuitry and the transmitter at the remote unit. A remote-data signal is defined herein as a data signal being sent from a remote unit to the base station. A remote-privacy-encoded-data signal is defined herein as an encoded remote-data signal being sent from the remote unit to the base station.

At the base station, a plurality of spread-spectrum signals are received from the plurality of remote units as a spread-spectrum-time-division signal, which is despread as a time-division signal. The time-division signal accordingly is demultiplexed as a plurality of remote-data signals, or a plurality of remote-privacy-encoded data signals. The spread-spectrum-time-division signal is defined herein to include a plurality of spread-spectrum signals received sequentially in time from a plurality of remote units. The time-division signal is defined herein to include a plurality of remote-data signals, or a plurality of remote-privacy-encoded data signals, which are in different time slots due to the timing of when they are sent from each of the plurality of remote units.

More particularly, a spread-spectrum transmitter at the base station includes base-synchronization means, a plurality of base-privacy means, multiplexer means, base-spreading means, and base-transmitter means. The synchronization means generates a synchronization-code signal, and the plurality of base-privacy means encodes a plurality of data signals with a plurality of privacy-code signals as a plurality

of privacy-encoded data signals, respectively. The encoding with a privacy-code signal may be an encryption type of privacy, or a less secure type of privacy. The multiplexer means time multiplexes the synchronization-code signal and the plurality of privacy-encoded data signals, respectively to generate a time-multiplexed signal. The base-spreading means spread-spectrum processes the time-multiplexed signal with a first chip-code signal to generate a spread-spectrum-time-multiplexed signal. The time multiplexed signal is converted by base-transmitter means to a form suitable for sending over the communications channel.

The plurality of base-privacy means is optional, and accordingly, the plurality of data signals need not be encoded with the plurality of privacy-code signals as a plurality of privacy-encoded data signals, if the plurality of privacy means were not used, then the multiplexer means time multiplexes the plurality of data signals to generate a time-multiplexed signal.

The spread-spectrum receiver at the base station processes a spread-spectrum-time-division signal using base-despreader means, base-demultiplexer means, base-synchronization means, and optionally, a plurality of base-decoder means. The base-despreader means despreads a received spread-spectrum-time-division signal as a time-division signal. The base-demultiplexer means demultiplexes the time-division signal as a plurality of remote-data signals or, in the event the plurality of data signals were encoded, as a plurality of remote-privacy-encoded data signals. The base-synchronization means, which is the same as used by, and operates cooperatively with, the spread-spectrum transmitter at the base station, generates the synchronization-code signal and a timing signal. In response to the timing signal, each of the base-decoder means decodes each of the remote-privacy-encoded signals as a remote-data signals.

At a remote unit, a spread-spectrum-time-multiplexed signal is received at the first carrier frequency. As set forth previously, the spread-spectrum-time-multiplexed signal includes a synchronization-code signal and a plurality of privacy-encoded data signals. The privacy-encoded-data signal to be received by the remote unit is defined herein to be the first privacy-encoded-data signal. A remote-data signal is spread-spectrum transmitted from the remote unit at a second carrier frequency.

The remote unit includes remote-despreader means, remote-synchronization, means, control means, remote-decoder means, remote-privacy means, remote-spreading means, and remote-transmitter means. The remote-despreader means despreads the spread-spectrum-time-multiplexed signal received from the base station as a time-multiplexed signal. The remote-synchronization means detects the synchronization-code signal embedded in the time-multiplexed signal, and generates a timing signal. The control means generates a control signal in response to the synchronization-code signal. The control signal has the proper timing, relative to the synchronization-code signal, for operating the remote unit. The proper timing includes having the appropriate data signal or privacy-encoded data signal embedded in the time-multiplexed signal stored in a buffer. The remote-decoder means, using timing from the control signal, decodes a first privacy-encoded data signal embedded in the time-multiplexed signal as a first data signal.

In response to the control signal, the remote-privacy means encodes the remote-data signal with a remote-privacy-code signal as a remote-privacy-encoded data signal. The remote-privacy-code signal is defined herein to include

any signal that can be used to encrypt or add privacy to the remote-data signal. The remote-spreading means spread-spectrum processes the remote-privacy-encoded data signal with a second chip-code signal as a spread-spectrum signal. The remote-transmitter means at the remote unit converts the spread-spectrum signal to a form suitable for sending over the communications channel. The second chip-code signal, which is generated at each of the plurality of remote units, may be the same as the first chip-code signal generated at the base station.

The present invention also includes, at a base station, the method for spread-spectrum processing a plurality of data signals on a first carrier frequency by generating a synchronization-code signal, encoding the plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded data signals, time multiplexing the synchronization-code signal and the plurality of privacy-encoded data signals, respectively, to generate a time-multiplexed signal, spread-spectrum processing the time-multiplexed signal with a first chip-code signal to generate a spread-spectrum-time-multiplexed signal, and converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over the communications channel.

Also, at the base station, the method includes receiving a spread-spectrum-time-division signal by despreading the spread-spectrum-time-division signal as a time-division signal, demultiplexing the time-division signal as a plurality of remote-privacy-encoded data signals, generating a timing signal, and decoding, using the timing signal, the plurality of remote-privacy-encoded signals as a plurality of remote-data signals.

Additional objects and advantages of the invention are set forth in part in the description which follows, and in part are obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention also may be realized and obtained by means of the instrumentalities and combinations particularly pointed out in the appended claims.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate particular embodiments of the invention, and together with the description, serve to explain the principles of the invention.

FIG. 1 is a block diagram of a base station transmitter;

FIG. 2 is a block diagram of a base station receiver;

FIG. 3 is a block diagram of a remote unit transmitter and receiver;

FIG. 4 is a block diagram of a correlator for despreading spread-spectrum signals;

FIG. 5 is a timing diagram of multiplexed data from the base station of FIGS. 1 and 2;

FIG. 6 is a timing diagram of a packet of data transmitted from a first remote unit relative to the multiplexed data transmitted from the base station of FIGS. 1 and 2;

FIG. 7 is a block diagram of a base station transmitter;

FIG. 8 is a timing diagram of data transmitted between the base station of FIG. 7 and a plurality of remote units;

FIG. 9 is a block diagram of a base station transmitter; and

FIG. 10 is a timing diagram of data transmitted between the base station of FIG. 9 and a plurality of remote units.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made to the preferred embodiments of the present invention, examples of which are

illustrated in the accompanying drawings, wherein like reference numerals indicate to like elements throughout the several views.

In the exemplary arrangement shown in FIG. 1, a spread-spectrum transmitter which can be used for spread-spectrum processing a plurality of data signals on a first carrier frequency f_1 , is shown comprising base-synchronization means, a plurality of base-privacy means, multiplexer means, base-spreading means, and base-transmitter means. The base-synchronization means is coupled to the multiplexer means. The plurality of base-privacy means is coupled between a plurality of inputs having the plurality of data signals, and the multiplexer means. The plurality of data signals includes the first data signal, $d_1(t)$, second data signal $d_2(t)$, through N^{th} data signal, $d_N(t)$. Each data signal is assumed to be sent to a respective remote unit. The base-spreading means is coupled between the multiplexer means and the base-transmitter means.

The base-synchronization means is shown as a synchronization code generator **81** and the synchronization buffer **82**. The synchronization buffer **82** is coupled to the synchronization code generator **81**. Also shown is a clock **57** which is coupled through a first divider **55** and a second divider **54** to the synchronization-code generator **81**.

The plurality of base-privacy means is embodied as a plurality of privacy-code generators, shown as first privacy-code generator **52**, second privacy-code generator **62**, through N^{th} privacy-code generator **72**, coupled to a plurality of EXCLUSIVE-OR gates, shown as first EXCLUSIVE-OR gate **51**, second EXCLUSIVE-OR gate **61**, through N^{th} EXCLUSIVE-OR gate **71**, respectively. More particularly, the first EXCLUSIVE-OR gate **51** is coupled to the first privacy-code generator **52** and to a first input having the first input signal, $d_1(t)$. The second EXCLUSIVE-OR gate is coupled to the second input which provides the second data signal, $d_2(t)$, and to second privacy-code generator **62**. The N^{th} EXCLUSIVE-OR gate is coupled to the N^{th} input which provides the N^{th} data signal, $d_N(t)$, and to the N^{th} privacy-code generator **72**.

The multiplexer means is embodied as a plurality of buffers, shown as first buffer **53**, second buffer **63** through N^{th} buffer **73** and a synchronization buffer **82**, and a multiplexer **75**. The multiplexer **75** is coupled to the first buffer **53**, second buffer **63**, through N^{th} buffer **73**, and to the synchronization buffer **82**. The first buffer **53** is coupled to the first EXCLUSIVE-OR gate **51**. The second buffer **63** is coupled to the second EXCLUSIVE-OR gate **61**. The N^{th} buffer **73** is coupled to the N^{th} EXCLUSIVE-OR gate **71**. The synchronization buffer **82** is coupled to the synchronization-code generator **81**. The multiplexer **75** has its timing coupled to the output of the first divider **55**. The first divider **55** divides the time of the clock signal from clock **57**.

The base-spreading means is embodied as an EXCLUSIVE-OR gate **76**, lowpass filter **77**, and a chip-code generator **56**. The EXCLUSIVE-OR gate **76** is coupled to the multiplexer **75**, to the lowpass filter **77**, and to the chip-code generator **56**. The chip-code generator **56** also is coupled to the clock **57**. The output of the EXCLUSIVE-OR gate **76** is coupled to a lowpass filter **77**.

The clock **57** provides an appropriate clock signal for operation of the spread-spectrum transmitter and receiver at the base station. The clock signals are time divided by first divider **55** and second divider **54**. The divided clock signal outputted from second divider **54** is used for timing of the plurality of privacy-code generators, and the synchronization code generator. The divided clock signal outputted from

first divider **55** is used for timing of the multiplexer **75**. For the embodiment of FIG. 1, the first divider **55** divides the timing of the clock signal by **15**, and the second divider **54** divides the timing from the first divider **55** by **100**.

The base-transmitter means is embodied as an oscillator **74** which generates a first carrier frequency, f_1 , a product device **78**, and a power amplifier **79**. The product device **78** is coupled between the oscillator **74**, and the lowpass filter **77** and power amplifier **79**. The output of the power amplifier **79** typically is coupled through an isolator **99** which may be embodied as a circulator, to an antenna **98**. The isolator **99** also is coupled to a receiver at the base station.

The plurality of data signals, $d_1(t)$, $d_2(t)$, . . . , $d_N(t)$, are encoded by the plurality of EXCLUSIVE-OR gates **51**, **61**, **71** with the plurality of privacy-code signals, $g_1(t)$, $g_2(t)$, . . . , $g_N(t)$, which are generated by the plurality of privacy-code generators **52**, **62**, **72**, respectively. The plurality of EXCLUSIVE-OR gates **51**, **61**, **71** modulo-2 add each of the respective privacy-code signals $g_1(t)$, $g_2(t)$, . . . , $g_N(t)$, to each of the plurality of data signals, $d_1(t)$, $d_2(t)$, . . . , $d_N(t)$, respectively, to generate a plurality of privacy-encoded-data signals. The plurality of privacy-encoded-data signals are stored in the plurality of buffers **53**, **63**, **73**.

Each of the privacy-code signals may be an encrypting signal or a signal which provides privacy to particular data signal, as is well known in the art. Other types of encoding may be used, such as encryption with the Data Encryption Standard.

The synchronization-code generator **81** generates a synchronization-code signal. The synchronization-code signal is stored in the synchronization buffer **82**.

The multiplexer **75** from the synchronization buffer **82** time multiplexes the synchronization-code signal and from the plurality of buffers **53**, **63**, **73**, the plurality of privacy-encoded-data signals, respectively, to generate a time-multiplexed signal. Typically, the synchronization-code signal is initially time multiplexed in a first time slot, and then sequentially, the first privacy-encoded-data signal, second privacy-encoded-data signal, through N^{th} privacy-encoded-data signal are time multiplexed in subsequent time slots. A frame of data is defined herein as the time-multiplexed synchronization-code signal and the plurality of privacy-encoded signals. Accordingly, a time-multiplexed signal includes a frame of data. The synchronization-code signal may be a sequence of 1-bits and 0-bits used for identifying the beginning of each frame of data.

Based on the timing from the synchronization-code signal, a particular privacy-encode data signal can be determined. Preferably, each of the privacy-encoded-data signals and the synchronization-code signal have the same number of bits for a time slot, although a different length sequence of bits could be used for the synchronization-code signal.

The chip-code generator **56** generates a first chip-code signal using a first chip codeword. The time-multiplexed signal outputted from the multiplexer **75**, and the first chip-code signal, $C_B(t)$, from the chip-code generator **56**, are spread-spectrum processed by the EXCLUSIVE-OR gate **76** to generate a spread-spectrum-time-multiplexed signal. The spread-spectrum processing typically is modulo-2 adding the time-multiplexed signal with the chip-code signal using the EXCLUSIVE-OR gate **76**. The lowpass filter **77** filters the spread-spectrum-time-multiplexed signal to remove out-of-band energy. The filtered spread-spectrum-time-multiplexed signal is then frequency translated, by operation of the product device **78** and the first carrier signal supplied by the first oscillator **74**, to the first carrier frequency, f_1 . Thus,

after amplification by power amplifier **79**, the spread-spectrum-time-multiplexed signal is transmitted at the first carrier frequency, f_1 , by antenna **98** over a communications channel.

As an example, assume the synchronization-code signal and **100** privacy-encoded data signals are multiplexed by the multiplexer **75** at multiplex rate, f_M . In this example, assume that each data signal is sampled at the rate of 16 kilobit per second (kb/s) and compressed by the factor **101**. The resulting data rate, d_M , in the time-multiplexed signal is 101×16 kb/s, which is approximately 1.6 Mb/s. The time-multiplexed signal is then Spread by EXCLUSIVE-OR gate **76** using a short first chip-code signal generated from a 15 chip codeword by chip-code generator **56**. Each remote unit uses the same first chip-code signal, $C_B(t)$.

As illustratively shown in FIG. 2, a spread-spectrum receiver for spread-spectrum processing a spread-spectrum-time-division signal is shown comprising the antenna **98**, the isolator **99**, a bandpass filter **101**, a low noise amplifier (LNA) **102**, a mixer **103**, local oscillator **104**, automatic-gain-control (AGC) circuit **105**, base-despreader means, base-demultiplexer means, base-synchronization means, and base-decoder means. The bandpass filter **101** is coupled through the oscillator **99** to the antenna **98**. The isolator **99** also coupled to the transmitter of FIG. 1. The low noise amplifier **102** is coupled between the mixer **103** and the bandpass filter **101**, and the mixer **103** is coupled to the local oscillator **104** which generates a first local signal. The AGC circuit **105** is coupled between the mixer **103** and the base-despreader means. The base-demultiplexer means is coupled to the base-despreader means, to the base-synchronization means and to the base-decoder means.

In FIG. 2, the base-despreader means is embodied as despreader circuitry **110**, the base-demultiplexer means is embodied as the demultiplexer **115**, the base-synchronization means is embodied as the synchronization-code generator **81** and the timing and synchronization circuit **120**, and the base-decoder means is embodied as a privacy-code generator **121** and an EXCLUSIVE-OR gate **122**. The despreader circuitry **110** may be a matched filter, a correlator, or any other circuit which can be used for despreading a received spread-spectrum signal having spread-spectrum modulation. A matched filter may be implemented using a tapped-delay-line filter, such as a surface-acoustic-wave device. A typical correlator which can be used for despreading a spread-spectrum signal is depicted in FIG. 4, and includes a mixer **410**, chip-code generator **415** and filter **420**.

The demultiplexer **115** is coupled to the despreader circuitry **110**. The synchronization-code generator **81** is coupled to the timing and synchronization circuit **120**, and the timing and synchronization circuit **120** is coupled to the demultiplexer **115** and to the privacy-code generator **121**. The privacy-code generator is coupled to the EXCLUSIVE-OR gate **122**. For this particular embodiment, the base-decoder means, and accordingly the privacy-code generator **121**, are shown for decoding a particular remote privacy-encoded data signal from the plurality of remote-privacy-encoded data signals received by the spread-spectrum receiver. Normally, a plurality of base-decoder means would be employed for decoding a plurality of remote-privacy-encoded-data signals.

A spread-spectrum-time-division signal received by antenna **98** passed through oscillator **99** and is filtered by bandpass filter **101** and amplified by low noise amplifier **102**. The mixer **103**, using the first local signal from the local oscillator **104**, shifts the received spread-spectrum-time-

division signal to the appropriate intermediate frequency or to baseband frequency for processing by the despreader circuitry **110**. The appropriate frequency depends on the particular embodiment of the despreader circuitry **110**. The AGC circuit **105** normalizes the power of the received spread-spectrum-time-division signal.

The spread-spectrum-time-division signal is defined herein to include a plurality of spread-spectrum signals received sequentially in time from the plurality of remote units. Each remote unit transmits a spread-spectrum signal for a short duration in time. The timing for transmitting from a particular remote unit is at the remote unit's time slot. The remote unit's time slot is with respect to when the remote unit receives the spread-spectrum-time-multiplexed signal from the base station, and decodes the synchronization-code signal. A time slot for a particular remote unit may be fixed, or variable. For a variable time slot, a protocol signal from the base station may set the location of the time slot.

The remote unit generates a control signal from the decoded synchronization-code signal. The control signal sets the time for when each remote unit transmits its own spread-spectrum signal. Each remote unit has its own time slot, which is different from the time slots of the other remote units, for transmitting a spread-spectrum signal. The time slots may be set by the base station by a protocol when a remote unit initiates communication with the base station. A synchronization-code signal is not received, however, at the base station. The timing for defining a frame of a received plurality of spread-spectrum signals from the plurality of remote units is provided at the base station by the synchronization-code generator **81**.

The despreader circuitry **110** despreads the received spread-spectrum-time-division signal as a time-division signal. The time-division signal is defined herein to include a plurality of remote-privacy-encoded data signals, or a plurality of remote-data signals, which are in different time slots based on the time when each remote unit sent the spread-spectrum signal having the remote-data signal or the remote-privacy-encoded data signal. The despreader circuitry removes the chip-code signal which was added to the spread-spectrum signal by each of the plurality of remote units. If each of the plurality of remote units uses the same chip codeword, then only one despreader circuitry is required. The plurality of remote units may be divided into two or more sets of remote units, with each set using its own chip codeword. For each of the chip codewords the despreader circuitry would include corresponding devices, connected in parallel, for despreading each of the corresponding set of spread-spectrum signals. Although some of the spread-spectrum signals would be received with a different spreading sequence, they are still received sequentially in time from the plurality of remote units. Thus, a time-division signal, as defined herein, would be outputted from the despreader circuitry.

The received time-division signal is demultiplexed by the demultiplexer **115** as a plurality of remote-privacy-encoded data signals, or a plurality of remote-data signals if the spread-spectrum signals sent by the plurality of remote units were not privacy encoded. Essentially, the plurality of remote-privacy-encoded data signals were transmitted by a remote unit, and each remote-privacy-encoded data signal is decoded by decoder circuitry which, for a particular remote-privacy-encoded-data signal, includes the privacy-code generator **121** and EXCLUSIVE-OR gate **122**.

The synchronization-code generator **81**, which is the same as used by the spread-spectrum transmitter of FIG. 1,

generates the synchronization-code signal which triggers the timing and synchronization circuit **120** to generate a timing signal for clocking the demultiplexer **115**. The timing signal also triggers the privacy-coded generator **121** so that the remote-privacy-encoded signal from the demultiplexer **115** is decoded at the appropriate time.

The present invention also includes a plurality of remote units, with each remote unit receiving the spread-spectrum-time-multiplexed signal which is transmitted from the base station. The spread-spectrum-time-multiplexed signal has a synchronization-code signal and the plurality of privacy-encoded data signals, at the first carrier frequency. Within the plurality of privacy-encoded data signals is a particular privacy-encoded data signal, defined herein as a first privacy-encoded data signal, to be received by the remote unit. The remote unit also spread-spectrum transmits a remote-data signal at a second carrier frequency. Generally, the remote unit includes remote-despreader means, remote-synchronization means, control means, remote-decoder means, remote-privacy means, remote-spreading means, and remote-transmitter means.

As illustratively shown in FIG. 3, an antenna **198** is coupled through a transmit-receive switch **199** to a bandpass filter **151**. The bandpass filter **151** is coupled to a mixer **152**, which is also coupled to the second oscillator **153**. The mixer **152** is coupled to an automatic-gain-control (AGC) circuit **154**.

The remote-despreader means is embodied as despreader circuitry **155**, the remote-synchronization means is embodied as synchronization-code matched filter **157**, control means is embodied as the controller **161**. The remote-decoder means is shown as buffer **156**, privacy-code generator **159**, and EXCLUSIVE-OR gate **158**. Also illustrated is a digital-to-analog converter **160**.

The spread-spectrum transmitter for the remote unit includes remote-privacy means, remote-spreading means, and remote-transmitter means. The remote-privacy means is embodied as a privacy-code generator **132**, an EXCLUSIVE-OR gate **133** and buffer **134**. The remote-spreading means is embodied as the chip-code generator **165**, an EXCLUSIVE-OR gate **135**, and lowpass filter **136**. The remote-transmitter means is embodied as an oscillator **137**, product device **138**, optionally an automatic-power-control (APC) circuit **139**, and a second product device **140** coupled to the oscillator **153**. The remote-transmitter means also may include a power amplifier **141** which is coupled through the transmit-receive switch **199** to the antenna **198**.

The clock **162** provides appropriate timing synchronization for operation of the spread-spectrum transmitter and receiver of the remote unit. The clock signals are time-divided by first remote divider **163** and second remote divider **164**. For the embodiment of FIG. 3, by way of example, the first remote-divider **163** divides the timing or the clock signal by **15**, and the second remote divider **164** divides the timing of the signal from the first remote divider **163** by **100**. The timing signals from the second divider **164** provide appropriate timing for the privacy-code generator **132**, and analog-to-digital converter **131**. The output of the first divider **163** provides timing for the buffer **134**.

A received spread-spectrum-time-multiplexed signal at antenna **198** passes through the transmit-receive switch **199** and is filtered by bandpass filter **151**. The mixer **152**, in cooperation with the oscillator **153**, shifts the received spread-spectrum-time-multiplexed signal to an appropriate intermediate frequency or baseband frequency for processing by despreader circuitry **155**. The appropriate intermedi-

ate frequency or baseband frequency is determined on the particular embodiment of despreader circuitry **155**. The AGC circuit **154** normalizes the power of the received spread-spectrum-time-multiplexed signal.

The despreader circuitry **155** may be embodied as a surface-acoustic-wave device, a tapped-delay-line match filter, or a correlator or any other circuitry which may be used for despreading the received spread-spectrum-time-multiplexed signal, as is well known in the art. As illustratively shown in FIG. 4, the correlator may include a chip-code generator **415**, a mixer **410** and a filter **42C**. The despread, spread-spectrum-time-multiplexed signal is the time-multiplexed signal, which was originally sent by the spread-spectrum transmitter at the base station.

The synchronization-code matched filter **157** detects the synchronization-code signal embedded in the time-multiplexed signal, and sends an appropriate timing signal to the controller **161**. In response to the timing signal from the synchronization-code-matched filter **157**, the controller **161** generates appropriate control signals which actuate buffer **156**, privacy-code generator **159** and digital-to-analog converter **160**, so that the appropriate channel from the time-multiplexed signal is demultiplexed and received at the remote unit. As an example, the synchronization-code-matched filter **157** may be embodied as a 160 bit stage matched filter, which is matched to a 160 bit codeword used to generate the synchronization-code signal. The buffer **156** stores only the selected privacy-encoded data signal, or the selected data signal, and not the entire time-multiplexed signal. The selected privacy-encoded data signal, or the selected data signal, is the signal which is desired to be received at the remote unit. When receiving the selected first privacy-encoded data signal, the privacy-code generator **159** generates a first privacy-coded signal which is processed by the EXCLUSIVE-OR gate **158** to generate the first data signal. In a preferred embodiment, analog voice may be converted to a data signal and transmitted to a remote unit. In this embodiment, the digital-to-analog converter **160** converts the first data signal to the analog voice signal as an output signal.

If the analog voice were to be transmitted from the remote unit to a base station, then the analog signal input would be converted by analog-to-digital converter **131** to a remote-data signal, $d_{HI}(t)$. When privacy is used, the remote-data signal is encoded with a remote-privacy-code signal by the EXCLUSIVE-OR gate **133** as a remote-privacy-encoded-data signal. The remote-privacy-code-signal is generated by the privacy-coded generator **132**. The remote-privacy-encoded data signal is stored in the buffer **134**. With an appropriate timing from the first divider **163**, the remote-privacy-encoded data signal is spread-spectrum processed by EXCLUSIVE-OR gate **135** with a second chip-code signal generated by the chip-code generator **165** using the appropriate chip codeword assigned to the remote unit. The lowpass filter **136** filters the spread-spectrum signal. The spread-spectrum signal is shifted to a second carrier frequency by operation of first mixer **138** and oscillator **137**, and second mixer **140** and oscillator **153**. The APC circuit **139** regulates the power transmitted by the remote station in response to a level provided by AGC circuit **154**. The spread-spectrum signal is amplified by power amplifier **141** and radiated by antenna **198**.

The controller **161** provides the control signal to the transmit-receive switch **199** so that upon receiving and decoding the synchronization-code signal, and thereby generating the control signal, the transmit-receive switch **199** is directed to the power amplifier **141** for transmitting the

spread-spectrum signal. After transmitting the spread-spectrum signal, the transmit-receive switch **199** returns to the position for receiving a spread-spectrum-time-multiplied signal. The transmit-receive switch **199** is always on receive except during transmission.

Thus, the spread-spectrum receiver of the remote unit detects its received time slot and the synchronization-code signal in the spread-spectrum-time-multiplexed signal received from the base station.

The present invention also includes, at a base station, the method for spread-spectrum processing a plurality, of data signals on a first carrier frequency by generating a synchronization-code signal, encoding the plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded data signals, respectively, time-multiplexing the synchronization-code signal and the plurality of privacy-encoded data signals, respectively, to generate a time-multiplexed signal, spread-spectrum processing the time-multiplexed signal with a chip-code signal to generate a spread-spectrum-time-multiplexed signal, and converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over the communications channel.

Also, at the base station, the method includes receiving a spread-spectrum-time-division signal by despreding the spread-spectrum-time-division as a time-division signal, demultiplexing the time-division signal as a plurality of remote-privacy-encoded data signals, generating a timing signal and decoding, using the timing signal, the plurality of remote-privacy-encoded signals as a plurality of remote-data signals.

At a remote unit, the method including receiving a spread-spectrum-time-multiplexed signal, which has a synchronization signal and a first privacy-encoded-data signal, at a first carrier frequency, and spread-spectrum transmitting a remote-data signal at a second carrier frequency. The second carrier frequency may be the same as the first carrier frequency. The method includes despreding the spread-spectrum-time-multiplexed signal as a time-multiplexed signal, and detecting in the time-multiplexed signal, the synchronization-code signal. In response to detecting the synchronization-code signal, a timing signal and a control signal are generated. A first privacy-encoded-data signal is decoded from the time-multiplexed signal as first data signal.

The method, at the remote unit, also includes encoding a remote-data signal with a remote-privacy-code signal as a remote-privacy-encoded-data signal. The method spread-spectrum processes the remote-privacy-encoded-data signal with a second chip-code signal as a spread-spectrum signal, and converting the second spread-spectrum signal to a form suitable for sending over a communications channel.

FIG. 5 illustratively shows, at the output of the multiplexer **75**, the time-multiplexed signal as a synchronization-code signal, $g_0(t)$ concatenated with a plurality of privacy-encoded data signals. The plurality of privacy-encoded-data signals are represented, by way or example, as **100** privacy-encoded data signals. The plurality of privacy-encoded-data signals alternatively may be a plurality of data signals, if privacy encoding is not used. The first privacy-encoded data signal **401**, 99th privacy-encoded data signal **499**, and 100th privacy-encoded data signal **500** are shown. In a particular embodiment, a particular privacy-encoded data signal might be encoded as 160 bits, as illustratively shown in FIG. 5.

FIG. 6 illustrates the time slots **300** or the time-multiplexed signal, where the synchronization-code signal is at position zero and subsequently followed by 100 slots for

privacy-encoded data signals. At a particular remote unit, for example a first remote unit which receives the first channel of the time-multiplexed signal, the remote unit transmits at a short time later a spread-spectrum signal back to the base station. Timing is shown as slot **350** for the remote unit, and the time slots **300** are shown for the base station.

The spread-spectrum transmitter at the base station alternatively may transmit the plurality of data signals, or the plurality of privacy-encoded-data signals, at the same time, using code division multiple access. A block diagram for such a base station transmitter is shown in FIG. 7 with its corresponding timing sequence illustrated in FIG. 8. An alternative block diagram for a base station transmitter is shown in FIG. 9 with its corresponding timing sequence illustrated in FIG. 10.

Accordingly, a spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency may comprise base-synchronization means, a plurality of base-privacy means, a plurality of base-spreading means, combiner means, multiplexer means, and base-transmitter means. The plurality of base-privacy means is optional. In FIG. 7, the base-synchronization means is embodied as a synchronization code generator **81**, and the plurality of base-privacy means is embodied as EXCLUSIVE-OR gate **51** and first privacy-code generator **52**, EXCLUSIVE-OR gate **61** and second privacy-code generator **62**, through EXCLUSIVE-OR gate **71** and Nth privacy-code generator **72**. The first privacy-code generator **51** generates a first privacy-code signal, the second privacy-code generator generates a second privacy-code signal, and the Nth privacy-code generator generates an Nth privacy code signal. EXCLUSIVE-OR gate **51** is coupled to first privacy code generator **52** and uses the first privacy-code signal for encoding the first data signal as a first privacy-encoded-data signal. EXCLUSIVE-OR gate **61** is coupled to second privacy-code generator **62** and uses the second privacy-code signal for encoding the second data signal as a second privacy-encoded-data signal. EXCLUSIVE-OR **71** is coupled to Nth privacy-code generator **72** and uses the Nth privacy-code signal for encoding the Nth data signal as an Nth privacy-encoded-data signal.

The plurality of base-spreading means is shown as EXCLUSIVE-OR gate **704** coupled to synchronization-code generator **81** and to synchronization-chip-code generator **701**, EXCLUSIVE-OR gate **703** coupled to first message-chip-code generator **702**, EXCLUSIVE-OR gate **773** coupled to second message-chip-code generator **772**, through EXCLUSIVE-OR gate **783** coupled to Nth message-chip-code generator **782**.

The synchronization-chip-code generator **81** uses a synchronization-chip codeword for generating a synchronization-chip-code signal. EXCLUSIVE-OR gate **704** spread-spectrum processes the synchronization-code signal with the synchronization-chip-code signal to generate a spread-spectrum processed-synchronization-code signal. The first message-chip-code generator **702** uses a first message-chip codeword for generating a first message-chip-code signal. EXCLUSIVE-OR gate **703** spread-spectrum processes the first privacy-encoded-data signal, or the first data signal if privacy encoding is not used, with the first chip-code signal to generate a first spread-spectrum signal. The second message-chip-code generator **772** uses a second message-chip codeword for generating a second message-chip-code signal. EXCLUSIVE-OR gate **773** spread-spectrum processes the second privacy-encoded-data signal, or the second data signal if privacy encoding is not used, with the second message-chip-code signal to generate a second spread-spec-

13

trum signal. Similarly, the N^{th} message-chip-code generator **782** uses an N^{th} message-chip codeword for generating a N^{th} message-chip-code signal. EXCLUSIVE-OR gate **783** spread-spectrum processes the N^{th} privacy-encoded-data signal, or the N^{th} data signal if privacy encoding is not used, with the N^{th} message-chip-code signal to generate an N^{th} spread-spectrum signal.

The spread-spectrum processing of each of the plurality of privacy-encoded-data signals or each of the plurality of data signals, is done with proper timing and chip rate to produce a desired spread-spectrum processing gain. Timing for each privacy-code generator and for each message-chip-code generator may be from a common clock signal as illustrated in FIGS. 7 and 9.

The combiner means is shown as combiner **705**. The EXCLUSIVE-OR gate **703** is coupled to the EXCLUSIVE-OR gate **51** and to combiner **705**. The EXCLUSIVE-OR gate **773** is coupled to the EXCLUSIVE-OR gate **61** and to the combiner **705**. The EXCLUSIVE-OR gate **783** is coupled to the EXCLUSIVE-OR gate **71** and to the combiner **705**.

In a preferred embodiment, the combiner **705** linearly combines the plurality of spread-spectrum signals from the plurality of base-spreading means. Nonlinear combining may equivalently work without serious degradation in performance, however. The combiner **705** combines the plurality of spread-spectrum signals as a combined-plurality of spread-spectrum signals.

The multiplexer means is shown as multiplexer **708**, first buffer **706** and second buffer **707**. EXCLUSIVE-OR gate **704** is coupled to synchronization-code generator **81** and through second buffer **707** to the multiplexer **708**. The combiner **705** is coupled through the first buffer **706** to the multiplexer **708**. The multiplexer **708** time multiplexes the spread-spectrum-processed-synchronization-code signal with the combined-plurality of spread-spectrum signals, as a multiplexed-spread-spectrum signal. The first buffer **706** stores the combined-plurality of spread-spectrum signals until the multiplexer **708** selects the first buffer **706**. The second buffer **707** stores the spread-spectrum-processed-synchronization-code signal until the multiplexer **708** selects the second buffer **707**.

The base transmitter means is shown as an oscillator **74**, a product device **78**, a power amplifier **79**, and an antenna **98**. An isolator **99** may be inserted between the antenna **98** and the power amplifier **79** for isolating the base-station receiver from the base-station transmitter. The product device **78** may be a mixer or other device which can raise a spread spectrum signal to a carrier frequency. The product device **78** is coupled to the oscillator **74**, the multiplexer **706** and the power amplifier **79**.

The synchronization-code generator **81** generates a synchronization-code signal. The synchronization-chip-code generator **701** generates a chip-code signal, and the EXCLUSIVE-OR gate **704**, spread-spectrum processes the synchronization-code signal with the chip-code signal to generator a spread-spectrum-processed-synchronization-code signal.

The plurality of privacy-code generators **52**, **62**, **72** generate a plurality of privacy-code signals. The plurality of EXCLUSIVE-OR gates **51**, **61**, **71**, encode the plurality of data signals, $d_1(t)$, $d_2(t)$, . . . , $d_N(t)$, with the plurality of privacy-code signals to generate a plurality of privacy-encoded-data signals, respectively. Thus, by way of example, the first data signal, $d_1(t)$, is encoded with the first privacy-code signal from the first privacy-code generator **52** by the EXCLUSIVE-OR gate **51** as the first privacy-en-

14

coded-data signal. The second data signal, $d_2(t)$, is encoded with the second privacy-code signal from the second privacy-code generator **62** by the EXCLUSIVE-OR gate **61** as the second privacy-encoded-data signal. The N^{th} data signal, $d_N(t)$, is encoded by the N^{th} privacy-code signal from the privacy-code generator **72** by the EXCLUSIVE-OR gate **71** as the N^{th} privacy-encoded-data signal.

The plurality of EXCLUSIVE-OR gates **704**, **703**, **773**, **783**, spread spectrum process the synchronization-code signal and the plurality of privacy-encode data signals, or data signals if privacy encoding is not used, with a plurality or chip-code signals to generate a plurality or spread-spectrum signals. The plurality of chip-code signals are generated by the synchronization-chip-code generator **701**, first message-chip-code generator **702**, second message-chip-code generator **772** through N^{th} message-chip-code generator **782**. The plurality of EXCLUSIVE-OR gates **704**, **703**, **773**, **783** spread-spectrum process the synchronization-code signal and the plurality of privacy-encoded-data signals by modulo-2 adding the plurality of chip-code signals. Accordingly, the synchronization-code signal is modulo-2 added to the synchronization-chip-code signal from synchronization-chip-code generator **701** by EXCLUSIVE-OR gate **704**. The first privacy-encoded-data signal is modulo-2 added by the EXCLUSIVE-OR gate **703** to the first chip-code signal from the first message-chip-code generator **702**. The second privacy-encoded-data signal is modulo-2 added by the EXCLUSIVE-OR gate **773** to the second chip-code signal from the second message-chip-code generator **772**. The N^{th} privacy-encoded-data signal is modulo-2 added to the N^{th} chip-code signal from the N^{th} message-chip-code generator **782** by the EXCLUSIVE-OR gate **783**.

The combiner **705** combines the plurality of spread-spectrum signals From the plurality of EXCLUSIVE-OR gates **703**, **773**, **783** to generate a combined-spread-spectrum signal. The multiplexer **706** time multiplexes the spread-spectrum-processed-synchronization-code signal with the combined-plurality or spread-spectrum signals.

The multiplexed-combined spread-spectrum signal is converted to a form suitable for sending over a communications channel by function of the oscillator **74** raising the multiplexed-combined-spread-spectrum signal to a carrier frequency with product device **78**. The power amplifier **79** amplifies the multiplexed-combined-spread-spectrum signal at the carrier frequency, which is radiated by antenna **98**. The spread-spectrum system timing is shown in FIG. 8. In this case, the spread-spectrum-processed-synchronization-code signal is sent first and then the combined-plurality of spread-spectrum signals is sent as a base CDMA signal. Subsequently, each mobile unit sends its signal to the base station in its selected time slot, as previously discussed.

The present invention of FIG. 7 can be modified as shown in FIG. 9 by having the synchronization-code signal become a generic-chip-code signal which is combined at the same time with the spread-spectrum signals from the plurality of EXCLUSIVE-OR gates **703**, **773**, **783**. A generic-chip-code signal is used without spread-spectrum processing a data signal, or for spread-spectrum processing a data signal with a relatively low data rate. Accordingly, a spread-spectrum channel which is despread with the generic-chip-code signal can be used to derive a carrier signal, which effectively can be used as a pilot signal. The carrier signal or pilot signal can be used for synchronously despread the other spread-spectrum channels and provide other timing at a remote unit receiver. In this case, as shown in FIG. 10, the generic-chip-code signal is sent concurrently in time with the plurality of spread-spectrum signals as the combined spread-spectrum

15

signal, over the communication channel. Subsequently, each mobile unit sends its message to the base station, as set forth previously, in a time slot measured from the generic-chip-code signal. Timing may be derived from a common clock signal and/or the generic-chip-code signal.

In use, a spread-spectrum transmitter of FIG. 1 at a base station encodes a plurality of data signals with a plurality of privacy-code signals to generate a plurality of privacy-encoded data signals, respectively. A synchronization-code signal is generated by the synchronization-code generator, and is time multiplexed with the plurality of privacy-encoded data signals by multiplexer 75 to generate a time-multiplexed signal. The time-multiplexed signal is spread-spectrum processed by EXCLUSIVE-OR gate 76 using a first chip-code signal generated by a chip-code generator 56, to generate a spread-spectrum-time-multiplexed signal. The spread-spectrum-time-multiplexed signal is transmitted on a first carrier frequency over a communications channel. The synchronization-code signal defines a frame which includes the plurality of privacy-encoded-data signals.

At a remote unit, the spread-spectrum-time-multiplexed signal is received and demultiplexed using despreader circuitry 155. A synchronization-code matched filter 157 detects the synchronization-code signal embedded in the despread signal, and generates a timing signal. The timing signal actuates the controller 161 for generating control signals, which cause the buffer 156 to store the selected privacy-encoded data signal embedded in the time-multiplexed signal from the despreader circuitry 155. The privacy-code generator 159 and EXCLUSIVE-OR gate 158 decodes the privacy-encoded data signal to generate the data signal being received from the base station.

At the remote unit, a remote-data signal, $d_{Hi}(t)$ is encoded by EXCLUSIVE-OR gate 133 by a remote-privacy-code signal from privacy-code generator 132, and the resulting remote-privacy-encoded data signal is stored in buffer 134. The buffer 134 stores the remote-privacy-encoded-data signal until the control signal is sent by controller 161 to transmit. The remote-privacy-encoded data signal is then spread-spectrum processed by EXCLUSIVE-OR gate 135 using a second chip-code signal generated by chip-code generator 165. The output of the EXCLUSIVE-OR gate 135 is a spread-spectrum signal. The control signal also actuated the transmit-receive switch 199 to the transmit position. The spread-spectrum signal is transmitted at a second carrier frequency over the communications channel to the base station.

The controller 161 generates the control signal which actuates the transmit-received switch 199, to be only in the transmit position while transmitting from the remote unit. Otherwise, the transmit-receive switch 199 is in the receive mode. Additionally, the remote unit has its timing based on detection of the synchronization-code signal, and transmits its spread-spectrum signal within a designated time slot. The designated time slot can correspond to the time slot of the privacy-encoded data signal being received by the remote unit from the base station.

At the base station a plurality of spread-spectrum signals are received and despread. The plurality of spread-spectrum signals have been designated herein as a spread-spectrum-time-division signal, inasmuch as the plurality of spread-spectrum signals are received sequentially in time. At the base station, each spread-spectrum signal is despread as a time-division signal. The time-division signal is demultiplexed by demultiplexer 115 as a plurality of remote-privacy-encoded data signals. Appropriate circuitry is used

16

to decode the remote-privacy-encoded data signal as the remote-data signal, $d_{Hi}(t)$.

It will be apparent to those skilled in the art that various modifications may be made to the CDMA/TDMA spread-spectrum system of the instant invention without departing from the scope or spirit of the invention, and it is intended that the present invention cover modifications and variations of the CDMA/TDMA spread-spectrum system provided they come within the scope of the appended claims and their equivalents.

I claim:

1. A spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency, f_0 , comprising:

a plurality of privacy-code generators for generating a plurality of privacy-code signals, respectively;

a plurality of EXCLUSIVE-OR gates coupled to said plurality of privacy-code generators for modulo adding each of the respective plurality of privacy-code signals to each of the plurality of data signals to generate a plurality of privacy-encoded data signals, respectively;

a plurality of data buffers coupled to said plurality of EXCLUSIVE-OR gates for storing the plurality of privacy-encoded data signals, respectively;

a synchronization-code generator for generating a synchronization-code signal;

a synchronization buffer coupled to said synchronization-code generator for storing the synchronization-code signal;

a multiplexer coupled to said synchronization buffer and to said plurality of data buffers for time multiplexing the synchronization-code signal and the plurality of privacy-encoded-data signals, respectively, to generate a time-multiplexed signal; p1 a chip-code generator for generating a chip-code signal;

an EXCLUSIVE-OR gate coupled to said multiplexer and to said chip-code generator, for spread-spectrum processing the time-multiplexed signal with the chip-code signal as a spread-spectrum-time-multiplexed signal; and

a transmitter for transmitting the spread-spectrum-time-multiplexed signal on the carrier frequency over a communications channel.

2. A spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising:

base-synchronization means for generating a synchronization-code signal;

base-privacy means for encoding a plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded-data signals, respectively;

multiplexer means for time multiplexing the synchronization-code signal and the plurality of privacy-encoded-data signals, respectively, to generate a time-multiplexed signal;

base-spreading means for spread-spectrum processing the time-multiplexed signal with a chip-code signal to generate a spread-spectrum-time-multiplexed signal; and

base-transmitter means for converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over a communications channel.

3. The spread-spectrum transmitter as set forth in claim 2 wherein said base-privacy means includes:

a plurality of privacy-code generators for generating the plurality of privacy-code signals, respectively; and

17

- a plurality of EXCLUSIVE-OR gates for modulo adding each of the respective plurality of privacy-code signals to each of the plurality of data signals, respectively.
4. The spread-spectrum transmitter as set forth in claim 2 wherein said multiplexer means includes:
- a plurality of data buffers for storing the plurality of privacy-encoded-data signals;
 - a synchronization buffer for storing the synchronization-code signal; and
 - a multiplexer for time multiplexing the synchronization-code signal and the plurality of privacy-encoded-data signals, respectively, to generate the time-multiplexed signal.
5. The spread-spectrum transmitter as set forth in claim 2 wherein said base-spreading means includes:
- a chip-code generator for generating a chip-code signal; and
 - an EXCLUSIVE-OR gate for spread-spectrum processing the time-multiplexed signal with the chip-code signal to generate the spread-spectrum-time-multiplexed signal.
6. The spread-spectrum transmitter as set forth in claim 2 wherein said base-transmitter means includes:
- an oscillator for generating a carrier frequency;
 - a product device for shifting the spread-spectrum-time-multiplexed signal to the carrier frequency;
 - a power amplifier for amplifying the spread-spectrum-time-multiplexed signal at the carrier frequency; and
 - an antenna for radiating the amplified spread-spectrum-time-multiplexed signal at the carrier frequency over the communications channel.
7. A spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising:
- a plurality of privacy-code generators for generating a plurality of privacy-code signals, respectively;*
 - a plurality of EXCLUSIVE-OR gates for modulo adding each of the respective plurality of privacy-code signals to a respective one of the plurality of data signals to generate a plurality of privacy-encoded data signals;*
 - synchronization means for generating a synchronization-code signal;
 - multiplexer means for time multiplexing the synchronization-code signal and the plurality of *privacy-encoded* data signals, respectively, to generate a time-multiplexed signal;
 - spreading means for spread-spectrum processing the time-multiplexed signal with a chip-code signal to generate a spread-spectrum-time-multiplexed signal; and
 - transmitter means for converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over a communications channel.
8. The spread-spectrum transmitter as set forth in claim 7 wherein said multiplexer means includes:
- a plurality of data buffers *coupled to said plurality of [EXCLUSIVE] ELUSIVE-OR gates*, respectively, for storing the plurality of *privacy-encoded* data signals;
 - a synchronization buffer for storing the synchronization-code signal; and
 - a multiplexer for time multiplexing the synchronization-code signal and the plurality of *privacy-encoded* data signals, respectively, to generate the time-multiplexed signal.
9. The spread-spectrum transmitter as set forth in claim 7 wherein said spreading means includes:

18

- a chip-code generator for generating a chip-code signal; and
 - an EXCLUSIVE-OR gate for spread-spectrum processing the time-multiplexed signal with the chip-code signal as the spread-spectrum-time-multiplexed signal.
10. The spread-spectrum transmitter as set forth in claim 7 wherein said transmitter means includes:
- an oscillator for generating a carrier frequency;
 - a product device for shifting the spread-spectrum-time-multiplexed signal to the carrier frequency;
 - a power amplifier for amplifying the spread-spectrum-time-multiplexed signal at the carrier frequency; and
 - an antenna for radiating the amplified spread-spectrum-time-multiplexed signal at the carrier frequency over a communications channel.
11. A spread-spectrum receiver for spread-spectrum processing a spread-spectrum-time-division signal, wherein the spread-spectrum-time-division signal includes a plurality of spread-spectrum signals received sequentially in time from a plurality of remote units, comprising:
- a despreader circuit for despreading the spread-spectrum-time-division signal as a time-division signal;
 - a demultiplexer coupled to said despreader circuit for demultiplexing the time-division signal as a plurality of remote-privacy-encoded-data signals;
 - a synchronization-code generator for generating a synchronization-code signal;
 - a timing circuit coupled to said synchronization-code generator and responsive to the synchronization-code signal for generating a timing signal; a plurality of privacy-code generators coupled to said timing circuit and responsive to the timing signal for generating a *respective* plurality of remote-privacy-code signals; and
 - a plurality of EXCLUSIVE-OR gates coupled to said demultiplexer and to said plurality of privacy-code generators for decoding the plurality of remote-privacy-encoded-data signals, respectively, as a plurality of remote-data signals.
12. The spread-spectrum receiver as set forth in claim 11 wherein said despreader [means] *circuit* includes a surface-acoustic-wave device for despreading the received spread-spectrum-time-division signal as the time-division signal.
13. The spread-spectrum receiver as set forth in claim 11 wherein said despreader [means] *circuit* includes a tapped-delay-line matched filter for despreading the received spread-spectrum-time-division signal as the time-division signal.
14. The spread-spectrum receiver as set forth in claim 11 wherein said despreader [means] *circuit* includes:
- a chip-code generator for generating a chip-code signal;
 - a mixer coupled to said chip-code generator and responsive to the chip-code signal for despreading the received spread-spectrum-time-division signal as the time-division signal; and
 - a filter coupled to said mixer for filtering the time-division signal.
- [15. A spread-spectrum receiver for spread-spectrum processing a spread-spectrum-time-division signal, wherein the spread-spectrum-time-division signal includes a plurality of spread-spectrum signals received sequentially in time from a plurality of remote units, comprising:
- despreader means for despreading the spread-spectrum-time-division signal as a time-division signal; and
 - demultiplexer means for demultiplexing the time-division signal as a plurality of remote-data signals.]

19

16. The spread-spectrum receiver as set forth in claim 15 wherein said despreader means includes a surface-acoustic-wave device for despreding the received spread-spectrum-time-division signal as the time-division signal.]

17. The spread-spectrum receiver as set forth in claim 15 wherein said despreader means includes a tapped-delay-line matched filter for despreding the received spread-spectrum-time-division signal as the time-division signal.]

18. The spread-spectrum receiver as set forth in claim 15 wherein said despreader means includes:

a chip-code generator for generating a chip-code signal;
a mixer coupled to said chip-code generator and responsive to the chip-code signal for despreding the received spread-spectrum-time-division signal as the time-division signal; and

a filter coupled to said mixer for filtering the time-division signal.]

19. The spread-spectrum receiver as set forth in claim 15 wherein said demultiplexer means includes a demultiplexer for demultiplexing the time-division signal as the plurality of data signals.]

20. A spread-spectrum receiver for spread-spectrum processing a spread-spectrum-time-division signal, wherein the spread-spectrum-time-division signal includes a plurality of spread-spectrum signal received sequentially in time from a plurality of remote units, comprising:

base-despreader means for despreding the spread-spectrum-time-division signal as a time-division signal;

base-demultiplexer means for demultiplexing the time-division signal as a plurality of remote-privacy-encoded data signals;

base-synchronization means for generating a timing signal; and

base-decoder means responsive to the timing signal for decoding the plurality of remote-privacy-encoded signals as a plurality of remote-data signals, respectively.

21. The spread-spectrum receiver as set forth in claim 20 wherein said base-despreader means includes a surface-acoustic-wave device for despreding the received spread-spectrum-time-division signal as the time-division signal.

22. The spread-spectrum receiver as set forth in claim 20 wherein said base-despreader means includes a tapped-delay-line matched filter for despreding the received spread-spectrum-time-division signal as the time-division signal.

23. The spread-spectrum receiver as set forth in claim 20 wherein said base-despreader means includes:

a chip-code generator for generating a chip-code signal;
a mixer coupled to said chip-code generator and responsive to the chip-code signal for despreding the received spread-spectrum-time-division signal as the time-division signal; and

a filter coupled to said mixer for filtering the time-division signal.

24. The spread-spectrum receiver as set forth in claim 20 wherein said base-demultiplexer means includes a demultiplexer for demultiplexing the time-division signal as the plurality of privacy-encoded-data signals.

25. The spread-spectrum receiver as set forth in claim 20 wherein said base-synchronization means includes:

a synch-code generator for generating a synchronization code; and

a timing circuit responsive to the synchronization-code signal for generating a timing signal.

26. The spread-spectrum-receiver as set forth in claim 20 wherein said base-decoder means includes:

20

a plurality of privacy-code generators responsive to the timing signal for generating a plurality of privacy-code signals, *respectively*; and

a plurality of EXCLUSIVE-OR gates for [the] decoding the plurality of privacy-encoded data signals as a plurality of data signals, *respectively*.

27. A remote unit for receiving a spread-spectrum-time-multiplexed signal, having a synchronization signal and a plurality of privacy-encoded data signals including a first privacy-encoded-data signal, on a first carrier frequency, f_1 , and for spread-spectrum transmitting a remote-data signal on a second carrier frequency, f_2 , comprising:

an antenna;

a despreader circuit coupled to said antenna for despreding the spread-spectrum-time-multiplexed signal as a time-multiplexed signal;

a synchronization-code matched filter coupled to said despreader circuit and responsive to a synchronization-code signal embedded in the time-multiplexed signal for generating a timing signal;

a controller coupled to said synchronization-code matched filter and responsive to the timing signal for generating a control signal;

a first buffer coupled to said despreader circuit and to said controller, said first buffer responsive to the control signal for storing the first privacy-encoded-data signal embedded in the time-multiplexed signal;

a first privacy-code generator coupled to said controller and responsive to the control signal for generating a first privacy-code signal;

a first EXCLUSIVE-OR gate coupled to said first privacy-code generator and to said first buffer for decoding the first privacy-encoded-data signal as a first data signal;

a second privacy-code generator coupled to said controller and responsive to the control signal for generating a remote-privacy-code signal;

a second EXCLUSIVE-OR gate coupled to said second privacy-code generator for encoding the remote-data signal with the remote-privacy-code signal as a remote-privacy-encoded-data signal;

a second buffer for storing the remote-privacy-encoded-data signal;

a second chip-code generator for generating a second chip-code signal;

a third EXCLUSIVE-OR gate coupled to said second buffer and to said second chip-code generator for spread-spectrum processing the [remote-privacy-encoded] *remote-privacy-encoded-data* signal with the second chip-code signal as a spread-spectrum *encoded* signal;

a transmitter for transmitting the spread-spectrum encoded signal on the second carrier frequency, f_2 ; and

a transmit-receive switch responsive to the control signal for switching the antenna from the despreader circuit to the transmitter.

28. The remote unit as set forth in claim 27 wherein said despreader circuit includes a surface-acoustic-wave device for despreding the received spread-spectrum-time-multiplexed signal as the time-multiplexed signal.

29. The remote unit as set forth in claim 27 wherein said despreader circuit includes a [tapped-delay-live] *tapped-delay-line* matched filter for despreding the received spread-spectrum-time-multiplexed signal.

30. The remote unit as set forth in claim 27 wherein said despreader circuit includes:

21

a first chip-code *generator for generating a first chip-code* signal;

a mixer coupled to said first chip-code generator and responsive to the first chip-code signal for despreding the received spread-spectrum-time-multiplexed signal as the time-multiplexed signal; and

a filter for filtering the time-multiplexed signal.

31. A remote unit for receiving a spread-spectrum-time-multiplexed signal, having a synchronization-code signal and a plurality of privacy-encoded data signals including a first privacy-encoded data signal, at a first carrier frequency, and for spread-spectrum transmitting a remote-data signal at a second carrier frequency, comprising:

remote-despredader means for despreding the spread-spectrum-time-multiplexed signal as a time-multiplexed signal;

remote-synchronization means responsive to the time-multiplexed signal for detecting the synchronization-code signal and generating a timing signal;

control means responsive to the timing signal for generating a control signal;

remote-decoder means responsive to the control signal for decoding the first privacy-encoded data signal embedded in the time-multiplexed signal as a first data signal;

remote-privacy means responsive to the control signal for encoding the remote-data signal with a remote-privacy-code signal as a remote-privacy-encoded data signal;

remote-spreading means for spread-spectrum processing the remote-privacy-encoded data signal with a second chip-code signal to generate a spread-spectrum signal; and

remote-transmitter means for converting the spread-spectrum signal to a form suitable for sending over a communications channel.

32. The remote unit as set forth in claim **31** wherein said remote-despredader means includes a surface-acoustic-wave device for despreding the spread-spectrum-time-multiplexed signal as the time-multiplexed signal.

33. The remote unit as set forth in claim **31** wherein said remote-despredader means includes a tapped-delay-time matched filter for despreding the spread-spectrum-time-multiplexed signal as the time-multiplexed signal.

34. The remote unit as set forth in claim **31** wherein said remote-despredader means includes:

a first chip-code *generator for generating a first chip-code* signal;

a mixer coupled to said first chip-code generator and responsive to the first chip-code signal for despreding the received spread-spectrum-time-multiplexed signal as the time-multiplexed signal; and

a filter for filtering the time-multiplexed signal.

35. The remote unit as set forth in claim **31** wherein:

said remote-synchronization means includes a synchronization-matched filter responsive to the synchronization-code signal for generating the timing signal; and

said control means includes a controller responsive to the timing signal for generating the control signal.

36. The remote unit as set forth in claim **31** wherein said remote-decoder means includes:

a first buffer responsive to the control signal for storing the first privacy-encoded data signal embedded in the time-multiplexed signal;

a first-privacy-code generator responsive to the control signal for generating a privacy-code signal; and

22

a first EXCLUSIVE-OR gate for decoding the first privacy-encoded data signal as the first data signal.

37. The remote unit as set forth in claim **31** wherein said remote-privacy means includes:

a second privacy-code generator responsive to the control signal for generating the remote-privacy-code signal; and

a second EXCLUSIVE-OR gate for encoding the remote-data signal with the remote-privacy-code signal as the remote-privacy-encoded data signal.

38. The remote unit as set forth in claim **31** wherein said remote-spreading means includes:

a second buffer for storing the remote-privacy-encoded data signal;

a second chip-code generator for generating a second chip-code signal; and

a third EXCLUSIVE-OR gate for spread-spectrum processing the second privacy-encoded signal with the second chip-code signal as a spread-spectrum signal.

39. The remote unit as set forth in claim **31** further including:

an antenna; and

a transmit-receive switch responsive to the control signal for switching the antenna from said [despredader] *remote-despredader* means to said [transmitter] *remote-transmitter* means.

40. A remote unit for receiving a spread-spectrum-time-multiplexed signal, having a synchronization-code signal and a plurality of data signals including a first data signal, at a first carrier frequency, and for spread-spectrum transmitting a remote-data signal at a second carrier frequency, comprising: remote-despredader means for despreding the spread-spectrum-time-multiplexed signal as a time-multiplexed signal;

remote-synchronization means responsive to the time-multiplexed signal for detecting the synchronization-code signal and generating a control signal;

remote-privacy means responsive to the control signal for encoding the remote-data signal with a remote-privacy code signal as a remote-privacy-encoded-data signal;

remote-spreading means for spread-spectrum processing the [remote-data] *remote-privacy-encoded-data* signal with a second chip-code signal as a spread-spectrum signal; and

remote-transmitter means for converting the spread-spectrum signal to a form suitable for sending over a communications channel.

41. The remote unit as set forth in claim **40** wherein said remote-despredader means includes a surface-acoustic-wave device for despreding the spread-spectrum-time-multiplexed signal as the time-multiplexed signal.

42. The remote unit as set forth in claim **40** wherein said remote-despredader means includes a tapped-delay-time matched filter for despreding the spread-spectrum-time-multiplexed signal as the time-multiplexed signal.

43. The remote unit as set forth in claim **40** wherein said remote-despredader means includes:

a first chip-code *generator for generating a first chip-code* signal;

a mixer coupled to said first chip-code generator and responsive to the first chip-code signal for despreding the received spread-spectrum-time-multiplexed signal as the time-multiplexed signal; and

a filter for filtering the time-multiplexed signal.

44. The remote unit as set forth in claim **40** wherein:

23

said remote-synchronization means includes a synchronization-matched filter responsive to the synchronization-code signal for generating [and] a timing signal; and

further including control means, responsive to the timing signal, for generating the control signal.

45. The remote unit as set forth in claim 40 wherein said remote-spreading means includes:

a second buffer for storing the [remote-data] remote-privacy-encoded-data signal;

a second chip-code generator for generating [a] the second chip-code signal; and

a third EXCLUSIVE-OR gate for spread-spectrum processing the [remote-data] remote-privacy-encoded data signal with the second chip-code signal to generate a spread-spectrum signal.

46. The remote unit as set forth in claim 40 further including:

an antenna; and

a transmit-receive switch responsive to the control signal for switching the antenna from said [despreader] remote-despreader means to said [transmitter] remote-transmitter means.

47. A method for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising the steps of:

generating a synchronization-code signal;

encoding a plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded data signals, respectively;

time multiplexing the synchronization-code signal and the plurality of privacy-encoded data signals, respectively, to generate a time-multiplexed signal;

spread-spectrum processing the time-multiplexed signal with a chip-code signal to generate a spread-spectrum-time-multiplexed signal; and

converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over a communications channel.

[48. A method for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising the steps of:

generating a synchronization-code signal;

time-multiplexing the synchronization-code signal and the plurality of data signals, respectively, to generate a time-multiplexed signal;

spread-spectrum processing the time-multiplexed signal with a chip-code signal to generate a spread-spectrum-time-multiplexed signal; and

converting the spread-spectrum-time-multiplexed signal to a form suitable for sending over a communications channel.]

[49. A method for receiving a spread-spectrum-time-multiplexed signal, comprising the steps of:

despreading the spread-spectrum-time-multiplexed signal as a time-multiplexed signal; and

demultiplexing the time-multiplexed signal as a plurality of data signals.]

50. A method for receiving a spread-spectrum-time-division signal, comprising the steps of:

despreading the spread-spectrum-time-division signal as time-division signal;

demultiplexing the time-division signal as a plurality of remote-privacy-encoded remote-data [signal] signals;

24

generating a timing signal; and

decoding in response to the timing signal, the plurality of remote-privacy-encoded data signals as a plurality of remote-data signals.

51. A method of receiving a spread-spectrum-time-multiplexed signal, having a [synchronization] synchronization-code signal and a first privacy-encoded data signal, at a first carrier frequency, and for [a] spread-spectrum transmitting a remote-data signal at a second carrier frequency, comprising the steps of:

despreading the spread-spectrum-time-multiplexed signal as a time-multiplexed signal;

detecting, in the time-multiplexed signal, the synchronization-code signal and generating a timing signal;

generating, in response to the timing signal, a control signal;

decoding [a] the first privacy-encoded data signal embedded in the time-multiplexed signal as a first data signal;

encoding, in response to the control signal, the remote-data signal with a remote-privacy-code signal as a remote-privacy-encoded data signal;

spread-spectrum processing the remote privacy-encoded data signal with a [second] chip-code signal as a spread-spectrum signal; and

converting the spread-spectrum signal to a form suitable for sending over a communications channel.

52. A spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising:

base-synchronization means for generating a synchronization-code signal;

a plurality of base-spreading means for spread-spectrum processing the synchronization-code signal and the plurality of data signals [and] with a plurality of chip-code signals, respectively, to generate a spread-spectrum-processed-synchronization-code signal and a plurality of spread-spectrum signals[, respectively];

combiner means for combining the plurality of spread-spectrum signals[, respectively,] to generate a combined-spread-spectrum signal;

multiplexer means for time multiplexing the spread-spectrum-processed-synchronization-code signal and the combined-spread-spectrum signal as a multiplexed-spread-spectrum signal; and

base-transmitter means for converting the [time-multiplexed spread-spectrum] multiplexed-spread-spectrum signal to a form suitable for sending over a communications channel.

53. The spread-spectrum transmitter as set forth in claim [2] 45, further including:

a plurality of base-privacy means for encoding the plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded-data signals, respectively; and

wherein said plurality of base-spreading means spread-spectrum processes the plurality of privacy-encoded-data signals with the plurality of chip-code signals to generate the plurality of spread-spectrum signals, respectively.

54. The spread-spectrum transmitter as set forth in claim 53 wherein each of said plurality of base-privacy means includes:

a privacy-code generator for generating [the] a privacy-code signal; and

25

an EXCLUSIVE-OR gate for modulo-2 adding the [respective] privacy-code signal to *a respective one of the plurality of data [signal, respectively] signals.*

55. The spread-spectrum transmitter as set forth in claim [52] 53 wherein each of said *plurality of base-spreading* 5 means includes:

a chip-code generator for generating a chip-code signal; and

an EXCLUSIVE-OR gate for spread-spectrum processing *a respective one of the plurality of privacy-encoded-data [signal] signals* with the chip-code signal to generate *a respective one of the plurality of spread-spectrum [signal] signals.*

56. The spread-spectrum transmitter as set forth in claim 52 wherein said multiplexer means includes: 15

a first data buffer for storing the combined-spread-spectrum signal;

a second buffer for storing the spread-spectrum-processed-synchronization-code signal; and 20

a multiplexer for time multiplexing the spread-spectrum-processed-synchronization-code signal and the combined-spread-spectrum signal, respectively, to generate the multiplexed-spread-spectrum signal.

57. The spread-spectrum transmitter as set forth in claim 52 wherein said base-transmitter means includes: 25

an oscillator for generating a carrier frequency;

a product device for shifting the combined-spread-spectrum signal to the carrier frequency;

a power amplifier for amplifying the multiplexed-spread-spectrum signal at the carrier frequency; and 30

an antenna for radiating the amplified multiplexed-spread-spectrum signal at the carrier frequency over the communications channel. 35

58. A spread-spectrum transmitter for spread-spectrum processing a plurality of data signals on a carrier frequency, comprising:

base-genetic means for generating a generic-chip-code signal; 40

a plurality of base-spreading means for spread-spectrum processing the plurality of data signals with a plurality of chip-code signals to generate a plurality of spread-spectrum signals;

combiner means for combining the generic-chip-code signal and the plurality of spread-spectrum signals, respectively, to generate a combined-spread-spectrum signal; [and] 45

base-transmitter means for converting the combined-spread-spectrum signal to a form suitable for sending over a communications channel; 50

26

a plurality of base-privacy means for encoding a plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded data signals, respectively; and

wherein said plurality of base-spreading means spread-spectrum processes the plurality of privacy-encoded-data signals with the plurality of chip-code signals to generate the plurality of spread-spectrum signals, respectively.

[59. The spread-spectrum transmitter as set forth in claim 58, further including:

a plurality of base-privacy means for encoding a plurality of data signals with a plurality of privacy-code signals as a plurality of privacy-encoded-data signals, respectively; and

wherein said plurality of base-spreading means spread-spectrum processes the plurality of privacy-encoded-data signals with the plurality of chip-code signals to generate the plurality of spread-spectrum signals, respectively.]

60. The spread-spectrum transmitter as set forth in claim [59] 58 wherein each of said *plurality of base-privacy* means includes:

a privacy-code generator for generating *a respective one of the plurality of privacy-code [signal, respectively] signals*; and

an EXCLUSIVE-OR gate for modulo-2 adding the respective privacy-code signal to *a respective one of the plurality of data [signal, respectively] signals.*

61. The spread-spectrum transmitter as set forth in claim 58 wherein each of said *plurality of base-spreading* means includes:

a chip-code generator for generating a respective chip-code signal; and

an EXCLUSIVE-OR gate for spread-spectrum processing *a respective one of the plurality of privacy-encoded-data [signal] signals* with the *respective* chip-code signal to generate *a respective one of the plurality of spread-spectrum [signal, respectively] signals.*

62. The spread-spectrum transmitter as set forth in claim 58 wherein [each of] said base-transmitter means includes:

an oscillator for generating a carrier frequency;

a product device for shifting the combined-spread-spectrum signal to the carrier frequency;

a power amplifier for amplifying the combined-spread-spectrum signal at the carrier frequency; and

an antenna for radiating the amplified combined-spread-spectrum signal at the carrier frequency over the communications channel.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : Re. 35,402
DATED : December 17, 1996
INVENTOR(S) : Donald L. Schilling

Page 1 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Column 2, line 21: delete "tint" and insert --first--.
Column 3, line 15: delete "signals, if" and insert
--signal. If--.
Column 7, line 12: delete "Spread" and insert --spread--.
Column 9, line 9: delete "multiplexer" and insert
--multiplexed--;
line 10: delete "multiplexer" and insert
--multiplexed--; and
line 53: delete "or" and insert --of--.
Column 10, line 11: delete "42C" and insert --420--; and
line 27: delete "buffer" and insert
--buffer--.
Column 11, line 11: delete ",";
line 22: delete "For" and insert --for--;
line 31: delete "including" and insert
--includes--; and
line 64: delete "or" and insert --of--.
Column 12, line 25: delete "." and insert --,--.
Column 14, line 11: delete "or" and insert --of--;
line 12: delete "or" and insert --of--;
line 34: delete "From" and insert --from--; and
line 38: delete "or" and insert --of--.

In the Claims:

Column 16, line 34: delete "p1" and insert a hard
return before "a chip-code
generator for".
Column 17, line 56: delete "[EXCLUSIVE] ELUSIVE" and
insert --EXCLUSIVE--.

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : Re. 35,402
DATED : December 17, 1996
INVENTOR(S) : Donald L. Schilling

Page 2 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

In the Claims:

Column 18, line 30: after "a timing signal;" insert a
hard return.
Column 21, line 39: delete "plexer" and insert --plexed--.
Column 22, line 32: after "comprising:" insert a
hard return.
Column 23, line 62: before "time-division" insert --a--.
Column 24, line 47: delete "spread spectrum";
line 50: delete "45" and insert --52--; and
line 64: delete ":" and insert --;--.

Signed and Sealed this
Twentieth Day of May, 1997

Attest:



BRUCE LEHMAN

Attesting Officer

Commissioner of Patents and Trademarks