



US00RE36508E

United States Patent [19] **Gornati et al.**

[11] E

Patent Number: Re. 36,508

[45] **Reissued Date of Patent: Jan. 18, 2000**

[54] **METHOD OF AUTOMATICALLY MEASURING THE HORIZONTAL SCAN FREQUENCY OF A COMPOSITE SYNCHRONISM SIGNAL, AND AN ELECTRONIC CIRCUIT OPERATING IN ACCORDANCE WITH THE METHOD**

[75] Inventors: **Silvano Gornati; Giorgio Betti**, both of Milan; **Fabrizio Sacchi; Gianfranco Vai**, both of Pavia; **Maurizio Zuffada**, Milan, all of Italy

[73] Assignee: **SGS-Thomson Microelectronics S.r.l.**, Agrate, Italy

[21] Appl. No.: **08/932,000**

[22] Filed: **Sep. 17, 1997**

Related U.S. Patent Documents

Reissue of:

[64] Patent No.: **5,134,481**
Issued: **Jul. 28, 1992**
Appl. No.: **07/631,915**
Filed: **Dec. 21, 1990**

U.S. Applications:

[63] Continuation of application No. 08/282,844, Jul. 28, 1994, abandoned.

Foreign Application Priority Data

Dec. 21, 1989 [IT] Italy 22782-A/89

[51] **Int. Cl.⁷** **H04N 5/08; H04N 5/04; H04N 7/01**

[52] **U.S. Cl.** **348/558; 348/531; 348/194**

[58] **Field of Search** 348/531, 558, 348/525, 526, 194, 180, 505, 506, 507, 508, 500, 540, 542, 441, 604; H04N 5/08, 5/04, 7/01

[56] **References Cited**

U.S. PATENT DOCUMENTS

4,353,091	10/1982	Hoppe	348/194
4,402,011	8/1983	Newton .	
4,561,021	12/1985	Abe .	
4,672,449	6/1987	Kraus et al.	348/194
4,675,734	6/1987	Widom .	
4,769,704	9/1988	Hirai et al. .	
4,792,852	12/1988	Narusawa .	
4,812,906	3/1989	Wölber .	
4,954,893	9/1990	Urakami .	
4,999,708	3/1991	Aoki et al. .	
5,003,392	3/1991	Wischermann .	

FOREIGN PATENT DOCUMENTS

2431825	2/1974	Germany .
3021417	6/1980	Germany .

Primary Examiner—Victor R. Kostak


Attorney, Agent, or Firm—Theodore E. Galanthay; Lisa K. Jorgenson

[57] **ABSTRACT**

A method of automatically measuring the horizontal scan frequency of a composite synchronism signal, comprising horizontal synchronization impulses at line frequency, consists of first performing a count of a number of impulses having a repeat frequency higher than said line frequency, as intervening between two successive impulses at line frequency.

The count value, corresponding to said number of impulses, is stored to obtain the line frequency of the signal, and thereafter, a series of down counts is effected, as initiated at predetermined times, until a change of frequency of the signal is detected.

18 Claims, 3 Drawing Sheets






Fig-1




Fig. 2




Fig. 3

1

**METHOD OF AUTOMATICALLY
MEASURING THE HORIZONTAL SCAN
FREQUENCY OF A COMPOSITE
SYNCHRONISM SIGNAL, AND AN
ELECTRONIC CIRCUIT OPERATING IN
ACCORDANCE WITH THE METHOD**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

This application is a continuation of application Ser. No. 08/282,844 filed on Jul. 28, 1994, now abandoned, which is a reissue of Ser. No. 07/631,915 filed on Dec. 21, 1990 now U.S. Pat. No. 5,134,481.

DESCRIPTION

This invention relates to a method of automatically measuring the horizontal scan frequency of a composite synchronism signal.

The invention relates, moreover, to an electronic circuit operating in accordance with the above method.

BACKGROUND OF INVENTION

No unique broadcasting and/or operating standard is currently available as relates to composite synchronism video signals.

As a result, for proper operation of video sets, the latter must be equipped with devices which [be] are capable of detecting in an automatic manner the type of the input signal, or more specifically, the repeat frequency f_h of the video picture line, which is representative of the broadcasting standard.

For instance with monitors, the composite synchronism video signal contains n impulses at the horizontal line frequency f_h , followed by a single impulse at the vertical frequency f_v , the duration whereof is equal to a multiple n' of the duration of the line frequency impulses and tied to the broadcasting standard being used.

The prior art has indeed proposed a solution to the problem of finding the line frequency f_h .

This prior solution consists of providing a counter, having a predetermined scan frequency f_c higher than the line frequency f_h , and of detecting the number of count impulses occurring between two successive impulses at line frequency.

By comparison of two chronologically successive measurements it becomes possible to decide whether a frequency change did occur.

However, this prior solution cannot prevent the measurement from being affected by the presence of vertical synchronization impulses.

SUMMARY OF INVENTION

The underlying technical problem of this invention is to provide a method of automatically measuring the horizontal scan frequency of a composite synchronism signal, which has such functional characteristics as to make the measurement unaffected by the presence of vertical frequency raster synchronisms and by any missed line frequency impulse due to occasional or temporary malfunctions.

This problem is solved by a method as indicated being characterized in that it comprises the following steps:

effecting a count of a number of impulses, which impulses have a repeat frequency higher than said line frequency, intervening between two successive, line frequency impulses;

2

storing the count value, corresponding to said number of impulses, to obtain the line frequency; and

effecting successive checking counts, in the reverse order, until a change of frequency of the composite synchronism signal is detected.

This technical problem is also solved by an electronic circuit for automatically measuring the horizontal scan frequency of a composite synchronism signal comprising horizontal synchronization impulses at line frequency and at least one synchronization impulse at vertical frequency, characterized in that it comprises:

a timer receiving on its input said synchronization signal and a clock signal having a predetermined repeat frequency higher than said line frequency;

a counter connected downstream from the timer to detect the number of the impulses at the clock frequency between two successive impulses at line frequency;

a memory connected two-directionally to the counter for storing said number of impulses; and

a control logic having inputs connected to outputs of the timer and the counter, and outputs connected to respective inputs of the counter and the memory to enable up or down counting and the storing of said number based upon timing signals from the timer.

The features and advantages of the method and the circuit according to the invention will become apparent from the following detailed description of embodiments thereof, to be taken by way of illustration and not of limitation with reference to the accompanying drawings.

BRIEF DESCRIPTION OF DRAWINGS

In the drawings:

FIG. 1 is a block diagram depicting schematically the electronic circuit of this invention;

FIG. 2 is a detailed diagram of the same circuit as in FIG. 1; and

FIG. 3 shows a series of signals having the same time base, present in the circuit of FIG. 1.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENT

With reference to the drawing figures, generally and schematically indicated at **1** is an electronic circuit adapted to automatically measure the horizontal scan frequency of a composite synchronism video signal **2** from a generic video source, not shown because conventional.

The signal **2** comprises a first series of m synchronization impulses **3** at line horizontal frequency f_h , followed by a vertical synchronization impulse **4** having a different frequency f_v .

The composite synchronism signal **2** is input to a timer **5**. A second input of the timer **5** is to receive a clock signal **6** having a predetermined scan frequency f_c higher than the line frequency f_h , e.g. from a quartz oscillator.

Specifically, the timer **5** incorporates a divider **7** which receives on its input the synchronization signal **2** and performs division of said signal by six.

The divider **7** issues on an output **8** a signal s_1 which has the pattern shown in FIG. 3 and corresponds to a step impulse with a duration of $1/f_h$ every six impulses **3** at line frequency. The output **8** is connected directly to one input of a logic AND gate **9** receiving, on another input, the clock signal **6** and outputting a signal s_2 which corresponds to a first count of those impulses at clock frequency f_c which occur between two successive impulses **3** at line frequency.

3

The output of said AND gate **9** is connected to an input of a counter **12** of the up/down type, i.e. capable of counting in either the "up" or "down" directions.

The "count-up" or "count-down" operating condition of the counter **12** will be determined by [a] control logic **20** whereto a pair of signals **s3** and **s4** are input from respective outputs **13** and **14** of the divider **7**.

This control logic **20** is composed of certain circuit portions or blocks to be described in detail herein below. A first block **B1** comprises a pair of logic gates **11** and **16** of the AND type and a bistable memory cell **15** of the delay type.

The output **14** is connected to a corresponding input of each gate, **11** and **16**, as well as to the clock input **T** of the cell **15** and a load input **L** of the counter **12**.

The cell **15** has an output connected directly to another input of the gate **16** which has the output connected to a reset input **C** of the counter **12**. The output of the cell **15** is also connected to a further UP/DOWN input of the counter **12** to set the operating condition of the counter **12**, and the data input **D** of a bistable cell **25**, of the D type, which forms a third block **B3** of the logic **20**.

This logic **20** comprises a second block **B2** including a shift register **26**, composed of a pair of bistable cells **21** and **22**, and a logic gate **17** of the AND type. The cells **21** and **22** are of the so-called D type with a data input **D**, reset input **R**, and clock input **T**.

The output **13** of the divider **7** is connected directly to both clock inputs **T** of the cells **21** and **22** and to the clock input **T** of the cell **25** of block **B3**.

The cell **21** has its output connected directly to the data input **D** of the cell **22**. Each cell **21** and **22**, moreover, has its respective output connected directly to a corresponding input of the logic gate **17**.

The interaction of the blocks **B1** and **B2** described in the foregoing is provided by the links of the output of the gate **17** of block **2** to one input of the gate **11** and the data input **D** of the cell **15**.

In addition, the output of the gate **11** is connected directly to both reset inputs **R** of the cells **21** and **22**.

The logic **20** further comprises a fourth block **27** made up of an exclusive OR logic gate EXOR having a single output connected to the data input **D** of the cell **21** and a plurality of inputs.

The structure of the circuit **1** is completed by a memory **30** connected two-directionally to the counter **12**.

In particular, the counter **12** has a plurality of outputs, denoted by the references **U1** to **Un**, which are connected to respective inputs **19** of the memory **30**, the latter having outputs **18** which are connected to respective inputs **10** of the counter. The first **n-1** outputs of the counter are also connected to respective inputs of the gate **27** except, of course, output **Un**.

In addition, the output of the bistable cell **25** in block **B3** is connected to an enable input **23** of the memory **30**.

The measuring method of this invention, to be implemented by the electronic circuit **1** just described, consists of the following steps.

At the initial time t_0 , a count of the number of the impulses at clock frequency f_c is effected which occur between two successive line impulses at frequency f_h . The counter **12** will provide the count of such impulses, it being set in the "up" operating condition by the block **B1** of the logics **20**.

4

This first count, from 0 to a value m , results in the value of the line frequency f_h being found, with the clock frequency f_c being a known factor. This value m is stored in the memory **30** at the time t_1 on the basis of signal **s3**.

Subsequently to storing the value m corresponding to the frequency f_h into the memory **30**, the counter **12** is set by the block **B1** to the "down" operating condition and initialized to count from the value m down to 0.

At the time t_2 , the counter **12** is initialized on the basis of the synchronization signal **s4**, loading into it the value m present in the memory **30** following reception of an enable impulse on the input **L**.

From now on, at each successive count interval, it will be necessary to check that the contents of the counter **12** has returned to the value 0.

This check is carried out by the EXOR gate **27** on the $n-1$ most meaningful bits of the counter **12**; that is, the least meaningful bit present on the output **Un** is neglected.

Advantageously, the provision of the gate **27** allows any error by \pm one impulse in the down count to be corrected.

In fact, since the composite synchronism signal and the clock signal at the frequency f_c are not synchronized with each other, it may occur that a different number of impulses be considered at subsequent count intervals. In other words, it might happen that at the end of the down count, the counter **12** has counted one impulse more or one impulse less.

Advantageously, the gate **27** provided allows the return to 0 of the counter to be checked irrespective of this possible error situation.

The portion **B2** of the logics **20** is instead effective to detect the change of frequency in the composite synchronism video signal. When, at the end of the series of n impulses at line frequency f_h , the impulse **4** at vertical frequency f_v arrives, the shift register **26** consisting of the cells **21** and **22** can detect the change of frequency because a fresh down count has been started at the time t_3 .

Understandably, the counter **12** should be adequately sized; that is, if N is the number of the impulses at the clock frequency f_c which occur within a vertical impulse of maximum duration, it shall have to be the logarithm to base 2 of N , as rounded off to the upper integer.

Where the count interval coincides with the duration of the vertical impulse, at the time t_4 , the contents of the counter **12** will be other than 0. However, the contents of the memory **30** which still contains the value m , will not be changed.

The portion **B2** of the logics **20** will then check at the time t_6 that the signal corresponding to the change in frequency at the time t_4 was due to the vertical impulse **4**. This because of the composite signal being restored to a pulsive pattern at the line frequency f_h . At the end of this further count interval in the "down" mode, the contents of the counter **12** will be back to the value 0 and the logics **20** will ignore the frequency change information received at the end of the previous count interval.

In other words, the output of the AND gate **17** will be only switched to a logic high where two successive returns to a value other than 0 are detected in the countdown performed by the counter **12**; return to a value other than 0 would be indicated by the output of the gate **27** being at a high.

Advantageously, the circuit of this invention automatically detects the line frequency of the composite video signal even without an impulse at frequency f_h .

Even in the most unlikely event that the missing impulse, at the frequency f_h , is the one that should appear after a

5

vertical impulse and after a number of impulses equal to the selected timing, the block B2 would detect a frequency change which actually did not occur.

Likewise, where the missing impulse, at the frequency fh, is the one that should appear before the vertical impulse and before a number of impulses equal to the selected timing, the block B2 would detect a frequency change which actually did not occur.

In this case, the counter 12 would be set for the "up" mode in order to measure the new frequency, but the number of the impulses at the clock frequency fc to be counted would be exactly the same as that measured at the time to. Consequently, the bistable cell 15 in the block B3 would update the memory with a value already there.

Where an impulse is missing instead at any other position of the signal 2, the information on the occurrence of a frequency change would not be confirmed, and accordingly, such a missed impulse would be uninfluential.

We claim:

1. Method of automatically measuring the broadcasting standard of a composite synchronism video signal comprising synchronization impulses at horizontal line frequency, characterized in that it comprises the following steps:

effecting a count of a number of impulses, which impulses have a repeat frequency higher than said line frequency, intervening between two successive, line frequency impulses to produce a count value representative of the line frequency;

storing the said count value, corresponding to said number of impulses, to obtain the line frequency; and

effecting successive check counts, [int he] in the reverse order, of the same said impulses between subsequent line frequency impulses until a change of frequency of the composite synchronism signal is detected.

2. An electronic circuit for automatically measuring the horizontal synchronization frequency of a composite synchronism signal comprising horizontal synchronization impulses at a line frequency and at least one synchronization impulse at vertical frequency, characterized in that it comprises:

a timer receiving on its input said synchronization signal and a clock signal having a predetermined repeat frequency higher than said line frequency;

a counter connected downstream from the timer to detect the number of the impulses at clock frequency between two successive impulses at line frequency, said number of impulses being representative of the line frequency;

a memory connected two-directionally to the counter for storing said number of impulses; and

control logic having inputs connected to outputs of said timer and said counter, and outputs connected to respective inputs of the counter and the memory to enable up or down counting and storing based upon timing signals from the timer.

3. A circuit according to claim 2, characterized in that said control logic comprises a circuit portion for detecting the change of frequency in said composite synchronism signal.

4. A circuit according to claim 2, characterized in that said control logic comprises a circuit portion effective to enable the counter to perform said up or down counting.

5. A circuit according to claim 3, characterized in that said control logic comprises a logic gate of the exclusive OR type having an output connected to said circuit portion and a plurality of inputs connected directly to respective outputs of the counter to check that the down count by said counter has actually gone back to zero.

6

6. A circuit according to claim 3, characterized in that said circuit portion comprises a shift register and a logic gate connected downstream from said register.

7. A circuit according to claim 2, characterized in that said timer comprises a frequency divider whereto said synchronization signal is input directly and which has an output connected to the input side of a logic gate receiving on another input said clock signal.

8. A circuit according to claim 5, characterized in that said gate of the exclusive OR type carries out a check on a predetermined number of most meaningful bits of the counter.

9. A circuit according to claim 5, characterized in that said gate of the exclusive OR type carries out a check on the n-1 most meaningful bits of the counter.

10. A method for measuring the horizontal scan frequency of a composite synchronism signal, comprising the steps of:

(a) initially measuring the duration between adjacent synchronization pulses, to obtain a stored value therefrom; and thereafter

(b) intermittently comparing the duration between adjacent synchronization pulses to said stored value, to ascertain whether the duration between adjacent synchronization pulses is significantly different from said stored value; and

(c) repeating said step (b) intermittently, until said step (b) indicates, for a predetermined plurality of repetitions, that the duration between adjacent synchronization pulses is significantly different from said stored value, and then initiating a resynchronization process and performing said step (a).

11. The method of claim 10, wherein said step (a) of measuring consists of counting clock pulses.

12. The method of claim 10, wherein said step (b) of intermittently comparing is performed periodically.

13. The method of claim 10, wherein said step (b) of comparing is performed at regular intervals of a predetermined number of lines.

14. The method of claim 10, wherein said step (b) of comparing ignores at least one least-significant bit position.

15. A circuit for measuring the horizontal scan frequency of a composite synchronism signal, comprising:

input circuitry connected to receive the composite synchronism signal and a clock signal, and to generate therefrom

a first output which repeatedly, at intervals determined by a count of said pulses of the composite synchronism signal, provides a burst of clock pulses corresponding to the separation between adjacent pulses in the composite synchronism signal, and

at least a first additional output which repeatedly, at intervals determined by a count of said pulses of the composite synchronism signal, provides a pulse after the end of said burst of clock pulses on said first output;

an up/down counter;

a memory connected to controllably transfer data to and receive data from said counter; and

logic circuitry connected to control transfer of data to and from said memory, and to control an up/down input of said counter, and to detect when said counter has a count value of approximately zero;

said logic circuitry being configured

to initially operate said counter in a first up/down direction to count pulses in one of said bursts, and thereafter

7

to transfer an initial count value from said counter into
said memory, and thereafter,
on each occurrence of a pulse on said first additional
output, to cause said counter to operate in a second
up/down direction starting from said initial count
value, and then to detect whether said counter
reaches a count value of approximately zero;
said logic circuitry returning said counter to operation
in said first up/down direction whenever said logic
circuitry twice successively detects that said counter,
while operating in a second up/down direction start-
ing from said initial count value, has not reached a
count value of approximately zero.

8

16. The circuit of claim 15, wherein said input circuitry is
a timer.

17. The circuit of claim 15, wherein said logic circuitry,
in detecting said counter has a count value of approximately
zero, ignores at least one least-significant bit of the count
value.

18. The circuit of claim 15, wherein said input circuitry
timer further comprises a second additional output which
repeatedly, at intervals determined by a count of said pulses
of the composite synchronism signal, provides a pulse after
the end of said burst of clock pulses on said first output and
prior to said pulse on said first additional output.

* * * * *