

US00RE42516E

(19) **United States**
(12) **Reissued Patent**
Kim et al.

(10) **Patent Number:** **US RE42,516 E**
(45) **Date of Reissued Patent:** **Jul. 5, 2011**

(54) **METHOD OF REMOVING BLOCKING ARTIFACTS IN A CODING SYSTEM OF A MOVING PICTURE**

(75) Inventors: **Hyun Mun Kim**, Rockville, MD (US); **Jong Beom Ra**, Taejeon-si (KR); **Sung Deuk Kim**, Taejeon-si (KR); **Young Su Lee**, Seoul (KR)

(73) Assignee: **Video Enhancement Solutions, LLC**, Frisco, TX (US)

(*) Notice: This patent is subject to a terminal disclaimer.

(21) Appl. No.: **11/851,517**

(22) Filed: **Sep. 7, 2007**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **6,240,135**
Issued: **May 29, 2001**
Appl. No.: **09/065,577**
Filed: **Apr. 24, 1998**

(30) **Foreign Application Priority Data**

Sep. 9, 1997 (KR) 1997-46368

(51) **Int. Cl.**
H04B 1/66 (2006.01)
G06K 9/40 (2006.01)

(52) **U.S. Cl.** **375/240.01**; 348/420; 382/268

(58) **Field of Classification Search** 375/240.01, 375/240.12, 240.13, 240.15, 240.24, 240.25, 375/240.26; 348/420.1, 403.1, 607; 382/236, 382/250, 252, 268, 275; 358/433, 432, 403; *H04B 1/66; G06K 9/40*

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,903,138 A 2/1990 Aragaki
4,941,043 A 7/1990 Jass
(Continued)

FOREIGN PATENT DOCUMENTS

EP 0808068 11/1997
(Continued)

OTHER PUBLICATIONS

Byeungwoo Jeon et al, Blocking Artifacts reduction in image compression with block boundary discontinuity criterion, Circuits and System for Video Technology, IEEE Transactions on, vol. Jun. 8, 1998, pp. 345-357.

(Continued)


Primary Examiner — Tung Vo

(74) *Attorney, Agent, or Firm* — Sherr & Vaughn, PLLC

(57) **ABSTRACT**

A method of coding a moving picture reduces blocking artifacts. The method includes defining pixel sets S₀, S₁, S₂ around a block boundary, selectively determining a deblocking mode as a default mode or a DC offset mode depending on the degree of blocking artifacts. If the default mode is selected, frequency information is obtained around the block boundary per pixel using a 4-point DCT kernel, for example, a magnitude of a discontinuous component belonging to the block boundary is replaced with a minimum magnitude of discontinuous components belonging to the surroundings of the block boundary in the frequency domain and the replacing step is applied to the spatial domain. If the DC offset mode is selected and a determination is made to perform DC offset mode, the blocking artifacts in a smooth region are removed in the DC offset mode.

17 Claims, 5 Drawing Sheets



U.S. PATENT DOCUMENTS

5,229,864 A * 7/1993 Moronaga et al. 382/261
 5,337,088 A 8/1994 Honjo
 5,367,385 A * 11/1994 Yuan 358/465
 5,422,964 A 6/1995 Devimeux
 5,454,051 A 9/1995 Smith
 5,565,921 A * 10/1996 Sasaki et al. 375/240.13
 5,590,064 A * 12/1996 Astle 708/203
 5,596,659 A * 1/1997 Normile et al. 382/253
 5,608,652 A * 3/1997 Astle 708/203
 5,629,778 A * 5/1997 Reuman 382/252
 5,677,736 A * 10/1997 Suzuki et al. 375/240.24
 5,680,477 A 10/1997 Asada
 5,740,283 A * 4/1998 Meeker 382/248
 5,787,204 A 7/1998 Fukuda
 5,787,210 A 7/1998 Kim
 5,796,875 A 8/1998 Read
 5,852,682 A 12/1998 Kim
 5,903,679 A * 5/1999 Park 382/253
 5,911,008 A * 6/1999 Niikura et al. 382/236
 5,923,376 A * 7/1999 Pullen et al. 375/240.16
 5,937,101 A 8/1999 Jeon
 5,949,917 A 9/1999 Kawasaka
 5,974,196 A 10/1999 Chang et al.
 6,028,867 A 2/2000 Rawson et al.
 6,028,967 A * 2/2000 Kim et al. 382/268
 6,040,879 A * 3/2000 Park 375/240.27
 6,052,490 A * 4/2000 Haskell et al. 382/268
 6,104,434 A * 8/2000 Nakagawa et al. 375/240.16
 6,144,700 A 11/2000 Kim
 6,151,420 A 11/2000 Wober
 6,167,164 A 12/2000 Lee et al.
 6,188,799 B1 2/2001 Tan et al.
 6,240,135 B1 5/2001 Kim
 6,314,209 B1 * 11/2001 Kweon et al. 382/243
 6,317,522 B1 11/2001 Rackett
 6,320,905 B1 11/2001 Konstantinides
 6,463,182 B1 10/2002 Onishi et al.
 6,614,946 B1 9/2003 Edgar
 6,724,944 B1 4/2004 Kalevo
 7,003,170 B1 2/2006 Martucci
 7,003,174 B2 2/2006 Kryukov
 7,006,255 B2 2/2006 Sun et al.
 7,031,393 B2 4/2006 Kondo
 7,054,503 B2 5/2006 Ishikawa
 7,209,594 B1 4/2007 Martucci
 7,233,706 B1 6/2007 Kim
 7,239,755 B1 7/2007 Kim et al.
 7,262,886 B2 8/2007 Kim et al.
 7,277,593 B2 10/2007 Kim
 7,283,681 B2 10/2007 Kim
 7,283,682 B2 10/2007 Kim
 7,289,682 B2 10/2007 Kim
 7,292,733 B2 11/2007 Monobe et al.
 7,305,142 B2 12/2007 Kim
 7,305,143 B2 12/2007 Kim
 7,359,569 B2 4/2008 Kim
 7,359,570 B2 4/2008 Kim
 7,362,913 B2 4/2008 Kim et al.
 7,362,914 B2 4/2008 Kim
 7,379,616 B2 5/2008 Kim
 7,379,617 B2 5/2008 Kim
 7,382,930 B2 6/2008 Kim et al.
 7,391,921 B2 6/2008 Kim
 7,391,922 B2 6/2008 Kim
 7,391,923 B2 6/2008 Kim
 7,391,924 B2 6/2008 Kim
 7,394,945 B2 7/2008 Kim
 7,397,853 B2 7/2008 Kwon et al.
 7,397,965 B2 7/2008 Kim
 7,397,966 B2 7/2008 Kim
 7,397,967 B2 7/2008 Kim
 7,400,780 B2 7/2008 Kim
 7,403,667 B2 7/2008 Kim et al.
 7,406,209 B2 7/2008 Kim

7,437,015 B2 10/2008 Kim
 7,454,082 B2 11/2008 Kim
 7,463,786 B2 12/2008 Kim
 7,492,959 B2 2/2009 Kim
 7,492,960 B2 2/2009 Kim
 7,492,961 B2 2/2009 Kim
 7,496,239 B2 2/2009 Kim
 7,499,598 B2 3/2009 Kim
 2003/0138160 A1 7/2003 Ishikawa
 2003/0194013 A1 10/2003 Alvarez
 2005/0196066 A1 9/2005 Kim et al.
 2005/0243911 A1 11/2005 Kwon
 2005/0243912 A1 11/2005 Kwon
 2005/0243913 A1 11/2005 Kwon
 2005/0243914 A1 11/2005 Kwon
 2005/0243915 A1 11/2005 Kwon
 2005/0243916 A1 11/2005 Kwon
 2005/0244063 A1 11/2005 Kwon
 2006/0159351 A1 7/2006 Bae et al.
 2006/0274959 A1 12/2006 Piastowski
 2007/0071095 A1 3/2007 Lim
 2007/0223835 A1 9/2007 Yamada et al.
 2008/0037893 A1 2/2008 Okumichi et al.

FOREIGN PATENT DOCUMENTS

JP 2002-232889 8/2002
 WO WO-02/096117 11/2002

OTHER PUBLICATIONS

Barzykina, E et al., Removal of blocking artifacts using random pattern filtering, Image Processing, 1999 International Conference, vol. 3, 1999, pp. 904-908 vol. 2.
 Mei-Yin Shen te al., Fast compression artifact reduction technique based on nonlinear filter, Circuits and Systems, 1999. ISCAS '99. Proceedings of the 1999 IEEE International Symposium on, vol. 4, 1999, pp. 179-182.
 Yung-Kai Lai et al., Removal of blocking artifacts of DCT transform by classified space-frequency filtering, Signals, System and Computers, 1995, Conference Record of the Twenty-Nine Asilmar Conference on, vol. 2, 1996, pp. 1457-1461.
 Kasezawa, T., Blocking artifacts reduction using discrete cosine transform, Consumer Electronics, IEEE Transactions on, vol. 43 Issue: 1, Feb. 1997, pp. 48-55.
 Avideh Zakhor, "Iterative Procedures for Reduction of Blocking Effects in Transform Image Coding", IEEE Transactions on Circuits and Systems For Video Technology, vol. 2, No. 1, pp. 91-95 (Mar. 1992).
 Yongyi Yang et al., "Regularized Reconstructions to Reduce Blocking Artifacts of Block Discrete Cosine Transform Compressed Images", IEEE Transactions On Circuits and Systems For Video Technology, vol. 3, No. 6, pp. 421-432 (Dec. 1993).
 Gary J. Sullivan et al., "Motion Compensation for Video Compression Using Control Grid Interpolation", IEEE International Conference, pp. 2713-2716 (1991).
 G. de Haan et al., "IC For Motion-Compression 100Hz TV With Natural-Motion Move-Mode", IEEE Transactions On Consumer Electronics, vol. 42, pp. 165-174 (Feb. 1996).
 Ozcelik, Taner et al., "Image and Video Compression Algorithms Based on Recovery Techniques Using Mean Field Annealing", Proceedings of the IEEE, vol. 83, No. 2, pp. 304-316, Feb. 1995.
 Nakajima, Yasuyuki, et al., "A PEL Adaptive Reduction of Coding Artifacts for MPEG Video Signals", pp. 928-932, IEEE, 1994.
 Lai, Yung-Kai et al., "Image Enhancement for Low Bit-rate JPEG and MPEG Coding via Postprocessing", Proc. SPIE vol. 2727 Feb. 1996, 1484-1494.
 Minami, Shigenobu et al., "An Optimization Approach for Removing Blocking Effects in Transform Coding", IEEE Transactions on Circuits and Systems for Video Technology, vol. 5 No. 2 Apr. 1995, 74-82.

* cited by examiner

FIG.1
Prior art




FIG.2




FIG. 3




FIG. 4

- Amended -




FIG. 5

post filter simulation results

condition	sequence	QP	bits	PSNR _Y									
				VM Only	Telenor Deblocking	PSL Deblocking	NS Deblocking	SEC Deblocking	SEC Deblocking	LGS Deblocking	LGS+SEC Deblocking		
10Kps	Hall monitor	17	98583	30.04	30.22	30.14	30.10	30.30	30.20	30.37	30.43		
	Container ship	17	93556	29.21	29.29	29.05	29.24	29.38	29.34	29.43	29.50		
7.5Hz	Mother & daughter	15	95578	32.32	32.43	32.35	32.30	32.31	32.44	32.49	32.48		
	Hall monitor	9	236220	33.82	34.03	33.85	33.90	34.09	34.00	34.20	34.24		
QCIF	Container ship	10	217480	32.36	32.44	32.08	32.36	32.50	32.49	32.54	32.61		
	Mother & daughter	8	231791	35.20	35.31	35.19	35.07	35.23	35.25	35.36	35.31		
48Kbps	Foreman	13	478108	30.91	30.97	30.89	30.87	30.95	31.00	31.06	31.07		
	Coast guard	14	446028	29.01	28.99	28.54	28.97	28.98	28.92	29.08	28.93		
10Hz	Mother & daughter	7	484658	34.30	34.45	34.28	34.11	34.34	34.36	34.48	34.48		
	News	18	472973	31.20	31.32	31.19	31.21	31.33	31.31	31.40	31.40		
CIF	Container ship	10	468027	36.06	36.22	36.07	35.93	36.08	36.13	36.18	36.08		
	Hall monitor	12	458086	33.59	33.61	33.82	33.64	33.89	33.74	34.02	34.02		
7.5Hz	News	11	1139868	34.00	34.13	34.06	33.97	34.17	34.13	34.26	34.29		
	Foreman	30	1184538	28.25	28.33	28.09	28.24	28.23	28.32	28.35	28.37		
15Hz	Coast guard	29	1172406	26.36	26.35	25.95	26.34	26.31	26.28	26.42	26.28		
	Stefan	13	9796735	29.00	29.02	28.31	28.97	29.05	29.05	29.12	29.13		
1Mbps	Mobile & Calendar	14	10259224	28.25	26.21	25.61	25.68	26.30	26.30	26.29	26.33		

**METHOD OF REMOVING BLOCKING
ARTIFACTS IN A CODING SYSTEM OF A
MOVING PICTURE**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

Notice: More than one reissue application has been filed for the reissue of U.S. Pat. No. 6,240,135. The reissue applications are application Ser. Nos. 11/834,312; 11/834,347; 11/851,551; 11/851,529; and 11/851,517 (the present application), each of which are divisional reissues of U.S. Pat. No. 6,240,135.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a method of coding data, and more particularly, to a method of removing blocking artifacts when coding image signals such as in a moving picture at low-bit-rate.

2. Background of the Related Art

Generally, to efficiently compress a time variable video sequence, it is necessary to remove redundancy in the temporal domain as well as in the two-dimensional spatial domain. In moving picture experts group (MPEG), discrete cosine transform (DCT) is used to remove the redundancy in the two-dimensional spatial domain while a motion compensation method is used to remove the redundancy in the temporal domain.

The DCT is a method of removing the correlativity between data through a two-dimensional spatial transformation. Each block in a picture is spatially transformed using the DCT after the picture is divided into blocks. Data that has been spatially transformed tends to be driven to a certain direction. Only a group of the data driven in the certain direction is quantized and transmitted.

Pictures, which are consecutive in the temporal domain, tend to form motions of a human being or an object at the center of the frame. This property is used to reduce the redundancy of the temporal domain in the motion compensation method. A volume of data to be transmitted can be minimized by taking out a similar region from the preceding picture to fill a corresponding region, which has not been changed (or has very little change), in the present picture. The operation of finding the most similar blocks between pictures is called a motion estimation. The displacement representing a degree of motion is called a motion vector. MPEG uses a motion compensation-DCT method so that the two methods combine.

When a compression technique is combined with a DCT algorithm, the DCT transform is usually performed after input data is sampled in a unit size of 8×8, and the transform coefficients are quantized with respect to a visual property using quantization values from a quantization table. Then, the data is compressed through a run length coding (RLC). The data processed with the DCT is converted from a spatial domain to a frequency domain and compressed through the quantization with respect to the visual property of human beings, not to be visually recognized. For example, since eyes of human beings are insensitive to a high frequency, a high frequency coefficient is quantized in a large step size.

For the quantized data, the data having a relatively high frequency is coded with a short code word. The quantized

data having a low frequency is coded with a long code word. Thus, the data is finally compressed.

In processing a moving picture as discussed above, blocks are individually processed to maximize the compression ratio and coding efficiency. However, the individual process causes blocking artifacts that disturb the eyes of human beings at boundaries between blocks.

A related art method of removing blocking artifacts will be described with reference to FIGS. 1 and 2. FIG. 1 is a pixel matrix illustrating a method for removing blocking artifacts. FIG. 2 is a pixel matrix illustrating block boundaries in horizontal and vertical directions.

Various algorithms have been presented for removing blocking artifacts that appear in a coding system, which individually processes blocks. For example, MPEG-4 used a deblocking filter by Telenor, which uses the following algorithm:

If B is replaced with B1 and C is replaced with C1,

$B1=B+d1$,

$C1=C-d1$, and

$d1=\text{sign}(d) \cdot (\text{MAX}(0, |d| - \text{MAX}(0, 2 \cdot |d| - QP)))$

where $d=(3A-8B+8C-3D)/16$ and QP denotes the quantization parameter of the macroblock where pixel C belongs.

In processing a MPEG-4 moving picture, blocking artifacts are removed using the above algorithm to improve picture quality. However, it is difficult to effectively remove the blocking artifacts with the above with a small operation capacity in a real time operation. For example, coding and decoding a moving picture is a real time operation. In other words, to completely remove the blocking artifacts, a large calculation amount is needed, which is undesirable in efficiency.

Alternatively, to remove the blocking artifacts, there is provided a method of changing processes of coding and decoding. This method increases the amount of bits to be transmitted.

Still another method for removing blocking artifacts is based on the theory of projection onto convex sets (POCS). However, this method is applied only to a still picture because of an iteration structure and long convergence time.

Thus, the related art methods for removing blocking artifacts in a coding system of a moving picture have several problems. First, in performing an algorithm for removing the blocking artifacts, a calculation is complicated and the calculation amount and time become correspondingly large. Further, the blocking artifacts are not removed in either complex regions or smooth regions in a picture. In addition, the amount of bits to be transmitted increases.

SUMMARY OF THE INVENTION

An object of the present invention is to provide a method of removing blocking artifacts in a coding system that substantially obviates one or more of the problems due to limitations and disadvantages of the related art.

Another object of the present invention is to remove blocking artifacts when necessary in a smooth portion of a moving picture.

Yet another object of the present invention is to provide a method of removing blocking artifacts in a coding system of a moving picture where blocking artifacts of the moving picture are removed at real time using frequency features around a block boundary without increasing the amount of bits.

To achieve at least the above objects in a whole or in parts, a method of removing blocking artifacts in a coding system according to the present invention includes determining at

least pixel sets S0, S1, S2 around a block boundary, selecting one of a default mode and a DC offset mode as a deblocking mode based on an amount of blocking artifacts, deblocking filtering pixels adjacent the block boundary if a default mode is selected, deblocking filtering of pixels adjacent the block boundary if a default mode is selected, and removing artifacts in the DC offset mode when the DC offset mode is selected and a DC offset mode condition is satisfied, where the artifacts are removed in the DC offset mode according to the following equation:

$$v_n = \sum_{k=-4}^4 b_k \cdot p_{n+k}, 1 \leq n \leq 8$$

$$P_m = (|v_1 - v_0| < QP) ? v_0 : v_1,$$

If $m < 1$;

v_m , if $1 \leq m \leq 8$;

$[(|v_8 - v_9| < QP) ? v_9 : v_8]$, if $m > 8$;

$(|v_8 - v_9| < QP) ? v_9 : v_8$, if $m > 8$;

$\{b_k : -4 \leq k \leq 4\} = \{1, 1, 2, 2, 4, 2, 2, 1, 1\} // 16$,

wherein $v_0 - v_9$ are boundary pixels, QP is the quantization parameter of a block adjacent the block boundary, and v_n is an adjusted pixel value.

To further achieve the above advantages and in accordance with the purpose of the present invention, as embodied and broadly described, a method of removing blocking artifacts in a coding system of a moving picture according to the present invention includes the steps of defining pixel sets S0, S1, S2 around block boundary, selectively determining a deblocking mode as a default mode or a DC offset mode depending on the degree of blocking artifacts after obtaining a mode decision value, obtaining frequency information around the block boundary per pixel using 4-point DCT kernel if the default mode is determined, replacing a magnitude of a discontinuous component belonging to the block boundary with a minimum magnitude of discontinuous components belonging to the surroundings of the block boundary in the frequency domain and applying this replacing step to the spatial domain, judging whether or not it is necessary to perform DC offset mode if the DC offset mode is determined, and removing the blocking artifacts in a smooth region when the judgment is to perform the DC offset mode.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be described in detail with reference to the following drawings in which like reference numerals refer to like elements wherein:

FIG. 1 is a diagram showing a pixel matrix illustrating a related art method of removing blocking artifacts;

FIG. 2 is a diagram showing a pixel matrix illustrating block boundaries in horizontal and vertical directions;

FIG. 3 is a schematic diagram showing a 4-point DCT basis;

FIG. 4 is a flow chart showing a preferred embodiment of a method of removing blocking artifacts according to the present invention; and

FIG. 5 is a table showing exemplary results of a preferred embodiment of a method of removing blocking artifacts according to the present invention.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

In a preferred embodiment of the present invention, blocking artifacts at a block boundary are removed in a frequency

domain not a spatial domain. Frequency features around the block boundary are preferably obtained using a 4-point DCT kernel, which can be easily calculated. Thus, a complex region at the block boundary can effectively be processed by extending the smoothness of a picture from the frequency domain to the spatial domain.

Using the 4-point DCT kernel has advantages that frequency analysis is possible and deblocking can easily be processed. Therefore, the 4-point DCT Kernel can efficiently remove the blocking artifacts of a real time moving picture.

The blocking artifacts appear at the block boundary between fixed block patterns in the form of a line of discontinuity. Accordingly, removal of the blocking artifacts involves transformation of the discontinuity of the block boundary region to continuity.

FIG. 2 shows a block boundary region in a horizontal or a vertical direction. In one-dimensional images consisting of four points such as S0, S1 and S2 located around the block boundary, S1 and S2 are individually processed with a block-unit compression method. Thus, S1 and S2 are not influenced by the blocking artifacts. However, S0 is located across a block boundary. Thus, S0 is directly influenced by the blocking artifacts.

In the preferred embodiment according to the present invention, frequency information in S1 and S2 is used to reduce the blocking artifacts from S0. When images change smoothly, image features of S0, S1 and S2 are similar to one another. This means that image features of S0, S1 and S2 are also similar to one another in the frequency domain.

Since the frequency features of S0, S1 and S2 are similar, the frequency component of S0 influenced by the blocking artifacts is adjusted considering the frequency components of S1, S2, which can remove the blocking artifacts. Here, DCT, which is widely applied as an image compression technique, is used as a frequency analysis tool.

The blocking artifacts may appear in both horizontal and vertical block boundaries. In the preferred embodiment according to the present invention, after the blocking artifacts at the horizontal block boundary are removed, the blocking artifacts at the vertical block boundary are removed.

Pixel sets S0, S1 and S2, which overlap, can be defined around the horizontal block boundary. S0 is a 4-point pixel set arranged across the block boundary while S1 and S2 are 4-point pixel sets that adjoin the block boundary.

That is to say, the pixel set S0 contains a discontinuity. The discontinuity in S0 is removed in the preferred embodiment using common information (e.g., between S0 and S2), which are not directly influenced by the discontinuity of the block boundary.

The 4-point DCT basis is used to get information around the block boundary and is shown in FIG. 3. The 4-point DCT basis vectors have symmetric and anti-symmetric properties. In other words, assuming the 4-point DCT coefficients of S0 are defined as $a_{0,0}$ (DC), $a_{1,0}$, $a_{2,0}$, $a_{3,0}$, although both $a_{2,0}$ and $a_{3,0}$ are the high frequency components, $a_{2,0}$ is symmetric and $a_{3,0}$ is anti-symmetric around the center.

As shown in FIG. 2, since the center of S0 is coincident with the block boundary, a factor directly affecting the block discontinuity is not the symmetric component but the anti-symmetric component. Thus, in the preferred embodiment the magnitude of $a_{3,0}$ in the frequency domain is adjusted based on the anti-symmetric component so that the block discontinuity can be adjusted. An appropriate adjustment of $a_{3,0}$ in the frequency domain is directly related to the removal of the block discontinuity in the spatial domain.

Operations for reduction or removal of the block discontinuity will now be described. In the preferred embodiment, the

5

magnitude of $a_{3,0}$ is replaced with the minimum value of the magnitudes of $a_{3,1}$ and $a_{3,2}$. By doing this, a large blocking artifact, which appears when one side of the block boundary to be processed is smooth, can be removed. For a complex region where both S1 and S2 are the objects of motion (i.e., all the values of the magnitudes of $a_{3,0}$, $a_{3,1}$ and $a_{3,2}$ are large), there is little influence on the block boundary.

A method for removing the blocking artifacts in a default mode in the preferred embodiment is as follows:

$$v_4' = v_4 - d;$$

$$v_5' = v_5 + d; \text{ and}$$

$$d = \text{CLIP}(c_2 \cdot (a_{3,0}' - a_{3,0}) / c_3, 0, (v_4 - v_5) / 2) * \delta(|a_{3,0}| < \text{QP}),$$

where $a_{3,0}' = \text{SIGN}(a_{3,0}) * \text{MIN}(|a_{3,0}|, |a_{3,1}|, |a_{3,2}|)$,

$$a_{3,0} = ([c_1 - c_2 \ c_2 - c_1] * [v_3 \ v_4 \ v_5 \ v_6]^T) / c_3,$$

$$a_{3,1} = ([c_1 - c_2 \ c_2 - c_1] * [v_1 \ v_2 \ v_3 \ v_4]^T) / c_3, \text{ and}$$

$$a_{3,2} = ([c_1 - c_2 \ c_2 - c_1] * [v_5 \ v_6 \ v_7 \ v_8]^T) / c_3.$$

Thus, boundary pixels v_4 and v_5 that adjoin the boundary are replaced with v_4' and v_5' , respectively. QP is the quantization parameter of the macroblock where pixel v_5 belongs. Values c_1 , c_2 , c_3 are kernel constants used in the 4-point DCT. The values of c_1 and c_2 are approximated to an integer, and the value of c_3 is approximated to a multiple of 2. The values of $a_{3,0}$, $a_{3,1}$, $a_{3,2}$ are evaluated from the simple inner product of the DCT kernel and the pixel sets S0, S1 and S2.

The condition $|a_{3,0}| < \text{QP}$ is used to count the influence of the quantization parameter on the blocking artifacts. The condition $|a_{3,0}| < \text{QP}$ also prevents over-smoothing when the blocking artifacts are not very serious. The clipping operation on the compensated value is performed to prevent the direction of the gradient at the block boundary from being enlarged or changed in an opposite direction.

This filtering process is performed in both horizontal and vertical block boundaries. In this manner, the blocking artifacts in the whole frame can be removed.

In the default mode, only the boundary pixel values v_4 and v_5 are compensated. Thus, the default mode is not sufficient to remove the blocking artifacts in a very smooth region, such as a setting in a picture. Therefore, in the preferred embodiment the blocking artifacts in the smooth region are removed by a DC offset mode.

A method for removing the blocking artifacts in the DC offset mode in the preferred embodiment is as follows:

$$\text{max} = \text{MAX}(v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8),$$

$$\text{min} = \text{MIN}(v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8),$$

$$\text{if}(|\text{max} - \text{min}| < 2\text{QP}), /*\text{low pass filtering}*/$$

$$v_n = \sum_{k=-4}^4 b_k \cdot p_{n+k}, \quad 1 \leq n \leq 8$$

$$p_m = (|v_1 - v_0| < \text{QP}) ? v_0 : v_1,$$

if $m < 1$;

v_m , if $1 \leq m \leq 8$;

$[(|v_8 - v_9| < \text{QP}) \ v_9 : v_8, \text{ if } m > 8];$

$(|v_8 - v_9| < \text{QP}) ? v_9 : v_8, \text{ if } m > 8;$

$\{b_k : -4 \leq k \leq 4\} = \{1, 1, 2, 2, 4, 2, 2, 1, 1\} // 16.$

If the absolute value of the maximum data value minus minimum data value in the block boundary pixels is smaller than twice the quantization parameter (i.e., if deblocking is required), the blocking artifacts in the smooth region are removed by the DC offset mode.

6

The decision to use the default mode or to use the DC offset mode is preferably made based on the following condition:

$$\text{Mode decision value}(\text{eq_cnt}) = \phi(v_0 - v_1) + \phi(v_1 - v_2) + \phi(v_2 - v_3) + \phi(v_3 - v_4) + \phi(v_4 - v_5) + \phi(v_5 - v_6) + \phi(v_6 - v_7) + \phi(v_7 - v_8) + \phi(v_8 - v_9),$$

where $\phi(\gamma) = 1$ if $|\gamma| \leq \text{THR1}$ (first threshold value) and $\phi(\gamma) = 0$ otherwise.

If the mode decision value $\text{eq_cnt} \geq \text{THR2}$ (i.e., a second threshold value), the DC offset mode is applied. In the remaining cases, default mode is applied.

A method for removing the blocking artifacts to code a moving picture at low-rate-bit according to the preferred embodiment of the present invention will be described with reference to FIG. 4. After beginning in FIG. 4, control continues to step 401S. In step 401S, three pixel sets S0, S1, S2 are defined based on the horizontal block boundary. From step 401S, control continues to step 402S.

In step 402S, the mode decision value (e.g., eq_cnt) is determined and control continues to step 403S. In step 403S, the mode decision value is compared with a decision value (e.g., a second threshold value THR2 preferably set by a user) to perform deblocking filtering process by selecting the mode depending on the degree of the blocking artifacts in the picture.

If the determination in step 403S is negative, control continues to step 404S where the default mode is set. From step 404S, control continues to step 405S where frequency information around the block boundary on each of the pixel is determined, for example, using the 4-point DCT kernel. From step 405S, control continues to step 406S.

In step 406S, the magnitude of the discontinuous component belonging to the block boundary is replaced with the minimum magnitude of the discontinuous components belonging to the surroundings of the block boundary in the frequency domain. This adjusting operation is applied to the spatial domain. That is, the magnitude of the discontinuous component belonging to the block boundary is replaced with the minimum magnitude of the discontinuous components belonging to the surroundings of the block boundary in the spatial domain.

In the default mode of the preferred embodiment, the blocking artifacts are removed in step 406S using the method as described below:

$$v_4' = v_4 - d;$$

$$v_5' = v_5 + d; \text{ and}$$

$$d = \text{CLIP}(c_2 \cdot (a_{3,0}' - a_{3,0}) / c_3, 0, (v_4 - v_5) / 2) * \delta(|a_3| < \text{QP}),$$

where $a_{3,0}' = \text{SIGN}(a_{3,0}) * \text{MIN}(|a_{3,0}|, |a_{3,1}|, |a_{3,2}|)$,

$$a_{3,0} = ([c_1 - c_2 \ c_2 - c_1] * [v_3 \ v_4 \ v_5 \ v_6]^T) / c_3,$$

$$a_{3,1} = ([c_1 - c_2 \ c_2 - c_1] * [v_1 \ v_2 \ v_3 \ v_4]^T) / c_3,$$

$$a_{3,2} = ([c_1 - c_2 \ c_2 - c_1] * [v_5 \ v_6 \ v_7 \ v_8]^T) / c_3. \text{ In the default mode,}$$

the blocking artifacts are effectively removed in a complex region. However, the default mode does not sufficiently remove blocking artifacts in a smooth region.

If the determination in step 403S is affirmative, control continues to step 407S where the DC offset mode is set to remove the blocking artifacts. From step 407S, control continues to step 408S where the minimum and maximum data values (min, max) are determined. From step 408S, control continues to step 409S where a determination is made to remove the blocking artifacts in the default mode. If the determination in step 409S is negative, the process ends. If the determination in step 409S is affirmative, control continues to step 410S.

7

In the DC offset mode according to the preferred embodiment, in step 410S, the blocking artifacts are removed using the following algorithm.

max=MAX($v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8$),
min=MIN($v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8$),
if(|max-min|<2.QP), /*low pass filtering*/

$$v_n = \sum_{k=-4}^4 b_k \cdot p_{n+k}, 1 \leq n \leq 8$$

$$P_m = (|v_1 - v_0| < QP) ? v_0 : v_1,$$

if m<1;
 v_m , if $m \leq m \leq 8$;
[($|v_8 - v_9| < QP$) $v'_9 : v_8$, if $m > 8$];
($|v_8 - v_9| < QP$)? $v_9 : v_8$, if $m > 8$;
{ b_k : $-4 \leq k \leq 4$ } = {1,1,2,2,4,2,2,1,1} //16.

The maximum data value and the minimum data value in the block boundary pixels are obtained in step 408S. Then, if the absolute value of the maximum data value minus the minimum data value is smaller than 2QP (i.e., if deblocking is required), the blocking artifacts in the smooth region are removed by the DC offset mode in steps 409S and 410S.

From step 406S and 410S, control continues to step 411S. If the deblocking filtering process around the horizontal block boundary is completed, the deblocking filtering process around the vertical block boundary is performed in step 411S. From step 411S, control continues to step 412S.

In step 412S, the deblocking filtering processes around the horizontal and vertical block boundaries repeat over the whole frame. From step 412S, the process ends.

FIG. 5 is a table illustrating exemplary PSNR properties according to the method of removing the blocking artifacts of the preferred embodiment. The conditions yielding the exemplary results of FIG. 5 are as follows:

300 frames (only the initial frame was coded in intra.);
Fixed QP;
H.263 quantization;
F_code=1;
Enable DC/AC prediction; and
Rectangular shape VOP.

As shown in FIG. 5, the method for removing the blocking artifacts of the preferred embodiment improves results relative to VM (no filtering) of MPEG-4.

As described above, the method for removing the blocking artifacts according to the preferred embodiments of the present invention has various advantages. The deblocking filtering process is performed using features of the frequency domain so that the blocking artifacts are effectively removed. Further, the blocking artifacts are removed in both the complex and smooth regions. Thus, an excellent image or picture quality is provided. In addition, amount of bits does not increase.

The foregoing embodiments are merely exemplary and are not to be construed as limiting the present invention. The present teaching can be readily applied to other types of apparatuses. The description of the present invention is intended to be illustrative, and not to limit the scope of the claims. Many alternatives, modifications, and variations will be apparent to those skilled in the art.

What is claimed is:

[1. A method for removing blocking artifacts in a coding system of a moving picture comprising the steps of:

determining a plurality of pixel sets around a block boundary;

selecting one of a first mode and a second mode as a deblocking mode based on a degree of blocking artifacts;

8

performing an analysis, if the first mode is selected, comprising,

obtaining frequency information for each of the plurality of pixel sets,

5 replacing a magnitude of at least one discontinuous component in the frequency domain of a selected pixel set of the plurality of pixel sets belonging to the block boundary with a magnitude of at least one corresponding discontinuous component belonging to a replacement pixel set of the plurality of pixel sets near the block boundary, and

applying the replaced frequency information of the selected pixel set to the spatial domain to remove the blocking artifacts; and

15 removing the blocking artifacts in the second mode, if the second mode is selected and a second mode condition is satisfied.]

[2. The method as claimed in claim 1, wherein the magnitude of the discontinuous component of the selected pixel set is replaced with a minimum value of a magnitude of discontinuous components of one of a first pixel set and a second pixel set when the selected pixel set is located across the block boundary and the first and second pixel sets are located within a block adjacent the block boundary.]

25 **[3.** The method of claim 1, further comprising determining a mode decision value, wherein the second mode is selected if the mode decision value is greater than a first threshold value.]

30 **[4.** The method as claimed in claim 3, wherein mode decision value is determined based on the following equation:

$$\text{mode decision value} = \phi(v_0 - v_1) + \phi(v_1 - v_2) + \phi(v_2 - v_3) + \phi(v_3 - v_4) + \phi(v_4 - v_5) + \phi(v_5 - v_6) + \phi(v_6 - v_7) + \phi(v_7 - v_8) + \phi(v_8 - v_9),$$

35 wherein $\phi(\gamma) = 1$ when $|\gamma| \leq$ a second threshold value and $\phi(\gamma) = 0$ otherwise, and wherein $v_0 - v_9$ are boundary pixel values.]

40 **[5.** The method as claimed in claim 1, wherein the second mode condition is satisfied when an absolute value of a maximum data value minus a minimum data value in block boundary pixels is smaller than 2QP, wherein the maximum data value = MAX($v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8$), the minimum data value = MIN($v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8$), QP is the quantization parameter of a block adjacent the block boundary and $v_1 - v_8$ are pixels.]

45 **[6.** The method as claimed in claim 1, wherein the second mode performs low pass filtering to remove the blocking artifacts.]

50 **[7.** The method as claimed in claim 1, wherein the deblocking filtering in the default mode is performed by replacing the magnitude of the discontinuous component of pixels v_4 and v_5 that sandwich the block boundary with v_4' and v_5' , according to the following equation:

$$v_4' = v_4 - d$$

$$v_5' = v_5 + d$$

$$55 d = \text{CLIP}(c_2 \cdot (a_{3,0}' - a_{3,0}) / c_3, 0, (v_4 - v_5) / 2) * \delta(|a_{3,0}| < QP)$$

$$a_{3,0}' = \text{SIGN}(a_{3,0}) * \text{MIN}(|a_{3,0}|, |a_{3,1}|, |a_{3,2}|)$$

$$a_{3,0} = ([c_1 - c_2 \ c_2 - c_1] * [v_3 \ v_4 \ v_5 \ v_6]^T) / c_3$$

$$a_{3,1} = ([c_1 - c_2 \ c_2 - c_1] * [v_1 \ v_2 \ v_3 \ v_4]^T) / c_3$$

$$a_{3,2} = ([c_1 - c_2 \ c_2 - c_1] * [v_5 \ v_6 \ v_7 \ v_8]^T) / c_3,$$

60 where QP is the quantization parameter of the block containing the pixel v_5 , values c_1, c_2, c_3 are kernel constants used in a DCT, and values of $a_{3,0}, a_{3,1}, a_{3,2}$ are the discontinuous component in each of the plurality of pixel sets, respectively.]

[8. The method as claimed in claim 7, wherein c_1 and c_2 are approximated to an integer and c_3 is approximated to a multiple of 2, wherein the DCT is a 4-point DCT used to determine the frequency information, and wherein $a_{3,0}, a_{3,1}, a_{3,2}$

9

are evaluated from an inner product of the DCT kernel and the selected pixel set being S0, a first pixel set S1 and a second pixel set S2.]

[9. The method as claimed in claim 7, wherein $|a_{3,0}| < QP$ prevents over-smoothing.]

[10. The method as claimed in claim 1, further comprising performing the deblocking filtering process around horizontal and vertical block boundaries in a frame.]

[11. The method of claim 1, wherein the removing blocking artifacts in the second mode satisfies the following equation:

$$v_n = \sum_{k=-4}^4 b_k \cdot p_{n+k}, 1 \leq n \leq 8$$

$$P_m = (|v_1 - v_0| < QP) ? v_0 : v_1,$$

if $m < 1$;

v_m , if $1 \leq m \leq 8$;

$(|v_8 - v_9| < QP) v_9 : v_8$, if $m > 8$;

$\{b_k: -4 \leq k \leq 4\} = \{1, 1, 2, 2, 4, 2, 2, 1, 1\} // 16$,

where $v_0 - v_9$ are boundary pixels, QP is the quantization parameter of a block adjacent the block boundary, and v_n is an adjusted pixel value.]

[12. The method of claim 1, wherein the replacement pixel set contains a minimum magnitude of the at least one corresponding discontinuous component.]

[13. The method of claim 1, wherein the first mode is the default mode and the second mode is the DC offset mode, and wherein each of the plurality of pixel sets has four pixels.]

14. A method for removing blocking artifacts in a coding system comprising:

determining at least pixel sets S0, S1, S2 around a block boundary;

selecting one of a default mode and a DC offset mode as a deblocking mode based on an amount of blocking artifacts;

deblocking filtering of pixels adjacent the block boundary if the default mode is selected, *and if a magnitude of the blocking artifacts is less than a quantization parameter QP used in coding a block adjacent to the block boundary*; and

removing artifacts in the DC offset mode, if the DC offset mode is selected and a DC offset mode condition is satisfied, wherein the artifacts are removed in the DC offset mode according to the following equation:

$$v_n = \sum_{k=-4}^4 b_k \cdot p_{n+k}, 1 \leq n \leq 8$$

$$P_m = (|v_1 - v_0| < QP) ? v_0 : v_1,$$

if $m < 1$;

v_m , if $1 \leq m \leq 8$;

$(|v_8 - v_9| < QP) v_9 : v_8$, if $m > 8$;

$(|v_8 - v_9| < QP) ? v_9 : v_8$, if $m > 8$;

$\{b_k: -4 \leq k \leq 4\} = \{1, 1, 2, 2, 4, 2, 2, 1, 1\} // 16$

wherein $v_0 - v_9$ are boundary pixels, QP is the [quantation] quantization parameter of [a] the block adjacent to the block boundary, and v_n is an adjusted pixel value,

wherein b_k and p_{n+k} are variables used to calculate the adjusted pixel value v_n where n is an integer among 1, 2, 3, 4, 5, 6, 7, and 8,

10

wherein b_k changes according to a value of k where k is one of $-4, -3, -2, -1, 0, 1, 2, 3, 4$,

wherein p_{n+k} is decided according to p_m where $m = n+k$ and m is an integer,

wherein P_m is one of boundary pixels values v_0 to v_9 according to given conditions of $(|v_1 - v_0| < QP)$ and $(|v_9 - v_0| < QP)$ and a value of m .

15. The method of claim 14, wherein the deblocking filtering step comprises:

obtaining frequency information for each of the plurality of pixel sets S0, S1, S2;

replacing a magnitude of at least one discontinuous component in the frequency domain of a selected pixel set S0 of the plurality of pixel sets belonging to the block boundary with a magnitude of at least one corresponding discontinuous component belonging to a replacement pixel set S1, S2 of the plurality of pixel sets near the block boundary; and

applying the replaced frequency information of the selected pixel set S0 to the spatial domain to remove the blocking artifacts.

16. The method of claim 14, further comprising determining a mode decision value, wherein the DC offset mode is selected if the mode decision value is greater than a first threshold value, wherein mode decision value is determined based on the following equation:

$$\text{mode decision value} = \phi(v_0 - v_1) + \phi(v_1 - v_2) + \phi(v_2 - v_3) + \phi(v_3 - v_4) + \phi(v_4 - v_5) + \phi(v_5 - v_6) + \phi(v_6 - v_7) + \phi(v_7 - v_8) + \phi(v_8 - v_9),$$

wherein $\phi(\gamma) = 1$ when $|\gamma| \leq a$ second threshold value and $\phi(\gamma) = 0$ otherwise, [and]

wherein $v_0 - v_9$ are boundary pixel values, *and*

wherein $\phi(\gamma)$ is a function generating 1 or 0 according to $|\gamma|$ and γ is a variable denoting a result of subtraction of two given boundary pixel values.

17. The method of claim 14, wherein the DC offset mode condition is satisfied when an absolute value of a maximum data value minus a minimum data value in block boundary pixels is smaller than $2QP$, wherein the maximum data value = $\text{MAX}(v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8)$, the minimum data value = $\text{MIN}(v_1, v_2, v_3, v_4, v_5, v_6, v_7, v_8)$, QP is the quantization parameter of a block adjacent the block boundary and $v_1 - v_8$ are the block boundary pixels.

18. The method of claim 14, wherein the deblocking filtering in the default mode is performed by replacing the magnitude of the discontinuous component of pixels v_4 and v_5 sandwiching the block boundary with v_4' and v_5' , according to the following equation:

$$v_4' = v_4 - d$$

$$v_5' = v_5 + d$$

$$[d = \text{CLIP}(c_2 \cdot (a_{3,0}' - a_{3,0}) / c_3, 0, (v_4 - v_5) / 2) * \delta(|a_{3,0}| < QP)$$

$$d = \text{CLIP}(c_2 \cdot (a_{2,0}' - a_{3,0}) / c_3, 0, (v_4 - v_5) / 2) * \delta(|a_{3,0}| < QP)$$

$$a_{3,0}' = \text{SIGN}(a_{3,0}) * \text{MIN}(|a_{3,0}|, |a_{3,1}|, |a_{3,2}|)$$

$$a_{3,0} = ([c_1 - c_2 \ c_2 - c_1] * [v_3 \ v_4 \ v_5 \ v_6]^T) / c_3$$

$$a_{3,1} = ([c_1 - c_2 \ c_2 - c_1] * [v_1 \ v_2 \ v_3 \ v_4]^T) / c_3$$

$$a_{3,2} = ([c_1 - c_2 \ c_2 - c_1] * [v_5 \ v_6 \ v_7 \ v_8]^T) / c_3,$$

where QP is the quantization parameter of the block containing the pixel v_5 , values c_1, c_2, c_3 are kernel constants used in a 4-point DCT, and values of $a_{3,0}, a_{3,1}, a_{3,2}$ are based on a simple inner product of the DCT kernel and the selected pixel set S0, a first pixel set S1 and the second pixel set S2, *and*

wherein $a_{3,0}, a_{3,1},$ and $a_{3,2}$ represent DCT coefficients of corresponding pixel sets,

wherein d is a variable used to calculate v_4' and v_5' and denotes a result of a function CLIP (x, p, q) where $x, p,$ and q are integers,

11

wherein the function $CLIP(x, p, q)$ clips x to a value between p and q ,

wherein $\delta(\text{condition})$ is a function generating 1 if the "condition" is true and generating 0 if the "condition" is not true,

wherein T denotes a transpose of vector matrix, and wherein $v_1, v_2, v_3, v_4, v_5, v_6, v_7,$ and v_8 denote boundary pixel values.

19. The method of claim 14, further comprising performing the determining through removing steps for each horizontal and vertical block boundaries in a frame.

20. The method of claim 14, further comprising: dividing a picture into blocks that each include multiple pixels, wherein the pixels of a first block are separated from pixels of a neighboring second block by the block boundary; and

obtaining frequency information for a neighboring second pixel of the second block,

wherein deblocking filtering of the pixels adjacent the block boundary further comprises adjusting a first pixel of the first block based upon the neighboring second pixel if the magnitude of the blocking artifacts is less than a quantization parameter of the second block.

21. The method of claim 20,

wherein adjusting the first pixel further comprises replacing a pixel value v_3 of the first pixel with a value v_3' , wherein the value v_3' is expressed as:

$v_3' = v_3 - d$,

wherein d is expressed as:

$d = CLIP(c_2(a_{3,0}' - a_{3,0}) / c_3, 0, (v_2 - v_4) / 2) * \delta(|a_{3,0}| < QP)$,

wherein $a_{3,0}'$ is expressed as:

$a_{3,0}' = SIGN(a_{3,0}) * MIN(|a_{3,0}|, |a_{3,1}|, |a_{3,2}|)$,

wherein QP represents a quantization parameter of the second block, c_2 , and c_3 represent DCT kernel coefficients, and v_4 represents a pixel value of the neighboring second pixel,

12

wherein $a_{3,0}, a_{3,1},$ and $a_{3,2}$ represent DCT coefficients of corresponding pixel sets,

wherein d is a variable used to calculate v_3' and denotes a result of a function $CLIP(x, p, q)$ where $x, p,$ and q are integers,

wherein the function $CLIP(x, p, q)$ clips x to a value between p and q , and

wherein $\delta(\text{condition})$ is a function generating 1 if the "condition" is true and generating 0 if the "condition" is not true.

22. The method of claim 21, wherein $\delta(|a_{3,0}| < QP) = 1$ if $|a_{3,0}| < QP$, and wherein $\delta(|a_{3,0}| < QP) = 0$ if $|a_{3,0}| \geq QP$.

23. The method of claim 21, wherein c_2 is an interger and c_3 is a multiple of 2.

24. The method of claim 23, wherein $c_2 = 5$ and $c_3 = 8$.

25. The method of claim 20, further comprising applying the adjusting operation to a spatial domain of the first pixel.

26. The method of claim 20, wherein the block boundary is a vertical or horizontal block boundary.

27. The method of claim 20, further comprising adjusting the neighboring second pixel based upon frequency information of the first pixel.

28. The method of claim 20, wherein a magnitude of the adjusting operation is constrained to be no greater than half of the difference between a value of the first pixel and a value of the second pixel, using a clipping function.

29. The method of claim 20, wherein a magnitude of the adjusting operation is based upon a minimum magnitude of frequency information of the first and second pixels.

30. The method of claim 20, wherein a magnitude of the adjusting operation is based upon frequency information of the first pixel and the neighboring second pixel.

* * * * *