

US00RE43812E

(19) **United States**  
(12) **Reissued Patent**  
**Schilling**

(10) **Patent Number:** **US RE43,812 E**  
(45) **Date of Reissued Patent:** **\*Nov. 20, 2012**

(54) **MULTIPLE-INPUT MULTIPLE-OUTPUT (MIMO) SPREAD-SPECTRUM SYSTEM AND METHOD**

(75) Inventor: **Donald L. Schilling**, Palm Beach Gardens, FL (US)

(73) Assignee: **Linex Technologies, Inc.**, West Long Branch, NJ (US)

(\*) Notice: This patent is subject to a terminal disclaimer.

(21) Appl. No.: **13/044,110**

(22) Filed: **Mar. 9, 2011**

**Related U.S. Patent Documents**

Reissue of:

(64) Patent No.: **7,068,705**  
Issued: **Jun. 27, 2006**  
Appl. No.: **10/862,198**  
Filed: **Jun. 7, 2004**

U.S. Applications:

(63) Continuation of application No. 12/147,104, filed on Jun. 26, 2008, now Pat. No. Re. 42,219, which is a continuation of application No. 10/254,461, filed on Sep. 25, 2002, now Pat. No. 6,757,322, and a continuation of application No. 09/665,322, filed on Sep. 19, 2000, now Pat. No. 6,466,610, and a continuation of application No. 09/198,630, filed on Nov. 24, 1998, now Pat. No. 6,128,330.

(51) **Int. Cl.**  
**H04B 1/00** (2006.01)

(52) **U.S. Cl.** ..... **375/141; 375/143; 375/144; 375/267; 375/347**

(58) **Field of Classification Search** ..... **375/147-149, 375/316, 340, 342; 455/132-135, 137**  
See application file for complete search history.

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

2,520,188 A	8/1950	Yando
3,144,647 A	8/1964	Sichak
3,204,035 A	8/1965	Ballard et al.
3,214,691 A	10/1965	Sproul et al.
3,311,832 A	3/1967	Schrader
3,383,599 A	5/1968	Miyagi
3,488,445 A	1/1970	Chang
3,500,303 A	3/1970	Johnson
3,633,107 A	1/1972	Brady
3,652,939 A	3/1972	Levasseur
3,751,596 A	8/1973	Tseng

(Continued)

**OTHER PUBLICATIONS**

U.S. Appl. No. 60/103,770, filed Oct. 9, 1998, Chheda et al.


(Continued)

*Primary Examiner* — Khanh C Tran

(57) **ABSTRACT**

A system and method for transmitting a plurality of spread-spectrum signals over a communications channel having fading. The plurality of spread-spectrum signals are radiated by a plurality of antennas, with each antenna preferably spaced by one-quarter wavelength. A plurality of receiver antennas receive the plurality of spread-spectrum signals and a plurality of fading spread-spectrum signals. Each receiver antenna is coupled to a plurality of matched filters having a respective plurality of impulse responses matched to the chip-sequence signals of the plurality of spread-spectrum signals. A RAKE and space-diversity combiner combines, for each respective chip-sequence signal, a respective plurality of detected spread-spectrum signals and a respective multiplicity of detected-multipath-spread-spectrum signals, to generate a plurality of combined signals. The symbol amplitudes can be measured and erasure decoding employed to improve performance.

**33 Claims, 5 Drawing Sheets**



# US RE43,812 E

Page 2

U.S. PATENT DOCUMENTS							
4,075,566	A	2/1978	D'Arcangelis	5,625,876	A	4/1997	Gilhousen et al.
4,112,370	A	9/1978	Monsen	5,633,889	A	5/1997	Schilling
4,112,430	A	9/1978	Ladstatter	5,636,242	A *	6/1997	Tsujimoto ..... 375/130
4,160,952	A	7/1979	Seastrand, Jr.	5,642,353	A	6/1997	Roy, III et al.
4,189,677	A	2/1980	Cooper et al.	5,648,983	A	7/1997	Kostic et al.
4,203,071	A	5/1980	Bowles et al.	5,652,764	A	7/1997	Kanzaki et al.
4,210,871	A	7/1980	Hill et al.	5,657,325	A	8/1997	Lou et al.
4,217,586	A	8/1980	McGuffin	5,657,343	A	8/1997	Schilling
4,278,978	A	7/1981	Easterling et al.	5,659,572	A	8/1997	Schilling
4,281,411	A	7/1981	Bonn et al.	5,680,419	A	10/1997	Bottomley
4,298,871	A	11/1981	Kennedy et al.	5,697,084	A	12/1997	Tingley
4,347,627	A	8/1982	Alter	5,748,623	A	5/1998	Sawahashi et al.
4,369,520	A	1/1983	Cerny, Jr. et al.	5,768,685	A	6/1998	Patel et al.
4,385,378	A	5/1983	Kreutel, Jr.	5,771,229	A	6/1998	Gavrilovich
4,425,639	A	1/1984	Acampora et al.	5,781,845	A	7/1998	Dybdal et al.
4,528,674	A	7/1985	Sweeney et al.	5,793,744	A	8/1998	Kanerva et al.
4,608,701	A	8/1986	Burgers et al.	5,809,060	A	9/1998	Cafarella et al.
4,615,040	A	9/1986	Mojoli et al.	5,812,542	A	9/1998	Bruckert et al.
4,656,642	A	4/1987	Apostolos et al.	5,825,807	A	10/1998	Kumar
4,670,885	A	6/1987	Parl et al.	5,828,658	A	10/1998	Ottersten et al.
4,694,467	A	9/1987	Mui	5,848,103	A	12/1998	Weerackody
4,707,839	A	11/1987	Andren et al.	5,856,971	A	1/1999	Gitlin et al.
4,715,048	A	12/1987	Masamura	5,859,840	A	1/1999	Tiedemann, Jr. et al.
4,723,321	A	2/1988	Saleh	5,859,842	A	1/1999	Scott
4,731,801	A	3/1988	Henriksson	5,859,875	A	1/1999	Kato et al.
4,733,402	A	3/1988	Monsen	5,859,879	A	1/1999	Bolgiano et al.
4,748,682	A	5/1988	Fukae et al.	5,864,548	A	1/1999	Liu
4,789,983	A	12/1988	Acampora et al.	5,886,987	A	3/1999	Yoshida et al.
4,797,950	A	1/1989	Rilling	5,887,021	A *	3/1999	Keskitalo et al. .... 375/144
4,817,089	A	3/1989	Paneth et al.	5,887,037	A	3/1999	Golden et al.
4,849,990	A	7/1989	Ikegami et al.	5,914,933	A	6/1999	Cimini et al.
4,901,307	A	2/1990	Gilhousen et al.	5,926,205	A	7/1999	Schilling
5,001,723	A	3/1991	Kerr	5,926,503	A	7/1999	Kelton et al.
5,028,931	A	7/1991	Ward	5,930,230	A	7/1999	Odenwalder et al.
5,048,057	A	9/1991	Saleh et al.	5,940,452	A	8/1999	Rich
5,063,571	A	11/1991	Vancraeynest	5,943,362	A	8/1999	Saito
5,081,643	A	1/1992	Schilling	5,943,372	A	8/1999	Gans et al.
5,081,645	A	1/1992	Resnikoff et al.	5,943,652	A	8/1999	Sisley et al.
5,109,390	A	4/1992	Gilhousen et al.	5,949,833	A	9/1999	Weerackody
5,155,742	A	10/1992	Ariyavisitakul et al.	5,956,369	A	9/1999	Davidovici et al.
5,166,951	A *	11/1992	Schilling ..... 375/145	5,960,039	A	9/1999	Martin et al.
5,228,053	A	7/1993	Miller et al.	5,966,644	A	10/1999	Suzuki
5,228,055	A	7/1993	Uchida et al.	5,982,825	A *	11/1999	Tsujimoto ..... 375/347
5,249,302	A	9/1993	Metroka et al.	5,991,332	A	11/1999	Lomp et al.
5,260,968	A	11/1993	Gardner et al.	5,999,560	A	12/1999	Ono
5,274,665	A	12/1993	Schilling	6,005,876	A	12/1999	Cimini, Jr. et al.
5,276,703	A	1/1994	Budin et al.	6,014,405	A	1/2000	Garodnick et al.
5,280,472	A	1/1994	Gilhousen et al.	6,018,317	A	1/2000	Dogan et al.
5,282,222	A	1/1994	Fattouche et al.	6,026,115	A	2/2000	Higashi
5,289,499	A	2/1994	Weerackody	6,052,378	A	4/2000	Park
5,291,515	A	3/1994	Uchida et al.	6,058,105	A	5/2000	Hochwald et al.
5,329,547	A	7/1994	Ling	6,064,338	A	5/2000	Kobayakawa et al.
5,345,302	A	9/1994	Wiedemann et al.	6,064,663	A	5/2000	Honkasalo et al.
5,345,467	A	9/1994	Lomp et al.	6,067,324	A	5/2000	Harrison
5,345,599	A	9/1994	Paulraj et al.	6,069,871	A	5/2000	Sharma et al.
5,351,269	A	9/1994	Schilling	6,069,912	A	5/2000	Sawahashi
5,369,663	A	11/1994	Bond	6,072,787	A	6/2000	Hamalainen et al.
5,400,359	A	3/1995	Hikoso et al.	6,073,032	A	6/2000	Keskitalo et al.
5,404,374	A	4/1995	Mullins et al.	6,078,576	A	6/2000	Schilling et al.
5,416,797	A	5/1995	Gilhousen et al.	6,081,536	A	6/2000	Gorsuch et al.
5,422,908	A	6/1995	Schilling	6,085,104	A *	7/2000	Kowalski et al. .... 455/506
5,422,913	A	6/1995	Wilkinson	6,087,986	A	7/2000	Shoki et al.
5,424,050	A	6/1995	Lamerant	6,088,408	A	7/2000	Calderbank et al.
5,437,055	A	7/1995	Wheatley, III	6,097,712	A	8/2000	Secord et al.
5,471,497	A	11/1995	Zehavi	6,097,771	A	8/2000	Foschini
5,479,448	A	12/1995	Seshadri	6,108,565	A	8/2000	Scherzer
5,504,936	A	4/1996	Lee	6,115,157	A	9/2000	Barnard et al.
5,515,378	A	5/1996	Roy, III et al.	6,115,406	A	9/2000	Mesecher
5,517,686	A	5/1996	Kennedy et al.	6,115,427	A	9/2000	Calderbank et al.
5,528,581	A	6/1996	De Bot	6,127,971	A	10/2000	Calderbank et al.
5,548,582	A	8/1996	Brajal et al.	6,128,276	A	10/2000	Agee
5,550,810	A	8/1996	Monogioudis et al.	6,128,486	A	10/2000	Keskitalo et al.
5,555,257	A	9/1996	Dent	6,144,711	A	11/2000	Raleigh et al.
5,561,686	A	10/1996	Kobayashi et al.	6,154,485	A	11/2000	Harrison
5,583,851	A *	12/1996	Kato et al. .... 370/342	6,154,659	A	11/2000	Jalali et al.
5,592,490	A	1/1997	Barratt et al.	6,157,512	A	12/2000	Weerackody et al.
5,614,914	A	3/1997	Bolgiano et al.	6,157,612	A	12/2000	Weerackody et al.
5,621,752	A	4/1997	Antonio et al.	6,167,039	A	12/2000	Karlsson et al.
				6,173,005	B1	1/2001	Kotzin et al.

6,178,196	B1	1/2001	Naguib et al.	
6,185,258	B1	2/2001	Alamouti et al.	
6,185,266	B1	2/2001	Kuchi et al.	
6,188,736	B1	2/2001	Lo et al.	
6,192,066	B1	2/2001	Asanuma	
6,192,068	B1	2/2001	Fattouche et al.	
6,198,749	B1	3/2001	Hui et al.	
6,198,775	B1	3/2001	Khayrallah et al.	
6,201,799	B1	3/2001	Huang et al.	
6,205,127	B1	3/2001	Ramesh	
6,208,669	B1	3/2001	Cimini, Jr. et al.	
6,219,162	B1	4/2001	Barnard et al.	
6,222,498	B1	4/2001	Ishii et al.	
6,232,927	B1	5/2001	Inoue et al.	
6,256,290	B1	7/2001	Ramesh	
6,269,238	B1	7/2001	Hashem et al.	
6,289,039	B1	9/2001	Garodnick	
6,298,038	B1	10/2001	Martin et al.	
6,301,293	B1	10/2001	Huang et al.	
6,304,561	B1	10/2001	Jin et al.	
6,307,882	B1	10/2001	Marzetta	
6,310,870	B1	10/2001	Li	
6,317,422	B1	11/2001	Khaleghi et al.	
6,317,466	B1	11/2001	Foschini et al.	
6,320,889	B1	11/2001	Chang et al.	
6,327,310	B1	12/2001	Hochwald et al.	
6,330,289	B1	12/2001	Keashly et al.	
6,353,626	B1	3/2002	Sunay	
6,373,831	B1	4/2002	Secord et al.	
6,373,832	B1	4/2002	Huang et al.	
6,377,613	B1 *	4/2002	Kawabe et al.	375/142
6,377,631	B1	4/2002	Raleigh et al.	
6,385,181	B1	5/2002	Tsutsui et al.	
6,389,000	B1	5/2002	Jou	
6,421,333	B1	7/2002	Jalali	
6,430,216	B1	8/2002	Kober et al.	
6,430,231	B1	8/2002	Calderbank et al.	
6,438,142	B1	8/2002	Bousquet	
6,470,194	B1	10/2002	Miya et al.	
6,512,737	B1	1/2003	Agee	
6,522,639	B1	2/2003	Kitade et al.	
6,526,064	B1	2/2003	Bousquet	
6,529,545	B2	3/2003	Tiirola et al.	
6,549,585	B2	4/2003	Naguib et al.	
6,590,889	B1	7/2003	Preuss et al.	
6,618,430	B1	9/2003	Khaleghi et al.	
6,618,454	B1	9/2003	Agrawal et al.	
6,621,858	B2	9/2003	Sourour et al.	
6,693,982	B1	2/2004	Naguib et al.	
6,704,370	B1	3/2004	Chheda et al.	
6,714,548	B2	3/2004	Lauret	
6,741,635	B2	5/2004	Lo et al.	
6,748,024	B2	6/2004	Kuchi et al.	
6,763,073	B2	7/2004	Foschini et al.	
6,775,329	B2	8/2004	Alamouti et al.	
6,847,658	B1	1/2005	Ling et al.	
6,888,899	B2	5/2005	Raleigh et al.	
6,904,076	B1	6/2005	Tsutsui et al.	
7,110,433	B2	9/2006	Feher	
7,194,237	B2	3/2007	Sugar et al.	
7,215,718	B1	5/2007	Calderbank et al.	
7,746,823	B2	6/2010	Schilling et al.	
7,876,709	B2	1/2011	Schilling et al.	
2001/0050964	A1	12/2001	Foschini et al.	

OTHER PUBLICATIONS

Takashi Inque et al, "Two-Dimensional Rake Reception Scheme for DS/CDMA Systems in DBF Antenna Configuration", ATR Adaptive Communication Research Laboratories, Soraku-gun, Kyoto, Japan, IEEE, Oct. 1997, 5 pages.

Ryuji Kohno et al, "Adaptive Array Antenna Combined with Tapped Delay Line Using Processing Gain for Spread-Spectrum CDMA Systems"; Yokohama National University, Yokohama, Japan, IEEE 1992, 5 pages.

Vijitha Weerackody, Diversity for the Direct-Sequence Spread Spectrum System Using Multiple Transmit Antennas; AT&T Bell Laboratories, Murray Hill, NJ, IEEE 1993, 5 pages.

Reinhard Jungbauer et al, "Coding for a CDMA-System with Higher User Data Rates by Combining Several Traffic Channels", Technical University of Munich, 7pgs.

G.D. Golden et al, "V-Blast: A High Capacity Space-Time Architecture for the Rich-Scattering Wireless Channel"; Wireless Communications Research Dept. Bell Laboratories, Lucent Technologies, International Symposium on Advanced Radio Technologies, Boulder, CO, Sep. 9-11, 1998, 14 pages.

Gerald J. Foschini, "Layered Space-Time Architecture for Wireless Communication in a Fading Environment When Using Multi-Element Antennas", Bell Labs Technical Journal, Autumn, 1996, 19 pages.

G.J. Foschini et al, "On Limits of Wireless Communications in a Fading Environment when Using Multiple Antennas", Wireless Personal Communications 6: 311-335, 1998.

G.D. Golden et al, "Detection algorithm and initial laboratory results using V-Blast space-time communication architecture", Electronics Letters, Jan. 7, 1999, vol. 35, 2 pgs.

Ryuji Kohno, "Spatial and Temporal Communication Theory Using Adaptive Antenna Array", Yokoham National University, Feb. 1998, 8 pgs.

Internet citation, BLAST: Bell Labs Layered Space-Time, An Architecture for Realizing Very High Data Rates over Fading Wireless Channels; rav@bell-labs.com, 3 pgs.

The Thirty-Second Asilomar Conference on Signals, Systems & Computers, Nov. 1-4, 1998, Pacific Grove, CA, Constantinos Papadias et al, "Adaptive Multi-User Detection of Fading CDMA Channels Using Antenna Arrays", Bell Laboratories/Lucent Technologies, Holmdel, NJ, 7 pgs.

48th IEEE Vehicular Technology Conference, May 18-21, 1998, Pathway to a Global Wireless Revolution, K.K. Wong et al, "Investigating the Performance of Smart Antenna Systems at the Mobile and Base Stations in the Down and Uplinks", Dept. of Electrical & Electronic Engineering, Hong Kong University of Science & Technology, Kowloon, Hong Kong, 7pgs.

P.W. Wolniansky et al. "V-BLAST: An Architecture for Realizing Very High Data Rates Over the Rich Scattering Wireless Channel", Bell Laboratories, Lucent Technologies, NJ, 7pp. 1998 URSI Symposium on Signals, Systems and Electronics.

Paulrai, A. "Space-time Processing for Third-Generation Wireless Networks," First Annual UCSD Conference on Wireless Communications in Cooperation with the IEEE Communications Society, Conference Record, 1998, pp. 133-137, San Diego CA.

Diouris, J.F., Zeidler, J., Buijore, S., "Space-Path Diversity in CDMA using a Compact Array," Anales de Telecommunications, Nov.-Dec. 1998, vol. 53, No. 11-12, pp. 425-434.

Vandendorpe, L., Van De Wiel, O., "Performance Analysis of Linear MIMO Equalizers for Multitone DS/SS Systems in Multipath Channels," Wireless Personal Communications, 1995, vol. 2, No. 1-2, pp. 145-165.

K. Rohani, "Open-Loop Transmit Diversity for CDMA Forward Link," Motorola Labs, 5 pgs.

Kondo, Y. et al, "Linear Predictive Transmission Diversity for TDMA/TDD Personal Communication Systems," IEICE Transactions on Communications, vol. E79-B, No. 10, Oct. 1996, 6 pgs.

Pauw, C.K., Schilling, D.L., "Probability of Error for M-ary PSK and DPSK on a Rayleigh Fading Channel," IEEE Transactions on Communications, vol. 36, No. 6, Jun. 1988, 2pgs.

Schilling, D.L., Milstein, L.B., Pichholtz, R.L., Brown, R.W., "Optimization of the Processing Gain of an M-ary Direct Sequence Spread Spectrum Communication System," IEEE Transactions on Communications, vol.-Com-28, No. 8, Aug. 1980, 10 pages.

Milstein, L.B., Schilling, D.L., "Performance of a Spread Spectrum Communication System Operating Over a Frequency-Selective Fading Channel in the Presence of Tone Interference," IEEE Transactions on Communications, vol. Com-30, No. 1., Jan. 1982, 6 pages.

Jensen, M., "A Guide to Improving Internet Access in Africa with Wireless Technologies," IDRC Study, Aug. 31, 1996, 3 pgs.

Gohring, N., "Nortel Demos CDMA High Speed Data," (Internet Article) www.telephonyonline.com/telecom\_nortel\_demos\_cdma, Jul. 13, 1998.

Internet Citation "Blast High-Level Overview" www1.bell-labs.com/project/blast/high-level-overview.html.

- Hanlen, L., Minyue, F., "Multiple Antenna Wireless Communication Systems: Limits to Capacity Growth", *Wireless Communication & Networking Conf. 2002*, 5pp.
- Jeong, I., Nakagawa, M., "A Novel Transmission Diversity System in TDD-CDMA," 1988 IEEE International Symposium on Spread Spectrum Techniques and Applications—Proceedings, Sep. 2-4, 1998, 6pgs.
- Park, M., "Performance Evaluation of Multiuser Detectors with V-Blast to MIMO Channel," Thesis submitted to the faculty of Virginia Polytechnic Institute and State University Blacksburg, VA, May 2003.
- Ramos, J. Zoltowski, M.D., Liu, H., "A Low-Complexity Space-Time RAKE Receiver for DS-SS," *IEEE Signal Processing Letters*, vol. 4, No. 9, Sep. 1997.
- Vandendorpe, L. et al., "MIMO DFE Equalization for Multitone DS/SS Systems over Multipath Channels," *IEEE Journal on Selected Areas in Communications*, vol. 14, No. 3, Apr. 1996.
- Weerackody, V., "Diversity for the Direct-Sequence Spread Spectrum System Using Multiple Transmit Antennas", *IEEE Int'l Conf. on Communications ICC '93*, Geneva, Switzerland, May 23-26, 1993, 6 pgs.
- Snoeren, Alex C., "Adaptive Inverse Multiplexing for Wide-Area Wireless Networks", Laboratory for Computer Science, M.I.T., *IEEE Globe Com. Rio de Janeiro*, Dec. 1999, 8 pgs.
- Pottie, Gregory J., "Wireless Multiple Access Adaptive Communications Techniques", Univ. of CA, LA, Elect. Eng. Dept., *Enycl. of Telecommun.* vol. 18, 1999, pp. 1-41.
- Kohno, Ryuji, "Spatially and Temporally Joint Optimum Transmitter—Receiver Based on Adaptive Array Antenna for Multi-User Detection in DS/CDMA", *Yokohama University, Japan. 1996 IEEE 4th Int'l Symposium on Spread Spectrum Techniques and Applications Proceedings*, Sep. 22-25, 1996, Mainz, Germany, 7 pgs.
- Rashid-Farrokh, Farrokh et al., "Transmit Beamforming and Power Control for Cellular Wireless Systems", *IEEE Journal on Selected Areas in Communications*, vol. 16, No. 8, Oct. 1998, 14 pages.
- Kohno, Ryuji et al., "Adaptive Array Antenna Combined with Tapped Delay Line Using Processing Gain for Spread-Spectrum CDMA Systems", *Yokohama National University, PIMRC '92*, Oct. 19-21, 1992, Boston, MA, 6 pages.
- Kohno, Ryuji et al., "Combination of an Adaptive Array Antenna and a Canceller of Interference for Direct-Sequence Spread-Spectrum Multiple-Access System", *IEEE journal on Selected Areas in Communications*, vol. 8., No. 4 May 1990, 8 pages.
- Wang, Jian-Guo et al., "An Adaptive Antenna Array with Parallel Beamformers for Indoor Radio Channel Enhancement", *University of Technology, Sydney, Australia, 1997 IEEE 47th Vehicular Technology Conference*, Phoenix, Arizona, May 4-7, 1997, 7pgs.
- Winters, Jack H., "On the Capacity of Radio Communication Systems with Diversity in a Rayleigh Fading Environment", *IEEE Journal on Selected Areas in Communications*, vol. SAC-5, No. 5, Jun. 1987, 8 pgs.
- Zacarias, Eduardo B., "BLAST Architectures", *Signal Processing Laboratory, S-72.333 Postgraduate Course in Radio Communications*, Autumn 2004, 6 pgs.
- Pickholtz, Raymond L. et al., "Revisions to 'Theory of Spread-Spectrum Communications—A Tutorial'", *IEEE*, Feb. 1984, 2 pgs.
- Shah, A., Hamovich, A.M., "On Spatial and Temporal Processing for CDMA Overlay Situations," *Department of Electrical and Computer Engineering, New Jersey Institute of Technology*, pp. 365-368, *IEEE 1997*.
- Buijore, S., Diouris, J.F., Zeidler, J., Milstein, L., "Performance Enhancements for DS-SS Receivers Using Space-Path Diversity," *Department of Electrical and Computer Engineering, University of California San Diego*, pp. 1108-1112, *IEEE 1997*.
- Shah, A., Halmovich, A.M., "Performance of Space-Time Receiver Architectures for CDMA Overlay of Narrowband Waveforms for Personal Communication Systems," *Department of Electrical and Computer Engineering, New Jersey Institute of Technology*, pp. 314-318, *IEEE 1997*.
- Baghaie, R., Werner, S., Laakso, T., "Pipelined Implementation of Adaptive Multiple-Antenna CDMA Mobile Receivers," *Helsinki University of Technology*, pp. 3229-3232, *IEEE 1998*.
- Winters, J.H., Gans, M.J., "The Range Increase of Adaptive Versus, Phased Arrays in Mobile Radio Systems," *ATT&T Bell Laboratories*, pp. 109-115, *IEEE 1995*.
- Diouris, J.F., Buljore, S. Zeidler, J., Saillard, J., "Space-Time Diversity Received for DS-SS Systems," *Department of Electrical and Computer Engineering, University of California, San Diego*, pp. 367-370, *IEEE 1997*.
- Pauraj, A.J., Ng, B.C., "Space-Time Modems for Wireless Personal Communications," *IEEE Personal Communications*, pp. 36-48, Feb. 1998.
- Ramos, J., Zoitowski, M.D., Martinez-Ramon, M., "Space-Time Optimal Combination for DS-SS. The 2D RAKE Receiver," *Telecommunications Engineering Department, University Carlos III of Madrid, Spain*, pp. 951-954, *IEEE 1998*.
- Hochwald, B.M., Marzetta, T.L., "Unitary Space-Time Modulation for Multiple-Antenna Communications in Rayleigh Flat Fading," *Bell Laboratories*.
- Rong, Z., Petrus, P., Rappaport, T.S., Reed, J.H., "Despread-Respread Multi-Target Constant Modulus Array for CDMA Systems," *IEEE Communications Letters*, vol. 1, No. 4, pp. 114-116, Jul. 1997.
- Winters, J.H., "Optimum Combining in Digital Mobile Radion with Cochannel Interference," *IEEE Journal on Selected areas in Communications*, vol. SAC-2, No. 4, pp 528-539, Jul. 1984.
- Winters, J.H., "Optimum Combining for Indoor Radio Systems with Multiple Users," *IEEE Transactions on Communications*, vol. COM-35, No. 11, pp. 1222-1230, Nov. 1987.
- Rohani, K., Harrison, M., Kuchi, K., "A Comparison of Base Station Transmit Diversity Methods for Third Generation Cellular Standards," *Motorola Labs, Access Technology Research*, pp. 351-355, *IEEE 1999*.
- Ban, K., Katayama, M., Yamazato, T., Ogawa, A., "A Simple Transmit/Receive Antenna Diversity for Indoor DS/CDMA Wireless Communications Systems," *IEICE Transactions on Communications*, vol. E80-B, No. 12, pp. 1790-1797, Dec. 1997.
- Cimini, Jr. L. Chuang, J.C., Sollenberger, N.R., "Advanced Cellular Internet Services (ACIS)," *IEEE Communications Magazine*, pp. 150-159, Oct. 1998.
- Seshadri, N., Sundberg, C.E., Weerackody, V., "Advanced Techniques for Modulation Error Correction, Channel Equalization, and Diversity," *AT&T Technical Journal*, pp. 48-62, Jul./Aug. 1993.
- Tehrani, A.M., Hassibi, A., Cioffi, J., Boyd, S., "An Implementation of Discrete Multi-Tone over Slowly Time-Varying Multiple-Input/Multiple-Output Channels," *Information Systems Lab, Department of Electrical Engineering, Stanford University*, Feb. 1998.
- Ojanpera, T., Prasad, R., "An Overview of Third-Generation Wireless Personal Communications, a European Perspective," *IEEE Personal Communications*, pp. 59-65, Dec. 1998.
- Ban, K., Katayama, M., Stark, W.E., Yamazato, T., Ogawa, A., "Convolutionally Coded DS/SS System Using Multi-Antenna Transmission," *Department of Information Electronics, Nagoya University, Japan*, pp. 92-96, *IEEE 1997*.
- Womell, G.W., Trott, M.D., "Efficient Signal Processing Techniques for Exploiting Transmit Antenna Diversity on Fading Channels," *IEEE Transactions on Signal Processing*, vol. 45, No. 1, pp. 191-205, Jan. 1997.
- Pickholtz, Raymond L. et al., "Theory of Spread-Spectrum Communications—A Tutorial", *IEEE Transactions on Communications*, vol. COM-30, No. 5, May 1982, 30 pgs.
- Jones, V.K. et al., "Channel Estimation for Wireless OFDM Systems", *Clarity Wireless, Inc., Belmont, CA*, 1998 *IEEE*, 6 pgs.
- Raleigh, Gregory G. et al., "Multivariate Modulation and Coding for Wireless Communication", *IEEE Journal on Selected Areas in Communications*, vol. 17, No. 5, May 1999, 15 pgs.
- Releigh, G.G. et al., "Spatio-Temporal Coding for Wireless Communications", *Information Systems Lab, Stanford Univ. CA*, 1996 *IEEE*, 6 pgs.
- Raleigh, Gregory G. et al., "Spatio-Temporal Coding for Wireless Communication", *IEEE Transactions on Communications*, vol 46, No. 3, Mar. 1998, 10 pgs.
- Chheda, Ashvin et al., "Performance Evaluation of Two Transmit Diversity Techniques for cdma2000", *Nortel Wireless Networks, Richardson, TX*, *IEEE 1999*, 5 pgs.

- Saifuddin, Ahmed et al, "Performance Evaluation of DS/CDMA Scheme with Diversity Coding and MUI Cancellation over Fading Multipath Channel", Communication Research Laboratory, Tokyo, Japan and Yokohama National University, Yokohama, Japan, IEEE 1996, 5 pgs.
- Agrawai, Dakshi et al, "Space-Time Coded OFDM for High Data-Rate Wireless Communication Over Wideband Channels", Coordinated Science Lab, University of IL, Urbana, IL and AT&T Labs Research, Florham Park, NJ, IEEE 1998, 5 pgs.
- Tarokh, Vahid et al, "Space-Time Codes for High Data Rate Wireless Communication: Performance Criterion and Code Construction", IEEE Transactions on Information Theory, vol. 44, No. 2, Mar. 1998, 22 pgs.
- Tehrani, Ardavan Maleki et al, "Space-Time Coding and Transmission Optimization for Wireless Channels", Information Systems Lab, Stanford University, CA, 1998 IEEE, 5 pgs.
- Tehrani, Ardavan Maleki et al, "Space-Time Coding and Transmission Optimization for Wireless Channels", Information Systems Lab, Stanford University, CA, IEEE 1999, 5 pgs.
- Rashi-Farrokhi, F. et al., "Transmit and Receive Diversity and Equalization in Wireless Networks with Fading Channels", University of MD, College Park, MD, 1997 IEEE, 6 pgs.
- Hottinen, Ari et al, "Transmit Diversity by Antenna Selection in CDMA Downlink", Nokia Research Center, Finland, 1998 IEEE, 4 pgs.
- Rajan, Dinesh, Rice University, Houston, TX and Gray, Steven D., Nokia Research Center, Irving, TX, Transmit Diversity Schemes for CDMA-2000, 1999 IEEE, 5 pgs.
- Li, Ye (Geoffrey) et al, "Transmitter Diversity for OFDM Systems and Its Impact on High-Rate data Wireless Networks", IEEE Journal on Selected Areas in Communications, vol. 17, No. 7, Jul. 1999, 11 pgs.
- Li, Ye.(Geoffrey) et al, "Transmitter Diversity for OFDM Systems with Mobile Wireless Channels", AT&T Labs—Research, IEEE 1998, 6 pgs.
- Seshadn, N. and Winters, Jack H., "Two Signaling Schemes for Improving the Error Performance of Frequency-Division-Duplex (FDD) Transmission Systems Using Transmitter Antenna Diversity", AT&T Bell Laboratories, Murray Hill and Holmdel, NJ. IEEE 1993, 4 pgs.
- Zvonar, Zoran, "Combined Multiuser Detection and Diversity Reception for Wireless CDMA Systems", IEEE Transactions on Vehicular Technology, vol. 45, No. 1, Feb. 1996, 7 pgs.
- Naguib, Ayman and Paulraj, Arogyaswami, "Performance of Wireless CDMA with M-ary Orthogonal Modulation and Cell Site Antenna Arrays", IEEE Journal on Selected Areas in Communications, vol. 14, No. 9, Dec. 1996, 14 pgs.
- Thompson, John S. et al, "Smart Antenna Arrays for CDMA Systems", IEEE Personal Communications, Oct. 1996, 10 pgs.
- Xiang, W., Waters, D., Pratt, T.G., Barry, J., Walkenhorst, B., "Implementation and Experimental Results of a Three-Transmitter Three-Receiver OFDM/BLAST Testbed," IEEE Communications Magazine, pp. 88-95, Dec. 2004.
- Rappaport, S.S., Schilling, D.L., "A Two-Level Coarse code Acquisition Scheme for Spread Spectrum Radio," IEEE Transactions on Communications, vol. COM-28, No. 9, pp. 1734-1742, Sep. 1980.
- Milstein, L., Davidovici, S., Schilling, D.L., "The Effect of Multiple-Tone Interfering Signals on a Direct Sequence Spread Spectrum Communication System," IEEE Transactions on Communications, vol. COM-30, No. 3, pp. 436-446, Mar. 1982.
- Schilling, D.L., Milstein, L., Pickholtz, R.L., Brown, R.W., "Optimization of the Processing Gain of an M-ary Direct Sequence Spread Spectrum Communication System," IEEE Transactions on Communications, vol. COM-29, No. 8, pp. 1389-1398, Aug. 1980.
- Milstein, L., Pickholtz, R.L., Schilling, D.L., "Comparison of Performance in Digital Modulation Techniques in the Presence of Adjacent Channel Interference," IEEE Transactions on Communication, vol. COM-30, No. 8, pp. 1984-1993, Aug. 1982.
- Milstein, L., Schilling, D.L., Pickholtz, R.L., "Comparison of Performance of 16-ary QASK and MSK Over a Frequency Selective Rician Fading Channel," IEEE Transactions on Communication, vol. COM-29, No. 11, pp. 1622-1633, Nov. 1981.
- Putman, C.A., Rappaport, S.S., Schilling, D.S., "Tracking of Frequency-Hopped Spread-Spectrum Signals in Adverse Environments," IEEE Transactions on Communications, vol. COM-31, No. 8, pp. 955-964, Aug. 1983.
- Putman, C.A., Rappaport, S.S., Schilling, D.S., "A Comparison of Schemes for Coarse Acquisition of Frequency-Hopped Spread Spectrum Signals," IEEE Transactions on Communications, vol. COM-31, No. 2, pp. 183-189, Feb. 1983.
- Hemmali, F., Schilling, D.L., "Upper Bounds on the Partial Correlation of PN Sequences," IEEE Transactions on Communications, vol. COM-31, No. 7, Jul. 1983.
- Davidovici, S., Milstein, L.B., Schilling, D.L., "A New Rapid Acquisition Technique for Direct Sequence Spread-Spectrum Communications," IEEE Transactions on Communications.
- Schilling, D.L., "Wireless Communications Going into the 21st Century," IEEE Transactions on Vehicular Technology, vol. 43, No. 3, pp. 645, Aug. 1994.
- Del Re, E., Fantacci, F., Morosi, S., Marapodi, S., "A Low-Complexity Multiuser Detector for Asynchronous CDMA QPSK Systems with Adaptive Antenna Arrays," Dipartimento di Ingegneria Elettronica IEEE 1998.
- Schilling, D.L., Bozovic, R., "On the Performance of Spectrally Efficient Trellis Coded FM Modulation Employing Noncoherent FM Demodulation," IEEE Journal on Selected Areas in Communications, vol. 9, No. 9, pp. 1318-1327, Dec. 1989.
- Subramanian, S., Shpak, D.J., Antoniou, A., "An Indoor Wireless System, Strategy Based on a Multiple-Antenna-Multiple-Equalizer System," pp. 206-209, Dept. of Electrical and Computer Engineering, University of Victoria, B.C., Canada, 1997 IEEE.
- Zoltowski, M.D., Chen, Y-F., "Joint Angle and Delay Estimation for Reduced Dimension Space-Time Rake Receiver with Application to IS-95 CDMA Uplink," pp. 606-610, School of Electrical and Computer Engineering, Purdue University, West Lafayette, Indiana, 1998 IEEE.
- Milstein, L.B., Davidovici, S., Schilling, D.L., "Coding and Modulation Techniques for Frequency-Hopped Spread-Spectrum Communications over a Pulse-Burst Jammed Rayleigh Fading Channel," IEEE Journal on Selected Areas in Communications, vol. SAC-3, No. 5, pp. 644-651, Sep. 1985.
- Pickholtz, R.L., Milstein, L.B., Schilling, D.L., "Spread Spectrum for Mobile Communications," IEEE Transactions on Vehicular Technology, vol. 40, No. 2, pp. 313-322 May 1991.
- Schilling, D.L., Milstein, L.B., Pickholtz, R.L., Kullback, M., Miller, F., "Spread Spectrum for Commercial Communications," IEEE Communications Magazine, pp. 66-79 Apr. 1991.
- Schilling, D.L., Milstein, L.B., Pickholtz, R.L., Bruno, F., Kanlerakis, E., Kullback, M., Erceg, V., Biederman, W., Fishman, D., Salerno, D., "Broadband CDMA for Personal Communications Systems," IEEE Communications Magazine, pp. 86-93, Nov. 1991.
- Erceg, V., Ghassemzadeh, S., Taylor, M., Li, D., Schilling, D.L., "Urban/Suburban Out-of-Sight Propagation Modeling," IEEE Communications Magazine, pp. 56-61 Jun. 1992.
- Milstein, L.B., Schilling, D.L., Pickholtz, R.L., Erceg, V., Kullback, M., Kanterakis, E., Fishman, D.S., Biederman, W.H., Salerno, D.C., "On the Feasibility of a CDMA Overlay for Personal Communications Networks," IEEE Journal on Selected Areas in Communications, vol. 10, No. 4, pp. 655-668, May 1992.
- Werner, S., Laakso, T., "Adaptive Multiple-Antenna Receiver for CDMA Mobile Reception," Helsinki University of Technology, pp/1053-1057, IEEE 1998.
- Buljore, S., Honig, M.L., Zeidler, J., Milstein, L., "Adaptive Multi-Sensor Receivers for Frequency Selective Channels in DS-SS-CDMA Communications Systems," Department of Electrical & Computer Engineering, University of California, La Jolla, California, 1998 IEEE.
- Zetterberg, P., "An Advanced Base Station Antenna System for Future Mobile Radion," Royal Institute of Technology, pp. 617-621. Stockholm, Sweden, IEEE 1997.
- Zoltowski, M.D., Chen, Y-F., Ramos, J., "Blind 2-D Rake Receivers Based on Space-Time Adaptive MVDR Processing for IS-95 CDMA System," School of Electrical Engineering, pp. 618-622, Purdue University, West Lafayette, Indiana, 1996 IEEE.

- Ban, K., Katayama, M., Yamazato, T., Ogawa, A., "The DS/CDMA System Using Transmission Diversity for Indoor Wireless Communications," Dept. of Information Electr., pp. 808-812 Nagoya University, Nagoya, Japan, 1996 IEEE.
- Pados, D.A., Bataiama, S.N., "Fast Joint Space-Time Adaptive Processing for DS/SS Antenna Array Systems," Dept. of Electrical Engineering, pp. 328-332, State University of NY, Buffalo, New York IEEE 1998.
- Kato, O., Miya, K., Homma, K., Kitade, T., Hayashi, M., Watanabe, M., "Experimental Performance Results of Coherent Wideband DS-CDMA with TDD Scheme," IEICE Trans. Commun., vol. E81-B., No. 7, pp. 1337-1344, Jul. 1998.
- Winters, J.H., "On the Capacity of Radio Communication Systems with Diversity in a Rayleigh Fading Environment," IEEE Jour. Selected Areas in Comm., vol. SAC-5, No. 5, Jun. 1997.
- Raleigh, G.G., Jones, V.K., "Multivariate Modulation and Coding for Wireless Communication," IEEE Journal on Selected Areas in Commun., vol. 17, No. 5, pp. 851-866, May 1999.
- Raleigh, G.G., Jones, V.K., "Multivariate Modulation and Coding for Wireless Communication," Clarity Wireless, Inc., pp. 3261-3269, IEEE 1998.
- Raleigh, G.G., Cioffi, J.M., "Spatio-Temporal Coding for Wireless Communication," IEEE Transactions on Commun., vol. 46, No. 3, pp. 357-366, Mar. 1998.
- Pickholtz, R.L., Milstein, L.B., Schilling, D.L., "Spread Spectrum for Mobile Communications," IEEE Transactions on Vehicular Tech., vol. 40, No. 2, pp. 313-322, May 1991.
- Padgett, Jay E. et al, "Overview of Wireless Personal Communications," IEEE Communications Magazine, Jan. 1995, pp. 28-41.
- Weng, Jianfeng et al, "Multistage Interference Cancellation with Diversity Reception for QPSK Asynchronous DS/CDMA System over Multipath Fading Channels", Dept. of Electrical and Computer Engineering, Concordia University, Sep. 1998, 44 pgs, Ericsson Research Canada.
- Lee, Ta-Sung, "MIMO Techniques for Wireless Communications", Dept. of Communication Engineering, National Chiao Tung University, 24 pgs.
- Telatar, I. Emre, "Capacity of Multi-antenna Gaussian Channels", Lucent Tech., Bell Labs, NJ, Eur. Transactions on Telecomm, vol. 10, No. 6, 11-12/1999, pp. 585-595.
- Rong, Zhigang, "Simulation of Adaptive Array Algorithms for CDMA Systems", Thesis submitted to VPI & SU, Sep. 1996, 143 pgs, (Only Abstract submitted).
- Naguib, Ayman F., "Adaptive Antennas for CDMA Wireless Networks", Dissertation, Stanford University, Aug. 1996, 198 pgs, (Only cover page and Abstract submitted).
- Ziemer, Rodger E. and Peterson, Roger L., "Digital Communications and Spread Spectrum Systems", MacMillan Publishing Company, NY, 1985 (Only cover, title and pub info pgs).
- Taub, Herbert and Schilling, Donald L., "Principles of Communication Systems, Second Edition", McGraw-Hill Book Company, 1986 (Only cover, title and pub. info pgs submitted).
- Dixon, Robert C., "Spread Spectrum Systems with Commercial Applications, Third Edition", John Wiley & Sons, Inc., NY, 1994 (Only cover, title & pub. info pgs submitted).
- Ziemer, R.E. and Tranter, W.H., "Principles of Communications Systems, Modulation and Noise, Third Edition", Houghton Mifflin Company, Boston, MA, 1990 (Only cover, title and publication information pages submitted).
- Ellersick, Fred W. et al, "Spread-Spectrum Communications", IEEE Press, NY, 1983, 293 pgs (Only cover and publication info pages submitted).
- Liang, Jen-Wei, Interference Reduction & Equalization with Space-Time Processing in TDMA Cellular Networks, Dissertation, Stanford Univ. Jun. 1998, 144pp, (title, abstract, publ).
- Khan, Sajid Anwar, "An Investigation into the Error Performance of Vertical-Bell Labs Layered Space-time Architecture V-Blast", Thesis, King Fahd University of Petroleum and Minerals, Dhahran, Saudi Arabia, May 2003, 180 pp. (only title, first page and abstract submitted).
- Cimini, Leonard J., Sollenberger, Nelson R., "OFDM with Diversity and Coding for Advanced Cellular Internet Services", IEEE, Nov. 1997, pp. 305-309.
- A. Jalali et al, "On Fast Forward Link Power Control in CDMA Systems", Nortel Wireless Networks, Richardson, TX, Sep. 1998, 4 pages, IEEE.
- A. Jalali et al. "Performance of Fast Forward Link Power Control for CDMA Systems", Nortel Wireless Networks, Richardson, TX, Apr. 1998, 4 pages, IEEE.
- Ashvin Chheda, "On the Forward Link Capacity of a cdma2000-1X System with Transmit Diversity", Nortel Networks, Richardson, TX, 2000, 6 pgs, IEEE.
- Hara, Shinsuke, Prasad, Ramjee, "Overview of Multicarrier CDMA", IEEE Communications Magazine, pp. 126-133, Dec. 1997.
- Kaleh, Ghassan Kawas, "Frequency-Diversity Spread-Spectrum Communication System to Counter Bandlimited Gaussian Interference", IEEE Transactions on Communications, vol. 44, No. 7, Jul. 1996, pp. 886-893.
- Saulnier, Gary J., Medley, Michael J., "Performance of a Spread Spectrum OFDM System in a Dispersive Fading Channel with Interference", 1998 IEEE, pp. 679-683.
- Saulnier, Gary J., Whyte, V.A. Alanzo, Medley, Michael J., "OFDM Spread Spectrum Communications using Lapped Transforms and Interference Excision", 1997 IEEE, pp. 944-948.
- Saulnier, Gary J. Mettke, Mike, Medley, Michael J., "Performance of an OFDM Spread Spectrum Communications System Using Lapped Transforms", 1997 IEEE, pp. 608-612.
- Newton, Henry, Newton's Telecom Dictionary, Mar. 1998, pp. HP775-0278191-HP775-00276192, Flatiron Publishing, New York, NY.
- Dixon, Robert C., "Radio Receiver Design", 1998, table of contents & p. 70, Copyright 1998 by Marcel Dekker, Inc., New York, NY.
- Kaiser, Stefan, "Multi-Carrier CDMA Mobile Radio Systems—Analysis and Optimization of Detection, Decoding, and Channel Estimation", Ph.D. thesis published with VDI-Verlag, Dusseldorf, Germany, Jan. 1998, 161 pages, ISBN 3-18-353110-0.
- Milstein, Laurence B., Donald L. Schilling, "Spread-Spectrum Communications", 1983, IEEE Press, New York, NY, 35 pages.
- Giordano, Arthur A. et al, "A Spread-Spectrum Simulcast MF Radio Network", IEEE Transactions on Communications, vol. COM-30, pp. 1057-1069, May, 1982.
- Davidovici, Sorin, Milstein, Laurence B. And Schilling, Donald L., "A New Rapid Acquisition Technique for Direct Sequence Spread-Spectrum Communications", IEEE Transactions on Communications, vol. COM-32, No. 11, Nov. 1984, pp. 1161-1168, New York, NY.
- Hochwald, Bertrand M., Marzetta, Thomas L., "Unitary Space-Time Modulation for Multiple-Antenna Communications in Rayleigh Flat Fading", IEEE Transactions on Information Theory, vol. 46, No. 2, Mar. 2000, pp. 543-564.
- Van De Beek, Jan-Jaap et al, "A time and Frequency Synchronization Scheme for Multiuser OFDM", IEEE Journal on Selected Areas in Communications, vol. 17, No. 11, Nov. 1999, pp. 1900-1914, Sweden.
- Van De Beek, Jan-Jaap, Sandell, Magnus, Borjesson, Per OLA, "ML Estimation of Time and Frequency Offset in OFDM Systems", IEEE Transactions on Signal Processing, vol. 45, No. 7, Jul. 1997, pp. 1800-1805, Sweden.
- Cimini, Jr., Leonard J., "Analysis and Simulation of a Digital Mobile Channel Using Orthogonal Frequency Division Multiplexing", IEEE Transactions on Communications, vol. Com-33, No. 7, Jul. 1985, pp. 665-675, AT&T Bell Laboratories, Holmdel, NJ.
- Lee, Ta-Sung, "Mimo Techniques for Wireless Communications", Department of Communication Engineering, National Chiao tung University, Taiwan, 24 pgs.
- Naguib, A.F. et al, "Space-Time Coded Modulation for High Data Rate Wireless Communications", Information Sciences Research Center, AT&T Labs—Research, Florham Park, NJ, IEEE, Aug. 1997, IEEE #0-7803-4198-8/97. pp. 102-109.
- Naguib, Ayman F., "Adaptive Antennas for CDMA Wireless Networks", Dissertation submitted to the Dept. of Electrical Engineering, Stanford University, CA, Aug. 1996, Copyright 1996 by UMI Company, Ann Arbor, Michigan, 196 pgs.

- Schilling, Donald L., "Oral-History: Donald Schilling", An Interview Conducted by David Hochfelder, IEEE History Center, GHN: IEEE Global History Network, The Institute of Electrical and Electronics Engineers, Inc., 11pgs.
- Papadias, Constantinos, Huang, Howard, Mailaender, "Adaptive Multi-user Detection of Fading CDMA Channels Using Antenna Arrays", Wireless Communications Research Department, Bell Laboratories/Lucent Technologies, Holmdel, NJ, IEEE #0-7803-5148, Jul. 1998, pp. 1564-1568.
- Peterson, Roger L., Ziemer, Rodger E., & Borth, David E., "Introduction to Spread Spectrum Communications", Hewlett-Packard Company Confidential Business Information, published by Prentice Hall, Upper Saddle River, NJ, 1995, ISBN 0-02-431623-7, 45 pgs.
- Alamouti, Siavash M., "A Simple Transmit Diversity Technique for Wireless Communications", IEEE Journal on Select Areas in Communications, vol. 16, No. 8, Oct. 1998, 8 pgs.
- Saifuddin, Ahmed and Kohno, Ryuji, "Performance Evaluation of DS/CDMA Scheme with Diversity Coding and MUI Cancellation over Fading Multipath Channel", Publisher Identifier No. 0-7803-3567-8/96—IEEE 1996, Tokyo and Yokohama, Japan pp. 308-312.
- Schmidl, Timothy M. And Cox, Donald C., "Robust Frequency and Timing Synchronization for OFDM", IEEE Transactions on Communications, vol. 45, No. 12, Dec. 1997, Dallas, Texas, pp. 1613-1621.
- Suwa, Keisuke and Kondo, Yasushi, "Transmitter Diversity Characteristics in Microcellular TDMA/TDD Mobile Radio", NTT Radio Communication System Laboratories, Kanagawa-ken, Japan, Publisher Identifier No. 0-7803-0841-7/92, pp. 545-549.
- Thompson, John S., Grant, Peter M., and Mulgrew, Bernard, "Analysis of CDMA Antenna Array Receivers with Fading Channels", Dept. of Electrical Engineering, University of Edinburgh, Edinburgh, Scotland, 5 pgs.
- Winters, Jack H., Salz, Jack, and Gitlin, Richard D., "The Impact of Antenna Diversity on the Capacity of Wireless Communication Systems", IEEE Transactions on Communications, vol. 42, No. 2/3/4, Feb./Mar./Apr. 1994, Dallas, Texas, pp. 1740-1751.
- Markus, John and Sclater, Neil, McGraw-Hill Electronics Dictionary, Fifth Edition, 1994, McGraw-Hill, Inc., New York, NY, HP775-02276387-HP775-00276389, 2 pgs.
- Graf, Rudolf F., "Modern Dictionary of Electronics, Seventh Edition", 1999, cover page and p. 101, Butterworth-Heinemann, Woburn, MA.
- Weik, Martin H., "Fiber Optics Standard Dictionary, Third Edition", 1997, 4 pages, Chapman & Hall, New York, NY.
- Weik, Martin H., "Communications Standard Dictionary, Third Edition", 1996, 4 pages, Chapman & Hall, New York, NY.
- Leabman, Michael A., "Adaptive Band-Partitioning for Interference Cancellation in Communication Systems", Feb. 1997, M.I.T., 70 pgs. Wi-Lan, Inc., before the Federal Communications Commission—Amendment of Part 15 of the Commission's Rules Regarding Spread Spectrum Devices, May 11, 2001, FCC-01-158, 18 pgs. Federal Communications Commission, FCC 02-151, Amendment of Part 15 of the Commission's Rules Regarding Spread Spectrum Devices, May 30, 2002, 25 pgs.
- Kahn, Robert E., Gronemeyer, Steven A., Burchfiel, Jerry, and Kunzelman, Ronald C., "Advances in Packet Radio Technology", Proceedings of the IEEE, vol. 66, No. 11, Nov. 1978, pp. 1468-1496, plus 2 pages of drawings.
- Sasaki, Shigenobu and Gen. Marubayashi, A Study on the Code Sequence for Parallel Spread-Spectrum Data Transmission System, Dept. Elec. Eng. Nagaoki Univ., 1989, 8pgs.
- Bingham, John A.C., "Multicarrier Modulation for Data Transmission: An Idea Whose Time Has Come", IEEE Communications Magazine, May 1990, pp. 5-14.
- Ertel, Richard B. and Schell, Stephan V., "Comparative Study of Adaptive Antenna Arrays in CDMA Communication Systems", Pennsylvania State University, and University of California Depts. of Electrical Engineering, Nov. 4, 1998, 12 pages.
- Ziemer, R.E. and Tranter, W.H., "Principles of Communications, Systems, Modulation, and Noise, Fourth Edition", 1995, John Wiley & Sons, Inc., New York, NY, 20 pgs.
- SDMA Technology for Personal Communications Services, presented at JTC, Nov. 1-5, 1993, Phoenix, AZ, 21 pgs.
- Improving Wireless Communication Systems with ArrayComm's SDMA Technology; presented to BellSouth Sep. 9, 1994, 3 pgs.
- Roy, Richard, "The Role of Intelligent Antenna Technology in World Wide Wireless Local Loop", IQPC WLL Conference, Nov. 13, 1996, 33 pgs.
- Roy, Richard, "Smart Antenna Technology in WLL Communication Systems", MTT WLL Workshop, Jun. 7, 1998, 22 pgs.
- Roy, Richard, Smart Antenna Technology in Wireless Communications, Wirelett Technology '96, Oct. 10, 1996, 43 pgs.
- Roy, Richard, "An Overview of Smart Antenna Technology—The Next Wave in Wireless Communications", ArrayComm, Inc., San Jose, CA, May 1998, 7 pgs.
- Roy, Richard, "Smart Antenna Technology—Past, Present, and Future", ITS ART Symposium Sep. 11, 1998, 30 pgs.
- Center for Telecommunications and Information Systems Laboratory, Dept of Electrical Engineering, Stanford Univ., Stanford, CA, Fifth Workshop on "Smart Antennas in Wireless Mobile Communications", Jul. 23-24, 1998, 25 pgs.
- Center for Telecommunications and Information Systems Laboratory, Dept of Electrical Engineering, Stanford Univ., Stanford, CA, Technology Overview, Fifth Workshop on "Smart Antennas in Wireless Mobile Communications", Jul. 24, 1998, 93 pgs.
- Winters, Jack H., "The Diversity Gain of Transmit Diversity in Wireless Systems with Rayleigh Fading", IEEE Transactions on Vehicular Technology, vol. 47, No. 1, Feb. 1998, 5 pgs.
- Andersen, J. Bach, "High Gain Antennas in a Random Environment", center for Personkommunikation, Aalborg University, Aalborg, Denmark, Sep. 1998, 5 pgs.
- Naguib, Ayman F., Paulraj, Arogyaswami, "Performance Enhancement and Trade-offs of smart Antennas in CDMA Cellular Networks", Information Systems Lab, Stanford University, Stanford, CA, 1995, 5 pgs.
- Schilling, Donald L, Pickholtz, Raymond L. and Milstein, Laurence B., "Spread spectrum goes commercial", IEEE Spectrum, Aug. 1990, 4 pgs.

\* cited by examiner




FIG. 1




FIG. 2






FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7

**MULTIPLE-INPUT MULTIPLE-OUTPUT  
(MIMO) SPREAD-SPECTRUM SYSTEM AND  
METHOD**

**Matter enclosed in heavy brackets [ ] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.**

RELATED PATENTS

*Notice: More than one reissue application has been filed for the reissue of U.S. Pat. No. 7,068,705. This application is a continuation reissue application based on co-pending reissue application Ser. No. 12/147,104 filed Jun. 26, 2008.*

This patent is a continuation of application Ser. No. 10/254,461, filed Sep. 25, 2002, now U.S. Pat. No. 6,757,322 and stems from a continuation application of U.S. patent application Ser. No. 09/665,322, and filing date of Sep. 19, 2000 now U.S. Pat. No. 6,466,610, entitled SPREAD-SPECTRUM SPACE DIVERSITY AND CODING ANTENNA SYSTEM AND METHOD, with inventor DONALD L. SCHILLING, and a continuation application of U.S. patent application Ser. No. 09/198,630, and filing date of Nov. 24, 1998, entitled EFFECT SHADOW REDUCTION ANTENNA SYSTEM FOR SPREAD SPECTRUM, with inventor DONALD L. SCHILLING which issued on Oct. 3, 2000, as U.S. Pat. No. 6,128,330. The benefit of the earlier filing date of the parent patent application is claimed for common subject matter pursuant to 35 U.S.C. § 120.

BACKGROUND OF THE INVENTION

This invention relates to antennas, and more particularly to reducing the effects of shadowing from a multipath environment, using space diversity and coding.

DESCRIPTION OF THE RELEVANT ART

Data sent from terminal to base, or vice versa, are often shadowed. Shadowing is a function of time, and may be caused by buildings, foliage, vehicles, people, motion of the terminal, etc. Shadowing is the blocking, or attenuating, of the transmitted signal. Shadowing may occur in fixed or mobile systems, and can vary slowly or quickly depending on the situation.

While shadowing has an effect which is similar to multipath, the causes and statistics of shadowing may be very different. For example, the presence of a building may result in total shadowing, independent of time, while multipath, caused by numerous multipath returns, produces a Rayleigh or Ricean fading distribution. Fading due to shadowing and multipath may be reduced by adding a receiver antenna to increase receiver diversity.

Coding techniques using space diversity as well as time, are known as "space-time" codes. In the prior art, with a multiple antenna system, the input to each receive antenna is assumed to have Rayleigh fading. A problem with multiple antenna systems is that a particular antenna output may be shadowed by 6 dB or more to a particular receive antenna. Such shadowing leaves the other antennas to receive a desired signal, effectively destroying one source of data.

SUMMARY OF THE INVENTION

A general object of the invention is to reduce the effects of shadowing and multipath in a fading environment.

Another object of the invention is to improve performance of a spread-spectrum communications system.

An additional object of the invention is to increase capacity of a spread-spectrum communications system.

A further object of the invention is to minimize fading and enhance overall performance in a spread-spectrum communications system.

According to the present invention, as embodied and broadly described herein, an antenna system is provided employing space diversity and coding, for transmitting data having symbols, over a communications channel. The transmitted signal passes through a communications channel having fading caused by multipath as well as shadowing.

In a first embodiment of the invention, the antenna system comprises a forward error correction (FEC) encoder, an interleaver, a demultiplexer, a plurality of spread-spectrum devices, a plurality of transmit antennas, and a plurality of receiver subsystems. Each receiver subsystem includes a receiver antenna and a plurality of matched filters. The receiver system further includes a RAKE and space-diversity combiner, a multiplexer, a de-interleaver, and a decoder.

The FEC encoder encodes the data using an error correction code to generate FEC data. The interleaver interleaves the symbols of the FEC data to generate interleaved data. The demultiplexer demultiplexes the interleaved data into a plurality of subchannels of data. The plurality of spread-spectrum devices, spread-spectrum processes the plurality of subchannels of data with a plurality of chip-sequence signals, respectively. Each chip-sequence signal of the plurality of chip-sequence signals is different from other chip-sequence signals in the plurality of chip-sequence signals. The plurality of spread-spectrum devices thereby generates a plurality of spread-spectrum subchannel signals, respectively. The plurality of transmit antennas radiate, at a carrier frequency using radio waves, the plurality of spread-spectrum-subchannel signals over a communications channel as a plurality of spread-spectrum signals. The plurality of spread-spectrum signals could use binary phase-shift-keying (BPSK) modulation, quadrature phase-shift-keying (QPSK) modulation, differential encoding, etc., and other modulations, which are all well known carrier modulation techniques.

The communications channel imparts fading on the plurality of spread-spectrum signals. The multipath generates a multiplicity of fading spread-spectrum signals. The fading also may include shadowing.

The plurality of receiver subsystems receive the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals from the communications channel. Each receiver subsystem has the receiver antenna for receiving the plurality of spread-spectrum signals, and the plurality of matched filters. Each receiver antenna in the plurality of receiver antennas is spaced from other receiver antennas in the plurality of receiver antennas preferably by at least one-quarter ( $\frac{1}{4}$ ) wavelength, and preferably as far apart as practicable. The present invention includes spacings less than one-quarter wavelength, but with degradation in performance. The plurality of matched filters has a plurality of impulse responses matched to the plurality of chip-sequence signals, respectively. The plurality of matched filters detect the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, as a plurality of detected spread-spectrum signals and a multiplicity of detected-fading spread-spectrum signals, respectively.

A plurality of RAKE and space-diversity combiners combine the plurality of detected spread-spectrum signals and the multiplicity of the detected-fading spread-spectrum signals from each of the plurality of receiver subsystems, to generate

3

a plurality of combined signals. A multiplexer multiplexes a plurality of combined signals thereby generating the multiplexed signal. The de-interleaver de-interleaves the multiplexed signal from the multiplexer, and thereby generates de-interleaved data. The decoder decodes the de-interleaved data.

As an alternative, a preferred embodiment is to select the received version of each received chip-sequence signal at each antenna and combine them in a RAKE. In this embodiment, the space and time combining of each channel from a respective chip-sequence signal occur in a single RAKE receiver. The total number of RAKE receivers is equal to the number of chip-sequence signals, or one or more RAKES could be time multiplexed to represent the number of chip-sequence signals.

A second embodiment of the invention has an antenna system for transmitting data having symbols over the communications channel having fading caused by multipath and shadowing. In the second embodiment of the invention, as previously described for the first embodiment of the invention, a multiplicity of delay devices is coupled between the interleaver and the plurality of spread-spectrum devices, respectively. A first signal of the plurality of signals of the interleaved data need not be delayed. The other signals of the plurality of signals of interleaved data are delayed, at least one symbol, one from the other, by the multiplicity of delay devices. Each delay device of the multiplicity of delay devices has a delay different from other delay devices of the multiplicity of delay devices relative to the first signal. The multiplicity of delay devices thereby generate a plurality of time-channel signals.

The plurality of spread-spectrum devices has a first spread-spectrum device coupled to the interleaver, and with the other spread-spectrum devices coupled to the multiplicity of delay devices, respectively. The plurality of spread-spectrum devices spread-spectrum process, with a plurality of chip-sequence signals, the first signal and the plurality of time-channel signals as a plurality of spread-spectrum signals. The plurality of transmit antennas radiate at the carrier frequency, using radio waves, the plurality of spread-spectrum signals over the communications channel.

The communications channel imparts fading due to multipath and shadowing on the plurality of spread-spectrum signals. The multipath generates a multiplicity of fading spread-spectrum signals.

The plurality of receiver subsystems receive the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals from the communications channel. Each receiver subsystem includes a receiver antenna for receiving the plurality of spread-spectrum signals and a plurality of matched filters; the plurality of matched filters has a plurality of impulse responses snatched to the plurality of chip-sequence signals, respectively. The plurality of matched filters detects the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, as a plurality of detected spread-spectrum signals and a multiplicity of detected-fading spread-spectrum signals.

A RAKE and space-diversity combiner combines the detected spread-spectrum signal and the multiplicity of detected-fading spread-spectrum signals from each of the plurality of receiver subsystems. This generates a plurality of combined signals. The FEC decoder decodes the de-interleaved signal as decoded data.

Additional objects and advantages of the invention are set forth in part in the description which follows, and in part are obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention

4

also may be realized and attained by means of the instrumentalities and combinations particularly pointed out in the appended claims.

#### BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate preferred embodiments of the invention, and together with the description serve to explain the principles of the invention.

FIG. 1 is a block diagram of a four code transmitter, using four antennas;

FIG. 2 is a block diagram of a four code transmitter, using four antennas and separate FEC encoders and bit interleavers for each channel;

FIG. 3 is a block diagram of a receiver system having four antennas, with four matched filters per antenna;

FIG. 4 is a block diagram of a transmitter having two codes and two antennas, and a delay on data;

FIG. 5 is a block diagram of a transmitter having two codes and two antennas, and a delay on data, with a separate FEC encoder and bit interleaver for each channel;

FIG. 6 is a block diagram of a receiver system having two receiver antennas, and two snatched filters per antenna; and

FIG. 7 is a block diagram of a receiver having three antennas and three rake and space combiners, coupled to a multiplexer.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference now is made in detail to the present preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings, wherein like reference numerals indicate like elements throughout the several views.

The present invention provides a novel approach for reducing the effect of fading due to shadowing and multipath, through the use of multiple antennas at the terminal and also at the base station, as well as a single RAKE/maximal ratio combiner to combine all time and space signals. Previous solutions have assumed multiple antennas at the base, where space diversity is then applied. Also, each antenna receiver has an individual RAKE. Placing multiple antennas at the terminal, however, can result in a significant improvement in system performance. The use of maximal ratio combining, RAKE and erasure decoding further enhance system performance.

As illustratively shown in FIGS. 1-6, the present invention broadly includes an antenna system employing time (RAKE) and space (antenna) diversity and coding of spread-spectrum signals. The antenna system is for transmitting data having symbols over a communications channel. The symbols may be bits, or may be based on pairs of bits or groups of bits. The communications channel is assumed to have fading due to multipath and shadowing.

The antenna system broadly includes forward error correction (FEC) means, interleaver means, demultiplexer means, spread-spectrum means, a plurality of transmit antennas, a plurality of receiver subsystems, RAKE and space-diversity means, multiplexer means, de-interleaver means, and decoder means. Each receiver subsystem includes receiver-antenna means and matched-filter means.

The interleaver means is coupled between the demultiplexer means and the FEC means. The spread-spectrum means is coupled between the demultiplexer means and the plurality of transmit antennas. Alternatively, the FEC means is coupled between the demultiplexer means and the inter-

leaver means, and the spread-spectrum means is coupled to the interleaver means. The communications channel is between the plurality of transmit antennas and the plurality of receiver subsystems.

Each receiver subsystem has receiver-antenna means exposed to the communications channel. The matched filter means is coupled to the receiver-antenna means.

The RAKE and space-diversity means is coupled to each matched filter means of the plurality of receiver subsystems, and the multiplexer means is coupled to the RAKE and space-diversity means. The de-interleaver means is coupled to the RAKE and space-diversity means, and the decoder means is coupled to the de-interleaver means.

The FEC means FEC encodes the data, thereby generating FEC data. FEC data is defined herein to be FEC encoded data. Forward-error-correction encoding is well known in the art, and the use of a particular FEC code is a design choice. The interleaver means interleaves symbols of the FEC data, thereby generating interleaved data. Interleaved data is defined herein to be interleaved FEC data. Interleaving, as is well known in the art, randomizes the errors. The demultiplexer means demultiplexes the interleaved data into a plurality of subchannels of data.

The spread-spectrum means spread-spectrum processes the plurality of subchannels of data with a plurality of chip-sequence signals, respectively. Each chip-sequence signal is different from other chip-sequence signals in the plurality of chip-sequence signals. The spread-spectrum means thereby generates a plurality of spread-spectrum-subchannel signals, respectively. Each spread-spectrum-subchannel signal is defined by a respective chip-sequence signal. In a preferred embodiment, each chip-sequence signal is designed to be orthogonal to other chip-sequence signals in the plurality of chip-sequence signals, when received at the receiver, neglecting multipath. In practice, however, orthogonality may not be realized.

The plurality of transmit antennas has each transmitter antenna spaced from other antennas in the plurality of transmit antennas, preferably by at least a quarter wavelength at a carrier frequency. If the transmitter antennas are spaced by less than a quarter wavelength, performance degrades. The present invention includes antennas spaced less than a quarter wavelength, with spacing of at least a quarter wavelength being a preferred embodiment. The plurality of transmit antennas radiates at the carrier frequency, using radio waves, the plurality of spread-spectrum-subchannel signals, respectively, over the communications channel, as a plurality of spread-spectrum signals. The carrier frequency typically is the frequency of a carrier signal generated by an oscillator, as is well known in the art. The plurality of spread-spectrum signals is mixed or multiplied by the carrier signal. Appropriate oscillator, mixer, amplifier and filter can be employed to assist radiating the plurality of spread-spectrum signals at the carrier frequency. Various modulations, such as QPSK, BPSK, differential encoding, etc., may be use as a carrier modulation for the plurality of spread-spectrum signals.

The communications channel imparts fading due to multipath and shadowing on the plurality of spread-spectrum signals. The communications channel thereby generates a plurality of fading spread-spectrum signals.

The plurality of receiver subsystems receive the plurality of spread-spectrum signals, arriving from the plurality of transmit antennas through the communications channel, and the multiplicity of fading spread-spectrum signals from the communications channel. Within each receiver subsystem, the receiver-antenna means receives a plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum

signals. The matched-filter means has a plurality of impulse responses matched to the plurality of chip-sequence signals, respectively. The matched-filter means detects the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, as a plurality of detected spread-spectrum signals and a multiplicity of detected-fading spread-spectrum signals, respectively.

The RAKE and space-diversity means combines the plurality of detected spread-spectrum signals and the multiplicity of detected-fading spread-spectrum signals from each of the plurality of receiver subsystems. The RAKE and space-diversity means thereby generates a plurality of combined signals.

The multiplexer means multiplexes the plurality of combined signals, as a multiplexed signal. The de-interleaver means de-interleaves the multiplexed signal from the multiplexer, thereby generating a de-interleaved signal. The decoder means decodes the de-interleaved signal.

FIGS. 1-3 illustratively show a system with four transmit antennas TA1, TA2, TA3, TA4 and four receive antennas RA1, RA2, RA3, RA4. The number of transmit antennas usually is not the same as the number of receiver antennas. In FIG. 1, the data are first forward-error-correction (FEC) encoded by FEC encoder 21 and interleaved by interleaver 22, and then demultiplexed by demultiplexer 32 into four data streams. The interleaving, FEC encoding, demultiplexing process alters the system performance. Alternatively, as shown in FIG. 2, the data could first be demultiplexed by demultiplexer 32 and then each data stream could be FEC encoded by a plurality of FEC encoders 521, 621, 721, 821 and interleaved by a plurality of interleavers 522, 622, 722, 822. The multipath FEC/interleavers could be built as individual devices, or as a single time-multiplexed device.

The first, second, third and fourth chip-sequence signals,  $g_1(t)$ ,  $g_2(t)$ ,  $g_3(t)$ , and  $g_4(t)$ , typically are pseudonoise (PN) spreading sequences. Since the transmit antennas are spaced more than one-quarter wavelength with respect to the carrier frequency, the chip-sequence signals can be adjusted to be orthogonal to a specific receiver antenna but not to all receiver antennas simultaneously. Thus, orthogonality is not required. The antenna could be "smart", e.g., steerable or phased array, however, ordinary omnidirectional antennas at the terminal are often most practical. Thus, on a car, omnidirectional antennas may be preferred, while in an office or home, a directional antenna may be preferred.

In the exemplary arrangement shown in FIG. 1, the FEC means is embodied as a forward-error-correction (FEC) encoder 21 and the interleaver means is embodied as an interleaver 22. The demultiplexer means is embodied as a demultiplexer 32 and the spread-spectrum means is embodied as a plurality of spread-spectrum devices 23, 33, 43, 53, and a chip-sequence signal generator 31. The spread-spectrum means alternatively may be embodied as an application specific integrated circuit (ASIC) with a plurality of matched filters, charged coupled devices (CCD) or, alternatively, surface-acoustic-wave (SAW) devices, as is well known in the art. The interleaver 22 is coupled between FEC encoder 21 and the demultiplexer 32. The plurality of spread-spectrum devices 23, 33, 43, 53 is coupled to the chip-sequence signal generator 31, and between the demultiplexer 32, and the plurality of transmit antennas TA1, TA2, TA3, and TA4.

The FEC encoder 21 encodes the data to generate FEC data. FEC encoding is well known in the art. A particular choice of an FEC encoding technique and code is a design choice. The interleaver 22 interleaves the FEC data to generate interleaved data. The interleaver selection is a design

choice. The demultiplexer **32** demultiplexes the interleaved data into a plurality of subchannels of data.

In FIG. 2, the FEC means is embodied as a plurality of FEC encoders **521, 621, 721, 821** and the interleaver means is embodied as a plurality of interleavers **522, 622, 722, 822**. The demultiplexer **32** first demultiplexes the data into a plurality of sub-data streams. The plurality of FEC encoders **521, 621, 721, 821** FEC encode the plurality of sub-data streams into a plurality of FEC-sub-data streams, respectively. The plurality of interleavers **522, 622, 722, 822** interleave the plurality of FEC-sub-data streams into the plurality of sub-channels, respectively.

In FIGS. 1 and 2, a chip-sequence generator **31** generates the plurality of chip-sequence signals. A chip-sequence signal typically is generated from a pseudonoise (PN) sequence, as is well known in the art. Each chip-sequence signal is different from other chip-sequence signal in the plurality of chip-sequence signals. In an embodiment, each chip-sequence signal may be orthogonal to other chip-sequence signals in the plurality of chip-sequence signals.

The plurality of spread-spectrum devices **23, 33, 43, 53** spread-spectrum process the plurality of subchannels of data with the plurality of chip-sequence signals, respectively. Each spread-spectrum-subchannel signal of the plurality of spread-spectrum-subchannel signals is defined by a respective chip-sequence signal from the plurality of chip-sequence signals. The plurality of spread-spectrum devices thereby generate a plurality of spread-spectrum-subchannel signals, respectively.

The plurality of transmit antennas **TA1, TA2, TA3, TA4** has each transmitter antenna of the plurality of transmit antennas preferably spaced from other antennas of the plurality of transmit antennas preferably by at least a quarter wavelength at a carrier frequency. This provides independence of transmitted signals. The plurality of transmit antennas **TA1, TA2, TA3, TA4** radiate at the carrier frequency using radio waves, the plurality of spread-spectrum-subchannel signals over the communications channel as a plurality of spread-spectrum signals. Appropriate oscillator product device and filter may be added to shift the plurality of spread-spectrum-subchannel signals to a desired carrier frequency. Amplifiers may be added as required.

The communications channel imparts fading on the plurality of spread-spectrum signals. The fading generates a multiplicity of fading spread-spectrum signals, some of which may have shadowing and multipath. The shadowing may be from buildings, foliage, and other causes of multipath and shadowing.

The spread-spectrum processing typically includes multiplying the plurality of subchannels of data by the plurality of chip-sequence signals, respectively. In an alternative embodiment, if a plurality of matched filters or SAW devices was employed in place of the spread-spectrum devices, then the plurality of matched filters or SAW devices would have a plurality of impulse responses, respectively, matched to the plurality of chip-sequence signals, respectively. If programmable matched filters were employed, then the plurality of impulse responses of the plurality of matched filters may be set by the plurality of chip-sequence signals or other control signals, from the chip-sequence signal generator **31** or other controller.

At the receiver, the plurality of receiver subsystems receives the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals from the communications channel. Each receiver subsystem of the plurality of receiver subsystem has a receiver antenna. As illustratively shown in FIG. 3, the plurality of receiver subsystems includes

a plurality of receiver antennas **RA1, RA2, RA3, RA4**, respectively. The plurality of receiver antennas **RA1, RA2, RA3, RA4** has each receiver antenna of the plurality of receiver antennas preferably spaced from other antennas of the plurality of receiver antennas preferably by at least one-quarter wavelength at the carrier frequency. Each receiver subsystem may include receiver circuitry which amplifies, filters, translates and demodulates received signals to base-band or an intermediate frequency (IF) for processing by the matched filter. Such receiver circuitry is well known in the art.

Each receiver subsystem has a respective receiver antenna coupled to a respective plurality of matched filters. The first receiver subsystem, by way of example, has the first receiver antenna **RA1** coupled to a first plurality of matched filters **24, 34, 44, 54**. The second receiver antenna **RA2** is coupled to a second plurality of matched filters **25, 35, 45, 55**. The third receiver antenna **RA3** is coupled to a third plurality of matched filters **26, 36, 46, 56**. The fourth receiver antenna **RA4** is coupled to a fourth plurality of matched filters **27, 37, 47, 57**. Each receiver antenna in the plurality of receiver antennas **RA1, RA2, RA3, RA4**, receives a plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals.

For each receiver antenna, as shown in FIG. 3, by way of example, the plurality of matched filters includes a matched filter having a impulse response **MF1** matched to a first chip-sequence signal  $g_1(t)$ ; a matched filter having a impulse response **MF2** matched to a second chip-sequence signal  $g_2(t)$ ; a matched filter having an impulse response **MF3** matched to a third chip-sequence signal  $g_3(t)$ ; and, a matched filter having an impulse response **MF4** matched to a fourth chip-sequence signal  $g_4(t)$ . More, particularly, the first plurality of matched filters **24, 34, 44, 54**, in FIG. 3, has a first matched filter **24** with an impulse response **MF1** matched to a first chip-sequence signal  $g_1(t)$  in the plurality of chip-sequence signals; a second matched filter **34** with an impulse response **MF2** matched to a second chip-sequence signal  $g_2(t)$  in the plurality of chip-sequence signals; a third matched filter **44** with an impulse response **MF3** matched to a third chip-sequence signal  $g_3(t)$  in the plurality of chip-sequence signals; and a fourth matched filter with an impulse response **MF4** matched to a fourth chip-sequence signal  $g_4(t)$  in the plurality of chip-sequence signals. The second plurality of matched filters **25, 35, 45, 55**, in FIG. 3, has a fifth matched filter **25** with an impulse response **MF1** matched to the first chip-sequence signal  $g_1(t)$  in the plurality of chip-sequence signals; a sixth matched filter **35** with an impulse response **MF2** matched to the second chip-sequence signal  $g_2(t)$  in the plurality of chip-sequence signals; a seventh matched filter **45** with an impulse response **MF3** matched to the third chip-sequence signal  $g_3(t)$  in the plurality of chip-sequence signals; and an eighth matched filter **55** with an impulse response **MF4** matched to the fourth chip-sequence signal  $g_4(t)$  in the plurality of chip-sequence signals. The third plurality of matched filters **26, 36, 46, 56**, in FIG. 3, has a ninth matched filter **26** with an impulse response **MF1** matched to the first chip-sequence signal  $g_1(t)$  in the plurality of chip-sequence signals; a tenth matched filter **36** with an impulse response **MF2** matched to the second chip-sequence signal  $g_2(t)$  in the plurality of chip-sequence signals; an eleventh matched filter **46** with an impulse response **MF3** matched to a third chip-sequence signal  $g_3(t)$  in the plurality of chip-sequence signals; and a twelfth matched filter **56** with an impulse response **MF4** matched to a fourth chip-sequence signal  $g_4(t)$  in the plurality of chip-sequence signals. The fourth plurality of matched filters **27, 37, 47, 57**, in FIG. 3, has a thirteenth matched filter **27** with an impulse response **MF1** matched to



the first chip-sequence signal  $g_1(t)$  in the plurality of chip-sequence signals; a fourteenth matched filter **37** with an impulse response MF2 matched to the second chip-sequence signal  $g_2(t)$  in the plurality of chip-sequence signals; a fifteenth matched filter **47** with an impulse response MF3 matched to the third chip-sequence signal  $g_3(t)$  in the plurality of chip-sequence signals; and a sixteenth matched filter **57** with an impulse response MF4 matched to the fourth chip-sequence signal  $g_4(t)$  in the plurality of chip-sequence signals. Thus, each plurality of matched filters has a plurality of impulse responses MF1, MF2, MF3, MF4 matched to the plurality of chip-sequence signals,  $g_1(t)$ ,  $g_2(t)$ ,  $g_3(t)$ ,  $g_4(t)$ , respectively.

Alternatively, all four antennas could be coupled to a single radio frequency (RF) RF-IF down converter, with in-phase and quadrature-phase components being formed, and a single matched filter for each impulse response. Thus, there would be a single matched filter with the impulse response MF1, there would be a single matched filter with the impulse response MF2, there would be a single matched filter with the impulse response MF3, and there would be a single matched filter with the impulse response MF4.

In FIG. 3, the first plurality of matched filters **24, 34, 44, 54**, by way of example, detects from the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, a first plurality of detected spread-spectrum signals and a first multiplicity of detected fading spread-spectrum signals, respectively. The second plurality of matched filters **25, 35, 45, 55** detects from the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, a second plurality of detected spread-spectrum signals and a second multiplicity of detected fading spread-spectrum signals, respectively. The third plurality of matched filters **26, 36, 46, 56** detects from the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, a third plurality of detected spread-spectrum signals and a third multiplicity of detected fading spread-spectrum signals, respectively. The fourth plurality of matched filters **27, 37, 47, 57** detects from the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, a fourth plurality of detected spread-spectrum signals and a fourth multiplicity of detected fading spread-spectrum signals, respectively.

The plurality of RAKE and space-diversity combiners combines each plurality of detected spread-spectrum signals and each multiplicity of detected-fading spread-spectrum signals, respectively, from each receiver subsystem. This generates a plurality of combined signals. More particularly, as depicted in FIG. 3, four RAKE and space-diversity combiners are used, with each respective RAKE and space-diversity combiner corresponding to a chip-sequence signal. A first RAKE and space-diversity combiner **161** is coupled to the first matched filter **24**, the fifth matched filter **25**, the ninth matched filter **26**, and the thirteenth matched filter **27**, all of which have an impulse response matched to the first chip-sequence signal. The plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, which have a spread-spectrum subchannel defined by the first chip-sequence signal, and detected by any or all of the first matched filter **24**, the fifth matched filter **25**, the ninth matched filter **26** and the thirteenth matched filter **27**, are combined by the first RAKE and space-diversity combiner **161**. At the output of the first RAKE and space-diversity combiner **161** is a first combined signal. The first RAKE and space-diversity combiner **161** may use any of a number of techniques for combining signals, such as selecting the four strongest signals and add-

ing their strengths, maximal ratio combining, maximal likelihood combining, etc. RAKE and combining techniques are well known in the art.

A second RAKE and space-diversity combiner **162** is coupled to the second matched filter **34**, the sixth matched filter **35**, the tenth matched filter **36**, and the fourteenth matched filter **37**, all of which have an impulse response matched to the second chip-sequence signal. The plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, which have a spread-spectrum subchannel defined by the second chip-sequence signal, and detected by any or all of the second matched filter **34**, the sixth matched filter **35**, the tenth matched filter **36** and the fourteenth matched filter **37**, are combined by the second RAKE and space-diversity combiner **162**. At the output of the second RAKE and space-diversity combiner **162** is a second combined signal. The second RAKE and space-diversity combiner **162** may use any of a number of techniques for combining signals, such as selecting the four strongest signals and adding their strengths, maximal ratio combining, maximal likelihood combining, etc. RAKE and combining techniques are well known in the art.

A third RAKE and space-diversity combiner **163** is coupled to the third matched filter **44**, the seventh matched filter **45**, the eleventh matched filter **46**, and the fifteenth matched filter **47**, all of which have an impulse response matched to the third chip-sequence signal. The plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, which have a spread-spectrum subchannel defined by the third chip-sequence signal, and detected by any or all of the third matched filter **44**, the seventh matched filter **45**, the eleventh matched filter **46** and the fifteenth matched filter **47**, are combined by the third RAKE and space-diversity combiner **163**. At the output of the third RAKE and space-diversity combiner **163** is a third combined signal. The third RAKE and space-diversity combiner **163** may use any of a number of techniques for combining signals, such as selecting the four strongest signals and adding their strengths, maximal ratio combining, maximal likelihood combining, etc. RAKE and combining techniques are well known in the art.

A fourth RAKE and space-diversity combiner **164** is coupled to the fourth matched filter **54**, the eighth matched filter **55**, the twelfth matched filter **56**, and the sixteenth matched filter **57**, all of which have an impulse response matched to the fourth chip-sequence signal. The plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, which have a spread-spectrum subchannel defined by the fourth chip-sequence signal, and detected by any or all of the fourth matched filter **54**, the eighth matched filter **55**, the twelfth matched filter **56** and the sixteenth matched filter **57**, are combined by the fourth RAKE and space-diversity combiner **164**. At the output of the fourth RAKE and space-diversity combiner **164** is a fourth combined signal. The fourth RAKE and space-diversity combiner **164** may use any of a number of techniques for combining signals, such as selecting the four strongest signals and adding their strengths, maximal ratio combining, maximal likelihood combining, etc. RAKE and combining techniques are well known in the art.

The multiplexer **132** is coupled to the plurality of RAKE and space-diversity combiners. As illustratively shown in FIG. 3, the multiplexer **132** is coupled to the first RAKE and space-diversity combiner **161**, to the second RAKE and space-diversity combiner **162**, to the third RAKE and space-diversity combiner **163**, and to the fourth RAKE and space-diversity combiner **164**. The multiplexer **132** multiplexes the

## 11

first combined signal, the second combined signal, the third combined signal and the fourth combined signal, to generate a multiplexed signal. Thus, more generally, the multiplexer **132** multiplexes the plurality of combined signals to generate the multiplexed signal. The de-interleaver **61** de-interleaves the multiplexed signal from the multiplexer **132** to generate a de-interleaved signal, and the FEC decoder **62** decodes the de-interleaved signal to output the data. Buffer or memory circuits may be inserted between the multiplexer **132** and de-interleaver **61**, for storing a plurality of multiplexed signals before the de-interleaver. Alternatively, the memory circuits may be incorporated as part of the de-interleaver.

In use, data are encoded by FEC encoder **21** as FEC data, and the FEC data are interleaved by interleaver **22** generating interleaved data. The demultiplexer **32** demultiplexes the interleaved data into a plurality of subchannels and the plurality of spread-spectrum devices **23**, **33**, **43**, **53** spread-spectrum process the plurality of subchannels of data with a plurality of chip-sequence signals, respectively. The spread-spectrum processing generates a plurality of spread-spectrum-subchannel signals, respectively.

The plurality of transmit antennas radiate the plurality of spread-spectrum-subchannel signals as a plurality of spread-spectrum signals, respectively, over the communications channel.

At the receiver, a plurality of receiver antennas RA1, RA2, RA3, RA4 receive the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals. At each receiver antenna, and by way of example, the first receiver antenna RA1, there are a plurality of matched filters which detect the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, as a plurality of detected spread-spectrum signals and a multiplicity of detected-fading spread-spectrum signals, respectively. The plurality of RAKE and space-diversity combiners **161**, **162**, **163**, **164** combine the plurality of detected spread-spectrum signals and the multiplicity of detected-fading spread-spectrum signals from each of the plurality of receiver subsystems, thereby generating a plurality of combined signals.

The multiplexer **132** multiplexes the plurality of combined signals as a multiplexed signal. The de-interleaver **61** de-interleaves the multiplexed signal, and the FEC decoder **62** decodes the de-interleaved signal.

Since the symbol amplitudes are readily available, the presence of a small or low level symbol amplitude, even after coding, is a good indication of a processing error. Thus, erasure decoding is preferred in this system to improve performance. During RAKE and space combining, the noise level in each symbol also is measured. This is readily done in a matched filter by sampling the matched filter at a time, not being the symbol sampling time. The noise level at each symbol is recorded or stored in memory, and any significant increase above a predefined threshold, such as 3 dB, is transmitted to the FEC decoder for erasure decoding. Erasure decoding is well known in the art.

As an example of the performance improvement resulting from the present invention, consider that a single transmitter antenna and a single receiver antenna are employed in a system. Let the probability of being shadowed be  $q$ . Then  $q$  represents the fractional outage time. The order of combining is important if each transmitter antenna sends different data. If each transmitter antenna sent the same data, then the ordering, with appropriate delays, is not important.

Consider using a single transmitter antenna and  $M$  receiver antennas. Assuming independence, the probability of a blocked transmission is  $q^M$ . Further, the multipath outputs at each receiver are combined using RAKE (time diversity), and

## 12

then the resulting output at each receiver is combined (space diversity). In the antenna system, the transmitted power, to each receiver antenna, is  $P_T$  and the processing gain is  $PG$ .

In the above example, assume independence, that is, the probability of being blocked to a first receiver antenna, RA1, does not alter the probability of being blocked to a second receiver antenna, RA2, for example. In many cases, however, this assumption may not be correct. A large building may block a first receiver antenna, RA1, a second receiver antenna, RA2, and a third receiver antenna, RA3, from a user's transmitter antenna. In such a situation it is often beneficial to transmit from several transmitting antennas. In a system employing  $N$  transmit antennas and  $M$  receiver antennas, the transmitted power from each transmitter antenna is reduced by  $N$  and the processing gain is increased by  $N$ . However, the interference also is increased by  $N$ . Thus, there is no signal-to-noise ratio (SNR) improvement in a Gaussian channel, and the advantage of such a system is increased access, i.e., significantly less outage time in a fading channel, a consideration needed for wireless system performance to approach that of a wired system.

A space coding technique is shown in FIGS. 4, 5 and 6. Note that the data are interleaved and FEC encoded using a rate  $R=1/2$  code, such as a convolutional code. The same data then is transmitted over all transmit antennas. In FIGS. 4 and 5, two transmit antennas are shown. In this system, after performing the RAKE operation, two receiver systems perform a standard space diversity maximal-ratio-combining to optimize performance.

Assume that each transmission is received by all four receiver antennas. Then such receiver performs a RAKE reception for each transmitter antenna's signal. These signals are then combined using maximal ratio combining for space diversity. The resulting output of each antenna can then be combined. Of course, any order of combining yields the same result and all combining from all receiver antennas can be done simultaneously (RAKE and space diversity). The order depends on system implementation and does not affect performance. Erasure decoding may be employed at the FEC decoder.

The second embodiment of the antenna system is shown in FIGS. 4, 5 and 6. In FIG. 4, the invention includes FEC encoder **21**, coupled to the interleaver **22**. From the interleaver **22**, the system includes at least one delay device **181** and at least two spread-spectrum devices **23**, **33**. The system may include a plurality of delay devices, with each delay device having a delay different from other delay devices in the plurality of delay devices. The delay device **181** delays the interleaved data going to the second spread-spectrum device **33**. The first spread-spectrum device **23** spread-spectrum processes the interleaved data with the first chip-sequence signal from the chip-sequence generator **31**, and the second spread-spectrum device **33** spread-spectrum processes the delayed version of the interleaved data with the second chip-sequence signal from chip-sequence sequence signal generator **31**. The first transmitter antenna TA1 radiates the first spread-spectrum signal from the first spread-spectrum device **23**, and the second transmitter antenna TA2 radiates the second spread-spectrum signal from the second spread-spectrum device **33**.

An alternative to FIG. 4 is shown in FIG. 5. Data are first demultiplexed by demultiplexer **32** into a first stream of data and a second stream of data. The second stream of data is delayed by delay device **181** with respect to the first stream of data. The first stream of data is FEC encoded by first FEC encoder **521** and interleaved by first interleaver **622**. The delayed second stream of data is FEC encoded by second FEC encoder **621** and interleaved by second interleaver **622**.

The receiver has a multiplicity of receiver subsystems which include a plurality of receiver antennas. Each subsystem corresponding to a receiver antenna has a plurality of matched filters. As shown in FIG. 6, by way of example, a first receiver antenna RA1 and a second receiver antenna RA2 are shown. The first receiver antenna RA1 is coupled to a first matched filter 24 and a second matched filter 34. The second receiver antenna RA2 is coupled to a fifth matched filter 25 and a sixth matched filter 35. The RAKE and space-diversity combiner 60 combines the outputs from the first matched filter 24, the second matched filter 34, the fifth matched filter 25, and the sixth matched filter 35 to form a combined signal. The de-interleaver 61 de-interleaves the combined signal, and the FEC decoder 62 decodes the de-interleaved signal.

As an alternative to the embodiments described in FIGS. 4-6, an identical chip-sequence signal can be used for the plurality of chip-sequence signals. In this alternative, only a single matched filter having an impulse response matched to the chip-sequence signal, is required. Each transmitted signal is delayed by at least one chip.

FIG. 7 is a block diagram of a receiver system having a plurality of matched filters 24, 25, 26, 34, 35, 36, 44, 45, 46, coupled to a receiver antenna. As with FIG. 3, the plurality of matched filters 24, 25, 26, 34, 35, 36, 44, 45, 46 has a plurality of impulse responses matched to the plurality of chip-sequence signals, respectively. The plurality of matched filters 24, 25, 26, 34, 35, 36, 44, 45, 46 detects the plurality of spread-spectrum signals and the multiplicity of fading spread-spectrum signals, as a plurality of detected spread-spectrum signals and a multiplicity of detected-fading spread-spectrum signals, respectively.

Also illustrated in FIG. 7 is a plurality of RAKE and space-diversity combiners 761, 762, 763, coupled to the plurality of matched filters 24, 25, 26, 34, 35, 36, 44, 45, 46, with a first RAKE and space-diversity combiner 761 coupled to each matched filter 24, 25, 26 having an impulse response matched to a first chip-sequence signal, and with respective RAKE and space-diversity combiners coupled to respective matched filters having impulse responses matched to respective chip-sequence signals. The plurality of RAKE and space-diversity combiners 761, 762, 763 combines, for a respective chip-sequence signal, the plurality of detected spread-spectrum signals and the multiplicity of detected-fading spread-spectrum signals from the plurality of matched filters 24, 25, 26, 34, 35, 36, 44, 45, 46. The combining generates a plurality of combined signals and a plurality of signal amplitudes, respectively. A first combined signal is from the first RAKE and space-diversity combiner 761, and respective combined signals are from respective RAKE and space-diversity combiners.

A multiplexer 765 is coupled to the plurality of RAKE and space diversity combiners 761, 762, 763. The multiplexer 765 multiplexes the plurality of combined signals, thereby generating a multiplexed signal. A de-interleaver 61 is coupled to the multiplexer 765 for de-interleaving the multiplexed signal from the multiplexer, thereby generating a de-interleaved signal. The decoder is coupled to the de-interleaver. The decoder 62 decodes the de-interleaved signal.

It will be apparent to those skilled in the art that various modifications can be made to the efficient shadow reduction antenna system for spread spectrum of the instant invention without departing from the scope or spirit of the invention, and it is intended that the present invention cover modifications and variations of the efficient shadow reduction antenna system for spread spectrum provided they come within the scope of the appended claims and their equivalents.

I claim:

[1. A multiple-input-multiple-output (MIMO) method for receiving data having symbols, with the data having symbols demultiplexed into a plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively, with the plurality of spread-spectrum-subchannel signals radiated, using radio waves, from a plurality of antennas as a plurality of spread-spectrum signals, respectively, with the plurality of spread-spectrum signals passing through a communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath, comprising the steps of:

receiving the first spread-spectrum signal and the second spread-spectrum signal with a plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal as a first plurality of detected spread-spectrum signals, respectively;

detecting, at each receiver antenna of the plurality of receiver antennas, the second spread-spectrum signal as a second plurality of detected spread-spectrum signals, respectively;

combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

[2. The MIMO method as set forth in claim 1, further comprising the step of multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed, signal.]

[3. The MIMO method, as set forth in claim 1, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising the steps of:

receiving the third spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

[4. The MIMO method as set forth in claim 3, further comprising the step of multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

[5. The MIMO method, as set forth in claim 3, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fourth spread-spectrum signal

15

having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising the steps of:

receiving the fourth spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

[6. The MIMO method as set forth in claim 5, further comprising the step of multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

[7. The MIMO method, as set forth in claim 5, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, the third path of the multipath, the fourth path, or a fifth path, further comprising the steps of:

receiving the fifth spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the fifth spread-spectrum signal, as a fifth plurality of detected spread-spectrum signals; and combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

[8. The MIMO method as set forth in claim 7, further comprising the step of multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

[9. A multiple-input-multiple-output (MIMO) system for receiving data having symbols, with the data having symbols demultiplexed into a plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively, with the plurality of spread-spectrum-subchannel signals radiated, using radio waves, from a plurality of antennas as a plurality of spread-spectrum signals, respectively, with the plurality of spread-spectrum signals passing through a communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath, comprising:

a plurality of receiver antennas for receiving the first spread-spectrum signal and the second spread-spectrum signal;

a plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal and the second spread-spectrum signal, as a first plurality of detected spread-spectrum signals and a second plurality of detected spread-spectrum signals, respectively; and

16

a plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal, and for combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

[10. The MIMO system as set forth in claim 9, further comprising a multiplexer for multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed signal.]

[11. The MIMO system as set forth in claim 9, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising:

said plurality of receiver antennas for receiving the third spread-spectrum signal;

said plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and

said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

[12. The MIMO system as set forth in claim 11, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

[13. The MIMO system, as set forth in claim 11, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fourth spread-spectrum signal having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising:

said plurality of receiver antennas for receiving the fourth spread-spectrum signal;

said plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

[14. The MIMO system as set forth in claim 13, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

[15. The MIMO system, as set forth in claim 13, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, or the third path of the multipath, the fourth path, or a fifth path, further comprising:

said plurality of receiver antennas for receiving the fifth spread-spectrum signal;

said plurality of spread-spectrum detectors for detecting, at each receiver antenna of the plurality of receiver anten-

17

nas, the fifth spread-spectrum signal, as a fifth plurality of detected spread-spectrum signals; and said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

[16. The MIMO system set forth in claim 15, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

[17. A MIMO system for receiving data having symbols, with the data having symbols demultiplexed into a plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively, with the plurality of spread-spectrum-subchannel signals radiated, using radio waves, from a plurality of antennas as a plurality of spread-spectrum signals, respectively, with the plurality of spread-spectrum signals passing through a communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath, comprising:

receiver-antenna means for receiving the first spread-spectrum signal and the second spread-spectrum signal;

despreading means, coupled to said receiver-antenna means, for detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal and the second spread-spectrum signal, as a first plurality of detected spread-spectrum signals and a second plurality of detected spread-spectrum signals, respectively; and

combiner means, coupled to said despreading means, for combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal, and for combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

[18. The MIMO system as set forth in claim 17, further comprising multiplexer means for multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed signal.]

[19. The MIMO system as set forth in claim 17, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising:

said receiver-antenna means for receiving the third spread-spectrum signal;

said despreading means for detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

18

[20. The MIMO method as set forth in claim 19, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

[21. The MIMO system, as set forth in claim 19, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fourth spread-spectrum signal having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising:

said receiver-antenna means for receiving the fourth spread-spectrum signal;

said despreading means for detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

[22. The MIMO system as set forth in claim 21, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

[23. The MIMO system, as set forth in claim 21, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, or the third path of the multipath, the fourth path, or a fifth path, further comprising:

said receiver-antenna means for receiving the fifth spread-spectrum signal;

said despreading, means for detecting, at each receiver antenna of the plurality of receiver antennas, the fifth spread-spectrum signal, as a fifth plurality detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

[24. The MIMO system as set forth in claim 23, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

[25. A multiple input multiple output (MIMO) method improvement, for transmitting data having symbols, over a communications channel, comprising the steps of:

demultiplexing the data into a plurality of subchannels of data;

spread-spectrum processing the plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively;

radiating from a plurality of antennas, using radio waves, the plurality of spread-spectrum-subchannel signals, over the communications channel, as a plurality of spread-spectrum signals, respectively;

imparting, from the communications channel, multipath on the plurality of spread-spectrum signals, thereby gen-

erating at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath;

receiving the first spread-spectrum signal and the second spread-spectrum signal with a plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal and the second spread-spectrum signal, as a first plurality of detected spread-spectrum signals and a second plurality of detected spread-spectrum signals, respectively;

combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

**[26.** The MIMO method as set forth in claim 25, further comprising the step of multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed signal.]

**[27.** The MIMO method, as set forth in claim 25, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, with a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising the steps of:

receiving the third spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

**[28.** The MIMO method as set forth in claim 27, further comprising the step of multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

**[29.** The MIMO method, as set forth in claim 27, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, with a fourth spread-spectrum signal having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising the steps of:

receiving the fourth spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

**[30.** The MIMO method as set forth in claim 29, further comprising the step of multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

**[31.** The MIMO method, as set forth in claim 29, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, the third path of the multipath, the fourth path, or a fifth path, further comprising the steps of:

receiving the fifth spread-spectrum signal with the plurality of receiver antennas;

detecting, at each receiver antenna of the plurality of receiver antennas, the fifth spread-spectrum signal, as a fifth plurality of detected spread-spectrum signals; and

combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

**[32.** The MIMO method as set forth in claim 31, further comprising the step of multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

**[33.** A multiple input multiple output (MIMO) system, for transmitting data having symbols, over a communications channel, comprising:

a demultiplexer for demultiplexing the data into a plurality of subchannels of data;

a plurality of spread-spectrum devices for spread-spectrum processing the plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively;

a plurality of transmitter antennas for radiating, using radio waves, the plurality of spread-spectrum-subchannel signals, over the communications channel, as a plurality of spread-spectrum signals, respectively;

said communications channel for imparting multipath on the plurality of spread-spectrum signals, thereby generating at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath;

a plurality of receiver antennas for receiving the first spread-spectrum signal and the second spread-spectrum signal;

a plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal and the second spread-spectrum signal, as a first plurality of detected spread-spectrum signals and a second plurality of detected spread-spectrum signals, respectively; and

a plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal, and for combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

**[34.** The MIMO system as set forth in claim 33, further comprising a multiplexer for multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed signal.]

21

**[35.** The MIMO system as set forth in claim 33, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising:

said plurality of receiver antennas for receiving the third spread-spectrum signal;

said plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and

said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

**[36.** The MIMO system as set forth in claim 35, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

**[37.** The MIMO system, as set forth in claim 35, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fourth spread-spectrum signal having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising:

said plurality of receiver antennas for receiving the fourth spread-spectrum signal;

said plurality of despreading devices for detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

**[38.** The MIMO system as set forth in claim 37, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

**[39.** The MIMO system, as set forth in claim 37, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, or the third path of the multipath, the fourth path, or a fifth path, further comprising:

said plurality of receiver antennas for receiving the fifth spread-spectrum signal;

said plurality of spread-spectrum detectors for detecting, at each receiver antenna of the plurality of receiver antennas, the fifth spread-spectrum signal, as a fifth plurality of detected spread-spectrum signals; and

said plurality of combiners for combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

**[40.** The MIMO system set forth in claim 39, further comprising a multiplexer for multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

22

**[41.** A multiple input multiple output (MIMO) system, for transmitting data having symbols, over a communications channel, comprising:

demultiplexer means for demultiplexing the data into a plurality of subchannels of data;

spread-spectrum processing means for spread-spectrum processing the plurality of subchannels of data, with the plurality of subchannels of data spread-spectrum processed with a plurality of chip-sequence signals, respectively, with each chip-sequence signal different from other chip-sequence signals in the plurality of chip-sequence signals, thereby generating a plurality of spread-spectrum-subchannel signals, respectively;

a plurality of transmitter-antenna means for radiating, using radio waves, the plurality of spread-spectrum-subchannel signals, over the communications channel, as a plurality of spread-spectrum signals, respectively;

said communications channel for imparting multipath on the plurality of spread-spectrum signals, thereby generating at least a first spread-spectrum signal having a first channel of data arriving from a first path of the multipath, and a second spread-spectrum signal having a second channel of data arriving from a second path of the multipath;

receiver-antenna means for receiving the first spread-spectrum signal and the second spread-spectrum signal;

despreading means, coupled to said receiver-antenna means, for detecting, at each receiver antenna of the plurality of receiver antennas, the first spread-spectrum signal and the second spread-spectrum signal, as a first plurality of detected spread-spectrum signals and a second plurality of detected spread-spectrum signals, respectively; and

combiner means, coupled to said despreading means, for combining, from each receiver antenna of the plurality of receiver antennas, each of the first plurality of detected spread-spectrum signals, thereby generating a first combined signal, and for combining, from each receiver antenna of the plurality of receiver antennas, each of the second plurality of detected spread-spectrum signals, thereby generating a second combined signal.]

**[42.** The MIMO system as set forth in claim 41, further comprising multiplexer means for multiplexing the first combined signal with the second combined signal, thereby generating a multiplexed signal.]

**[43.** The MIMO system as set forth in claim 41, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a third spread-spectrum signal having a third channel of data arriving from any of the first path, the second path, or a third path of the multipath, further comprising:

said receiver-antenna means for receiving the third spread-spectrum signal;

said despreading means for detecting, at each receiver antenna of the plurality of receiver antennas, the third spread-spectrum signal, as a third plurality of detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the third plurality of detected spread-spectrum signals, thereby generating a third combined signal.]

**[44.** The MIMO system as set forth in claim 43, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, and the third combined signal, thereby generating a multiplexed signal.]

**[45.** The MIMO system, as set forth in claim **43**, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fourth spread-spectrum signal having a fourth channel of data arriving from any of the first path, the second path, the third path, or a fourth path of the multipath, further comprising:

said receiver-antenna means for receiving the fourth spread-spectrum signal;

said despreading means for detecting, at each receiver antenna of the plurality of receiver antennas, the fourth spread-spectrum signal, as a fourth plurality of detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the fourth plurality of detected spread-spectrum signals, thereby generating a fourth combined signal.]

**[46.** The MIMO system as set forth in claim **45**, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, the third combined signal, and the fourth combined signal, thereby generating a multiplexed signal.]

**[47.** The MIMO system, as set forth in claim **45**, for receiving data having symbols, from the communications channel having multipath, thereby generating, from the plurality of spread-spectrum signals, a fifth spread-spectrum signal having a fifth channel of data arriving from any of the first path, the second path, or the third path of the multipath, the fourth path, or a fifth path, further comprising:

said receiver-antenna means for receiving the fifth spread-spectrum signal;

said despreading means for detecting, at each receiver antenna of the plurality of receiver antennas, the fifth spread-spectrum signal, as a fifth plurality detected spread-spectrum signals; and

said combiner means for combining, from each receiver antenna of the plurality of receiver antennas, each of the fifth plurality of detected spread-spectrum signals, thereby generating a fifth combined signal.]

**[48.** The MIMO system as set forth in claim **47**, further comprising multiplexer means for multiplexing the first combined signal, the second combined signal, the third combined signal, the fourth combined signal, and the fifth combined signal, thereby generating a multiplexed signal.]

**[49.** The MIMO method as set forth in claim **1** with the step of detecting the first spread-spectrum signal and the second spread-spectrum signal, including the step of detecting, responsive to a first chip-sequence signal and to a second chip-sequence signal, the first spread-spectrum signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum signals, respectively.]

**[50.** The MIMO method as set forth in claim **3** with the step of detecting the third spread-spectrum signal, including the step of detecting, responsive to a third chip-sequence signal, the third spread-spectrum signal as the third plurality of detected spread-spectrum signals, respectively.]

**[51.** The MIMO method as set forth in claim **5** with the step of detecting the fourth spread-spectrum signal, including the step of detecting, responsive to a fourth chip-sequence signal, the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

**[52.** The MIMO method as set forth in claim **7** with the step of detecting the fifth spread-spectrum signal, including the step of detecting, responsive to a fifth chip-sequence signal, the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

**[53.** The MIMO system as set forth in claim **9** with said plurality of despreading devices, responsive to a first chip-sequence signal and to a second chip-sequence signal, for detecting the first spread-spectrum signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum signals, respectively.]

**[54.** The MIMO method as set forth in claim **11** with said plurality of despreading devices, responsive to a third chip-sequence signal, for detecting the third spread-spectrum signal as the third plurality of detected spread-spectrum signals, respectively.]

**[55.** The MIMO system as set forth in claim **13** with said plurality of despreading devices, responsive to a fourth chip-sequence signal, for detecting the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

**[56.** The MIMO system as set forth in claim **15** with said plurality of despreading devices, responsive to a fifth chip-sequence signal, for detecting the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

**[57.** The MIMO system as set forth in claim **17** with said despreading means, responsive to a first chip-sequence signal and to a second chip-sequence signal, for detecting the first spread-spectrum signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum signals, respectively.]

**[58.** The MIMO system as set forth in claim **19** with said despreading means, responsive to a third chip-sequence signal, for detecting the third spread-spectrum signal as the third plurality of detected spread-spectrum signals, respectively.]

**[59.** The MIMO system as set forth in claim **21** with said despreading means, responsive to a fourth chip-sequence signal, for detecting the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

**[60.** The MIMO system as set forth in claim **23** with said despreading means, responsive to a fifth chip-sequence signal, for detecting the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

**[61.** The MIMO method as set forth in claim **25** with the step of detecting the first spread-spectrum signal and the second spread-spectrum signal, including the step of detecting, responsive to a first chip-sequence signal and to a second chip-sequence signal, the first spread-spectrum signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum signals, respectively.]

**[62.** The MIMO method as set forth in claim **27** with the step of detecting the third spread-spectrum signal, including the step of detecting, responsive to a third chip-sequence signal, the third spread-spectrum signal as the third plurality of detected spread-spectrum signals, respectively.]

**[63.** The MIMO method as set forth in claim **29** with the step of detecting the fourth spread-spectrum signal, including the step of detecting, responsive to a fourth chip-sequence signal, the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

**[64.** The MIMO method as set forth in claim **31** with the step of detecting the fifth spread-spectrum signal, including the step of detecting, responsive to a fifth chip-sequence signal, the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

**[65.** The MIMO system as set forth in claim **33** with said plurality of despreading devices, responsive to a first chip-





chip-sequence signal, the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

[89. The MIMO system as set forth in claim 33 with said plurality of despreading devices including a first filter 5 matched to a first chip-sequence signal and a second filter matched to a second chip-sequence signal, for detecting the first spread-spectrum signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum 10 signals, respectively.]

[90. The MIMO system as set forth in claim 35 with said plurality of despreading devices, including a third filter 15 matched to a third chip-sequence signal, for detecting the third spread-spectrum signal as the third plurality of detected spread-spectrum signals, respectively.]

[91. The MIMO system as set forth in claim 37 with said plurality of despreading devices including a fourth filter 20 matched to a fourth chip-sequence signal, for detecting the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

[92. The MIMO system as set forth in claim 39 with said plurality of despreading devices including a fifth filter 25 matched to a fifth chip-sequence signal, for detecting the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

[93. The MIMO system as set forth in claim 41 with said despreading means including a first filter matched to a first chip-sequence signal and a second filter matched to a second chip-sequence signal, for detecting the first spread-spectrum 30 signal and the second spread-spectrum signal as the first plurality of detected spread-spectrum signals and the second plurality of detected spread-spectrum signals, respectively.]

[94. The MIMO system as set forth in claim 42 with said despreading means including a third filter matched to a third chip-sequence signal, for detecting the third spread-spectrum 35 signal as the third plurality of detected spread-spectrum signals, respectively.]

[95. The MIMO system as set forth in claim 43 with said despreading means including a fourth filter matched to a 40 fourth chip-sequence signal, for detecting the fourth spread-spectrum signal as the fourth plurality of detected spread-spectrum signals, respectively.]

[96. The MIMO system as set forth in claim 44 with said despreading means including a fifth filter matched to a fifth 45 chip-sequence signal, for detecting the fifth spread-spectrum signal as the fifth plurality of detected spread-spectrum signals, respectively.]

97. *A receiver system for recovering data conveyed in data symbols by a plurality of different signals transmitted on 50 separate carrier waves from a single data source over a wireless channel, said data symbols being generated by demultiplexing said single data source, said signals being differentiated by different codes conveyed along with said signals, comprising:*

*plural receiving antennas for receiving said signals;*  
*receiver circuitry connected to each receiving antenna for demodulating said received signals;*  
*circuitry for separating said different signals in response to detection of said different codes conveyed in said sig- 60 nals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and*  
*a multiplexer for multiplexing data derived from said plural streams of data symbols to form a single stream of 65 data corresponding to the data from said single data source.*

98. *The receiver system of claim 97 further comprising space diversity combiner circuitry for combining signals received on said different receiving antennas, whereby said data inputs to said multiplexer are derived from data symbols 5 generated by combining symbols from each of said receiving antennas.*

99. *A method for recovering data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless chan- 10 nel, said data symbols being generated by demultiplexing said single data source, said signals being differentiated by different codes conveyed along with said signals, comprising the steps of:*

*receiving said signals at plural receiving antennas;*  
*demodulating the signals received at each receiving 15 antenna;*  
*separating said different signals in response to detection of said different codes conveyed in said signals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and*  
*multiplexing data derived from said plural streams of data symbols to form a single stream of data corresponding to 20 the data from said single data source.*

100. *The method of claim 99 wherein said receiving step includes space diversity combining signals received on the 25 different receiving antennas whereby the data inputs to be multiplexed are derived from data symbols generated by combining symbols from each of the receiving antennas.*

101. *A receiver system for recovering data in spread spec- 30 trum signals, the data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless channel, said data symbols being generated by demultiplexing said single data source, said signals being differentiated by different codes 35 conveyed along with said signals, comprising:*

*plural receiving antennas for receiving said spread spec- 40 trum signals;*  
*receiver circuitry connected to each receiving antenna for demodulating said received spread spectrum signals;*  
*circuitry for despreading and separating said different spread spectrum signals in response to detection of said 45 different codes conveyed in said signals and for forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and*  
*a multiplexer for multiplexing data derived from said plu- 50 ral streams of data symbols to form a single stream of data corresponding to the data from said single data source.*

102. *The receiver system of claim 101 further comprising space diversity combining circuitry for combining signals received on said different receiving antennas, whereby said data inputs to said multiplexer are derived from data symbols 55 generated by combining symbols from each of said receiving antennas.*

103. *A method for recovering data in spread spectrum signals, the data conveyed in data symbols by a plurality of 60 different signals transmitted on separate carrier waves from a single data source over a wireless channel, said data symbols being generated by demultiplexing said single data source, said signals being differentiated by different codes conveyed along with said signals, comprising the steps of:*

*receiving said spread spectrum signals at plural receiving 65 antennas;*  
*demodulating the spread spectrum signals received at each receiving antenna;*

despreading and separating said different spread spectrum signals in response to detection of said different codes conveyed in said signals;

recovering the data symbols conveyed in said spread spectrum signals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and  
multiplexing data derived from said plural streams of data symbols to form a single stream of data corresponding to the data from said single data source.

104. The method of claim 103 further comprising space diversity combining signals received on said different receiving antennas, whereby said data inputs to said multiplexer are derived from data symbols generated by combining symbols from each of said receiving antennas.

105. A receiver system for recovering data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless channel, said signals being differentiated by different codes conveyed along with said signals and said data having been error coded and interleaved, either before or after being demultiplexed, prior to transmission, comprising:

plural receiving antennas for receiving said signals;

receiver circuitry connected to each receiving antenna for demodulating said received signals;

circuitry for separating said different signals in response to detection of said different codes conveyed in said signals and for forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and

multiplexer for multiplexing data derived from said plural streams of combined data symbols to form a single stream of data, the data output from said multiplexer having the same state of error coding and interleaving as the demultiplexed data had at said single data source.

106. A method for recovering data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless channel, said signals being differentiated by different codes conveyed along with said signals and said data having been error coded and interleaved, either before or after being demultiplexed, prior to transmission, comprising the steps of:

receiving said signals at plural receiving antennas;  
demodulating the signals received at each receiving antenna;

separating said different signals in response to detection of said different codes conveyed in said signals and recovering the data symbols conveyed in said signals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves, and

multiplexing data derived from said plural streams of data symbols to form a single stream of data, the data output from said multiplexing step having the same state of error coding and interleaving as the demultiplexed data had at said single data source.

107. A receiver system for recovering data in spread spectrum signals, the data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless channel, said signals being differentiated by different codes conveyed along with said signals and said data having been error coded and interleaved, either before or after being demultiplexed, prior to transmission, comprising:

plural receiving antennas for receiving said spread spectrum signals;

receiver circuitry connected to each receiving antenna for demodulating said received spread spectrum signals;  
circuitry for despreading and separating said received spread spectrum signals in response to detection of said different codes conveyed in said signals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and

a multiplexer for multiplexing data derived from said plural streams of data symbols to form a single stream of data, the data output from said multiplexer having the same state of error coding and interleaving as the demultiplexed data had at said single data source.

108. A method for recovering data in spread spectrum signals, the data conveyed in data symbols by a plurality of different signals transmitted on separate carrier waves from a single data source over a wireless channel, said signals being differentiated by different codes conveyed along with said signals and said data having been error coded and interleaved, either before or after being demultiplexed, prior to transmission comprising the steps of:

receiving said spread spectrum signals at plural receiving antennas; demodulating the spread spectrum signals received at each receiving antenna; despreading and separating said received spread spectrum signals in response to detection of said different codes conveyed in said signals;

recovering the data symbols conveyed in said spread spectrum signals, thereby forming plural streams of data symbols, each stream representing a stream of data symbols conveyed on one of said carrier waves; and  
multiplexing data derived from said plural streams of data symbols to form a single stream of data, the data output from said multiplexing step having the same state of error coding and interleaving as the demultiplexed data had at said single data source.

109. The receiver system of claim 98 wherein said combiner circuitry further includes time-diversity combining circuitry for combining multipath components of signals conveyed on each one of said carrier waves.

110. The receiver system of claim 102 wherein said combiner circuitry further includes time-diversity combining circuitry for combining multipath components of signals conveyed on each one of said carrier waves.

111. The method of claim 100 wherein said step of combining signals further includes time-diversity combining of multipath components of signals conveyed on each one of said carrier waves.

112. The method of claim 104 wherein said step of combining signals further includes time-diversity combining of multipath components of signals conveyed on each one of said carrier waves.

113. The receiver system of claim 97 wherein said different codes conveyed along with said signals identify said signals and said circuitry detects said different codes.

114. The receiver system of claim 97 wherein said different codes conveyed along with said signals are spreading codes.

115. The method as recited in claim 99 wherein said different codes conveyed along with said signals identify said signals and said separating step includes using the different codes in identifying associated transmitted signals.

116. The method as recited in claim 99 wherein said different codes conveyed along with said signals are spreading codes.

117. The receiver system of claim 101 wherein said different codes conveyed along with said signals identify said signals and said circuitry detects said different codes.

118. The receiver system of claim 101 wherein said different codes conveyed along with said signals are spreading codes.

119. The method as recited in claim 103 wherein said different codes conveyed along with said signals identify said signals and said separating step includes using the different codes in identifying associated transmitted signals.

120. The method as recited in claim 103 wherein said different codes conveyed along with said signals are spreading codes.

121. The receiver system of claim 105 wherein said different codes conveyed along with said signals identify said signals and said circuitry detects said different codes.

122. The receiver system of claim 105 wherein said different codes conveyed along with said signals are spreading codes.

123. The method as recited in claim 106 wherein said different codes conveyed along with said signals identify said signals and said separating step includes using the different codes in identifying associated transmitted signals.

124. The method as recited in claim 106 wherein said different codes conveyed along with said signals are spreading codes.

125. The receiver system of claim 107 wherein said different codes conveyed along with said signals identify said signals and said circuitry detects said different codes.

126. The receiver system of claim 107 wherein said different codes conveyed along with said signals are spreading codes.

127. The method as recited in claim 108 wherein said different codes conveyed along with said signals identify said

signals and said separating step includes using the different codes in identifying associated transmitted signals.

128. The method as recited in claim 108 wherein said different codes conveyed along with said signals are spreading codes.

129. A receiver system for recovering a stream of data conveyed in data symbols by a plurality of demultiplexed different data signals from a transmitter, each of the data signals being a spread spectrum signal stream different from each of the other spread spectrum signal streams and each of the spread spectrum signal streams being transmitted using a different transmit antenna such that all of the spread spectrum signal streams use the same bandwidth in a frequency band, said receiver system comprising:

a plurality of receiver subsystems, each including a receiver antenna and matched filter means, each of said matched filter means being matched during operation to a different one of the received plurality of transmitted spread spectrum signals;

combiner means to combine signals from each matched filter means of the plurality of receiver subsystems during operation to a different one of the received plurality of transmitted spread spectrum signals thereby producing a plurality of combined signals equal in number to the number of transmit antennas, said combined signals representing the demultiplexed streams of data spread spectrum modulated and demultiplexed at the transmitter; and

multiplexer means forming a single multiplexed stream of data from said plurality of combined signals to be representative of the stream of data from the transmitter.

\* \* \* \* \*