

US00RE44564E

(19) **United States**
(12) **Reissued Patent**
Kim et al.

(10) **Patent Number:** **US RE44,564 E**
(45) **Date of Reissued Patent:** **Oct. 29, 2013**

(54) **METHOD FOR TRANSMITTING CONTROL SIGNAL USING EFFICIENT MULTIPLEXING**

(58) **Field of Classification Search**
None
See application file for complete search history.

(75) Inventors: **Hak Seong Kim**, Anyang-si (KR); **Sung Duk Choi**, Anyang-si (KR); **Ki Jun Kim**, Anyang-si (KR); **Suk Hyon Yoon**, Anyang-si (KR); **Joon Kui Ahn**, Anyang-si (KR); **Bong Hoe Kim**, Anyang-si (KR); **Dong Youn Seo**, Anyang-si (KR); **Young Woo Yun**, Anyang-si (KR); **Jung Hoon Lee**, Anyang-si (KR); **Seong Hoon Jeong**, Anyang-si (KR)

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,870,391 A 2/1999 Nago
6,452,936 B1 9/2002 Shiino
6,842,487 B1 1/2005 Larsson
6,934,318 B2 8/2005 Sarkar

(Continued)

(73) Assignee: **LG Electronics Inc.**, Seoul (KR)

FOREIGN PATENT DOCUMENTS

(21) Appl. No.: **13/476,973**

CN 1829373 9/2006
EP 1185001 3/2002

(22) Filed: **May 21, 2012**

(Continued)

Related U.S. Patent Documents

OTHER PUBLICATIONS

Reissue of:

(64) Patent No.: **7,953,061**
Issued: **May 31, 2011**
Appl. No.: **12/444,100**
PCT Filed: **Oct. 2, 2007**
PCT No.: **PCT/KR2007/004825**
§ 371 (c)(1),
(2), (4) Date: **Apr. 2, 2009**
PCT Pub. No.: **WO2008/041820**
PCT Pub. Date: **Apr. 10, 2008**

Ryu, H.G., "System Design and Analysis of MIMO SFBC CI-OFDM System against the Nonlinear Distortion and Narrowband Interference," IEEE Transactions on Consumer Electronics, vol. 54, No. 2, pp. 368-375, May 2008.

(Continued)

U.S. Applications:

(60) Provisional application No. 60/955,019, filed on Aug. 9, 2007, provisional application No. 60/827,852, filed on Oct. 2, 2006.

Primary Examiner — Kevin C Harper

(74) *Attorney, Agent, or Firm* — Lee, Hong, Degerman, Kang & Waimey

(30) **Foreign Application Priority Data**

Feb. 5, 2007 (KR) 10-2007-0011533
Oct. 2, 2007 (KR) 10-2007-0099055


(57) **ABSTRACT**

Methods of transmitting a control signal using efficient multiplexing are disclosed. One of the method includes the steps of multiplexing a plurality of 1-bit control signals within a prescribed time-frequency domain by code division multiple access (CDMA) and transmitting the multiplexed control signals, wherein a plurality of the 1-bit control signals include a plurality of the 1-bit control signals for a specific transmitting side. Accordingly, reliability on 1-bit control signal transmission can be enhanced.

(51) **Int. Cl.**
H04B 7/216 (2006.01)

(52) **U.S. Cl.**
USPC **370/342; 370/479**

10 Claims, 9 Drawing Sheets



US RE44,564 E

Page 2

(56)

References Cited

U.S. PATENT DOCUMENTS

7,069,050	B2	6/2006	Yoshida	JP	04-074026	3/1992
7,315,577	B2	1/2008	Shao	JP	2001044900	2/2001
7,336,633	B2	2/2008	Kruys	JP	2002369258	12/2002
7,386,076	B2	6/2008	Onggosanusi et al.	JP	2004-312291	11/2004
7,995,661	B2	8/2011	Xu et al.	JP	2004-312291 A	11/2004
2001/0005681	A1	6/2001	Kim	JP	2004364321	12/2004
2001/0034236	A1	10/2001	Tong et al.	JP	2005244960	9/2005
2003/0039227	A1	2/2003	Kwak	JP	2005253073	9/2005
2003/0133426	A1	7/2003	Schein et al.	JP	2005288300	10/2005
2004/0009780	A1	1/2004	Dick et al.	JP	2006166382	6/2006
2004/0081131	A1	4/2004	Walton et al.	JP	2007-124682	5/2007
2004/0190640	A1	9/2004	Dubuc et al.	JP	2007-124682 A	5/2007
2005/0083977	A1	4/2005	Moulsley et al.	JP	2007-511975	5/2007
2005/0117536	A1	6/2005	Cho et al.	JP	2007-221755	8/2007
2005/0122898	A1	6/2005	Jang et al.	JP	2008-053858	3/2008
2005/0165949	A1	7/2005	Teague	JP	2008-092377	4/2008
2005/0220000	A1	10/2005	Kim et al.	JP	2008092051	4/2008
2005/0232181	A1	10/2005	Park et al.	JP	2008236018	10/2008
2005/0233754	A1	10/2005	Beale	JP	2010506505	2/2010
2005/0286402	A1	12/2005	Byun et al.	JP	2011193521	9/2011
2006/0045001	A1	3/2006	Jalali	KR	101999013366	2/1999
2006/0198294	A1	9/2006	Gerlach	KR	10-2002-0009079	2/2002
2006/0209814	A1	9/2006	Fujii	KR	10-2002-0009079 A	2/2002
2006/0250941	A1	11/2006	Onggosanusi et al.	KR	1020020088085	11/2002
2006/0264218	A1	11/2006	Zhang et al.	KR	1020030081464	10/2003
2006/0274842	A1	12/2006	Pan et al.	KR	1020050021965	3/2005
2006/0280256	A1	12/2006	Kwon et al.	KR	10-2005-0043302	5/2005
2007/0064669	A1	3/2007	Classon et al.	KR	10-2005-0043302 A	5/2005
2007/0097915	A1	5/2007	Papasakellariou	KR	1020050073256	7/2005
2007/0097981	A1	5/2007	Papasakellariou	KR	10-2005-0120244	12/2005
2007/0110104	A1	5/2007	Sartori et al.	KR	10-2005-0120244 A	12/2005
2007/0149137	A1	6/2007	Richardson et al.	KR	1020060016600	2/2006
2007/0183533	A1	8/2007	Schmidl et al.	KR	10-2006-0081352	7/2006
2007/0184849	A1	8/2007	Zheng	KR	10-2006-0081352 A	7/2006
2007/0206559	A1	9/2007	Cho et al.	KR	10-2006-0092055	8/2006
2007/0208986	A1	9/2007	Luo et al.	KR	10-2006-0092055 A	8/2006
2007/0211667	A1	9/2007	Agrawal et al.	KR	1020060095576	8/2006
2007/0254662	A1	11/2007	Khan et al.	KR	1020070107614	11/2007
2007/0258373	A1	11/2007	Frederiksen et al.	KR	10-2008-0023664	3/2008
2007/0258540	A1	11/2007	Ratasuk et al.	KR	1020080030905	4/2008
2008/0025247	A1	1/2008	McBeath et al.	KR	1020080039772	5/2008
2008/0025337	A1	1/2008	Smith et al.	KR	10-2008-0065853	7/2008
2008/0090528	A1	4/2008	Malladi	KR	10-2008-0096088	10/2008
2008/0095106	A1	4/2008	Malladi et al.	KR	10-0894142	4/2009
2008/0225784	A1	9/2008	Tseng	KR	10-2009-0082843	7/2009
2008/0225791	A1	9/2008	Pi et al.	RU	2142672	10/1999
2008/0227398	A1	9/2008	Haghighat et al.	RU	2221335	1/2004
2008/0232307	A1	9/2008	Pi et al.	RU	2267225	5/2005
2008/0253469	A1	10/2008	Ma et al.	RU	2142672	10/2009
2008/0304593	A1	12/2008	Khan et al.	TW	545074	8/2003
2008/0310483	A1	12/2008	Lee et al.	WO	03/043245	5/2003
2009/0046793	A1	2/2009	Love et al.	WO	03/043245 A1	5/2003
2009/0059884	A1	3/2009	Zhang et al.	WO	03/077579	9/2003
2009/0060081	A1	3/2009	Zhang et al.	WO	03/085858	10/2003
2009/0154580	A1	6/2009	Ahn et al.	WO	2004/038991	5/2004
2009/0196279	A1	8/2009	Kim et al.	WO	2004/049591	6/2004
2009/0274037	A1	11/2009	Lee et al.	WO	2005/006250	1/2005
2009/0285163	A1	11/2009	Zhang et al.	WO	2005/050875	6/2005
2009/0310719	A1	12/2009	Stirling-gallacher	WO	2005/060132	6/2005
2009/0323615	A1	12/2009	Ihm et al.	WO	2005/065062	7/2005
2010/0034163	A1	2/2010	Damnjanovic et al.	WO	2005/074184	8/2005
2010/0098005	A1	4/2010	Lee et al.	WO	2005/074184 A2	8/2005
2010/0098019	A1	4/2010	Kim et al.	WO	2005/088869	9/2005
2010/0111031	A1	5/2010	Kim et al.	WO	2005/099123	10/2005
2010/0260164	A1	10/2010	Moon et al.	WO	2005/125140	12/2005
2011/0002309	A1	1/2011	Park et al.	WO	2005/125140 A1	12/2005
2012/0106478	A1	5/2012	Han et al.	WO	2005119959	12/2005
2012/0113945	A1	5/2012	Moon et al.	WO	2006/023192	3/2006

FOREIGN PATENT DOCUMENTS

EP	1248485	10/2002	WO	2006/073284	7/2006
EP	1746810	1/2007	WO	2006/073284	7/2006
EP	1746855	1/2007	WO	2006/102771	10/2006
			WO	2007007380	1/2007
			WO	2007/052941	5/2007
			WO	2007/052941 A1	5/2007
			WO	2007049208	5/2007

(56)

References Cited

FOREIGN PATENT DOCUMENTS

WO	2007/078146	7/2007
WO	2008/133439	11/2008
WO	2008/153331	12/2008

OTHER PUBLICATIONS

Ryu, H.G., et al., "Design and Performance Evaluation of the MIMO SFBC CI-OFDM Communication System," The Fourth International Conference on Wireless and Mobile Communications, pp. 60-64, Jul. 2008.

Panasonic, "Mapping Positions of Control Channel for Uplink SC-FDMA", TSG-RAN WG1 #43, Doc. No. R1-051395, XP-002450961, Nov. 7, 2005.

3rd Generation Partnership Project (3GPP), "3rd Generation Partnership Project; Technical Specification Group Radio Access Network; LTE Physical Layer—General Description (Release 8)" 3GPP TS 36.201 V1.2.0, XP-050380347, Jun. 2007.

Su, W., et al., "Obtaining full-diversity space-frequency codes from space-time codes via mapping," IEEE Transactions on Signal Processing, vol. 51, No. 11, pp. 2903-2916, Nov. 1, 2003; XP-011102805.

Samsung, "Transmit Diversity for 4-Tx Antenna", 3GPP TSG RAN WG1 Meeting #49, R1-072238, May 7, 2007, XP-002578959.

Zhang, W., et al., "Space-Time/Frequency Coding for MIMO-OFDM in Next Generation Broadband Wireless Systems," *Next-Generation CDMA vs. OFDMA for 4G Wireless Applications*, IEEE Wireless Communications, vol. 14, No. 3, pp. 32-43, Jun. 2007, XP-011189164.

Kim, I.G., et al., "Transmit Diversity and Multiplexing Methods for 3G-LTE Downlink Control Channels," 64th IEEE Vehicular Technology Conference, Sep. 2006, XP-031051218.

Zhang, W., et al., "Universal Space-Frequency Block Coding for MIMO-OFDM Systems", IEEE Asia-Pacific Conference on Communications, pp. 227-231, Oct. 5, 2005.

Zhang, M., et al., "Space-Frequency Block Code with Matched Rotation MIMO-OFDM System with Limited Feedback", EURASIP Journal on Advances in Signal Processing, Jun. 24, 2009.

LG Electronics, "Downlink resource allocation for localized and distributed transmission," R1-071549, 3GPP TSG RAN WG1 #48bis, Mar. 2007, XP-050105480.

Kaiser, "Space Frequency Block Coding in the Uplink of Broadband MC-CDMA Mobile Radio Systems with Pre-Equalization", Institute of Electrical and Electronics Engineers, Vehicular Technology Conference, Fall 2003, XP10701084.

Texas Instruments, "Shared Control Channel Structure and Coding for E-UTRA Downlink", 3GPP TSG RAN WG1 LTE Ad Hoc, R1-061740, Jun. 2006.

LG Electronics, "Downlink Cat0 signaling for scheduling assignments", 3GPP TSG RAN WG1 #47bis, R1-070247, Jan. 2007.

LG Electronics, "Downlink ACK/NACK Index Mapping", R1-071552, 3GPP RAN WG1 #48-BIS, Mar. 2007, XP-002660818.

Qualcomm Europe, "Considerations on Multiplexing of Control and User Data for xFDMA based E-UTRA Uplink Evaluation", R1-051102, 3GPP TSG-RAN WG1 #42bis, Oct. 2005, XP-002446638.

LG Electronics, "Uplink ACK/NACK Index Mapping", R1-071547, 3GPP RAN WG1 #48-BIS, Mar. 2007, XP-002660822.

Panasonic, "Assignment of Downlink ACK/NACK channel", R1-072794, 3GPP TSG-RAN WG1 Meeting #49bis, Jun. 2007, XP-002660823.

NTT Docomo et al., "Comparison between RB-level and Sub-carrier-level Distributed Transmission for Shared Data Channel in E-UTRA Downlink", R1-062089, 3GPP TSG RAN WG1 Meeting #46, Sep. 2006.

NTT DoCoMo et al., "Downlink L1/L2 Control Signaling Channel Structure Mapping," R1-070104, 3GPP TSG RAN WG Meeting #47bis, Jan. 2007.

Ericsson et al., "Way Forward on Downlink Control Signaling," R1-071223, 3GPP TSG RAN WG1 Meeting #48, Feb. 2007.

NEC Group, "Efficient Downlink ACK/NACK signalling for E-UTRA," R1-071508, TSG-RAN WG1#48Bis, Mar. 2007.

Huawei, "E-UTRA Downlink L1/L2 Control Channel Structure," R1-071689, 3GPP TSG-RAN-WG1 Meeting #48bis, Mar. 2007.

Nortel, "SCH Search Performance with Transmit Diversity", R1-061843, 3GPP TSG-RAN Working Group 1 Meeting on LTE, Jun. 2006.

Samsung, "Performance of 4-Tx Antenna diversity with realistic channel estimation", R1-072239, 3GPP TSG RAN WG1 Meeting #49, May 2007.

Morimoto et al., "Transmit Diversity Schemes Suitable for Common Control Channel in Evolved UTRA Downlink", RCS2007-50, IEICE Technical Report, pp. 125-130, Jul. 2007.

Samsung, "Downlink ACK/NACK Transmission Structure", R1-072247, 3GPP TSG RAN WG1 Meeting #49, May 2007.

NTT DoCoMo et al., "Coding Scheme of L1/L2 Control Channel for E-UTRA Downlink", R1-061672, 3GPP TSG RAN WG1 LTE Ad Hoc, Jun. 2006.

Sharp, "UE Identity in L1/L2 Downlink Control Signalling", R1-061136, 3GPP TSG-RAN WG1#45, May 2006.

LG Electronics, "Downlink control signaling", R1-063177, 3GPP TSG RAN WG1 #47, Nov. 2006.

LG Electronics, "DL ACK/NACK structure", R1-072878, 3GPP TSG RAN WG1 #49bis, Jun. 2007.

Intel Corporation: "Text Proposal for downlink OFDMA resource allocation and mapping rules for distributed mode users in E-UTRA, with discussion on control information", R1-061149, 3GPP TSG RAN WG1 #45, May 2006, XP002486595.

ETRI: "Downlink L1/L2 control signaling", R1-070079, 3GPP TSG RAN WG1 Meeting #47bis, Jan. 2007, XP050104134.

Qualcomm Europe, "Mapping of UL ACK Transmission based on DL VRB", R1-070660, 3GPP TSG RAN1 #48, Feb. 2007.

Nortel, "Discussion on linkage of PHICH to uplink transmissions", R1-080771, 3GPP TSG-RAN WG1 Meeting #52, Feb. 2007.

United States Patent and Trademark Office Application U.S. Appl. No. 13/014,665, Office Action dated Nov. 29, 2012, 24 pages.

United States Patent and Trademark Office Application U.S. Appl. No. 13/295,987 Office Action dated Feb. 6, 2013, 8 pages.

United States Patent and Trademark Office Application U.S. Appl. No. 13/295,974 Office Action dated Jan. 29, 2013, 8 pages.

NTT DoCoMo et al., "RB-level Distributed Transmission Method for Shared Data Channel in E-UTRA Downlink", R1-062285, 3GPP TSG-RAN WG1#46, Aug.-Sep. 2006.

Texas Instruments, "Shared Control Channel Structure and Coding for E-UTRA Downlink", R1-061433, 3GPP TSG-RAN WG1#45, May 2006.

United States Patent and Trademark Office Application U.S. Appl. No. 13/165,711, Office Action dated Mar. 13, 2013 10 pages.

United States Patent and Trademark Office Application U.S. Appl. No. 13/295,884, Office Action dated Mar. 14, 2013 8 pages.

United States Patent and Trademark Office Application U.S. Appl. No. 13/217,204, Notice of Allowance dated Apr. 8, 2013, 8 pages.

Taiwan Intellectual Property Office Application Serial No. 096136988, Office Action dated May 17, 2013, 6 pages.

United States Patent and Trademark Office U.S. Appl. No. 13/014,665, Final Office Action dated May 22, 2013, 25 pages.

United States Patent and Trademark Office U.S. Appl. No. 13/165,711, Final Office Action dated Aug. 9, 2013, 9 pages.

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8





FIG. 9



METHOD FOR TRANSMITTING CONTROL SIGNAL USING EFFICIENT MULTIPLEXING

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a reissue of U.S. Pat. No. 7,953,061, which issued on May 31, 2011, from U.S. application Ser. No. 12/444,100, filed on Apr. 2, 2009, which is the National Stage filing under 35 U.S.C. 371 of International Application No. PCT/KR2007/004825, filed on Oct. 2, 2007, which claims the benefit of earlier filing date and right of priority to Korean Application Nos. 10-2007-0011533, filed on Feb. 5, 2007 and 10-2007-0099055, filed on Oct. 2, 2007, and also claims the benefit of U.S. Provisional Application Ser. Nos. 60/827,852, filed on Oct. 2, 2006, and 60/955,019, filed on Aug. 9, 2007.

TECHNICAL FIELD

The present invention relates to a method for transmitting a control signal in a multi-carrier mobile communication system, and more particularly, to a control signal transmitting method. Although the present invention is suitable for a wide scope of applications, it is particularly suitable for transmitting a control signal reliably in uplink/downlink transmission by multiplexing a plurality of 1-bit control signals efficiently.

BACKGROUND ART

Generally, in a multi-carrier mobile communication system, a base station performs downlink data packet transmission to user equipments (hereinafter abbreviated UEs) belonging to a cell or each of a plurality of cells. Meanwhile, a plurality of UEs may exist within a cell. Since each of the UEs is unable to know how a data packet will be transmitted to itself using a prescribed format, when a base station transmits a downlink data packet to a specific UE, the base station should transmit such necessary information as an ID of a UE that will receive the corresponding data packet, a time-frequency domain for carrying the data packet, a data transmission format including a coding rate, a modulation scheme and the like, HARQ relevant information, and the like in downlink for each downlink data packet transmission.

On the contrary, in order to enable a UE to transmit a data packet in uplink, a base station should transmit such necessary information as an ID of a UE that will be approved for data packet transmission, an uplink time-frequency domain enabling the UE to transmit the data packet, a data transmission format including a coding rate, a modulation scheme and the like, HARQ relevant information, and the like in downlink for each uplink data packet transmission.

In case of the uplink data packet transmission, a base station should transmit reception success acknowledgement/non-acknowledgement (ACK/NACK) information on each data having been transmitted by a UE to the corresponding UE in uplink. On the other hand, in case of downlink data packet transmission, each UE transmits information about reception success or failure for each data packet having been transmitted by a base station through ACK/NACK information in uplink.

In order to maintain an uplink transmission/reception power of each UE at a proper level, a base station should transmit power control information to each UE in downlink.

Among the above-explained control signals, an ACK/NACK signal, a power control signal or the like is mainly able to indicate the corresponding information using one bit and can be named '1-bit control signal'.

In order to operate and manage a system efficiently, it is necessary to multiplex an uplink/downlink control signal for carrying the above-explained control information, and more particularly, the 1-bit control signal with a data packet and other signals in a time-frequency resource efficiently.

As a multiplexing scheme normally used for a multi-carrier mobile communication system, time division multiple access (TDMA) for multiplexing a plurality of signals by dividing them on a time domain, frequency division multiple access (FDMA) for multiplexing a plurality of signals by dividing them on a frequency domain, code division multiple access (CDMA) for multiplexing signals on a prescribed time-frequency domain using an orthogonal code or a pseudo-orthogonal code, or the like can be used.

Yet, in case that the 1-bit control signal is multiplexed using TDMA and/or FDMA only, since a transmission power of each control signal considerably differs, an effect on a neighbor cell may differ on a time domain and/or a frequency domain.

In particular, when a random cell multiplexes to transmit ACK/NACK signals for different UEs within a single TTI by TDMA or FDMA for example, in case that an ACK/NACK signal transmission power for each of the UEs considerably differs, a quantity of interference imposed on neighbor cells by the corresponding cell may differ considerably on a time domain or a frequency domain. And, this may have a bad influence on performing downlink data packet scheduling in a cellular environment or time-frequency-energy distributions efficiently.

Moreover, in case that a control signal such as an ACK/NACK signal of a transmitting side is lost in the course of downlink/uplink channel transmission, there may be a problem of reliability on the corresponding signal transmission.

DISCLOSURE OF THE INVENTION

Technical Problem

Technical Solution

Accordingly, the present invention is directed to a method for transmitting a control signal in a multi-carrier mobile communication system that substantially obviates one or more of the problems due to limitations and disadvantages of the related art.

An object of the present invention is to provide a method of transmitting a plurality of control signals efficiently, by which a control signal of a specific transmitting side can be reliably transmitted in a manner of performing multiplexing efficiently to minimize inter-cell interference in control signal transmission.

Additional features and advantages of the invention will be set forth in the description which follows, and in part will be apparent from the description, or may be learned by practice of the invention. The objectives and other advantages of the invention will be realized and attained by the structure particularly pointed out in the written description and claims thereof as well as the appended drawings.

To achieve these and other advantages and in accordance with the purpose of the present invention, as embodied and

broadly described, a method of transmitting a control signal according to the present invention includes multiplexing a plurality of 1-bit control signals within a prescribed time-frequency domain by code division multiple access (CDMA), repeating the multiplexed control signals in different frequency domains, and transmitting the repeated control signals.

To achieve these and other advantages and in accordance with the purpose of the present invention, as embodied and broadly described, a method of transmitting a control signal according to the present invention includes multiplexing a plurality of 1-bit control signals within a prescribed time-frequency domain by code division multiple access (CDMA), and transmitting the multiplexed control signals, wherein a plurality of the 1-bit control signals include a plurality of the 1-bit control signals for a specific transmitting side.

Preferably, wherein the prescribed time-frequency domain comprises a time-frequency domain within 1 OFDM symbol zone.

Preferably, wherein in case that a time domain used for the control signal transmission comprises a single OFDM symbol zone, the repeating is carried out in a manner of repeating the multiplexed control signals into the different frequency domains within the single OFDM symbol zone.

Preferably, wherein in case that a time domain used for the control signal transmission comprises a plurality of OFDM symbol zones, the repeating is carried out in a manner of repeating the multiplexed control signals into the different frequency domains within the OFDM symbol zones differing from each other.

Preferably, in the multiplexing, a plurality of the 1-bit control signals are discriminated by an orthogonal or pseudo-orthogonal code used for multiplexing of each of the 1-bit control signals.

More preferably, a plurality of the 1-bit control signals are modulated by being discriminated by different orthogonal phase components, respectively and wherein in the multiplexing, a plurality of the 1-bit control signals are additionally discriminated by the different orthogonal phase components used for the modulation.

Preferably, the prescribed time-frequency domain includes a plurality of time-frequency domains. In the multiplexing, additional multiplexing is carried out by at least one selected from the group consisting of time division multiple access (TDMA) and frequency division multiple access (FDMA). And, a plurality of the 1-bit control signals for the specific transmitting side are multiplexed by being spread in a plurality of the time-frequency domains.

More preferably, the 1-bit control signals for different transmitting sides are multiplexed in a plurality of the time-frequency domains by the code division multiple access, respectively. In this case, a plurality of the 1-bit control signals for the specific transmitting side are multiplexed by different orthogonal or pseudo-orthogonal codes.

And, the orthogonal or pseudo-orthogonal code includes a code sequence having a length corresponding to a size of a plurality of the time-frequency domains.

Besides, the 1-bit control signal can include either an ACK/NACK signal or a power control signal. And, the 1-bit control signal can be transmitted in either uplink or downlink.

It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory and are intended to provide further explanation of the invention as claimed.

ADVANTAGEOUS EFFECTS

According to one embodiment of the present invention, in multiplexing a plurality of 1-bit control signals, CDMA is

mainly used. And, it is able to transmit a plurality of controls signals of a specific UE through different orthogonal or pseudo-orthogonal codes, respectively. Hence, it is able to enhance reliability on the corresponding control signal transmission.

And, the number of multiplexed signals in coherence bandwidth and/or coherence time can be increased by carrying out FDMA and/or TDMA on the 1-bit control signal transmission side by side and by distributing to transmit a plurality of control signals for a specific UE on each time-frequency domain.

Moreover, in case of transmitting the 1-bit control signal through a plurality of time-frequency domains, by specifying to use an orthogonal code used for transmission in accordance with the size the whole time-frequency domains instead of the size of each the time-frequency domain, it is able to increment a number of control signals that can be simultaneously transmitted.

Besides, in case that a plurality of OFDM symbols are used for 1-bit control signal transmission, by transmitting a CDMA modulated 1-bit control signal on a different OFDM symbol area through a different frequency domain, it is able to perform efficient transmission in aspects of resource efficiency and diversity gain. And, it is also able to make a power allocation more flexible within each OFDM symbol area.

DESCRIPTION OF DRAWINGS

The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this specification, illustrate embodiments of the invention and together with the description serve to explain the principles of the invention.

In the drawings:

FIG. 1 is a diagram for explaining a method of multiplexing to transmit ACK/NACK signals by CDMA according to one embodiment of the present invention;

FIG. 2 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA and FDMA according to one embodiment of the present invention;

FIG. 3 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA, TDMA and FDMA according to one embodiment of the present invention;

FIG. 4 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA and FDMA according to one embodiment of the present invention, in which a plurality of ACK/NACK signals transmitted by a specific transmitting side among a plurality of ACK/NACK signals are transmitted through a plurality of frequency domains;

FIG. 5 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA, TDMA and FDMA according to one embodiment of the present invention, in which a plurality of ACK/NACK signals transmitted by a specific transmitting side among a plurality of ACK/NACK signals are transmitted through a plurality of time-frequency domains;

FIG. 6 is a diagram for explaining a method of transmitting ACK/NACK in case of using 1 OFDM symbol zone for ACK/NACK transmission according to one embodiment of the present invention;

FIG. 7 is a diagram for explaining a method of transmitting ACK/NACK in case of using at least 2 OFDM symbol zones for ACK/NACK transmission according to one embodiment of the present invention;

5

FIG. 8 is a diagram for explaining a method of transmitting ACK/NACK in case of using at least 2 OFDM symbol zones for ACK/NACK transmission according to one preferred embodiment of the present invention; and

FIG. 9 is a diagram to explain a principle that power allocation flexibility is increased in case of transmitting ACK/NACK signals by the embodiment shown in FIG. 8.

BEST MODE

Mode for Invention

Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings.

Generally, a base station transmits an ACK/NACK signal indicating a success or failure in receiving a data packet transmitted by each UE within a cell or a control signal playing a role similar to that of the ACK/NACK signal to the corresponding UE in downlink. In doing so, since a plurality of UEs are able to transmit uplink data packets within a single TTI, the base station is able to transmit ACK/NACK signals to a plurality of the UEs within a single TTI as well.

And, a base station multiplexes a plurality of power control signals for controlling transmission powers of uplink data of a plurality of UEs for a single TTI within a cell and then transmits the multiplexed signal to each of the UEs.

Hence, according to one embodiment of the present invention, in order to multiplex and transmit a plurality of 1-bit control signals efficiently, a method of multiplexing to transmit a plurality of 1-bit control signals by CDMA within a partial time-frequency domain of a transmission band in a multi-carrier system is proposed. And, this will be explained with reference to a detailed example.

Meanwhile, the description for one embodiment of the present invention relates to a case that a 1-bit control signal is an ACK/NACK signal for example. In a control signal transmitting method according to one embodiment of the present invention, a 1-bit control signal needs not to be an ACK/NACK signal necessarily. And, it is apparent to those skilled in the art that the present invention includes a random 1-bit control signal in a format that a plurality of signals are transmitted within 1 TTI.

FIG. 1 is a diagram for explaining a method of multiplexing to transmit ACK/NACK signals by CDMA according to one embodiment of the present invention.

Referring to FIG. 1, according to one embodiment of the present invention, a base station reserves a specific time-frequency domain within 1 TTI for ACK/NACK transmission to use. And, ACK/NACK signals for different UEs are discriminated from each other by an orthogonal or pseudo-orthogonal code multiplied on a time-frequency domain.

In this case, the 'orthogonal code' or the 'pseudo-orthogonal code' is a code used for signal multiplexing in CDMA and means a code that indicates that a correlation is 0 or a value smaller than a prescribed threshold.

According to one preferred embodiment of the present invention, in case of performing a transmission through modulation that uses components having phases orthogonal to each other like QPSK, a plurality of ACK/NACK signals can be additionally discriminated through the different orthogonal phase components.

In an example shown in FIG. 1, since an ACK/NACK signal is transmitted through a time-frequency domain including 12 subcarriers across six OFDM symbols within a single TTI, it is able to use an orthogonal code having a chip length 72 (=6×12) for the ACK/NACK transmission.

6

Hence, it is possible to simultaneously transmit 72 different orthogonal signals. Yet, a number of simultaneously transmittable orthogonal signals may vary in accordance with a type of a used orthogonal/pseudo-orthogonal code.

In case of using QPSK as a modulation scheme in the example shown in FIG. 1, it is able to use two orthogonal phases. Hence, it is able to transmit different orthogonal signals amounting to a double of the seventy-two orthogonal signals.

Meanwhile, an ACK/NACK signal for a single UE can be transmitted via a single orthogonal signal among the orthogonal signals generated by the above-explained method. Yet, one embodiment of the present invention proposes that an ACK/NACK signal for a single UE is set to be transmitted via a plurality of orthogonal signals if the single ACK/NACK signal carries information exceeding 1 bit or if a single UE transmits a plurality of data packets for a single TTI.

Like the above-explained one embodiment of the present invention, an advantage in multiplexing to transmit an ACK/NACK signal by CDMA in downlink lies in that a quantity of interference generated in downlink by an ACK/NACK signal on a time-frequency domain of a single TTI can be maintained relatively equal.

In particular, if a random cell multiplexes to transmit ACK/NACK signals for different UEs by TDMA or FDMA within a single TTI, as mentioned in the foregoing description, if ACK/NACK signal transmission powers for the respective UEs considerably differ from each other, an interference quantity having influence on neighbor cells by the corresponding cell can vary on a time domain or a frequency domain considerably. And, this may have bad influence on performing downlink data packet scheduling or other time-frequency-energy distribution in a cellular environment. Yet, in case that an ACK/NACK signal is multiplexed by CDMA like one embodiment of the present invention, even if different ACK/NACK signal transmission powers are allocated to different UEs, ACK/NACK signals for the entire UEs are added together within a same time-frequency domain for a single TTI and then transmitted. Hence, fluctuation of transmission power on a time-frequency domain can be minimized.

Like one embodiment of the present invention, in case that a plurality of ACK/NACK signals transmitted by a single UE or for data transmission of a single UE are transmitted via a plurality of orthogonal signals, it is able to enhance reliability of ACK/NACK signal transmission to the corresponding UE.

Moreover, the above-explained principle for the downlink transmission of the ACK/NACK signal is identically applicable to uplink transmission.

Meanwhile, in multiplexing ACK/NACK signal by CDMA, as mentioned in the foregoing description, orthogonality between the different ACK/NACK signals multiplexed by CDMA can be maintained only if a downlink radio channel response characteristic is not considerably changed on a time-frequency domain for carrying the ACK/NACK signal. Hence, it is able to obtain satisfactory reception performance without applying a special reception algorithm such as a channel equalizer in a receiving end. Preferably, CDMA multiplexing of ACK/NACK signal is carried out within a time-frequency domain, in which a radio channel response is not considerably changed, i.e., within a coherent time and a coherent bandwidth.

According to a detailed embodiment of the present invention, a CDMA multiplexing scheme of ACK/NACK signal can be carried out side by side with a FDMA or TDMA multiplexing scheme to narrow a time-frequency domain for multiplexing ACK/NACK signal by CDMA within a coher-

ent range in which a radio channel response characteristic is not considerably changed. This is explained as follows.

FIG. 2 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA and FDMA according to one embodiment of the present invention.

Referring to FIG. 2, different ACK/NACK signals can be transmitted in time-frequency domains separated from each other on two frequency axes. And, different ACK/NACK signals can be multiplexed by CDMA in each of the time-frequency domains. In this case, according to one embodiment of the present invention, as ACK/NACK signals are transmitted through two frequency domains, it can be observed that a width of each of the frequency domains is set to a 6-subcarrier zone narrower than a 12-subcarrier zone.

In particular, in the example shown in FIG. 2, since each of the two time-frequency domains includes six OFDM symbols and twelve subcarriers, it is able to transmit 36 ($=6 \times 6$) orthogonal signals by CDMA. Since two time-frequency domains are used within a single TTI, it is able to transmit 72 ($=36 \times 2$) orthogonal signals.

In case that QPSK modulation is used, since ACK/NACK signal can be additionally discriminated using two orthogonal phases, it is able to transmit different orthogonal signals amounting to two times of the 72 orthogonal signals.

FIG. 3 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA, TDMA and FDMA according to one embodiment of the present invention.

In particular, FIG. 3 shows an example that multiplexing is carried out on ACK/NACK signals side by side with CDMA, FDMA and TDMA.

Referring to FIG. 3, different ACK/NACK signals can be transmitted on four time-frequency domains having less channel variations. And, different ACK/NACK signals can be multiplexed in each of the time-frequency domains by CDMA.

In particular, in the example shown in FIG. 3, since each of the time-frequency domains includes three OFDM symbols and six subcarriers, it is able to transmit 18 ($=3 \times 6$) ACK/NACK signals in each domain by CDMA. Since four time-frequency domains are used within a single TTI, it is also able to transmit 72 ($=18 \times 4$) ACK/NACK signals. Since two orthogonal phases are usable for QPSK transmission, it is able to transmit a double of the different ACK/NACK signals.

In the above-explained ACK/NACK signal multiplexing scheme shown in FIG. 2 or FIG. 3, the scheme for transmitting the different ACK/NACK signals in each of the time-frequency domains is more advantageous than that of FIG. 1 in that each of the ACK/NACK signals can be transmitted within the time-frequency domain having not considerable fluctuation of the radio channel response characteristic. Yet, in case that a radio channel quality for a prescribed UE in the time-frequency domain for carrying the ACK/NACK signals is poor, ACK/NACK reception performance of the corresponding UE can be considerably degraded.

Hence, one embodiment of the present invention proposes that ACK/NACK signals for a specific UE within a single TTI are transmitted across time-frequency domains distant from a plurality of time-frequency axes. And, one embodiment of the present invention also proposes a scheme for obtaining a time-frequency diversity gain for ACK/NACK signal reception in a receiving end by multiplexing ACK/NACK signals for different UEs by CDMA in each time-frequency domain.

FIG. 4 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA and FDMA according to one embodiment

of the present invention, in which a plurality of ACK/NACK signals transmitted by a specific transmitting side among a plurality of ACK/NACK signals are transmitted through a plurality of frequency domains.

Referring to FIG. 4, a receiving side is able to obtain a frequency diversity gain in a manner that an ACK/NACK signal is transmitted across two different frequency domains. In the example shown in FIG. 4, an ACK/NACK signal is transmitted across two time-frequency domains and different ACK/NACK signals are multiplexed in each of the time-frequency domains.

In particular, since each of the time-frequency domains includes six OFDM symbols and six subcarriers, there exist 36 (6×6) ACK/NACK signals that can be multiplexed by CDMA in each of the time-frequency domains. Since two orthogonal phases are usable for QPSK transmission, it is able to transmit a double of the different ACK/NACK signals.

As mentioned in the foregoing description, in multiplexing different ACK/NACK signals within each of the time-frequency domains using an orthogonal code regulated in accordance with the size of each time-frequency domain, ACK/NACK signals transmitted via different time-frequency domains for a specific UE can be multiplexed using the same orthogonal code among orthogonal codes used for each of the time-frequency domains.

Yet, one embodiment of the present invention proposes that ACK/NACK signals transmitted via different time-frequency domains for a specific UE are multiplexed using different orthogonal codes among orthogonal codes used for each of the time-frequency domains.

Thus, in case that ACK/NACK signals for a specific UE are multiplexed using different orthogonal codes in each domain, it is able to prevent reception performance from being reduced by special orthogonality reduction influence with other ACK/NACK signals with which a specific ACK/NACK signal is CDMA multiplexed for a specific TTI. And, this scheme can be extended to enable ACK/NACK signal of a specific UE to be transmitted using different orthogonal codes in different time-frequency domains even if the ACK/NACK signal is transmitted via at least three time-frequency domains.

In case that ACK/NACK signals are transmitted via a plurality of time-frequency domains, as shown in FIG. 4, one preferred embodiment of the present invention proposes that more ACK/NACK signals can be simultaneously transmitted in a manner of specifying orthogonal codes in accordance with the size of the entire domains instead of specifying an orthogonal code in accordance with in the size of each the time-frequency domain and then transmitting a plurality of ACK/NACK signals correspondingly.

In particular, in the example shown in FIG. 4, by obtaining 72 orthogonal codes in accordance with 72 ($=6 \times 12$) chip length according to six OFDM symbols and 12 subcarriers belonging to two time-frequency domains for carrying a plurality of ACK/NACK signals of a specific UE instead of 36 chip length according to six OFDM symbols and six subcarriers belonging to a single time-frequency domain, it is able to simultaneously transmit 144 ACK/NACK signals using different orthogonal phases in case of using QPSK transmission.

In this case, a problem generated from a fact that orthogonality between orthogonal codes is reduced due to a considerable difference between radio channel responses of different time-frequency domains can be overcome by allocating ACK/NACK transmission powers differing from each other in accordance with partial cross correlation characteristics between orthogonal codes.

In particular, if transmission powers of orthogonal codes within a corresponding group are matched by grouping codes decided as having low orthogonality among the above-specified orthogonal codes, the above orthogonality problem can be solved.

FIG. 5 is a diagram for explaining a method of transmitting ACK/NACK signals by carrying out multiplexing side by side with CDMA, TDMA and FDMA according to one embodiment of the present invention, in which a plurality of ACK/NACK signals transmitted by a specific transmitting side among a plurality of ACK/NACK signals are transmitted through a plurality of time-frequency domains.

FIG. 5 shows an example that a time-frequency diversity gain is obtained in a manner that ACK/NACK signals for a specific UE are transmitted across two different time-frequency domains.

In particular, ACK/NACK signals for UEs 1 to N/4 are transmitted via a time-frequency domain placed in a left upper part of FIG. 5 and a time-frequency domain placed in a right lower part of FIG. 5, while ACK/NACK signals for UEs N/4+1 to N/2 are transmitted via a time-frequency domain placed in a left lower part of FIG. 5 and a time-frequency domain placed in a right upper part of FIG. 5.

In particular, ACK/NACK signals for a specific UE in the example shown in FIG. 5 are transmitted across two time-frequency domains. Different ACK/NACK signals are multiplexed by CDMA within each of the time-frequency domains and then transmitted.

Moreover, eighteen ACK/NACK signals can be transmitted via orthogonal codes corresponding to 18 ($=3 \times 6$) chip length across three OFDM symbols and six subcarriers within each of the time-frequency domains. Since two orthogonal phases are usable for QPSK transmission, it is able to transmit 36 different ACK/NACK signals amounting to a double of the former ACK/NACK signals.

In the example shown in FIG. 5, it is able to discriminate ACK/NACK signals transmitted via different time-frequency domains for a specific UE from other ACK/NACK signals using the same orthogonal code. Yet, a diversity gain can be obtained by multiplexing the ACK/NACK signals within each of the time-frequency domains using different orthogonal codes.

Moreover, in the example shown in FIG. 5, in case that orthogonal codes are specified with reference to in the size of the entire time-frequency domains instead of specifying orthogonal codes with reference to in the size of each time-frequency domain, it is able to transmit more ACK/NACK signals simultaneously.

In particular, by specifying orthogonal codes not for chip length constructed with three symbols and six subcarriers included in each of the time-frequency domains but for 72 chip length constructed with total six OFDM symbols and 12 subcarriers, it is able to transmit more ACK/NACK signals simultaneously.

In the above-explained embodiments shown in FIGS. 1 to 5, a 1-bit control signal such as an ACK/NACK signal is transmitted by spreading in 3 or 6 OFDM symbol zones by CDMA for example. Yet, an OFDM symbol zone usable for transmission of 1-bit control signal such as ACK/NACK signal can include at least one or more OFDM symbols.

Among the 1-bit control signal (ACK/NACK signal) transmitting methods according to the above-explained embodiments of the present invention, the method of transmitting ACK/NACK signals repeatedly in a plurality of time-frequency domains to secure the transmission diversity gain can be diversified in accordance with a number of available OFDM symbol zones. In the following description, a method

of transmitting ACK/NACK efficiently in accordance with a number of OFDM symbols used for the ACK/NACK signal transmission is described.

FIG. 6 is a diagram for explaining a method of transmitting ACK/NACK in case of using 1 OFDM symbol zone for ACK/NACK transmission according to one embodiment of the present invention.

In detail, FIG. 6 shows that four ACK/NACK signals are spread at a spreading factor (SF) 4 in 1 OFDM symbol zone, multiplexed by CDMA and then transmitted. In FIG. 6, a single box indicates a single subcarrier zone. And, A_{ij} indicates an ACK/NACK signal multiplexed by CDMA. In this case, 'i' is an index of a spread and multiplexed signal and 'j' is an index indicating a group of the multiplexed ACK/NACK signal. An ACK/NACK group indicates a set of the multiplexed ACK/NACK signals. And, a plurality of ACK/NACK groups can exist in accordance with necessity of each system and a resource situation. For clarity and convenience, FIG. 6 assumes that there exists a single ACK/NACK group only.

Since the present embodiment assumes a case that a single OFDM symbol is used for ACK/NACK transmission only, it is unable to obtain a diversity gain on a time axis for ACK/NACK signal transmission.

Yet, to obtain a diversity gain on a frequency axis, ACK/NACK signals multiplexed on the frequency axis by CDMA can be repeatedly transmitted in different frequency domains.

FIG. 6 shows an example that ACK/NACK signals multiplexed by CDMA are four times repeated in different frequency domains. In this case, the four times repetition is just an example to obtain diversity. A count of repetitions can vary in accordance with a channel status and a resource situation of system. In FIG. 6, each of the four times repeated ACK/NACK signals has the same indices (i, j) for emphasizing the repetition of the signals. But, each of the four times repeated ACK/NACK signals can be multiplexed by different orthogonal code or like, so in this case, these signals can be a different signal to each other. But, for convenience of explanation, this possibility of differentiation of each repeated signal will be ignored in the whole context.

FIG. 6 deals with a case that a single OFDM symbols is used for ACK/NACK transmission. The case of using a single OFDM symbols is just an example for describing the present invention. And, the present invention is applicable to a case of using a plurality of OFDM symbols as well.

In more particularly, in case that ACK/NACK is transmitted via several OFDM symbols, repetition on a time axis is also applicable as well as a repetition on a frequency axis in order to obtain additional diversity as well as transmitting antenna diversity.

In the following description, a case of using a plurality of OFDM symbols for ACK/NACK signal transmission is described.

In case that OFDM symbols for ACK/NACK transmission are incremented, it is able to use ACK/NACK signals in case of using a single OFDM symbol for ACK/NACK transmission can be repeatedly used for the incremented OFDM symbols intactly. In this case, since the OFDM symbols used for the ACK/NACK transmission are incremented, it is able to more power of a signal used for the ACK/NACK transmission. Hence, it is able to transmit the ACK/NACK signals to a wider area of a cell.

FIG. 7 is a diagram for explaining a method of transmitting ACK/NACK in case of using at least 2 OFDM symbol zones for ACK/NACK transmission according to one embodiment of the present invention.

FIG. 7 shows an ACK/NACK signal transmitting method when a number of OFDM symbols for ACK/NACK signal

transmission is incremented into 2, in transmitting ACK/NACK signals having the same spreading factor as FIG. 6. In particular, FIG. 7 shows a case that a structure in using a single OFDM symbol for ACK/NACK transmission like FIG. 6 is intactly and repeatedly applied to a second OFDM symbol.

In case of the transmission with the above structure, even if a symbol number is incremented, the number of transmittable ACK/NACK signals is equal to that of the case of using a single OFDM symbol. This is because more time-frequency resources are used for the transmission of the same number of ACK/NACK signals by substantially incrementing the time-frequency repetition count as more OFDM symbols are used for the ACK/NACK signals repeated on the frequency axis only in case of using a single OFDM symbol only.

In case of performing the transmission by this method, more power can be allocated to the ACK/NACK transmission but waste or resource may take place. In case that more OFDM symbols are used for the ACK/NACK signal transmission to reduce the waste of resource, if a transmission is performed by decrementing the repetition count on the frequency axis per the OFDM symbol, the same time-frequency domain as the case of using a single OFDM symbol can be occupied. Hence, it is able to utilize resources more efficiently.

FIG. 8 is a diagram for explaining a method of transmitting ACK/NACK in case of using at least 2 OFDM symbol zones for ACK/NACK transmission according to one preferred embodiment of the present invention.

FIG. 8 shows an example that resources are more efficiently utilized by decrementing a frequency axis repetition count of ACK/NACK signals multiplexed by CDMA in case that the number of OFDM symbols for ACK/NACK signal transmission are incremented into two.

Although ACK/NACK signals are repeated twice compared to four times in FIG. 6, as the number of OFDM symbols used for the ACK/NACK signal transmission is incremented, the use of four time-frequency resource domains is the same as the case of using a single OFDM symbol.

Compared to FIG. 7 which shows the case of performing transmission by applying the same ACK/NACK signal structure to the entire OFDM symbols, assuming that the same time-frequency resource is used, FIG. 8 shows that ACK/NACK signal transmission is possible twice. Hence, resources can be more efficiently used.

Comparing to FIG. 7, since the number of, time-frequency resource domains used for the ACK/NACK signal transmission is decremented, a signal power for the ACK/NACK signal transmission may become less. Yet, since the overall ACK/NACK signals are transmitted across the time-frequency domain, more efficient transmission power allocation per symbol is possible rather than the case of transmitting the ACK/NACK signals using a single OFDM symbol only.

Referring to FIG. 8, when a plurality of OFDM symbol zones are used for ACK/NACK transmission, in case that the method of transmitting a specific ACK/NACK signal via a different frequency domain in each OFDM symbol zone according to the present embodiment is taken, it is more advantageous that power allocation to each ACK/NACK signal can be carried out more flexibly rather than the method of transmitting ACK/NACK via different frequency domains within each OFDM symbol zone. This is explained in detail with reference to FIG. 9 as follows.

FIG. 9 is a diagram to explain a principle that power allocation flexibility is increased in case of transmitting ACK/NACK signals by the embodiment shown in FIG. 8.

In (a) and (b) of FIG. 9, A_1 , A_2 , A_3 and A_4 indicate ACK/NACK signal groups multiplexed by CDMA, respectively. In particular, (a) of FIG. 9 shows a format that CDMA-multiplexed ACK/NACK signals are transmitted by being repeated in different frequency domains within a same symbol zone. And, (b) of FIG. 9 shows a format that CDMA-multiplexed ACK/NACK signals of the present embodiment are transmitted by being repeated in different frequency domains within different OFDM symbol zones, respectively.

In case that ACK/NACK signals are transmitted in a same manner shown in (a) of FIG. 9, total powers allocated to the respective OFDM symbol zones should be allocated by being distributed to two ACK/NACK signals. On the contrary, in case that ACK/NACK signals are transmitted in a same manner shown in (b) of FIG. 9, total powers allocated to the respective OFDM symbol zones can be allocated by being distributed to four ACK/NACK signals. Hence, flexibility of power allocation can be enhanced more than that of the case shown in (a) of FIG. 9.

In other words, when the number of OFDM symbol zones available for ACK/NACK transmission is plural like the present embodiment, in case that ACK/NACK signals are transmitted via different frequency domains in different OFDM symbols, flexibility in power allocation is enhanced to diversify power allocation for ACK/NACK signals per a user.

In the above-explained embodiment of the present invention, a spreading factor for multiplexing of a plurality of ACK/NACK signals, a repetition count in time-frequency domain, and the number of OFDM symbols for ACK/NACK signal transmission are just exemplary for the accurate explanation of the present invention but other spreading factors, other repetition counts and various numbers of OFDM symbols are applicable to the present invention.

In the above-described example for explaining the present invention in accordance with the time-frequency resource, a case of using a single transmitting antenna that does not use transmitting antenna diversity is represented only. Alternatively, the present invention is also applicable to the case of using a two transmitting antennas diversity scheme or a four transmitting antennas diversity scheme.

It is apparent to those skilled in the art that the above-explained scheme for obtaining the time-frequency diversity gain from the ACK/NACK signal transmission can be used side by side with the scheme of using FDMA or TDMA as well as the case of using CDMA for the multiplexing of different ACK/NACK signals according to one embodiment of the present invention.

The above-explained multiplexing and transmission schemes of ACK/NACK signals are identically applicable to the multiplexing and transmission scheme of a plurality of power control signals transmitted to different UEs in downlink. Particularly, a downlink ACK/NACK signal and a downlink power control signal can be transmitted by being multiplexed in the same time-frequency domain by CDMA.

Moreover, the above-explained ACK/NACK signal multiplexing and transmission schemes are identically applicable to uplink ACK/NACK signal transmission for data packets transmitted in downlink as well.

Moreover, if the number of OFDM symbols used for transmission of ACK/NACK signal can be variable in a specific system, it is preferable that the number of repetition of ACK/NACK signal is decreased in accordance with the increase of the OFDM symbols used.

INDUSTRIAL APPLICABILITY

According to one embodiment of the present invention, in multiplexing a plurality of 1-bit control signals, a plurality of

control signals of a specific UE can be transmitted via orthogonal or pseudo-orthogonal codes differing from each other using CDMA mainly. Hence, the present invention enhances reliability on a corresponding control signal transmission.

And, frequency and/or time diversity can be obtained by carrying out FDMA and/or TDMA on the 1-bit control signal transmission side by side and by distributing to transmit a plurality of control signals for a specific UE on each time-frequency domain.

Moreover, in case of transmitting the 1-bit control signal through a plurality of time-frequency domains, by specifying to use an orthogonal code used for transmission in accordance with the size of the whole time-frequency domains instead of in the size of each time-frequency domain, it is able to increment a number of control signals that can be simultaneously transmitted.

Besides, in case that a plurality of OFDM symbols are used for 1-bit control signal transmission, by transmitting a CDMA modulated 1-bit control signal on a different OFDM symbol area through a different frequency domain, it is able to perform efficient transmission in aspects of resource efficiency and diversity gain. And, it is also able to make a power allocation more flexible within each OFDM symbol area.

Accordingly, a control information transmitting method according to the present invention has a configuration suitable to be applied to 3GPP LTE system. Moreover, a control information transmitting method according to the present invention is applicable to random communication systems that require specifications for a control information transmission format in time-frequency domain as well as to the 3GPP LTE system.

While the present invention has been described and illustrated herein with reference to the preferred embodiments thereof, it will be apparent to those skilled in the art that various modifications and variations can be made therein without departing from the spirit and scope of the invention. Thus, it is intended that the present invention covers the modifications and variations of this invention that come within the scope of the appended claims and their equivalents.

What is claimed is:

1. A method of transmitting a control signal, the method comprising:

multiplexing a plurality of 1-bit control signals within a single prescribed time-frequency domain by a code division multiple access (CDMA) scheme, wherein the plurality of 1-bit control signals multiplexed within the single prescribed time-frequency domain are distinguished by orthogonal or pseudo-orthogonal codes used for multiplexing each of the plurality of 1-bit control signals;

repeating multiplexing of the plurality of multiplexed control signals in different frequency domains; and transmitting the repeatedly multiplexed control signals.

2. The method of claim 1, wherein when a time domain used for the control signal transmission comprises a single OFDM symbol zone, the repeating comprises repeatedly multiplexing the multiplexed control signals in the different frequency domains within the single OFDM symbol zone.

3. The method of claim 1, wherein when a time domain used for the control signal transmission comprises a plurality of OFDM symbol zones, the repeating comprises repeatedly multiplexing the multiplexed control signals in the different frequency domains within the plurality of OFDM symbol zones that are different from each other.

4. The method of claim 1, wherein in the multiplexing, the plurality of 1-bit control signals are further distinguished by different orthogonal phase components.

5. A method of transmitting a control signal, the method comprising:

multiplexing a plurality of 1-bit control signals within a single prescribed time-frequency domain by a code division multiple access (CDMA) scheme;

multiplexing the multiplexed plurality of 1-bit control signals by at least a time division multiple access (TDMA) scheme or a frequency division multiple access (FDMA) scheme such that the multiplexing of the plurality of 1-bit control signals is repeated within an additional time-frequency domain other than the single prescribed time-frequency domain; and

transmitting the multiplexed control signals.

6. The method of claim 5, wherein the plurality of 1-bit control signals for different transmitting sides are multiplexed within the single prescribed time-frequency domain and the additional time-frequency domain by the CDMA scheme, respectively.

7. The method of claim 5, wherein a 1-bit control signal for a specific transmitting side is multiplexed with other 1-bit control signals using orthogonal or pseudo-orthogonal codes that are different from each other, the method further comprising:

repeating the multiplexing of the 1-bit control signal for the specific transmitting side within the additional time-frequency domain other than the single prescribed time-frequency domain; and

transmitting the repeatedly multiplexed 1-bit control signal for the specific transmitting side.

8. The method of claim 7, wherein the orthogonal or pseudo-orthogonal codes comprise a code sequence having a length corresponding to a size of the single prescribed time-frequency domain.

9. The method of claim 1, wherein the plurality of 1-bit control signals comprise ACK/NACK signals.

10. The method of claim 5, wherein the plurality of 1-bit control signals comprise ACK/NACK signals.

* * * * *