



US00RE47879E

(19) **United States**
(12) **Reissued Patent**
Nam et al.

(10) **Patent Number:** **US RE47,879 E**
(45) **Date of Reissued Patent:** **Feb. 25, 2020**

(54) **APPARATUS AND METHOD FOR CHANNEL-STATE-INFORMATION PILOT DESIGN FOR AN ADVANCED WIRELESS NETWORK**

(71) Applicant: **Samsung Electronics Co., Ltd.**, Suwon-si (KR)

(72) Inventors: **Young-Han Nam**, Richardson, TX (US); **Jin-Kyu Han**, Allen, TX (US)

(73) Assignee: **Samsung Electronics Co., Ltd.**, Suwon-si (KR)

(21) Appl. No.: **15/422,408**

(22) Filed: **Feb. 1, 2017**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **9,119,209**
Issued: **Aug. 25, 2015**
Appl. No.: **13/828,530**
Filed: **Mar. 14, 2013**

U.S. Applications:

(60) Provisional application No. 61/618,213, filed on Mar. 30, 2012, provisional application No. 61/635,152, filed on Apr. 18, 2012.

(51) **Int. Cl.**
H04W 72/04 (2009.01)
H04L 1/00 (2006.01)
(Continued)

(52) **U.S. Cl.**
CPC **H04W 72/046** (2013.01); **H04B 7/0469** (2013.01); **H04L 1/0053** (2013.01);
(Continued)

(58) **Field of Classification Search**
CPC ... H04W 72/046; H04W 72/04; H04W 88/02; H04W 88/08; H04L 1/0053; H04B 7/0469

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,963,868 A 10/1999 Baek
6,950,678 B1* 9/2005 Mujtaba et al. 455/562.1
(Continued)

FOREIGN PATENT DOCUMENTS

CN 1325241 A 12/2001
CN 101501927 A 8/2009
(Continued)

OTHER PUBLICATIONS

Foreign Communication from a Related Counterpart Application, Russian Patent Application No. 2014143812, Decision on Grant dated Feb. 27, 2017; 13 pages.


(Continued)

Primary Examiner — Ovidio Escalante

(57) **ABSTRACT**

A base station and mobile station communicate using a multiple input multiple output (MIMO) communication. The base station includes a two dimensional (2D) antenna array comprising a number N of antenna elements configured in a 2D grid. The 2D antenna array is configured to communicate with at least one subscriber station. The base station also includes a controller configured to transmit N channel-state-information reference-signal (CSI-RS) antenna ports (APs) associated with each of the N antenna elements. The subscriber station includes an antenna array configured to communicate with at least one base station. The subscriber station also includes processing circuitry configured receives physical downlink shared channels (PDSCHs) from a 2D active antenna array at the at least one base station. The 2D active antenna array includes a number N antenna elements. The processing circuitry further configured to estimate a full CSI associated with the N antenna elements.

42 Claims, 13 Drawing Sheets



- (51) **Int. Cl.**
H04W 88/02 (2009.01)
H04W 88/08 (2009.01)
H04B 7/0456 (2017.01)
- (52) **U.S. Cl.**
 CPC *H04W 72/04* (2013.01); *H04W 88/02*
 (2013.01); *H04W 88/08* (2013.01)

(56) **References Cited**

U.S. PATENT DOCUMENTS

8,989,114	B2 *	3/2015	Kim	H04B 7/024 370/329
9,161,241	B2 *	10/2015	Thomas	H04W 24/02
9,608,699	B2 *	3/2017	Kim	H04L 5/0053
9,788,244	B2 *	10/2017	Dinan	H04L 5/0053
9,866,358	B2 *	1/2018	Chen	H04L 25/0202
9,893,866	B2 *	2/2018	Yoon	H04L 5/0057
9,917,625	B2 *	3/2018	Dinan	H04B 7/046
2002/0159506	A1	10/2002	Alamouti et al.		
2005/0002468	A1 *	1/2005	Walton et al.	375/267
2005/0181799	A1	8/2005	Laroia et al.		
2005/0272472	A1	12/2005	Goldberg et al.		
2008/0258981	A1	10/2008	Achour et al.		
2010/0098012	A1	4/2010	Bala et al.		
2011/0261894	A1	10/2011	Yu et al.		
2012/0034952	A1	2/2012	Lo et al.		
2012/0120905	A1	5/2012	Ko et al.		
2012/0147766	A1 *	6/2012	Kim	H04W 24/10 370/252
2012/0281783	A1 *	11/2012	Cheng et al.	375/295
2012/0287875	A1 *	11/2012	Kim et al.	H04B 7/024 370/329
2013/0142103	A1	6/2013	Tenny		
2013/0229980	A1 *	9/2013	Wernersson et al.	370/328
2015/0078472	A1	3/2015	Vook et al.		
2015/0103939	A1	4/2015	Yu et al.		
2016/0094287	A1	3/2016	Kim et al.		
2016/0373231	A1 *	12/2016	Yoon	H04L 5/0023

FOREIGN PATENT DOCUMENTS

CN	101771445	A	7/2010
CN	102187726	A	9/2011
EP	1158824	A2	11/2001
JP	2006135426	A	5/2006
JP	2008500777	A	1/2008
JP	2015513280	A	4/2015
KR	20100138261	A	12/2010
KR	20110091839	A	8/2011
KR	20120015977	A	2/2012
KR	20120029338	A	3/2012
RU	2437252	C2	12/2011
WO	2008077097	A1	6/2008
WO	2009083960	A2	7/2009
WO	WO 2009/083960	A2	7/2009
WO	2010079748	A1	7/2010
WO	2011019228	A2	2/2011
WO	2011115421	A2	9/2011

OTHER PUBLICATIONS

Foreign Communication from a Related Counterpart Application, European Patent Application No. 13161878.7, Extended European Search Report and Written Opinion dated Mar. 22, 2017, 10 pages.

“Intra-Cell CSI-RS Design,” 3GPP TSG-RAN WG1 Meeting #60bis, Nokia and Nokia Siemens Networks, R1-101898, Beijing, China, Apr. 12-16, 2010, 6 pages.

“Considerations on CSI Feedback Enhancements for High-Priority Antenna Configurations,” 3GPP TSG-RAN WG1 #66, Alcatel-Lucent Shanghai Bell and Alcatel Lucent, R1-112420, Athens, Greece, Aug. 22-26, 2011, 7 pages.

“Reference and Synchronisation Signals in Additional Carrier Type,” 3GPP TSG-RAN WG1#68, Motorola Mobility, R1-120515, Feb. 6-10, 2012, Dresden, Germany, 3 pages.

“Corrections to 36.211 & 36.213 Related to Enhanced DL MIMO,” TSG-RAN Meeting #54, TSG RAN WG1, RP-111668, Berlin, Germany, Dec. 6-9, 2011, 41 pages.

Hoshino, et al., “Throughput Improvement with Vertical Plane Beam Control of Base Station Antenna by using Pre-Coding in Cellular Mobile Communications,” Institute of Electronics, Information and Communication Engineers, IEICE Technical Report RCS2011-18(2011-4), vol. 111, No. 12, Apr. 14, 2014, pp. 101-106.

Foreign Communication From A Related Counterpart Application, Japanese Application No. 2015-503128, Notification of Reason for Rejection dated Jan. 23, 2017, 8 pages.

Foreign Communication From A Related Counterpart Application, Chinese Application No. 201380017577.7, Text of the First Office Action dated Sep. 27, 2016, 17 pages.

Communication from a foreign patent office in a counterpart foreign application, “Notification of Reason for Rejection,” Japanese Patent Application No. 2015-503128, dated Jun. 26, 2017, 8 pages.

Pantech, “Multiple CSI-RS Resource Configuration for CoMP,” 3GPP TSG RAN1 #67, R1-113831, San Francisco, USA, Nov. 14-18, 2011, 3 pages.

Samsung, “CSI-RS Configuration for DL CoMP,” 3GPP TSG RAN WG1 #68, R1-120176, Dresden, Germany, Feb. 6-10, 2012, 2 pages.

Nokia Siemens Networks, Nokia, “Remaining issues of CSI-RS design for CoMP,” 3GPP TSG RAN WG1 Meeting #68, R1-120725, Dresden Germany, Feb. 6-10, 2012, 3 pages.

Communication from a foreign patent office in a counterpart foreign application, European Patent Office, “Communication pursuant to Article 94(3) EPC”, Application No. EP 13161878.7, Apr. 24, 2018, 7 pages.

Potevio, “Signaling for CSI-RS Configuration,” R1-105231, 3GPP TSG RAN WG1 Meeting #62bis, Xi’an China, Oct. 11-15, 2010, 6 pages.

Japan Patent Office, “Notification of Reason for Rejection,” Application No. JP 2015-503128, Appeal No. 2018-2879, dated Nov. 19, 2018, 11 pages.

New Postcom, “Downlink reference signal enhancements for CoMP,” R1-113700, 3GPP TSG RAN WG1 Meeting #67, San Francisco, USA, Nov. 14-18, 2011, 3 pages.

Pantech, “Multiple codebooks for CSI feedback to enhance MIMO,” R1-111651, 3GPP TSG RAN #65, Barcelona, Spain, May 9-13, 2011, 2 pages.

Hitachi Ltd., “Consideration on CSI-RS Configurations”, 3GPP TSG RAN WG1 #68bis, Mar. 26-30, 2012, 2 pages, R1-121304.

Office Action dated Jun. 28, 2019 in connection with Korean Patent Application No. 10-2014-7030680, 7 pages.

Chinese National Intellectual Property Administration, The First Office Action regarding Application No. 201710650599.7, dated Oct. 22, 2019, 15 pages.

International Search Report dated Sep. 24, 2013 in connection with International Patent Application No. PCT/KR2013/002688, 4 pages.

Written Opinion of International Searching Authority dated Sep. 24, 2013 in connection with International Patent Application No. PCT/KR2013/002688, 6 pages.

Tran, et al.; “Overview of enabling technologies for 3GPP LTE-advanced”; EURASIP Journal on Wireless Communications and Networking 2012; Feb. 20, 2012; 12 pages.

* cited by examiner




FIG. 1




FIG. 2A




FIG. 2B




FIG. 3






FIG. 4






FIG. 7




FIG. 9

FIG. 8A




FIG. 8B





FIG. 8C






FIG. 10





FIG. 12





FIG. 13







FIG. 15



**APPARATUS AND METHOD FOR
CHANNEL-STATE-INFORMATION PILOT
DESIGN FOR AN ADVANCED WIRELESS
NETWORK**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue; a claim printed with strikethrough indicates that the claim was canceled, disclaimed, or held invalid by a prior post-patent action or proceeding.

CROSS-REFERENCE TO RELATED
APPLICATION(S) AND CLAIM OF PRIORITY

The present application *is an application for reissue of U.S. Pat. No. 9,119,209 issued Aug. 25, 2015 on U.S. Non-Provisional patent application Ser. No. 13/828,530 filed Mar. 14, 2013, and which claims priority to U.S. Provisional Patent Application [Ser.] No. 61/618,213, filed Mar. 30, 2012, entitled "CHANNEL-STATE-INFORMATION PILOT DESIGN FOR ADVANCED WIRELESS COMMUNICATIONS SYSTEM" and U.S. Provisional Patent Application [Ser.] No. 61/635,152, filed Apr. 18, 2012, entitled "CHANNEL-STATE-INFORMATION PILOT DESIGN FOR ADVANCED WIRELESS COMMUNICATIONS SYSTEM". The content of the above-identified patent documents is incorporated herein by reference.*

TECHNICAL FIELD

The present application relates generally to wireless communication systems and, more specifically, to a channel-state-information pilot design for advanced wireless communications system.

BACKGROUND

3GPP Long Term Evolution (LTE) and Long Term Evolution Advanced (LTE-A) systems may operate in a Frequency Division Duplex (FDD) mode or a Time Division Duplex (TDD) mode. In the FDD mode, two different frequencies are used for uplink and downlink transmission, and the base station and user equipment may send and receive data at the same time. In the TDD mode, the same frequency is used for uplink and downlink transmission, and the base station and user equipment cannot send and receive data at the same time. Therefore, in the TDD mode, the LTE system has configurations specifying subframes for either uplink or downlink.

SUMMARY

A base station is provided. The base station includes a two dimensional (2D) antenna array comprising a number N of antenna elements configured in a 2D grid $N_H \times N_V$. The 2D antenna array is configured to communicate with at least one subscriber station. The base station also includes a controller configured to transmit N channel-state-information reference-signal (CSI-RS) antenna ports (APs) associated with each of the N antenna elements.

A subscriber station is provided. The subscriber station includes an antenna array configured to communicate with at least one base station. The subscriber station also includes processing circuitry configured receives physical downlink shared channels (PDSCHs) from a 2D active antenna array

at the at least one base station. The 2D active antenna array includes a number N antenna elements. The processing circuitry further configured to estimate a horizontal and vertical CSI associated with the N antenna elements.

A method is provided. The method includes transmitting, from a two dimensional (2D) antenna array, N channel-state-information reference-signal (CSI-RS) antenna ports (APs). The 2D antenna array includes a number N of antenna elements configured in a 2D grid $N_H \times N_V$. The CSI-RS APs is associated with each of the N antenna elements.

Before undertaking the DETAILED DESCRIPTION below, it may be advantageous to set forth definitions of certain words and phrases used throughout this patent document: the terms "include" and "comprise," as well as derivatives thereof, mean inclusion without limitation; the term "or," is inclusive, meaning and/or; the phrases "associated with" and "associated therewith," as well as derivatives thereof, may mean to include, be included within, interconnect with, contain, be contained within, connect to or with, couple to or with, be communicable with, cooperate with, interleave, juxtapose, be proximate to, be bound to or with, have, have a property of, or the like; and the term "controller" means any device, system or part thereof that controls at least one operation, such a device may be implemented in hardware, firmware or software, or some combination of at least two of the same. It should be noted that the functionality associated with any particular controller may be centralized or distributed, whether locally or remotely. Definitions for certain words and phrases are provided throughout this patent document, those of ordinary skill in the art should understand that in many, if not most instances, such definitions apply to prior, as well as future uses of such defined words and phrases.

BRIEF DESCRIPTION OF THE DRAWINGS

For a more complete understanding of the present disclosure and its advantages, reference is now made to the following description taken in conjunction with the accompanying drawings, in which like reference numerals represent like parts:

FIG. 1 illustrates a wireless network according to embodiments of the present disclosure;

FIG. 2A illustrates a high-level diagram of a wireless transmit path according to embodiments of the present disclosure;

FIG. 2B illustrates a high-level diagram of a wireless receive path according to embodiments of the present disclosure;

FIG. 3 illustrates a subscriber station according to embodiments of the present disclosure;

FIG. 4 illustrates a transmission point equipped with 2D active antenna array according to embodiments of the present disclosure;

FIG. 5 illustrates azimuth and elevation angles to a mobile station from the 2D active antenna array according to embodiments of the present disclosure;

FIG. 6 illustrates H-PMI and V-PMI according to embodiments of the present disclosure;

FIG. 7 illustrates a first and a second CSI-RS APs according to embodiments of the present disclosure;

FIGS. 8A through 8C illustrates joint configuration of A- and B-CSI-RS according to embodiments of the present disclosure;

FIG. 9 illustrates Vertical CSI-RS APs and horizontal CSI-RS APs according to embodiments of the present disclosure;

FIGS. 10 and 11 illustrate construction of the horizontal and the vertical CSI-RS APs according to embodiments of the present disclosure;

FIG. 12 illustrates first and second sets of horizontal CSI-RS APs according to embodiments of the present disclosure;

FIGS. 13 and 14 illustrate construction of two sets of H-CSI-RS APs according to embodiments of the present disclosure;

FIG. 15 illustrates primary and secondary CSI-RS APs according to embodiments of the present disclosure; and

FIG. 16 illustrates construction of the primary and the secondary CSI-RS according to embodiments of the present disclosure.

DETAILED DESCRIPTION

FIGS. 1 through 16, discussed below, and the various embodiments used to describe the principles of the present disclosure in this patent document are by way of illustration only and should not be construed in any way to limit the scope of the disclosure. Those skilled in the art will understand that the principles of the present disclosure may be implemented in any suitably arranged wireless communication system.

The following documents and standards descriptions are hereby incorporated into the present disclosure as if fully set forth herein: 3GPP TS 36.211 v10.1.0, “E-UTRA, Physical channels and modulation” (REF1); 3GPP TS 36.212 v10.1.0, “E-UTRA, Multiplexing and Channel coding” (REF2); 3GPP TS 36.213 v10.1.0, “E-UTRA, Physical Layer Procedures” (REF 3); and 3GPP TS 36.331 V10.1.0 (REF4).

FIG. 1 illustrates a wireless network 100 according to one embodiment of the present disclosure. The embodiment of wireless network 100 illustrated in FIG. 1 is for illustration only. Other embodiments of wireless network 100 could be used without departing from the scope of this disclosure.

The wireless network 100 includes a base station eNodeB (eNB) 101, eNB 102, and eNB 103. The eNB 101 communicates with eNB 102 and eNB 103. The eNB 101 also communicates with Internet protocol (IP) network 130, such as the Internet, a proprietary IP network, or other data network.

Depending on the network type, other well-known terms may be used instead of “eNodeB,” such as “base station” or “access point”. For the sake of convenience, the term “eNodeB” shall be used herein to refer to the network infrastructure components that provide wireless access to remote terminals. In addition, the term “user equipment” or “UE” is used herein to designate any remote wireless equipment that wirelessly accesses an eNB and that can be used by a consumer to access services via the wireless communications network, whether the UE is a mobile device (e.g., cell phone) or is normally considered a stationary device (e.g., desktop personal computer, vending machine, etc.). Other well known terms for the remote terminals include “mobile stations” (MS) and “subscriber stations” (SS), “remote terminal” (RT), “wireless terminal” (WT), and the like.

The eNB 102 provides wireless broadband access to network 130 to a first plurality of user equipments (UEs) within coverage area 120 of eNB 102. The first plurality of UEs includes UE 111, which may be located in a small business; UE 112, which may be located in an enterprise; UE 113, which may be located in a WiFi hotspot; UE 114, which may be located in a first residence; UE 115, which may be

located in a second residence; and UE 116, which may be a mobile device, such as a cell phone, a wireless laptop, a wireless PDA, or the like. UEs 111-116 may be any wireless communication device, such as, but not limited to, a mobile phone, mobile PDA and any mobile station (MS).

The eNB 103 provides wireless broadband access to a second plurality of UEs within coverage area 125 of eNB 103. The second plurality of UEs includes UE 115 and UE 116. In some embodiments, one or more of eNBs 101-103 may communicate with each other and with UEs 111-116 using 5G, LTE, LTE-A, or WiMAX techniques including techniques for using a new channel-state-information pilot design as described in embodiments of the present disclosure.

Dotted lines show the approximate extents of coverage areas 120 and 125, which are shown as approximately circular for the purposes of illustration and explanation only. It should be clearly understood that the coverage areas associated with base stations, for example, coverage areas 120 and 125, may have other shapes, including irregular shapes, depending upon the configuration of the base stations and variations in the radio environment associated with natural and man-made obstructions.

Although FIG. 1 depicts one example of a wireless network 100, various changes may be made to FIG. 1. For example, another type of data network, such as a wired network, may be substituted for wireless network 100. In a wired network, network terminals may replace eNBs 101-103 and UEs 111-116. Wired connections may replace the wireless connections depicted in FIG. 1.

FIG. 2A is a high-level diagram of a wireless transmit path. FIG. 2B is a high-level diagram of a wireless receive path. In FIGS. 2A and 2B, the transmit path 200 may be implemented, e.g., in eNB 102 and the receive path 250 may be implemented, e.g., in a UE, such as UE 116 of FIG. 1. It will be understood, however, that the receive path 250 could be implemented in an eNB (e.g. eNB 102 of FIG. 1) and the transmit path 200 could be implemented in a UE. In certain embodiments, transmit path 200 and receive path 250 are configured to perform methods for communication using a new channel-state-information pilot design as described in embodiments of the present disclosure.

Transmit path 200 comprises channel coding and modulation block 205, serial-to-parallel (S-to-P) block 210, Size N Inverse Fast Fourier Transform (IFFT) block 215, parallel-to-serial (P-to-S) block 220, add cyclic prefix block 225, up-converter (UC) 230. Receive path 250 comprises down-converter (DC) 255, remove cyclic prefix block 260, serial-to-parallel (S-to-P) block 265, Size N Fast Fourier Transform (FFT) block 270, parallel-to-serial (P-to-S) block 275, channel decoding and demodulation block 280.

At least some of the components in FIGS. 2A and 2B may be implemented in software while other components may be implemented by configurable hardware (e.g., a processor) or a mixture of software and configurable hardware. In particular, it is noted that the FFT blocks and the IFFT blocks described in this disclosure document may be implemented as configurable software algorithms, where the value of Size N may be modified according to the implementation.

Furthermore, although this disclosure is directed to an embodiment that implements the Fast Fourier Transform and the Inverse Fast Fourier Transform, this is by way of illustration only and should not be construed to limit the scope of the disclosure. It will be appreciated that in an alternate embodiment of the disclosure, the Fast Fourier Transform functions and the Inverse Fast Fourier Transform functions may easily be replaced by Discrete Fourier Trans-

form (DFT) functions and Inverse Discrete Fourier Transform (IDFT) functions, respectively. It will be appreciated that for DFT and IDFT functions, the value of the N variable may be any integer number (i.e., 1, 2, 3, 4, etc.), while for FFT and IFFT functions, the value of the N variable may be any integer number that is a power of two (i.e., 1, 2, 4, 8, 16, etc.).

In transmit path **200**, channel coding and modulation block **205** receives a set of information bits, applies coding (e.g., LDPC coding) and modulates (e.g., Quadrature Phase Shift Keying (QPSK) or Quadrature Amplitude Modulation (QAM)) the input bits to produce a sequence of frequency-domain modulation symbols. Serial-to-parallel block **210** converts (i.e., de-multiplexes) the serial modulated symbols to parallel data to produce N parallel symbol streams where N is the IFFT/FFT size used in eNB **102** and UE **116**. Size N IFFT block **215** then performs an IFFT operation on the N parallel symbol streams to produce time-domain output signals. Parallel-to-serial block **220** converts (i.e., multiplexes) the parallel time-domain output symbols from Size N IFFT block **215** to produce a serial time-domain signal. Add cyclic prefix block **225** then inserts a cyclic prefix to the time-domain signal. Finally, up-converter **230** modulates (i.e., up-converts) the output of add cyclic prefix block **225** to RF frequency for transmission via a wireless channel. The signal may also be filtered at baseband before conversion to RF frequency.

The transmitted RF signal arrives at UE **116** after passing through the wireless channel and reverse operations to those at eNB **102** are performed. Down-converter **255** down-converts the received signal to baseband frequency and remove cyclic prefix block **260** removes the cyclic prefix to produce the serial time-domain baseband signal. Serial-to-parallel block **265** converts the time-domain baseband signal to parallel time domain signals. Size N FFT block **270** then performs an FFT algorithm to produce N parallel frequency-domain signals. Parallel-to-serial block **275** converts the parallel frequency-domain signals to a sequence of modulated data symbols. Channel decoding and demodulation block **280** demodulates and then decodes the modulated symbols to recover the original input data stream.

Each of eNBs **101-103** may implement a transmit path that is analogous to transmitting in the downlink to UEs **111-116** and may implement a receive path that is analogous to receiving in the uplink from UEs **111-116**. Similarly, each one of UEs **111-116** may implement a transmit path corresponding to the architecture for transmitting in the uplink to eNBs **101-103** and may implement a receive path corresponding to the architecture for receiving in the downlink from eNBs **101-103**.

FIG. **3** illustrates a subscriber station according to embodiments of the present disclosure. The embodiment of subscriber station, such as UE **116**, illustrated in FIG. **3** is for illustration only. Other embodiments of the wireless subscriber station could be used without departing from the scope of this disclosure.

UE **116** comprises antenna **305**, radio frequency (RF) transceiver **310**, transmit (TX) processing circuitry **315**, microphone **320**, and receive (RX) processing circuitry **325**. Although shown as a single antenna, antenna **305** can include multiple antennas. SS **116** also comprises speaker **330**, main processor **340**, input/output (I/O) interface (IF) **345**, keypad **350**, display **355**, and memory **360**. Memory **360** further comprises basic operating system (OS) program **361** and a plurality of applications **362**. The plurality of applications can include one or more of resource mapping tables (Tables 1-10 described in further detail herein below).

Radio frequency (RF) transceiver **310** receives from antenna **305** an incoming RF signal transmitted by a base station of wireless network **100**. Radio frequency (RF) transceiver **310** down-converts the incoming RF signal to produce an intermediate frequency (IF) or a baseband signal. The IF or baseband signal is sent to receiver (RX) processing circuitry **325** that produces a processed baseband signal by filtering, decoding, and/or digitizing the baseband or IF signal. Receiver (RX) processing circuitry **325** transmits the processed baseband signal to speaker **330** (i.e., voice data) or to main processor **340** for further processing (e.g., web browsing).

Transmitter (TX) processing circuitry **315** receives analog or digital voice data from microphone **320** or other outgoing baseband data (e.g., web data, e-mail, interactive video game data) from main processor **340**. Transmitter (TX) processing circuitry **315** encodes, multiplexes, and/or digitizes the outgoing baseband data to produce a processed baseband or IF signal. Radio frequency (RF) transceiver **310** receives the outgoing processed baseband or IF signal from transmitter (TX) processing circuitry **315**. Radio frequency (RF) transceiver **310** up-converts the baseband or IF signal to a radio frequency (RF) signal that is transmitted via antenna **305**.

In certain embodiments, main processor **340** is a micro-processor or microcontroller. Memory **360** is coupled to main processor **340**. According to some embodiments of the present disclosure, part of memory **360** comprises a random access memory (RAM) and another part of memory **360** comprises a Flash memory, which acts as a read-only memory (ROM).

Main processor **340** executes basic operating system (OS) program **361** stored in memory **360** in order to control the overall operation of wireless subscriber station **116**. In one such operation, main processor **340** controls the reception of forward channel signals and the transmission of reverse channel signals by radio frequency (RF) transceiver **310**, receiver (RX) processing circuitry **325**, and transmitter (TX) processing circuitry **315**, in accordance with well-known principles.

Main processor **340** is capable of executing other processes and programs resident in memory **360**, such as operations for performing communications including a new channel-state-information pilot design as described in embodiments of the present disclosure. Main processor **340** can move data into or out of memory **360**, as required by an executing process. In some embodiments, the main processor **340** is configured to execute a plurality of applications **362**, such as applications for CoMP communications and MU-MIMO communications. The main processor **340** can operate the plurality of applications **362** based on OS program **361** or in response to a signal received from BS **102**. Main processor **340** is also coupled to I/O interface **345**. I/O interface **345** provides subscriber station **116** with the ability to connect to other devices such as laptop computers and handheld computers. I/O interface **345** is the communication path between these accessories and main controller **340**.

Main processor **340** is also coupled to keypad **350** and display unit **355**. The operator of subscriber station **116** uses keypad **350** to enter data into subscriber station **116**. Display **355** may be a liquid crystal display capable of rendering text and/or at least limited graphics from web sites. Alternate embodiments may use other types of displays.

Embodiments of the present disclosure provide methods and apparatus to for a channel-state-information (CSI) pilot design for advanced wireless communications system. In REF4, the following configuration is defined for channel-state-information reference signal (CSI-RS). A information element (IE) CSI-RS configuration (CSI-RS-Config) is used to specify the CSI-RS configuration as shown in here:

CSI-RS-Config information elements

```

-- ASN1START
CSI-RS-Config-r10 ::= SEQUENCE {
  csi-RS-r10 CHOICE {
    release NULL,
    setup SEQUENCE {
      antennaPortsCount-r10 ENUMERATED {an1, an2, an4, an8},
      resourceConfig-r10 INTEGER (0..31),
      subframeConfig-r10 INTEGER (0..154),
      p-C-r10 INTEGER (-8..15)
    }
  }
  OPTIONAL, -- Need ON
  zeroTxPowerCSI-RS-r10 CHOICE {
    release NULL,
    setup SEQUENCE {
      zeroTxPowerResourceConfigList-r10 BIT STRING (SIZE (16)),
      zeroTxPowerSubframeConfig-r10 INTEGER (0..154)
    }
  }
  OPTIONAL -- Need ON
}
-- ASN1STOP

```

the CSI-RS-Config field descriptions as follows:

-continued

CSI-RS-Config field descriptions	25
antennaPortsCount Parameter represents the number of antenna ports used for transmission of CSI reference signals where an1 corresponds to 1, an2 to 2 antenna ports etc. see TS 36.211 [21, 6.10.5].	30
p-C Parameter: P_c , see TS 36.213 [23, 7.2.5].	
resourceConfig Parameter: CSI reference signal configuration, see TS 36.211 [21, table 6.10.5.2-1 and 6.10.5.2-2].	35
subframeConfig Parameter: I_{CSI-RS} , see TS 36.211 [21, table 6.10.5.3-1].	
zeroTxPowerResourceConfigList Parameter: ZeroPowerCSI-RS, see TS 36.211 [21, 6.10.5.2].	40
zeroTxPowerSubframeConfig Parameter: I_{CSI-RS} , see TS 36.211 [21, table 6.10.5.3-1].	

$$l = l' + \begin{cases} l'' & \text{CSI reference signal configurations 0-19,} \\ & \text{normal cyclic prefix} \\ 2l'' & \text{CSI reference signal configurations 20-31,} \\ & \text{normal cyclic prefix} \\ l'' & \text{CSI reference signal configurations 0-27,} \\ & \text{extended cyclic prefix} \end{cases}$$

$$w_{l''} = \begin{cases} 1 & p \in \{15, 17, 19, 21\} \\ (-1)^{l''} & p \in \{16, 18, 20, 22\} \end{cases}$$

$$l'' = 0, 1$$

$$m = 0, 1, \dots, N_{RB}^{DL} - 1$$

$$m' = m + \left\lfloor \frac{N_{RB}^{max,DL} - N_{RB}^{DL}}{2} \right\rfloor$$

The quantity (k', l') and the necessary conditions on n_s are given by TABLE 1 for normal cyclic prefix.

Also, according to section 6.10.5.2 Mapping to resource elements in REF1, CSI-RS mapping to resource elements are described as—In subframes configured for CSI reference signal transmission, the reference signal sequence $r_{l,n_s}(m)$ is mapped to complex-valued modulation symbols $a_{k,l}^{(p)}$ used as reference symbols on antenna port p according to Equation 1:

$$a_{k,l}^{(p)} = w_{l''} \cdot r_{l,n_s}(m')$$

where

$$k = k' + 12m + \begin{cases} -0 & \text{for } p \in \{15, 16\}, \text{ normal cyclic prefix} \\ -6 & \text{for } p \in \{17, 18\}, \text{ normal cyclic prefix} \\ -1 & \text{for } p \in \{19, 20\}, \text{ normal cyclic prefix} \\ -7 & \text{for } p \in \{21, 22\}, \text{ normal cyclic prefix} \\ -0 & \text{for } p \in \{15, 16\}, \text{ extended cyclic prefix} \\ -3 & \text{for } p \in \{17, 18\}, \text{ extended cyclic prefix} \\ -6 & \text{for } p \in \{19, 20\}, \text{ extended cyclic prefix} \\ -9 & \text{for } p \in \{21, 22\}, \text{ extended cyclic prefix} \end{cases}$$

45

TABLE 1

Mapping from CSI reference signal configuration to (k', l') for normal cyclic prefix

CSI reference signal Configuration	Number of CSI reference signals configured						
	1 or 2	4	8				
(resourceConfig)	$(k', l') \bmod 2$	$(k', l') \bmod 2$	$(k', l') \bmod 2$				
Frame structure type 1 and 2	0	(9, 5)	0	(9, 5)	0	(9, 5)	0
	1	(11, 2)	1	(11, 2)	1	(11, 2)	1
	2	(9, 2)	1	(9, 2)	1	(9, 2)	1
	3	(7, 2)	1	(7, 2)	1	(7, 2)	1
	4	(9, 5)	1	(9, 5)	1	(9, 5)	1
	5	(8, 5)	0	(8, 5)	0	(8, 5)	0
	6	(10, 2)	1	(10, 2)	1	(10, 2)	1
	7	(8, 2)	1	(8, 2)	1	(8, 2)	1
	8	(6, 2)	1	(6, 2)	1	(6, 2)	1
	9	(8, 5)	1	(8, 5)	1	(8, 5)	1
	10	(3, 5)	0				
	11	(2, 5)	0				
	12	(5, 2)	1				
	13	(4, 2)	1				
	14	(3, 2)	1				

(1)

55

60

65

TABLE 1-continued

Mapping from CSI reference signal configuration to (k', l') for normal cyclic prefix				
CSI reference signal Configuration	Number of CSI reference signals configured			
	1 or 2	4		8
(resourceConfig)	n_s (k', l') mod 2	n_s (k', l') mod 2	n_s (k', l') mod 2	n_s (k', l') mod 2
	15	(2, 2)	1	
	16	(1, 2)	1	
	17	(0, 2)	1	
	18	(3, 5)	1	
	19	(2, 5)	1	
Frame structure type 2 only	20	(11, 1)	1	(11, 1) 1
	21	(9, 1)	1	(9, 1) 1
	22	(7, 1)	1	(7, 1) 1
	23	(10, 1)	1	
	24	(8, 1)	1	
	25	(6, 1)	1	
	26	(5, 1)	1	
	27	(4, 1)	1	
	28	(3, 1)	1	
	29	(2, 1)	1	
	30	(1, 1)	1	
	31	(0, 1)	1	

According to section 6.10.5.3—CSI reference signal subframe configuration, the cell-specific subframe configuration period T_{CSI-RS} and the cell-specific subframe offset Δ_{CSI-RS} for the occurrence of CSI reference signals are listed in TABLE 2. The parameter I_{CSI-RS} can be configured separately for CSI reference signals for which UE 116 assume non-zero and zero transmission power. Subframes containing CSI reference signals shall satisfy Equation 2:

$$(10n_f + \lfloor n_s/2 \rfloor - \Delta_{CSI-RS}) \bmod T_{CSI-RS} = 0. \quad (2)$$

TABLE 2

CSI reference signal subframe configuration		
CSI-RS-SubframeConfig I_{CSI-RS}	CSI-RS periodicity T_{CSI-RS} (subframes)	CSI-RS subframe offset Δ_{CSI-RS} (subframes)
0-4	5	I_{CSI-RS}
5-14	10	$I_{CSI-RS}-5$
15-34	20	$I_{CSI-RS}-15$
35-74	40	$I_{CSI-RS}-35$
75-154	80	$I_{CSI-RS}-75$

In REF1, CSI-RS sequence generation is explained as in the following section 6.10.5.1-Sequence generation: The reference-signal sequence $r_{l,n_s}(m)$ is defined by Equation 3:

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m + 1)), \quad (3)$$

$$m = 0, 1, \dots, N_{RB}^{max,DL} - 1$$

where n_s is the slot number within a radio frame and l is the OFDM symbol number within the slot. The pseudo-random sequence $c(i)$ is defined in Section 7.2. The pseudo-random sequence generator is initialized with

$$c_{init} = 2^{10} \cdot (7 \cdot (n_s + 1) + 1 + 1) \cdot (2 \cdot N_{ID}^{cell} + 1) + 2 \cdot N_{ID}^{cell} + N_{CP} \quad (4)$$

at the start of each OFDM symbol.

Further, for CSI-RS configuration for CoMP: Configuration of multiple non-zero-power CSI-RS resources includes at least:

antennaPortsCount, resourceConfig

Independently configured among CSI-RS resources

subframeConfig

Whether common or independent among CSI-RS resources is FFS

Configurable parameter to derive the pseudo-random sequence generator initialisation (c_{init})

c_{init} is independently configured among CSI-RS resources,

$$C_{init} = 2^{10} \cdot (7 \cdot (n_s + 1) + 1 + 1) \cdot (2 \cdot X + 1) + 2 \cdot X + N_{CP} \quad (5)$$

where X is configurable in a UE-specific manner and may take on any value in the range of 0 to 503,

FFS whether Rel-10 formula can be used without a change

FFS whether beyond 503 are supported

FFS whether CSI-RS ports always have the same scrambling or can have different scrambling within a CSI-RS resource

P_c

Details of signaling is FFS.

Additional Parameters May be Considered

Quasi Co-location: Two antenna ports are said to be quasi co-located if the large-scale properties of the channel over which a symbol on one antenna port is conveyed can be inferred from the channel over which a symbol on the other antenna port is conveyed. The large-scale properties include one or more of delay spread, Doppler spread, Doppler shift, average gain, and average delay.

CSI Process: UE 116 in transmission mode 10 can be configured with one or more CSI processes per serving cell by higher layers. Each CSI process is associated with a CSI-RS resource (defined in Section 7.2.5) and a CSI-interference measurement (CSI-IM) resource (defined in Section 7.2.6). A CSI reported by UE 116 corresponds to a CSI process configured by higher layers. Each CSI process can be configured with or without PMI/RI reporting by higher layer signalling.

For UE 116 in transmission mode 10, UE 116 derives the interference measurements for computing the CQI value reported in uplink subframe n and corresponding to a CSI process, based on only the zero power CSI-RS (defined in REF3) within the configured CSI-IM resource associated with the CSI process. If UE 116 in transmission mode 10 is configured by higher layers for CSI subframe sets $C_{CSI,0}$ and $C_{CSI,1}$, the configured CSI-IM resource within the subframe subset belonging to the CSI reference resource is used to derive the interference measurement.

CSI-Process: the IE CSI-Process is the CSI process configuration that E-UTRAN can configure on a serving frequency.

CSI-Process information elements

```

CSI-Process-r11 ::= SEQUENCE {
  csi-ProcessIdentity-r11      CSI-ProcessIdentity-r11,
  csi-RS-IdentityNZIP-r11     CSI-RS-IdentityNZIP-r11,
  csi-IM-Identity-r11         CSI-IM-Identity-r11,
  p-C-AndAntennaInfoDedList-r11 SEQUENCE (SIZE (1..2)) OF P-C-AndAntennaInfoDed-r11,
  cqi-ReportBothPS-r11        CQI-ReportBothPS-r11          OPTIONAL, -- Need OR
  cqi-ReportPeriodicId-r11    INTEGER (0..maxCQI-Ext-r11)      OPTIONAL, -- Need OR
  cqi-ReportAperiodicPS-r11   CQI-ReportAperiodicPS-r11      OPTIONAL, -- Need OR
  ...
}
P-C-r11 ::= INTEGER (-8..15)
P-C-AndAntennaInfoDed-r11 ::= SEQUENCE {
  p-C-r11                      P-C-r11,
  antennaInfoDedConfigId-r11   AntennaInfoConfigDedId-r11
}

```

CSI-Process field descriptions

antennaInfoDedConfigId
Refers to a dedicated antenna info configuration that is configured for the same frequency as the CSI process.

csi-IM-Identity
Refers to a CSI-IM configuration that is configured for the same frequency as the CSI process.

csi-RS-IdentityNZIP
Refers to a CSI RS configuration that is configured for the same frequency as the CSI process.

cqi-ReportBothPS
Includes CQI configuration parameters applicable for both aperiodic and periodic CSI reporting, for which CSI process specific values may be configured. E-UTRAN configures the field if and only if cqi-ReportPeriodicId is included and/or if cqi-ReportAperiodicPS is included and set to setup.

cqi-ReportPeriodicId
Refers to a periodic CQI reporting configuration that is configured for the same frequency as the CSI process. Value 0 refers to the set of parameters defined by the REL-10 CQI reporting configuration fields, while the other values refer to the additional configurations E-UTRAN assigns by CQI-ReportPeriodicExt-r11 (and as covered by CQI-ReportPeriodicExtId).

p-C
Parameter: P_c , see TS 36.213 [23, 7.2.5].

p-C-AndAntennaInfoDedList
A p-C-AndAntennaInfoDedList including 2 entries indicates that the subframe patterns configured for CSI (CQI/PMI/PTI/RI) reporting (i.e. as defined by field csi-MeasSubframeSet1 and csi-MeasSubframeSet2) are to be used for this CSI process, while a single entry indicates that the subframe patterns are not to be used for this CSI process. E-UTRAN does not include 2 entries in p-C-AndAntennaInfoDedList for CSI processes concerning a secondary frequency. E-UTRAN includes 2 entries in p-C-AndAntennaInfoDedList when configuring both cqi-pmi-ConfigIndex and cqi-pmi-ConfigIndex2.

CSI-ProcessIdentity: the IE CSI-ProcessIdentity is used to identify a CSI process that is configured by the IE CSI-Process. The identity is unique within the scope of a carrier frequency.

50

CSI-ProcessIdentity Information Elements

CSI-ProcessIdentity-r11::=INTEGER (1 . . . maxCSI-Proc-r11)

CSI-RS-ConfigNZIP: the IE CSI-RS-ConfigNZIP is the CSI-RS resource configuration using non-zero power transmission that E-UTRAN may configure on a serving frequency.

55

CSI-RS-ConfigNZIP information elements

```

CSI-RS-ConfigNZIP-r11 ::= SEQUENCE {
  csi-RS-IdentityNZIP-r11     CSI-RS-IdentityNZIP-r11,
  antennaPortsCount-r11      ENUMERATED {an1, an2, an4, an8},
  resourceConfig-r11         INTEGER (0..31),
  subframeConfig-r11         INTEGER (0..154),
  scramblingIdentity-r11     INTEGER (0..503),
}

```

-continued

CSI-RS-ConfigNWP information elements	
qcl-CRS-Info-r11	SEQUENCE {
qcl-ScramblingIdentity-r11	INTEGER (0..503),
crs-PortsCount-r11	ENUMERATED {n1, n2, n4, spare1},
mbsfn-SubframeConfig-r11	MBSFN-SubframeConfig OPTIONAL,-- Need OR
}	OPTIONAL,-- Need OR
...	}
}	}

CSI-RS-ConfigZP: the IE CSI-RS-ConfigZP is the CSI-RS resource configuration, for which UE **116** assumes zero transmission power, that E-UTRAN can configure on a serving frequency.

CSI-RS-ConfigZP information elements	
CSI-RS-ConfigZP-r11 ::=	SEQUENCE {
csi-RS-IdentityZP-r11	CSI-RS-IdentityZP-r11,
resourceConfigList-r11	BIT STRING (SIZE (16)),
subframeConfig-r11	INTEGER (0..154)
}	}

CSI-RS-IdentityZP Information Elements

15 CSI-RS-IdentityZP-r11 ::= INTEGER (1 . . . maxCSI-RS-ZP-r11)

RRC Multiplicity and Type Constraint Values:

Multiplicity and Type Constraint Definitions

maxCSI-IM-r11	INTEGER ::= 3	-- Maximum number of CSI-IM configurations -- (per frequency)
maxCSI-Proc-r11	INTEGER ::= 4	-- Maximum number of CSI RS processes (per frequency)
maxCSI-RS-NWP-r11	INTEGER ::= 3	-- Maximum number of CSI RS resource -- configurations using non-zero Tx power -- (per frequency)
maxCSI-RS-ZP-r11	INTEGER ::= 4	-- Maximum number of CSI RS resource -- configurations using zero Tx power(per frequency)
maxCQI-Ext-r11	INTEGER ::= 3	-- Maximum number of additional periodic CQI -- configurations (per frequency)

CSI-RS-ConfigZP field descriptions	
resourceConfigList	40
Parameter: CSI reference signal configuration, see TS 36.211 [21, table 6.10.5.2-1 and 6.10.5.2-2].	
subframeConfig	45
Parameter: I_{CSI-RS} , see TS 36.211 [21, table 6.10.5.3-1].	

CSI-RS-IdentityNWP: the IE CSI-RS-IdentityNWP is used to identify a CSI-RS resource configuration using non-zero transmission power, as configured by the IE CSI-RS-ConfigNWP. The identity is unique within the scope of a carrier frequency.

CSI-RS-IdentityNWP Information Elements

CSI-RS-IdentityNWP-r11 ::= INTEGER (1 . . . maxCSI-RS-NWP-r11)

CSI-RS-IdentityZP: the IE CSI-RS-IdentityZP is used to identify a CSI-RS resource configuration for which UE assumes zero transmission power, as configured by the IE CSI-RS-ConfigZP. The identity is unique within the scope of a carrier frequency.

CSI-IM-CONFIG: the IE CSI-IM-Config is the CSI-IM configuration that E-UTRAN may configure on a serving frequency.

CSI-IM-Config information elements	
CSI-IM-Config-r11 ::=	SEQUENCE {
csi-im-Identity-r11	CSI-IM-Identity-r11,
resourceConfig-r11	INTEGER (0..15),
subframeConfig-r11	INTEGER (0..154),
...	}
}	}

CSI-IM-Config field descriptions	
resourceConfig	50
Parameter: CSI-IM configuration, see TS 36.211 [21, table 6.10.5.2-1 and 6.10.5.2-2] for 4 REs.	
subframeConfig	55
Parameter: I_{CSI-RS} , see TS 36.211 [21, table 6.10.5.3-1].	

CSI-IM-Identity: the IE CSI-IM-Identity is used to identify a CSI-IM configuration that is configured by the IE CSI-IM-Config. The identity is unique within the scope of a carrier frequency.

CSI-IM-Identity Information Elements

CSI-IM-Identity-r11 ::= INTEGER (1 . . . maxCSI-IM-r11)

65 Various embodiments of the present disclosure consider pilot transmissions from transmission points equipped with 2-dimensional (2D) active antenna array depicted in FIG. 4. Here, transmission points (TPs) are a network node can

transmit downlink signals and receive uplink signals in a cellular network, examples of which include base stations, NodeBs, enhanced NodeBs (eNBs) remote radio heads (RRHs), and so forth. Alternatively, an entity controlling at least one TP is called the controller, the network or eNB. Each active antenna array may have separate base band, which could dynamically control the antenna weights in frequency selective manner.

FIG. 4 illustrates a transmission point equipped with 2D active antenna array according to embodiments of the present disclosure. The embodiment of the transmission point 400 shown in FIG. 4 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

The transmission point 400 includes an antenna array 405 and a controller 410. The Antenna array 405 that includes $N (=N_H \times N_V)$ 2D active antenna elements 415, and the N antenna elements are placed in 2D grid of $N_H \times N_V$. The horizontal spacing between any two closest antenna elements is denoted by d_H 420, and the vertical spacing between any two closest antenna elements is denoted by d_V 425.

FIG. 5 illustrates azimuth and elevation angles to a mobile station from the 2D active antenna array according to embodiments of the present disclosure. The embodiment of the 2D active antenna array 405 shown in FIG. 5 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

A transmission vector between the transmission point 400 equipped with 2D antenna array and UE 116 is transmitted at azimuth and elevation angles. In the example placement shown in FIG. 5, antenna elements 415 are placed in a rectangle on XZ plane in an orthogonal XYZ coordinate system. The origin 505 of the coordinate system is placed at the center of the rectangle. The azimuth (horizontal) angle θ_k 510 for UE 116 is defined as the angle between Y axis 515 and the projection vector 520 of a straight line between the TP and UE 116 to the XY plane. Alternatively, the elevation (vertical) angle θ_k 525 is defined as the angle between Y axis and the projection vector of the straight line to the YZ plane.

In the cellular networks, the network utilizes UEs' channel state information (CSI) to schedule time-frequency resources, to select precoders and modulation and coding schemes (MCS) for each individual UE. To facilitate the UEs' CSI estimation, the network can configure and transmit CSI reference signals (CSI-RS). At the same time, each UE can be configured to feed back estimated precoding matrix information (PMI), channel quality information (CQI) and rank information (RI), by receiving and processing the CSI-RS. Traditionally, the UEs' CSI feedback is designed with mainly targeting horizontal CSI associated with the azimuth angles. For example, PMI/CQI feedback for downlink beamforming in LTE informs the eNB the horizontal direction (or the azimuth angle) along which the UE receives the strongest signal and the associated channel strength. When active antenna array elements are introduced in the vertical domain as well, the necessity of vertical CSI feedback emerges. To facilitate the vertical CSI feedback, the corresponding CSI-RS design is crucial.

Embodiments of the present disclosure illustrate CSI-RS designs and associated configuration methods to be used in the wireless communication networks (e.g., cellular networks) having TPs equipped with 2D active antenna array. It is noted that unless otherwise specified, the CSI-RS disclosed herein refers to NZP CSI-RS.

A new transmission mode (TM), referenced hereinafter as TM X, is defined for helping UEs' reception from the 2D

active antenna array 405. When UE 116 is configured with TM X, UE 116 receives PDSCHs from the 2D active antenna array 405, and is configured with a newly designed CSI-RS. The MIMO transmission from the 2D active antenna array 405 is also referenced as full-dimensional MIMO or FD-MIMO.

In one method (method 1), TP 400 is capable of transmitting all the N CSI-RS antenna ports (APs) associated with each of the N antenna elements 415, and the network is capable of configuring all the N CSI-RS APs to each UE using a UE-specific RRC configuration or a broadcast signaling, so that UE 116 can estimate the full CSI associated with the N antenna elements 415.

In another method (method 2), TP 400 is capable of transmitting at least two sets of CSI-RS APs, and the network is capable of configuring the at least two sets of CSI-RS APs to each UE, wherein UE 116 derives and feeds back horizontal CSI (H-CSI) and vertical CSI (V-CSI) estimated by receiving and processing the at least two sets of CSI-RS. Here the total number of CSI-RS APs can be less than N , and hence the CSI-RS transmission overhead is reduced as compared to method 1.

For Horizontal CSI and vertical CSI: the H-CSI of a UE is horizontal CSI estimated at UE 116, which are channel characteristics mainly associated with horizontally placed antenna elements 415 at TP 400. The horizontal CSI includes horizontal CQI (H-CQI), horizontal PMI (H-PMI) and horizontal RI (H-RI). For example, the H-CSI can be the same as the CSI (PMI, CQI and RI) in another LTE system, because the certain LTE systems CSI feedback contents and mechanism are designed considering horizontal antenna array.

The V-CSI of a UE is vertical CSI estimated at UE 116, which are channel characteristics mainly associated with vertically placed antenna elements at TP 400. The vertical CSI includes vertical CQI (V-CQI), vertical PMI (V-PMI) and vertical RI (V-RI).

FIG. 6 illustrates H-PMI and V-PMI according to embodiments of the present disclosure. The embodiment of the H-PMI and V-PMI 600 shown in FIG. 6 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, UE 1 116, UE 2 115 and UE 3 114 receives the strongest signal when the (H-PMI, V-PMI) pairs are (P1, Q1), (P2, Q2) and (P3, Q3), respectively, according to their respective horizontal directions (or azimuth angles) and vertical directions (or elevation angles). When configured to feed back H-PMIs, UE 1 116, UE 2 115 and UE 3 114 report H-PMIs P1 605, P2 610 and P3 615, respectively. When configured to feed back V-PMIs, UE 1 116, UE 2 115 and UE 3 114 report V-PMIs Q1 620, Q2 625 and Q3 630, respectively.

As for CQI, two feedback methods can be considered: 1) H-CQI and V-CQI are separately derived and are independently fed back to the network; and 2) One joint CQI is derived and is fed back to the network for the N antenna channel. In one design, UE 116 constructs a desired precoding matrix for the N -Tx antenna channel using H-PMI and V-PMI, and calculates a received power under the assumption that the TP transmits signals using the precoding matrix. From the received power, UE 116 derives CQI, where the CQI can be a desired MCS. In one example, the desired precoding matrix is found by taking Kronecker product of H-PMI $= [p_1, p_2, \dots, p_{NH}]^T \in C^{NH \times 1}$ and V-PMI $= [q_1, q_2, \dots, q_{NV}]^T \in C^{NV \times 1}$. In this case, when $N_H=2$, $N_V=2$, H-RI=1 and V-RI=1, the Kronecker product would be calculated as in the Equations 5 and 6:

$$\text{H-PMI} \otimes \text{V-PMI} = \begin{bmatrix} p_1 \\ p_2 \end{bmatrix} \otimes \begin{bmatrix} q_1 \\ q_2 \end{bmatrix} = \begin{bmatrix} p_1 q_1 \\ p_1 q_2 \\ p_2 q_1 \\ p_2 q_2 \end{bmatrix}, \quad (5)$$

$$\text{V-PMI} \otimes \text{H-PMI} = \begin{bmatrix} q_1 \\ q_2 \end{bmatrix} \otimes \begin{bmatrix} p_1 \\ p_2 \end{bmatrix} = \begin{bmatrix} q_1 p_1 \\ q_1 p_2 \\ q_2 p_1 \\ q_2 p_2 \end{bmatrix}. \quad (6)$$

Joint RI is the rank information about the MIMO channels between the N-Tx antenna and a number of receive antennas at the UE.

For ease of illustration, the example shown in FIG. 6 illustrates only line-of-sight channels. However, the non-line-of-sight channels, the V-CSI and H-CSI can be described and defined in a similar way. The example shown in FIG. 6 is for illustration only and it does not prevent other similar constructions and definitions of V-CSI and H-CSI.

FIG. 7 illustrates a first and a second CSI-RS APs according to embodiments of the present disclosure. The embodiment of the transmitter chain 700 including the first and second CSI-RS APs shown in FIG. 7 is for illustration only. Other embodiments could be used without departing from the scope of the present disclosure.

The transmitter chain 700 is configured for multiplexing a first set of CSI-RS 705 (denoted by A-CSI-RS APs) and a second set of CSI-RS APs 710 (denoted by B-CSI-RS APs) for the at least two sets of CSI-RS APs. Here, the multiplexer operation 715 for A-CSI-RS APs 705 and B-CSI-RS APs 710 can be time-domain multiplexing (TDM), CDM (code-domain multiplexing), FDM (frequency-domain multiplexing) and SDM (spatial-domain multiplexing) and any combination of TDM, FDM, CDM and SDM. When TDM multiplexing is applied, A-CSI-RS APs 705 and B-CSI-RS APs 710 transmit their CSI-RS at two different time location, e.g., in two different time slots, or in two different subframes, or in two different sets of OFDM symbols. When FDM multiplexing is applied, A-CSI-RS APs 705 and B-CSI-RS APs 710 transmit their CSI-RS at two different frequency (or subcarrier) location. When CDM multiplexing is applied, A-CSI-RS APs 705 and B-CSI-RS APs 710

APs 705 and B-CSI-RS APs 710 transmit their CSI-RS at two different time-frequency location. Two sets of CSI-RS APs are (quasi) co-located if large-scale propagation properties of the channel over which a symbol on the first antenna port is conveyed can be inferred from the channel over which another symbol on the other antenna port is conveyed.

In certain embodiments, for deriving at least one of joint CQI, joint PMI and joint RI for the $N=N_H \times N_V$ antenna channels utilizing the two sets of CSI-RS, UE 116 can assume that the two sets of CSI-RS APs are (quasi) co-located. In certain embodiments, the network can indicate whether UE 116 can assume that the two sets of CSI-RS APs are (quasi) co-located or not for deriving joint CQI, joint PMI and joint RI.

In certain embodiments, (A-CSI-RS, B-CSI-RS) can be (H-CSI-RS, V-CSI-RS), (a first H-CSI-RS, a second H-CSI-RS), (a primary CSI-RS, a secondary CSI-RS), as illustrated in later embodiments.

In certain embodiments, the CSI-RS configurations defined in Rel-10 LTE or Rel-11 LTE is reused for configuring each of A-CSI-RS and B-CSI-RS. When Rel-10 LTE CSI-RS configuration is used, some of the following parameters in the Table 3 are separately configured for each of A-CSI-RS and B-CSI-RS.

TABLE 3

CSI-RS-Config field descriptions	
AntennaPortsCount	Parameter represents the number of antenna ports used for transmission of CSI reference signals where an1 corresponds to 1, an2 to 2 antenna ports etc. see TS 36.211 [21, 6.10.5].
p-C	Parameter: P_c , see TS 36.213 [23, 7.2.5].
resourceConfig	Parameter: CSI reference signal configuration, see TS 36.211 [21, table 6.10.5.2-1 and 6.10.5.2-2].
subframeConfig	Parameter: I_{CSI-RS} , see TS 36.211 [21, table 6.10.5.3-1].

When Rel-11 LTE NZP CSI-RS configuration is used, some of the parameters defining a CSI-RS-ConfigNZP-r11 (whose fields are copied below and in the background section) are separately configured for each of A-CSI-RS and B-CSI-RS.

```

CSI-RS-ConfigNZP-r11 ::= SEQUENCE {
  csi-RS-IdentityNZP-r11      CSI-RS-IdentityNZP-r11,
  antennaPortsCount-r11      ENUMERATED {an1, an2, an4, an8},
  resourceConfig-r11         INTEGER (0..31),
  subframeConfig-r11         INTEGER (0..154),
  scramblingIdentity-r11     INTEGER (0..503),
  qcl-CRS-Info-r11           SEQUENCE {
    qcl-ScramblingIdentity-r11 INTEGER (0..503),
    crs-PortsCount-r11        ENUMERATED {n1, n2, n4, spare1},
    mbsfn-SubframeConfig-r11  MBSFN-SubframeConfig OPTIONAL,-- Need OR
  }
  ...
}

```

transmit their CSI-RS using two different orthogonal codes (e.g., Walsh code, CAZAC code) in the same time-frequency location. When SDM is applied, A-CSI-RS APs 705 and B-CSI-RS APs 710 transmit their CSI-RS in two different spatial beams, and they can be differently scrambled using two different scrambling initializations. Some example combinations of TDM, CDM, FDM and SDM are described below. When FDM/TDM multiplexing is applied, A-CSI-RS

The resource configurations (resourceConfig) and AntennaPortsCount for A-CSI-RS and B-CSI-RS can be independently or jointly configured.

In one example of independent configuration, (A-resourceConfig, A-AntennaPortsCount) and (B-resourceConfig, B-AntennaPortCount) are configured for A-CSI-RS and B-CSI-RS. When these are configured to UE, UE 116 derives each of A-CSI-RS pattern B-CSI-RS pattern with

replacing (resourceConfig,AntennaPortCount) by each of (A-resource-Config,A-AntennaPortCount) and (B-resource-Config, B-AntennaPortCount) according to TABLE 1.

In one example of joint configuration, (resourceConfig, AntennaPortCount) is configured for both A-CSI-RS and B-CSI-RS. When (resourceConfig,AntennaPortCount) is configured to UE 116, UE 116 first derives a CSI-RS pattern according to TABLE 1 with the configured (resourceConfig, AntennaPortCount). Then, the time frequency locations for N_1 A-CSI-RS APs and N_2 B-CSI-RS APs are determined according to a pre-defined way, where $\text{AntennaPortCount}=N_1+N_2$. Note that N_1 and N_2 can be RRC configured or be constants in the standard specification. Some examples of joint configuration are described in FIG. 8 and below.

In a first example (Example 1) When AntennaPortCount=8, $N_1=4$ and $N_2=4$, APs 15-18 are assigned for A-CSI-RS, and APs 19-22 are assigned for B-CSI-RS. In other words, A-CSI-RS and B-CSI-RS are FDM-multiplexed; and multiple CSI-RS ports in each of A-CSI-RS and B-CSI-RS are CDM multiplexed.

In a second example (Example 2) When AntennaPortCount=8, $N_1=4$ and $N_2=4$, APs (15, 17, 19, 21) are assigned for A-CSI-RS, and APs (16, 18, 20, 22) are assigned for B-CSI-RS. In other words, the 8 CSI-RS are multiplexed in 4 CDM groups of 2 REs each, wherein a first CDM code, e.g., [+1, +1] is assigned for A-CSI-RS; and a second CDM code, e.g., [+1, -1] is assigned for B-CSI-RS.

The resource configurations (resourceConfig) and AntennaPortsCount for A-CSI-RS and B-CSI-RS can be independently or jointly configured.

In one example of independent configuration, (A-resourceConfig, A-AntennaPortsCount) and (B-resourceConfig, B-AntennaPortCount) are configured for A-CSI-RS and B-CSI-RS. When these are configured to UE 116, UE 116 derives each of A-CSI-RS pattern B-CSI-RS pattern with replacing (resourceConfig,AntennaPortCount) by each of (A-resourceConfig,A-AntennaPortCount) and (B-resourceConfig, B-AntennaPortCount) according to TABLE 1.

In one example of joint configuration, (resourceConfig, AntennaPortCount) is configured for both A-CSI-RS and B-CSI-RS. When (resourceConfig,AntennaPortCount) is configured to UE 116, UE 116 first derives a CSI-RS pattern according to TABLE 1 with the configured (resourceConfig, AntennaPortCount). Then, the time frequency locations for N_1 A-CSI-RS APs and N_2 B-CSI-RS APs are determined according to a pre-defined way, where $\text{AntennaPortCount}=N_1+N_2$. Note that N_1 and N_2 can be RRC configured or be constants in the standard specification. Some examples of joint configuration are described in FIGS. 8 and below.

In a first example, (Example 1) When AntennaPortCount=8, $N_1=4$ and $N_2=4$, APs 15-18 are assigned for A-CSI-RS, and APs 19-22 are assigned for B-CSI-RS. In other words, A-CSI-RS and B-CSI-RS are FDM-multiplexed; and multiple CSI-RS ports in each of A-CSI-RS and B-CSI-RS are CDM multiplexed.

In a second example (Example 2) When AntennaPortCount=8, $N_1=4$ and $N_2=4$, APs (15, 17, 19, 21) are assigned

for A-CSI-RS, and APs (16, 18, 20, 22) are assigned for B-CSI-RS. In other words, the 8 CSI-RS are multiplexed in 4 CDM groups of 2 REs each, wherein a first CDM code, e.g., [+1, +1] is assigned for A-CSI-RS; and a second CDM code, e.g., [+1, -1] is assigned for B-CSI-RS.

FIGS. 8A through 8C illustrates joint configuration of A- and B-CSI-RS according to embodiments of the present disclosure. The embodiments of the joint configuration 800, 810, 820 shown in FIGS. 8A through 8C are for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, a common AntennaPortCount is configured for both A-CSI-RS and B-CSI-RS, and at the same time, A-resourceConfig and B-resourceConfig are separately configured for UE 116. In this case, UE 116 derives A-CSI-RS pattern and B-CSI-RS pattern with (A-resourceConfig, AntennaPortCount) and (B-resourceConfig, AntennaPortCount), respectively.

In addition, the total N number of antenna ports at TP 400 can be additionally signaled from A-AntennaPortCount and B-AntennaPortCount.

The subframe configurations (subframeConfig) for A-CSI-RS and B-CSI-RS can be independently or jointly configured.

In one example of independent configuration, for each of A-CSI-RS and B-CSI-RS, the subframe period and the subframe offset for the occurrence are configured as in the same way as the Rel-10 CSI-RS are configured. In this case, two parameters are configured to UE 116, i.e., A-CSI-RS-SubframeConfig and B-CSI-RS-SubframeConfig and UE 116 derives the subframe period and the subframe offset for the occurrence of each of B-CSI-RS and A-CSI-RS according to TABLE 2, with replacing CSI-RS-SubframeConfig by each of A-CSI-RS-SubframeConfig and B-CSI-RS-SubframeConfig.

In one example of joint configuration, for both A-CSI-RS and B-CSI-RS, the subframe configuration period and the subframe offset for the occurrence are configured as in the same way as the Rel-10 CSI-RS are configured. In this case, one parameter is configured to UE 116 as in Rel-10, i.e., CSI-RS-SubframeConfig and UE 116 derives the subframe period and the subframe offset for the occurrence of both B-CSI-RS and A-CSI-RS according to TABLE 2 with the configured CSI-RS-SubframeConfig.

It is noted that (A-CSI-RS, B-CSI-RS) can be (H-CSI-RS, V-CSI-RS), (a first H-CSI-RS, a second H-CSI-RS), (a primary CSI-RS, a secondary CSI-RS), as illustrated in later embodiments.

For configuration of CSI-RS transmission and CSI feedback for UE 116 configured with TM X, a new CSI process, referenced hereafter as CSI-Process-r12, is defined. To facilitate joint CQI transmission, the new CSI process is associated with two CSI resources, i.e., A-CSI-RS and B-CSI-RS, rather than one CSI-RS and one CSI-IM.

One illustration example construction of CSI-process-r12 is described below, where a common P_c (p-C-AndAntennaInfoDedList-r12) is configured for A-CSI-RS and B-CSI-RS.

```
CSI-Process-r12 ::= SEQUENCE {
    csi-ProcessIdentity-r12          CSI-ProcessIdentity-r12,
    a-csi-RS-IdentityNZIP-r12      CSI-RS-IdentityNZIP-r12,
    b-csi-RS-IdentityNZIP-r12      CSI-RS-IdentityNZIP-r12,
    p-C-AndAntennaInfoDedList-r12 SEQUENCE (SIZE (1..2)) OF P-C-
    AndAntennaInfoDed-r12,
```

-continued

cqi-ReportBothPS-r12	CQI-ReportBothPS-r12	
OPTIONAL, -- Need OR		
cqi-ReportPeriodidd-r12	INTEGER (0..maxCQI-Ext-r12)	
OPTIONAL, -- Need OR		
cqi-ReportAperiodicPS-r12	CQI-ReportAperiodicPS-r12	OPTIONAL,
-- Need OR		
...}		

In certain embodiments, when configuring a set of CSI-RS, a CSI-RS type is signaled in addition to other CSI-RS configuration parameters, e.g., CSI-RS pattern, subframe period, subframe offset, and power. The signaling can be either UE-specific or cell-specific. Depending on the configured CSI-RS type information, UE 116 derives CSI differently with estimating channels using the configured CSI-RS, e.g., based on different PMI codebooks.

In one example, a first CSI-RS type is associated with a first PMI codebook, and a second CSI-RS type is associated with a second PMI codebook.

The first and the second PMI codebooks can be a horizontal PMI codebook and a vertical PMI codebook, respectively. Here, the horizontal PMI codebook can be the same as one of Rel-8 and Rel-10 downlink 2-Tx, 4-Tx and 8-Tx PMI codebooks defined in the LTE specifications; and the vertical PMI codebook can be differently designed from the Rel-8 and Rel-10 downlink 2-Tx, 4-Tx and 8-Tx codebooks.

The first and the second PMI codebooks can have different sizes. That is, the first and the second PMI codebooks are composed of M_1 number of PMI matrices and M_2 number of PMI matrices respectively, wherein M_1 and M_2 can be different.

In one example, the first PMI codebook is a 4-bit codebook, composed of $M_1=16$ matrices; and the second PMI codebook is a 2-bit codebook, composed of $M_2=4$ matrices.

In certain embodiments, UE 116 is configured with a first set of CSI-RS of a first CSI-RS type and a second set of CSI-RS of a second CSI-RS type. UE 116 derives a first PMI according to the first PMI codebook with estimating channels using the first set of CSI-RS. UE 116 also derives a second PMI according to the second PMI codebook with estimating channels using the second set of CSI-RS.

The feedback reporting of the first PMI and the second PMI is configured either jointly or independently.

When the feedback reporting is independently (or individually) configured, the first PMI and the second PMI are reported to the eNB 102 according to the respective configurations.

When the feedback reporting is jointly configured, both the first PMI and the second PMI are reported in a single uplink physical channel transmitted in a subframe, e.g., on a PUSCH or a PUCCH.

Similarly, when configuring a set of CSI-RS, a PMI codebook information is signaled in addition to the other CSI-RS configuration parameters. According to the configured PMI codebook, UE 116 derives PMI with estimating channels using the configured CSI-RS. For example, when UE 116 is configured with a first set of CSI-RS and the first PMI codebook; and a second set of CSI-RS and the second PMI codebook, then, UE 116 derives a first PMI according to the first PMI codebook with estimating channels using the first set of CSI-RS. In addition, UE 116 derives a second PMI according to the second PMI codebook with estimating channels using the second set of CSI-RS. In one example,

the first PMI codebook and the second PMI codebook are a horizontal PMI codebook and a vertical PMI codebook, respectively.

In certain embodiments, when CSI-process-r12 is newly defined as above, a CSI-RS configuration is implicitly associated with a PMI codebook. In one example, PMI estimated with A-CSI-RS (a-csi-RS-IdentityNzp-r12) is selected from the first codebook; and PMI estimated with B-CSI-RS (a-csi-RS-IdentityNzp-r12) is selected from the second codebook.

FIG. 9 illustrates Vertical CSI-RS APs and horizontal CSI-RS APs according to embodiments of the present disclosure. The embodiment of the transmitter chain 900 including the Vertical CSI-RS APs and horizontal CSI-RS APs shown in FIG. 9 is for illustration only. Other embodiments could be used without departing from the scope of the present disclosure.

Configuration of Vertical and Horizontal CSI-RS APs:

In certain embodiments, two sets of CSI-RS APs 905, 910 out of the at least two sets of CSI-RS APs are separately constructed: one set consists of N_V vertical CSI-RS (V-CSI-RS) APs 905, and the other set consists of N_H horizontal CSI-RS (H-CSI-RS) APs 910. Here, the horizontal CSI-RS APs 910 are used for UEs' horizontal CSI (H-CSI) estimation, and the vertical CSI-RS APs 905 is used for UEs' vertical CSI (V-CSI) estimation.

When UE 116 is configured with N_V V-CSI-RS APs 905 and N_H H-CSI-RS APs 910, UE 116 can assume that the total number of antenna ports at the TP 400 is $N=N_H \times N_V$ for deriving at least one of joint CQI and joint PMI for the N antenna channels. In another design the total number of antenna ports at the TP is separately signaled to UE 116.

In certain embodiments, H-CSI-RS is associated with H-PMI codebook and V-CSI-RS is associated with V-PMI codebook. In certain embodiments, H-PMI codebook and V-CSI-RS codebook can be identical.

In one alternative, 3GPP LTE Rel-8 and Rel-10 2-Tx, 4-Tx and 8-Tx DL codebooks are reused for both H-PMI and V-PMI. In certain embodiments, UE 116 derives H-CSI using H-CSI-RS by applying the same procedure used for deriving Rel-10 CQI/PMI/RI based on Rel-10 CSI-RS. In certain embodiments, UE 116 derives V-CSI using V-CSI-RS by applying the same procedure used for deriving Rel-10 CQI/PMI/RI based on Rel-10 CSI-RS.

In another alternative, 3GPP LTE Rel-8 and Rel-10 2-Tx, 4-Tx, and 8-Tx DL codebooks are reused for H-PMI codebook only and V-PMI codebook is newly designed; or both the H-PMI and the V-PMI codebooks are newly designed.

Then, the CSI-RS configuration can include a CSI-RS type field, to indicate whether the configured CSI-RS is H-CSI-RS or V-CSI-RS. When UE 116 is configured with H-CSI-RS, UE 116 derives a PMI (H-PMI) using the H-PMI codebook with estimating channels using H-CSI-RS. Alternatively, when UE 116 is configured with V-CSI-RS, UE 116 derives a PMI (V-PMI) using the V-PMI codebook with estimating channels using V-CSI-RS.

Similarly, the CSI-RS configuration can include a PMI codebook information field, to indicate which PMI codebook should be used for deriving PMI using the configured CSI-RS. When UE 116 receives a configuration signaling of a CSI-RS and a H-PMI codebook, UE 116 derives a PMI (H-PMI) using the H-PMI codebook with estimating channels using the configured CSI-RS; on the other hand when UE 116 receives a configuration signaling of a CSI-RS and a V-PMI codebook, UE 116 derives a PMI (V-PMI) using the V-PMI codebook with estimating channels using the configured CSI-RS.

In another alternative, a PMI codebook information can be separately signaled from the CSI-RS configuration. Then, UE 116 derives H-PMI and V-PMI using either a first PMI codebook or a second PMI codebook, depending on the configured PMI codebook information. In certain embodiments, the first PMI codebook can be 3GPP LTE Rel-8 and Rel-10 2-Tx, 4-Tx, and 8-Tx DL codebooks; and the second PMI codebook can be a newly designed codebook.

In certain embodiments, the codebook sizes of the H-PMI codebook and the V-PMI codebook are different. In one example, for assigning better beam resolution of horizontal beams more than that of vertical beams, a larger size codebook is used for H-PMI than for V-PMI. In one example, for assigning better beam resolution of vertical beams more than that of horizontal beams, a larger size codebook is used for V-PMI than for H-PMI.

FIG. 10 illustrates construction of the horizontal and the vertical CSI-RS APs according to embodiments of the present disclosure. The embodiment of the construction 1000 shown in FIG. 10 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, in the construction 1000 of the horizontal and the vertical CSI-RS APs (Construction Example 1) includes the N_H horizontal CSI-RS APs (say, H-APs 0, . . . , N_H-1) are transmitted from a row 1005 of the active antenna array, while the N_V vertical CSI-RS APs (say, V-APs 0, . . . , $N-1$) are transmitted from a column 1010 of the active antenna array. In the example shown in FIG. 10, the horizontal CSI-RS APs are transmitted from the first row 1005 of the antenna array, while the vertical CSI-RS APs are transmitted from the first column 1010 of the antenna array.

When the H-CSI-RS and V-CSI-RS are transmitted in the same subframe, one CSI-RS AP can be shared between the two sets of the CSI-RS APs. For example, only a single CSI-RS signal mapped onto single-port CSI-RS REs is transmitted for H-AP 0 and V-AP 0. Alternatively, the H-CSI-RS and V-CSI-RS can also be orthogonally and independently mapped in the time-frequency grid, even if the two CSI-RS APs are scheduled in the same subframe.

FIG. 11 illustrates construction of the horizontal and the vertical CSI-RS APs according to embodiments of the present disclosure. The embodiment of the construction 1100 shown in FIG. 11 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, in the construction 1100 of the horizontal and the vertical CSI-RS APs (Construction Example 2), each of the N_H horizontal CSI-RS for the N_H H-CSI-RS APs (say, H-APs 0, . . . , N_H-1) are transmitted from a column 1105 of the active antenna array. Each H-CSI-RS signal is precoded with a precoding vector of $[p_1 \ p_2 \ \dots \ p_{N_V}]^T$, where the precoding is applied across the antenna elements in each column of the active antenna array.

Alternatively, each of the N_V vertical CSI-RS for the N_V APs (say, V-APs 0, . . . , N_V-1) are transmitted from a row

1110 of the active antenna array. Each H-CSI-RS signal is precoded with a precoding vector of $[q_1 \ q_2 \ \dots \ q_{N_H}]$, where the precoding is applied across the antenna elements in each row of the active antenna array.

The precoding to generate a CSI-RS signal also is referenced as antenna virtualization precoding. As shown in FIG. 11, the construction 1100 can be easily extended to a construction in which different precoding vectors are applied across different rows (or columns) corresponding to the different V-CSI-RS (or H-CSI-RS).

FIG. 12 illustrates first and second sets of horizontal CSI-RS APs according to embodiments of the present disclosure. The embodiment of the transmitter chain 1200 including the first and second sets of horizontal CSI-RS APs shown in FIG. 12 is for illustration only. Other embodiments could be used without departing from the scope of the present disclosure.

Configuration of a First and a Second Horizontal CSI-RS APs:

In certain embodiments, two sets of CSI-RS APs 1205, 1210 out of the at least two sets of CSI-RS APs are separately constructed: each of the two sets consists of N_H H-CSI-RS APs corresponding to a row of antenna elements in the 2D active antenna array 405. Here, the two sets of H-CSI-RS APs 1205, 1210 are used for UEs' horizontal and vertical CSI estimation.

In this case, the total number of antenna ports at the TP N is separately RRC configured from the configurations for the two sets of CSI-RS 1205, 1210. The total number of antenna ports $N=N_H \times N_V$ is used for deriving at least one of joint CQI and joint PMI for the N antenna channels

FIG. 13 illustrates construction of two sets of H-CSI-RS APs according to embodiments of the present disclosure. The embodiment of the construction 1300 shown in FIG. 13 is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, in the construction 1300 of the two sets of H-CSI-RS APs (Set Construction Example 1), the two rows of antenna elements corresponding to the two sets of H-CSI-RS APs are the first two rows 1305 in the 2D active antenna array 405. In this case, UE 116 determines the vertical CSI for the entire $N_H \times N_V$ antennas in the 2D active antenna array 405 by estimating the phase difference between the two rows, as well as the horizontal CSI by relying on the traditional methods of estimating horizontal CSI. The two rows are configurable by the network, in which case, the network is configured to indicate to each UE at least one of the following: The indices of the two rows corresponding to the two H-CSI-RS APs. For example, when the first two rows 1305, 1310 are corresponding to the two H-CSI-RS APs as in the example shown in FIG. 13, the network configures to each UE two row indices, row index 0 1305 and row index 1 1310.

In certain embodiments, eNB 102 signals to UE 116 the difference of the two indices of the two rows corresponding to the two H-CSI-RS APs. For example, when the first two rows are corresponding to the two H-CSI-RS APs as in the example shown in FIG. 13, the network configures to each UE the difference of the two row indices, i.e., $(1-0)=1$.

The example shown in FIG. 13 is for illustration only. The same idea can be used for constructing N_V sets of H-CSI-RS APs corresponding to the N_V rows of the 2D antenna array.

In one alternative, CSI-RS configuration includes a CSI-RS type field to indicate whether the configured CSI-RS is the first H-CSI-RS or the second H-CSI-RS.

FIG. 14 illustrates Construction of two sets of H-CSI-RS APs according to embodiments of the present disclosure.

The embodiment of the construction **1400** shown in FIG. **14** is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In certain embodiments, in the construction **1400** of the two sets of H-CSI-RS APs (Set Construction Example 2), two different virtualization precoding vectors are applied to the two sets of H-CSI-RS APs **1405**, **1410**. Each H-CSI-RS signal in the first set **1405** is precoded with a precoding vector of $[p_1 \ p_2 \ \dots \ p_{N_V}]^t$, and each H-CSI-RS in the second set is precoded with a precoding vector of $[q_1 \ q_2 \ \dots \ q_{N_V}]^t$, where the precoding vector is applied across the antenna elements in each column of the active antenna array in each set of H-CSI-RS APs. UE **116** determines the vertical CSI for the entire $N_H \times N_V$ antennas in the 2D active antenna array **405** by estimating the phase difference between the two sets of H-CSI-RS APs **1405**, **1410**, as well as the horizontal CSI by relying on the traditional methods of estimating horizontal CSI. The two virtualization precoding vectors can be indicated by the network to each UE.

FIG. **15** illustrates primary and secondary CSI-RS APs according to embodiments of the present disclosure. The embodiment of the transmitter chain **1500** including the primary and secondary CSI-RS APs shown in FIG. **15** is for illustration only. Other embodiments could be used without departing from the scope of the present disclosure.

In one alternative, CSI-RS configuration includes a CSI-RS type field, to indicate whether the configured CSI-RS is the primary CSI-RS or the secondary CSI-RS.

Configuration of a First and a Second Horizontal CSI-RS APs:

In certain embodiments, two sets of CSI-RS APs out of the at least two sets of CSI-RS APs are separately constructed and configured (period as well): a set of primary CSI-RS APs **1505** and a set of secondary CSI-RS APs **1510**.

Primary CSI-RS APs **1505**: in certain embodiments, UE **116** utilizes the set of primary CSI-RS APs **1505** to derive either H-CSI or V-CSI, depending on whether the primary CSI-RS **1505** are corresponding to the (N_H) horizontally placed antenna elements or (N_V) vertically placed antenna elements. Whether UE **116** can derive H-CSI or V-CSI out of the primary CSI-RS **1505** is indicated by the network, or fixed in the standard specification (e.g., pre-stored in memory **360**).

Secondary CSI-RS APs **1510**: in certain embodiments, UE **116** combines the primary CSI-RS APs **1505** and the secondary CSI-RS APs **1510** to determine either V-CSI-RS or H-CSI-RS. In one example, when the primary CSI-RS APs **1505** correspond to the horizontally placed antenna elements and are used for estimating H-CSI-RS, the secondary CSI-RS APs **1510**, together with the primary CSI-RS APs **1505**, can be used for estimating the V-CSI-RS. In another example, when the primary CSI-RS APs **1505** correspond to the vertically placed antenna elements and are used for estimating V-CSI-RS, the secondary CSI-RS APs **1510** together with the primary CSI-RS APs **1505** can be used for estimating the H-CSI-RS. The number of secondary APs can be less than the number of the primary APs, and can be separately configured from the number of the primary CSI-RS APs **1505**.

In this case, the total number of antenna ports at TP N is separately RRC configured from the configurations for the two sets of CSI-RS. The total number of antenna ports $N=N_H \times N_V$ is used for deriving at least one of joint CQI and joint PMI for the N antenna channels.

FIG. **16** illustrates construction of the primary and the secondary CSI-RS according to embodiments of the present disclosure. The embodiment of the construction **1600** shown

in FIG. **16** is for illustration only. Other embodiments could be used without departing from the scope of this disclosure.

In the example construction of the primary and the secondary CSI-RS shown in FIG. **16**, the primary CSI-RS **1605** are H-CSI-RS, while only one AP is provided for the secondary CSI-RS **1610**, which is the first antenna element **1615** of the second row of the 2D active antenna array **405**. When UE **116** is configured with these primary and secondary CSI-RS, UE **116** derives H-CSI utilizing the primary CSI-RS, and UE **116** derives V-CSI utilizing the primary and the secondary CSI-RS, such as, by estimating the phase difference between the two types of CSI-RS. The relative location of the secondary CSI-RS with respect to the primary CSI-RS can be configured by the network.

In another method (method 3), the network is capable of configuring and transmitting at least two sets of CSI-RS APs. A first set of CSI-RS APs is used for horizontal CSI estimation at a first group of UEs, and a second set of CSI-RS APs is used for horizontal CSI estimation at a second group of UEs.

Each of the at least two sets of CSI-RS APs can be targeted to be best received in a certain distance from the TP (or a certain range of elevation angles). For example, a first set of CSI-RS is best received at distance of 0 m to 200 m, while the second set of CSI-RS is best received at distance of 200 m to 400 m. For this operation, the network can tailor antenna virtualization precoding method of each set of CSI-RS accordingly. That is, the first set of CSI-RS is virtualized with a first virtualization precoding so that it is best received at a first range of distances, and the second set of CSI-RS is virtualized with a second virtualization precoding so that it is best received at a second range of distances.

UE **116** can be configured for one set out of the at least two sets of CSI-RS APs by an RRC configuration. Then, UE **116** estimates horizontal CSI based on the configured set of CSI-RS APs.

UE **116** can be re-configured to estimate horizontal CSI based on a first set of CSI-RS APs from a second set of CSI-RS APs, by an RRC configuration.

UE **116** can be configured for the at least two sets of CSI-RS APs. UE **116** can estimate and report RSRPs for the at least two sets of CSI-RS APs, e.g., depending on a configured triggering condition.

Although the present disclosure has been described with an exemplary embodiment, various changes and modifications may be suggested to one skilled in the art. It is intended that the present disclosure encompass such changes and modifications as fall within the scope of the appended claims.

What is claimed is:

1. For use in a wireless communication network, a base station comprising:

a two dimensional (2D) antenna array comprising a number N of antenna elements configured in a 2D grid $N_H \times N_V$, the 2D antenna array configured to communicate with at least one subscriber station; and

a controller configured to transmit N channel-state-information reference-signal (CSI-RS) antenna ports (APs) associated with each of the N antenna elements, wherein the controller is configured to transmit at least two sets of CSI-RS APs and the at least one subscriber station derives and feeds back horizontal CSI (H-CSI) and vertical CSI (V-CSI) estimated by the at least one subscriber station receiving and processing the at least two sets of CSI-RS APs, and wherein a total number of CSI-RS APs is less than N.

2. The base station as set forth in claim 1, wherein the H-CSI comprises channel characteristics mainly associated with horizontally placed antenna elements estimated at the at least one subscriber station and includes horizontal channel quality indicator (CQI) (H-CQI), horizontal precoding matrix index (PMI) (H-PMI) and horizontal rank indicator (RI) (H-RI).

3. The base station as set forth in claim 1, wherein the V-CSI comprises channel characteristics mainly associated with vertically placed antenna elements estimated at the at least one subscriber station and includes vertical CQI (V-CQI), vertical PMI (V-PMI) and vertical RI (V-RI).

4. The base station as set forth in claim 1, wherein the controller is configured to multiplex a first set of CSI-RS APs and a second set of CSI-RS APs for the at least two sets of CSI-RS APs.

5. The base station as set forth in claim 4, wherein the multiplexer operation comprises one or more of: a time-domain multiplexing (TDM), code-domain multiplexing (CDM), frequency-domain multiplexing (FDM) and spatial-domain multiplexing (SDM) and wherein:

when TDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different time locations comprising at least one of: in two different time slots, in two different subframes, in two different sets of OFDM symbols;

when FDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different frequency or subcarrier locations;

when CDM multiplexing is applied, the controller is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs using two different orthogonal codes in the same time-frequency location;

when SDM is applied, the controller is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs in two different spatial beams and wherein the at least two sets of CSI-RS APs are differently scrambled using two different scrambling initializations; and

when FDM/TDM multiplexing is applied, the controller is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs at two different time-frequency location.

6. The base station as set forth in claim 1, wherein the at least two sets of CSI-RS APs comprise one of:

A-CSI-RS AP and B-CSI-RS AP;

a vertical CSI-RS AP and a horizontal CSI-RS AP;

two horizontal CSI-RS APs; and

a primary CSI-RS AP and a secondary CSI-RS AP.

7. A subscriber station configured to communicate with at least one base station using a multiple input multiple output (MIMO) communication, the subscriber station comprising:

an antenna array configured to communicate with at least one base station; and

processing circuitry configured to receive physical downlink shared channels (PDSCHs) from a two dimensional (2D) active antenna array at the at least one base station, the 2D active antenna array comprising a number N antenna elements; the processing circuitry further configured to estimate a horizontal channel state information (CSI) and vertical CSI associated with the N antenna elements, wherein the processing circuitry is configured to receive and process at least two sets of CSI-RS antenna ports (APs), and derive and feedback

horizontal CSI (H-CSI) and vertical CSI (V-CSI) from the at least two sets of CSI-RS APs, wherein a total number of CSI-RS APs is less than N.

8. The subscriber station as set forth in claim 7, wherein the H-CSI comprises channel characteristics mainly associated with horizontally placed antenna elements estimated at the at least one subscriber station and includes horizontal channel quality indicator (CQI) (H-CQI), horizontal precoding matrix index (PMI) (H-PMI) and horizontal rank indicator (RI) (H-RI).

9. The subscriber station as set forth in claim 7, wherein the V-CSI comprises channel characteristics mainly associated with vertically placed antenna elements estimated at the at least one subscriber station and includes vertical CQI (V-CQI), vertical PMI (V-PMI) and vertical RI (V-RI).

10. The subscriber station as set forth in claim 7, wherein a first set of CSI-RS and a second set of CSI-RS APs for the at least two sets of CSI-RS APs are multiplexed.

11. The subscriber station as set forth in claim 10, wherein the multiplexer operation comprises one or more of: a time-domain multiplexing (TDM), code-domain multiplexing (CDM), frequency-domain multiplexing (FDM) and spatial-domain multiplexing (SDM) and wherein:

when TDM multiplexing is applied, the [controller] *processing circuitry* is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different time locations comprising at least one of: in two different time slots, in two different subframes, in two different sets of OFDM symbols;

when FDM multiplexing is applied, the [controller] *processing circuitry* is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs at two different frequency or subcarrier locations;

when CDM multiplexing is applied, the [controller] *processing circuitry* is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs using two different orthogonal codes in the same time-frequency location;

when SDM is applied, the [controller] *processing circuitry* is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs in two different spatial beams and wherein the at least two sets of CSI-RS APs are differently scrambled using two different scrambling initializations; and

when FDM/TDM multiplexing is applied, the [controller] *processing circuitry* is configured to transmit the CSI-RS APs corresponding to the at least two sets of CSI-RS APs at two different time-frequency location.

12. The subscriber station as set forth in claim 7, wherein the at least two sets of CSI-RS APs comprise one of:

A-CSI-RS AP and B-CSI-RS AP;

a vertical CSI-RS AP and a horizontal CSI-RS AP;

two horizontal CSI-RS APs; and

a primary CSI-RS AP and a secondary CSI-RS AP.

13. For use in a wireless communication network, a method comprising:

transmitting, from a two dimensional (2D) antenna array, N channel-state-information reference-signal (CSI-RS) antenna ports (APs), the 2D antenna array comprising a number N of antenna elements configured in a 2D grid $N_H \times N_V$, the CSI-RS APs associated with each of the N antenna elements, wherein transmitting comprises transmitting at least two sets of CSI-RS APs; and receiving a feedback signal from the at least one subscriber station, the feedback signal comprising horizontal CSI (H-CSI) and vertical CSI (V-CSI) estimated by the at least one subscriber station receiving and

processing the at least two sets of CSI-RS APs, and wherein a total number of CSI-RS APs is less than N.

14. The method as set forth in claim 13, wherein the H-CSI comprises channel characteristics mainly associated with horizontally placed antenna elements estimated at the at least one subscriber station and includes horizontal CQI (H-CQI), horizontal PMI (H-PMI) and horizontal RI (H-RI).

15. The method as set forth in claim 13, wherein the V-CSI comprises channel characteristics mainly associated with vertically placed antenna elements estimated at the at least one subscriber station and includes vertical CQI (V-CQI), vertical PMI (V-PMI) and vertical RI (V-RI).

16. The method as set forth in claim 13, wherein transmitting comprises multiplexing a first set of CSI-RS and a second set of CSI-RS for the at least two sets of CSI-RS.

17. The method as set forth in claim 16, wherein multiplexing comprises one or more of: a time-domain multiplexing (TDM), code-domain multiplexing (CDM), frequency-domain multiplexing (FDM) and spatial-domain multiplexing (SDM) and wherein:

when TDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different time locations comprising at least one of: in two different time slots, in two different subframes, in two different sets of OFDM symbols;

when FDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different frequency or subcarrier locations;

when CDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs using two different orthogonal codes in the same time-frequency location;

when SDM is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs in two different spatial beams and wherein the at least two sets of CSI-RS APs are differently scrambled using two different scrambling initializations; and

when FDM/TDM multiplexing is applied, the controller is configured to transmit the CSI-RS corresponding to the at least two sets of CSI-RS APs at two different time-frequency location.

18. The method as set forth in claim 13, wherein the at least two sets of CSI-RS APs comprise one of:

A-CSI-RS and B-CSI-RS;
a vertical CSI-RS AP and a horizontal CSI-RS AP;
two horizontal CSI-RS APs; and
a primary CSI-RS AP and a secondary CSI-RS AP.

19. An apparatus in a base station for transmitting channel state information reference signal (CSI-RS), the apparatus comprising:

a controller configured to:
identify a same number of antenna ports associated with aggregation of each of at least two CSI-RS configurations, the at least two CSI-RS configurations including a first CSI-RS configuration and a second CSI-RS configuration; and

a transceiver configured to:
transmit information on the same number of antenna ports,
transmit information on the at least two CSI-RS configurations, and
transmit a first CSI-RS corresponding to the same number of antenna ports and the first CSI-RS con-

figuration and a second CSI-RS corresponding to the same number of antenna ports and the second CSI-RS configuration.

20. The apparatus of claim 19, wherein one subframe configuration is set for the at least two CSI-RS configurations, the at least two CSI-RS configurations are aggregated in a subframe.

21. The apparatus of claim 19, wherein a resource configuration for each of the at least two CSI-RS configurations is set separately.

22. The apparatus of claim 19, wherein the same number of antenna ports is 8.

23. The base station of claim 1, wherein the antenna array is further configured to:

transmit information indicating a codebook for the at least two CSI-RS configurations.

24. An apparatus in a mobile station for receiving channel state information reference signal (CSI-RS), the apparatus comprising:

a transceiver configured to:

receive information on a same number of antenna ports, and

receive information on at least two CSI-RS configurations, wherein the same number of antenna ports is associated with aggregation of the at least two CSI-RS configurations and the at least two CSI-RS configurations include a first CSI-RS configuration and a second CSI-RS configuration; and

a controller configured to identify the same number of antenna ports associated with the aggregation of the at least two CSI-RS configurations,

wherein the transceiver is configured to receive a first CSI-RS corresponding to the same number of antenna ports and the first CSI-RS configuration and a second CSI-RS corresponding to the same number of antenna ports and the second CSI-RS configurations.

25. The apparatus of claim 24, wherein one subframe configuration is set for the at least two CSI-RS configurations, the at least two CSI-RS configurations are aggregated in a subframe.

26. The apparatus of claim 24, wherein a resource configuration for each of the at least two CSI-RS configurations is set separately.

27. The apparatus of claim 24, wherein the same number of antenna ports is 8.

28. The apparatus of claim 24, wherein the transceiver is further configured to:

receive information indicating a codebook for the at least two CSI-RS configurations.

29. A method for transmitting channel state information reference signal (CSI-RS) by a base station, the method comprising:

identifying a same number of antenna ports associated with aggregation of each of at least two CSI-RS configurations, the at least two CSI-RS configurations including a first CSI-RS configuration and a second CSI-RS configuration;

transmitting information on the same number of antenna ports;

transmitting information on the at least two CSI-RS configurations; and

transmitting a first CSI-RS corresponding to the same number of antenna ports and the first CSI-RS configuration and a second CSI-RS corresponding to the same number of antenna ports and the second CSI-RS configurations.

31

30. The method of claim 29, wherein one subframe configuration is set for the at least two CSI-RS configurations, the at least two CSI-RS configurations are aggregated in a subframe.

31. The method of claim 29, wherein a resource configuration for each of the at least two CSI-RS configurations is set separately.

32. The method of claim 29, wherein the same number of antenna ports is 8.

33. The method of claim 29, further comprising:
transmitting information indicating a codebook for the at least two CSI-RS configurations.

34. A method for receiving channel state information reference signal (CSI-RS), comprising:

receiving information on a same number of antenna ports;
receiving information on at least two CSI-RS configurations, wherein the same number of antenna ports is associated with aggregation of the at least two CSI-RS configurations and the at least two CSI-RS configurations include a first CSI-RS configuration and a second CSI-RS configuration;

identifying the same number of antenna ports associated with the aggregation of the at least two CSI-RS configurations; and

receiving a first CSI-RS corresponding to the same number of antenna ports and the first CSI-RS configuration and a second CSI-RS corresponding to the same number of antenna ports and the second CSI-RS configurations.

35. The method of claim 34, wherein one subframe configuration is set for the at least two CSI-RS configurations, and the at least two CSI-RS configurations are aggregated in a subframe.

36. The method of claim 34, wherein a resource configuration for each of the at least two CSI-RS configurations is set separately.

37. The method of claim 34, wherein the same number of antenna ports is 8.

38. The method of claim 34, further comprising:
receiving information indicating a codebook for the at least two CSI-RS configurations.

39. An apparatus in a base station for transmitting channel state information reference signal (CSI-RS), the apparatus comprising:

a controller configured to:
identify a total number of antenna ports associated with aggregation of at least two CSI-RS configurations;
and

a transceiver configured to:
transmit information on the at least two CSI-RS configurations, and
transmit CSI-RSs corresponding to the total number of antenna ports and the at least two CSI-RS configurations,

wherein the antenna ports associated with aggregation of at least two CSI-RS configurations comprise, for a two dimensional (2D) antenna array, channel state information reference signal (CSI-RS) antenna ports (APs) corresponding to two rows of antenna elements including a first row of N antenna elements and a second row of N antenna elements for a total of $2N$ antenna elements, and wherein the CSI-RS APs are each mapped 1:1 with one of the $2N$ antenna elements.

32

40. An apparatus in a mobile station for receiving channel state information reference signal (CSI-RS), the apparatus comprising:

a transceiver configured to:

receive information on at least two CSI-RS configurations, and

receive CSI-RSs corresponding to a total number of antenna ports and the at least two CSI-RS configurations; and

a controller configured to:

identify the total number of antenna ports associated with aggregation of the at least two CSI-RS configurations,

wherein the antenna ports associated with aggregation of at least two CSI-RS configurations comprise, for a two dimensional (2D) antenna array, channel state information reference signal (CSI-RS) antenna ports (APs) corresponding to two rows of antenna elements including a first row of N antenna elements and a second row of N antenna elements for a total of $2N$ antenna elements, and wherein the CSI-RS APs are each mapped 1:1 with one of the $2N$ antenna elements.

41. A method for transmitting channel state information reference signal (CSI-RS) by a base station, the method comprising:

identifying a total number of antenna ports associated with aggregation of at least two CSI-RS configurations;
and

transmitting information on the at least two CSI-RS configurations;

transmitting CSI-RSs corresponding to the total number of antenna ports and the at least two CSI-RS configurations,

wherein the antenna ports associated with aggregation of at least two CSI-RS configurations comprise, for a two dimensional (2D) antenna array, channel state information reference signal (CSI-RS) antenna ports (APs) corresponding to two rows of antenna elements including a first row of N antenna elements and a second row of N antenna elements for a total of $2N$ antenna elements, and wherein the CSI-RS APs are each mapped 1:1 with one of the $2N$ antenna elements.

42. A method for receiving channel state information reference signal (CSI-RS), comprising:

receiving information on at least two CSI-RS configurations;

identifying a total number of antenna ports associated with aggregation of the at least two CSI-RS configurations;

receiving CSI-RSs corresponding to the total number of antenna ports and the at least two CSI-RS configurations,

wherein the antenna ports associated with aggregation of at least two CSI-RS configurations comprise, for a two dimensional (2D) antenna array, channel state information reference signal (CSI-RS) antenna ports (APs) corresponding to two rows of antenna elements including a first row of N antenna elements and a second row of N antenna elements for a total of $2N$ antenna elements, and wherein the CSI-RS APs are each mapped 1:1 with one of the $2N$ antenna elements.

* * * * *