



US 20060162768A1

(19) **United States**(12) **Patent Application Publication**
Wanlass et al.(10) **Pub. No.: US 2006/0162768 A1**(43) **Pub. Date: Jul. 27, 2006**(54) **LOW BANDGAP, MONOLITHIC,
MULTI-BANDGAP, OPTOELECTRONIC
DEVICES****Publication Classification**(51) **Int. Cl.**
H01L 31/00 (2006.01)(52) **U.S. Cl.** **136/262; 438/93**(57) **ABSTRACT**

Low-bandgap, monolithic, multi-bandgap, optoelectronic devices (10), including PV converters, photodetectors, and LED's, have lattice-matched (LM), double-heterostructure (DH), low-bandgap GaInAs(P) subcells (22, 24) including those that are lattice-mismatched (LMM) to InP, grown on an InP substrate (26) by use of at least one graded lattice constant transition layer (20) of InAsP positioned somewhere between the InP substrate (26) and the LMM sub-cell(s) (22, 24). These devices are monofacial (10) or bifacial (80) and include monolithic, integrated, modules (MIMs) (190) with a plurality of voltage-matched subcell circuits (262, 264, 266, 270, 272) as well as other variations and embodiments.

(76) Inventors: **Mark W. Wanlass**, Golden, CO (US);
Jeffrey J. Carapella, Evergreen, CO
(US)

Correspondence Address:

Paul White**National Renewable Energy Laboratory****1617 Cole Blvd****Golden, CO 80401 (US)**(21) Appl. No.: **10/515,243**(22) PCT Filed: **May 21, 2002**(86) PCT No.: **PCT/US02/16101****Monofacial
General Structure****Example Eg Profile**




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17

LOW BANDGAP, MONOLITHIC, MULTI-BANDGAP, OPTOELECTRONIC DEVICES

CONTRACTUAL ORIGIN OF INVENTION

[0001] The United States Government has rights in this invention under Contract No. DE-AC36-99GO10337 between the United States D Renewable Energy Laboratory, a Division of the Midwest Research Institute.

TECHNICAL FIELD

[0002] This invention relates to optoelectronic devices, and, more specifically, to low bandgap, monolithic, multi-bandgap solar photovoltaic (SPV) and thermophotovoltaic (TPV) cells for converting solar and/or thermal energy to electricity as well as for related photodetector devices for detecting light signals and light emitting diode (LED) devices for converting electricity to light and/or infrared (IR) radiant energy.

BACKGROUND OF THE INVENTION

[0003] It is well known that the most efficient conversion of radiant energy to electrical energy with the least thermalization loss in semiconductor materials is accomplished by matching the photon energy of the incident radiation to the amount of energy needed to excite electrons in the semiconductor material to transcend the bandgap from the valence band to the conduction band. However, since solar radiation and blackbody radiation usually comprise a wide range of wavelengths, use of only one semiconductor material with one bandgap to absorb such radiant energy and convert it to electrical energy will result in large inefficiencies and energy losses to unwanted heat.

[0004] Ideally, there would be a semiconductor material with a bandgap to match the photon energy for every wavelength in the radiation. That kind of device is impractical, if not impossible, but persons skilled in the art are building monolithic stacks of different semiconductor materials into devices commonly called tandem converters and/or monolithic, multi-bandgap or multi-bandgap converters, to get two, three, four, or more bandgaps to match more closely to different wavelengths of radiation and, thereby, achieve more efficient conversion of radiant energy to electrical energy. Essentially, the radiation is directed first into a high bandgap semiconductor material, which absorbs the shorter wavelength, higher energy portions of the incident radiation and which is substantially transparent to longer wavelength, lower energy, portions of the incident radiation. Therefore, the higher energy portions of the radiant energy are converted to electric energy by the larger bandgap semiconductor materials without excessive thermalization and loss of energy in the form of heat, while the longer wavelength, lower energy portions of the radiation are transmitted to one or more subsequent semiconductor materials with smaller bandgaps for further selective absorption and conversion of remaining radiation to electrical energy.

[0005] Semiconductor compounds and alloys with bandgaps in the various desired energy ranges are known, but that knowledge alone does not solve the problem of making an efficient and useful energy conversion device. Defects in crystalline semiconductor materials, such as impurities, dislocations, and fractures provide unwanted recombination sites for photogenerated electron-hole pairs, resulting in

decreased energy conversion efficiency. Therefore, high-performance, photovoltaic conversion cells comprising semiconductor materials with the desired bandgaps, often require high quality, epitaxially grown crystals with few, if any, defects. Growing the various structural layers of semiconductor materials required for a multi-bandgap, tandem, photovoltaic (PV) conversion device in a monolithic form is the most elegant, and possibly the most cost-effective, approach.

[0006] Epitaxial crystal growth of the various compound or alloy semiconductor layers with desired bandgaps is most successful, when all of the materials are lattice-matched (LM), so that semiconductor materials with larger crystal lattice constants are not interfaced with other materials that have smaller lattice constants or vice versa. Lattice-mismatching (LMM) in adjacent crystal materials causes lattice strain, which, when high enough, is usually manifested in dislocations, fractures, wafer bowing, and other problems that degrade or destroy electrical characteristics and capabilities of the device. Unfortunately, the semiconductor materials that have the desired bandgaps for absorption and conversion of radiant energy in some energy or wavelength bands do not always lattice match other semiconductor materials with other desired bandgaps for absorption and conversion of radiant energy in other energy or wavelength bands. Therefore, fabrication of device quality, multi-bandgap, monolithic, converter structures is difficult, if not impossible, for some portions of the radiation frequency or wavelength spectrum.

[0007] This problem has been particularly difficult to solve in the infrared (IR) portion of the spectrum, where options for suitable, commercially available substrates on which to grow thin films with the necessary bandgaps for absorption and conversion of the infrared radiation to electrical energy are very limited, and where compatible, i.e., lattice-matched, semiconductor materials with the different bandgaps needed to absorb and convert different portions of the infrared spectrum efficiently are also quite limited.

[0008] For example, the group III-V family of semiconductor alloys include some of the best materials for fabricating photovoltaic converters with bandgaps in a range of about 0.35 eV to 1.65 eV to absorb and convert infrared (IR) radiation with wavelengths in a range of about 3.54 μm to 0.75 μm . Group III-V alloys comprise combinations of binary compounds formed from Groups III and V of the Periodic Table. These binary compounds can be alloyed together into various ternary or quaternary compositions to obtain any desired bandgap in the range of 0.35 eV to 1.65 eV. These alloys also have direct bandgaps (i.e., no change in momentum is required for an electron to cross the bandgap between the valence band and the conduction band), which facilitate efficient absorption and conversion of radiant energy to electricity. However, InP, which has a lattice constant of 5.869 Å (sometimes rounded to 5.87 Å) and a bandgap of 1.35 eV, is one of only a few feasible, commercially available substrate materials with a lattice constant even close to those lower bandgap Group III-V alloys i.e., InP-based or related ternary and quaternary compounds. The lowest bandgap Group III-V alloy that can be lattice-matched to the 5.869 Å lattice constant of an InP substrate is $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$, which has a bandgap of about 0.74 eV, which leaves a significant range of lower frequency, longer wavelength ($>1.67 \mu\text{m}$), infrared (IR) radiation that

cannot be absorbed and converted to electricity in monolithic converters in which the semiconductor absorption materials are lattice-matched to the substrate.

[0009] While the current unavailability of efficient and cost-effective solar photovoltaic (SPV) converters, especially multi-bandgap, monolithic, converter devices, capable of absorbing and converting infrared (IR) radiation in wavelengths greater than $1.67\text{ }\mu\text{m}$ leaves substantial amounts of energy in the solar spectrum to remain unconverted to electricity, in state-of-the-art SPV's, it is an even greater problem for thermophotovoltaic (TPV) devices. Infrared (IR) radiation of wavelengths greater than $1.67\text{ }\mu\text{m}$ comprises a substantial amount of the energy radiated from blackbodies, and thermophotovoltaic (TPV) converters are intended to absorb and convert as much radiant energy from blackbodies to electric power as possible. Therefore, solutions to these problems, especially if such solutions could enable fabrication of monolithic converters with multiple bandgaps in infrared (IR) energy ranges, they would facilitate capture of more electric energy from solar and/or blackbody radiation.

[0010] U.S. Pat. No. 5,479,032 issued to S. Forrest et al., teaches that one or more ternary $\text{In}_x\text{Ga}_{1-x}\text{As}$ alloys with $x>0.53$, i.e., with band-gaps less than 0.75 eV , can be grown epitaxially on an InP substrate by using intervening, graded layers of $\text{InAs}_y\text{P}_{1-y}$ between the InP substrate and the $\text{In}_x\text{Ga}_{1-x}\text{P}$ ($x>0.53$) layers. However, those Forrest et al., patent teachings, which were directed to pixel detection of near infrared radiation incident on a focal plane for telecommunications applications, are not useful in SPV and TPV applications.

SUMMARY OF THE INVENTION

[0011] Accordingly, a general object of the present invention is to provide a monolithic, multi-bandgap, photovoltaic converter for absorbing and converting infrared (IR) radiation of multiple wavelengths to electricity.

[0012] A more specific object of this invention is to provide a photovoltaic converter with at least one bandgap less than 0.74 eV to absorb infrared radiation in wavelengths longer than $1.67\text{ }\mu\text{m}$ and convert it to electricity.

[0013] An even more specific object of this invention is to provide a electric device quality, multi-bandgap, monolithic, photovoltaic converter that has at least one lattice-matched (LM), double-heterostructure (DH) with a bandgap less than 0.74 eV to absorb infrared (IR) energy in wavelengths longer than $1.67\text{ }\mu\text{m}$ and convert it to electricity.

[0014] Another specific object of the invention is to provide a device quality, multi-bandgap, monolithic, photovoltaic device with at least one lattice-matched (LM), double-heterostructure (DH) with a bandgap less than 0.74 eV , which is not lattice-matched to an InP substrate, but including a lattice constant transition layer or layers, which is transparent to infrared radiation wavelengths longer than about $1.67\text{ }\mu\text{m}$, positioned somewhere between such lattice-matched (LM), double-heterostructure (DH) and the InP substrate.

[0015] Still another of this invention object is to provide a lattice constant transition layer or layers, which is transparent to infrared (IR) radiation wavelengths longer than about $1.67\text{ }\mu\text{m}$, positioned between two subcells in a multi-band-

gap, monolithic device, where the two subcells are not lattice-matched to each other and at least one of the subcells has a bandgap, which is less than the bandgap of the other subcell and is less than 0.74 eV .

[0016] Another object of the present invention is to provide one or more subcells with bandgaps less than 0.74 eV on an InP substrate.

[0017] Another object of the present invention is to provide a bifacial, monolithic, integrated, module (QI) comprising multiple subcells, at least one subcell of which absorbs and converts radiation wavelengths less than $0.92\text{ }\mu\text{m}$ to electricity.

[0018] Another object of the present invention is to provide a bifacial, monolithic, integrated, module (MIM) comprising multiple subcells, at least one subcell of which absorbs and converts radiation wavelengths less than $1.67\text{ }\mu\text{m}$ to electricity.

[0019] Another specific object of this invention is to provide a method of voltage-matching a plurality of subcell circuits that have subcells with different bandgaps less than or equal to 1.35 eV .

[0020] Additional objects, advantages, and novel features of the invention are set forth in part in the description that follows and will become apparent to those skilled in the art upon examination of the following description and figures or may be learned by practicing the invention. Further, the objects and the advantages of the invention may be realized and attained by means of the instrumentalities and in combinations particularly pointed out in the appended claims.

[0021] To achieve the foregoing and other objects and in accordance with the purposes of the a present invention, as embodied and broadly described herein, a method of this invention may comprise growing one or more subcell(s) that has a lattice constant greater than $5.869\text{ }\text{\AA}$, either alone or in combination with other subcells, on an InP substrate by using a lattice constant transition material between the InP substrate and the subcell(s) that have the lattice constants greater than $6.869\text{ }\text{\AA}$. The lattice constant transition material can be $\text{InAs}_y\text{P}_{1-y}$, where y is graded either continuously or in discrete stepped increments from one (1) to a value at which the $\text{InAs}_y\text{P}_{1-y}$ has a lattice constant that matches the lattice constant of at least one of the subcells with a lattice constant greater than $5.869\text{ }\text{\AA}$. The subcell bandgap is lower than the bandgap of the InP substrate and lower than the bandgap of the $\text{InAs}_y\text{P}_{1-y}$, lattice constant transition material. Additional subcells with even lower bandgaps can also be added, and, if any of such additional subcells has an even greater lattice constant that cannot be matched to the first subcell, then one or more additional lattice constant transition layers can also be added. All of the subcells can be grown on only one side of the substrate (monofacial) or one or more subcells can be grown on the front side of the substrate while one or more other subcells can be grown on the back side (bifacial), using whatever lattice constant transition layers are necessary to accommodate the subcell(s) on each side of the substrate.

[0022] Isolation layers can be used between subcells for independent electrical connection of the subcells, although, in bifacial embodiments, the substrate can be insulating or semi-insulating to serve as an isolation layer. Alternately, tunnel junctions can be used for intra-cell current flow

between subcells. Either the monofacial or bifacial subcell structures can be made in monolithic, integrated, modules (MIMs), which are particularly useful for voltage-matching a plurality of such subcells, although the bifacial embodiments are particularly suitable for such MIM structures and voltage matching. On the other hand, the monofacial embodiments are particularly useful in ultra-thin devices in which the substrate is removed.

[0023] To achieve the foregoing and other objects and in accordance with the purposes of the a present invention, as embodied and broadly described herein, of this invention may also comprise a monolithic, multi-bandgap, photovoltaic converter that has a first subcell comprising GaInAs(P) with a first bandgap and a first lattice constant, a second subcell comprising GaInAs(P) with a second bandgap and a second lattice constant, wherein the second bandgap is less than the first bandgap and the second lattice constant is greater than the first lattice constant, and further, wherein the second lattice constant is equal to a lattice constant of a $\text{InAs}_{1-y}\text{P}_y$ alloy with a bandgap greater than the first bandgap, and a lattice constant transition material positioned between the first subcell and the second subcell, said lattice constant transition material comprising $\text{InAs}_y\text{P}_{1-y}$ alloy with a lattice constant that changes gradually from the first lattice constant to the second lattice constant.

[0024] The first subcell is preferably a lattice-matched, double-heterostructure, comprising homojunction layers of GaInAs(P) clad by $\text{InAs}_y\text{P}_{1-y}$ cladding layers wherein the $\text{InAs}_y\text{P}_{1-y}$ cladding has a value for y in a range of $0 \leq y < 1$, such that the $\text{InAs}_y\text{P}_{1-y}$ cladding layers of the first subcell have a lattice constant equal to the first lattice constant. The second subcell is also preferably a lattice-matched, double-heterostructure comprising homojunction layers of GaInAs(P) clad by $\text{InAs}_y\text{P}_{1-y}$ cladding layers, wherein the $\text{InAs}_y\text{P}_{1-y}$ cladding has a value for y in a range of $0 \leq y < 1$, such that the $\text{InAs}_y\text{P}_{1-y}$ cladding layer of the second subcell have a lattice constant equal to the second lattice constant. Either a tunnel junction or an isolation layer is also positioned between subcells. The InP substrate can be doped with deep acceptor atoms to make the substrate more electrically insulating, and, in bifacial structures, this feature allows the substrate to serve as an electrical isolation between subcells positioned on opposite sides of the substrate.

[0025] A plurality of the monolithic, multi-bandgap, photovoltaic converters can also be grown on a common substrate in a monolithic, integrated, module (MIM), comprising the plurality of monolithic, multi-bandgap, photovoltaic converters, each of which comprises: (i) a first subcell with a first bandgap and a first lattice constant; (ii) a second subcell with a second bandgap and a second lattice constant, wherein the second bandgap is less than the first bandgap and the second lattice constant is greater than the first lattice constant; and (iii) a lattice constant transition material positioned between the first subcell and the second subcell, said lattice constant transition material having a bandgap at least as large as the first bandgap and a lattice constant that changes from the first lattice constant to the second lattice constant. Either monofacial structures or bifacial structures can be grown in MIM configurations, but the bifacial structure is particularly suited to MIM applications. The subcells in MIM structures can be isolated for independent electrical connection, or tunnel junctions can be provided.

Isolated, independently connected, subcells are particularly adapted for voltage-matching in MIM structures. There can be more subcell stacks on one side of the substrate than the other to facilitate such voltage-matching, where the subcells on one side of the substrate are lower bandgap than subcell on the other side of the substrate.

[0026] The substrates can also be removed to provide ultra-thin photovoltaic devices.

BRIEF DESCRIPTION OF THE DRAWINGS

[0027] The accompanying drawings, which are incorporated in and form a part of the specification, illustrate the preferred embodiments of the present invention, and together with the descriptions serve to explain the principles of the invention.

In the drawings:

[0028] **FIG. 1** is a diagrammatic illustration of the general, significant components of a monofacial, inverted, multi-bandgap, monolithic, photovoltaic device with two lattice-matched (LM), double-heterostructure (DH) subcells grown on an InP substrate and series connected, wherein the second subcell, which has a bandgap that is less than the bandgap of the first subcell and is less than about 0.74 eV, is lattice-mismatched (LMM) to the InP substrate, but is grown on a transparent, lattice constant transition layer positioned between the two subcells to accommodate the lattice mismatch;

[0029] **FIG. 2** is a more detailed cross-sectional view of the device of **FIG. 1** showing some of the auxiliary structures and components useful in an embodiment of the device;

[0030] **FIG. 3** is a bandgap versus lattice parameter chart showing bandgap and lattice constant parameters of semiconductor materials used as examples in the embodiments of **FIGS. 1 and 2** according to this invention;

[0031] **FIG. 4** is a detailed cross-sectional view of a monofacial, inverted, multi-bandgap, monolithic, photovoltaic device similar to **FIGS. 1 and 2**, but with the subcells isolated electrically for independent connection;

[0032] **FIG. 5** is a simplified cross-sectional view of a photovoltaic device illustrating more subcells and graded transparent layers according to this invention;

[0033] **FIG. 6** is a diagrammatic illustration of a variation of the monolithic, multi-bandgap, photovoltaic converter similar to **FIG. 1**, but with the lattice constant transition layer positioned between the substrate and the first subcell;

[0034] **FIG. 7** is a bandgap versus lattice parameter chart showing bandgap and lattice constant parameters of the semiconductor materials used as examples in the embodiment of **FIG. 6**;

[0035] **FIG. 8** is a diagrammatic illustration of a variation of the monolithic, multi-bandgap, photovoltaic converter similar to **FIG. 6**, but with an additional lattice constant transition layer and an additional subcell added to the structure;

[0036] **FIG. 9** is a diagrammatic illustration of the bifacial, buried substrate, embodiment of the invention in which subcells are grown epitaxially on opposite faces of the substrate;

[0037] **FIG. 10** is a bandgap versus lattice parameter chart showing bandgap and lattice constant parameters of the semiconductor materials used as examples in the embodiment of **FIGS. 9 and 11**;

[0038] **FIG. 11** is an illustration of a more complex, bifacial, monolithic, multi-bandgap, photovoltaic device according to this invention;

[0039] **FIG. 12** is an illustration of another more complex, bifacial, monolithic, multi-bandgap, photovoltaic device according to this invention that is particularly useful for solar photovoltaic (SPV) converter applications;

[0040] **FIG. 13** is a bandgap versus lattice parameter chart showing bandgap and lattice constant parameters of the semiconductor materials used as examples in the embodiment of **FIG. 12**;

[0041] **FIG. 14** is a cross-sectional view of a bifacial, monolithic integrated module (WM) according to this invention;

[0042] **FIG. 15** is a schematic diagram of an equivalent electric circuit showing the voltage-matched electric subcell circuits of the bifacial MIM in **FIG. 14**;

[0043] **FIG. 16** is a diagrammatic illustration of a monolithic, multi-bandgap, photovoltaic device similar to **FIG. 2**, but with an added stop-etch layer and with the structure mounted on a panel, heat sink, printed circuit board, or other object; and

[0044] **FIG. 17** is a diagrammatic view similar to **FIG. 16**, but with the substrate removed.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0045] A schematic diagram of principle components of a monofacial embodiment of a low-bandgap, monolithic, multi-bandgap (tandem) photovoltaic (PV) converter **10** according to this invention is shown in **FIG. 1** juxtaposed to a corresponding bandgap energy (E_g) profile. The diagram in **FIG. 1** illustrates a cross-section of the PV converter **10** profile in a manner that is conventional in the industry, i.e., not necessarily in proportion to actual sizes, because actual layer thicknesses are too small to illustrate in actual proportions. Additional structural components used to fabricate an example of the PV converter **10** of **FIG. 1** are illustrated in **FIG. 2**, which will be described in more detail below.

[0046] In the monofacial embodiment or approach of this invention illustrated in **FIG. 1**, all of the subcells, for example, subcells **22, 24** in **FIG. 1**, are grown epitaxially on only one side or face **25** of a substrate **26**. Bifacial embodiments or approaches of this invention (not shown in **FIG. 1**), in which subcells are grown epitaxially on opposite sides or faces of a substrate, will be illustrated in other figures and described below.

[0047] The monofacial PV converter **10** illustrated in **FIG. 1** is designed according to this invention with low bandgap, Group III-V semiconductor alloy materials, especially for bandgaps below about 0.74 eV, where ternary GaInAs or AlInAs and quaternary (GaInAsP or AlGaInAs semiconductor alloys do not match the crystal lattice constant of InP substrates **26**. A quick reference to the lattice parameter versus bandgap chart in **FIG. 3** shows that the crystal lattice

constant of InP is about 5.87 Å, as indicated by broken line **12**, while the lowest possible bandgap for a Group III-V alloy with that same lattice constant of 5.87 Å is about 0.74 eV, which is provided by the ternary alloy $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$, as indicated by the broken line **14**. Lattice-matched (LM) materials refers to materials with lattice constants that are either equal or similar enough that when the materials are grown epitaxially, one or the other adjacent each other in a single crystal, any difference in size of crystalline structures of the respective materials is resolved substantially by elastic deformation and not by inelastic relaxation, separation, dislocations, or other undesirable inelastic effects. A lattice-mismatch (LMM) is generally considered to occur when a second crystalline material being grown on a first crystalline material has a lattice constant that is not equal to the lattice constant of the first material and is not lattice-matched as described above. (The terms "lattice parameter" and "lattice constant" mean substantially the same thing and are often used interchangeably in the art and in this description.) Therefore, as shown by broken lines **16, 18** in **FIG. 3**, any Group III-V alloy with a bandgap less than about 0.74 eV will be a lattice-mismatched (LW with an InP substrate. Since a significant feature of this invention is to provide a monolithic, multi-bandgap, photovoltaic (PV) converter with at least one bandgap less than about 0.74 eV, such a lattice-mismatch has to be mitigated in order to avoid the adverse manifestations of lattice strain and stresses caused by such lattice-mismatch, such as dislocations, fractures, wafer bowing, rough surface morphologies, and the like.

[0048] Referring again to the exemplary monofacial, monolithic, multi-bandgap, photovoltaic (PV) converter **10** illustrated in **FIG. 1**, such mitigation of lattice-mismatch between a first Group III-V semiconductor subcell **22** and a second Group III-V semiconductor subcell **24** with a different bandgap below about 0.74 eV is provided by a lattice constant transition layer **20** that: (i) has graded (either distinctly stepped increments or continuously increasing) lattice constants, which span the difference between the respective lattice constants of the first and second subcells **22, 24**; and (ii) is transparent to infrared wavelengths longer than those absorbed by the first subcell **22**. While a transparent lattice constant transition layer **20**, which is graded to have lattice constants that vary continuously from the lattice constant of the first subcell **22** to the lattice constant of the second subcell **24**, is satisfactory for this purpose, a transparent lattice constant transition layer **20** comprising, discrete or stepped changes in lattice constants is preferred. Dislocations in semiconductor crystals are undesirable, because they facilitate recombination of charge carriers (electron hole pairs), which is deleterious to the electrical performance of a semiconductor device.

[0049] A preferred lattice constant transition layer **20** according to this invention is a ternary $\text{InAs}_y\text{P}_{1-y}$ material in which the proportion of As is gradually increased, either continuously or in discrete increments as will be discussed in more detail below. A significant feature of this invention is that the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** is transparent to infrared (IR) radiation wavelengths longer than those absorbed by the ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or optional quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ in the first subcell **22**, so there is virtually no loss of energy, or production of heat, in the lattice constant transition layer **20**.

[0050] The monofacial, monolithic, multi-bandgap, photovoltaic (PV) converter **10** illustrated in **FIG. 1** has an inverted structure with the active subcell layers **22**, **24**, transparent lattice constant transition layer **20**, and preferred or optional other layers (shown in **FIG. 2**, which will be described in more detail below), grown epitaxially on one side **25** of a substrate **26**. This structure is called inverted, because the radiation energy R enters the converter **10** through the substrate **26**, so it has to be transmitted through the substrate **26** before being absorbed and converted to electricity by the subcells **22**, **24**. Therefore, as will be explained in more detail below, the substrate **26** has to be transparent to all the incident radiation R so that none of the incident radiation R is absorbed and thermalized or lost as heat before it reaches the subcells **22**, **24**, where it can be converted to electricity. Likewise, the incident radiation R transmitted by the substrate **26** should encounter the subcell **22** with the highest bandgap before it encounters the subcell **24** with the lowest bandgap, because higher bandgap subcells will absorb only the higher energy radiation (higher frequency and shorter wavelength) and convert it to electricity while transmitting unabsorbed, lower energy radiation (lower frequency and longer wavelength). Therefore, any of the remaining lower energy incident radiation R that is not absorbed and converted to electricity by the higher bandgap, first subcell **22** will be transmitted to the lower bandgap, second subcell **24**, where at least some, if not all, of it can be absorbed and converted to electricity. The amount of the remaining, lower energy, incident radiation that can be absorbed and converted to electricity by the second subcell **24** will depend on the particular bandgap of the subcell **24** and the particular radiation wavelengths in such remaining, lower energy, incident radiation. Of course, the lattice constant transition layer **20** has to be transparent to, and not absorptive of, the remaining, lower energy, incident radiation that is not absorbed by the first subcell **22** so that all of such remaining, lower energy, incident radiation can reach the second subcell **24**. Further, as will be explained in more detail below, additional subcells with different bandgaps can also be included in order to optimize absorption and conversion of various incident radiation energy levels or bands to electricity.

[0051] The back-surface reflector (BSR) or other spectral control element **28**, which can also function as an electrode contact or lateral current flow element, is deposited on the second subcell **24**, as will be described in more detail below. A spectral control layer **30** would usually be deposited on the front side **27** of the substrate **26** either to minimize reflection of incident radiation R , e.g., an anti-reflective coating (ARC), as is well-known to persons skilled in the art, especially for SPV converter applications, or to reflect all incident radiation R with wavelengths lower than those absorbable by the lowest bandgap subcell **24**, especially for the TPV converter applications used for generating electricity and not heat. These structures and functions will be discussed in more detail below. The terms front and back, as used in this description, relate to the direction in which incident radiation propagates into and through a device or layers in a device. Therefore, radiation is incident first on the front of a device or layer and propagates toward the back of the device or layer.

[0052] In converter **10**, the preferred substrate **26** comprises InP, because, as explained above: (i) InP has a lattice constant (5.87 Å), which is one of a few commercially

available bulk, single crystal materials that are close to the lattice constants of Group III-V alloys that have bandgaps less than 0.74 eV (for absorbing infrared radiation wavelengths longer than about 1.67 μm); (ii) InP has a bandgap of about 1.35 eV (see **FIGS. 1 and 3**), thus does not absorb, and is transparent to, infrared radiation wavelengths longer than 0.93 μm; (iii) InP can be doped to be highly resistive and thereby function as an insulator or semi-insulator, as described in more detail below; (iv) Lattice-mismatch between InP and $\text{InAs}_y\text{P}_{1-y}$ or GaInAs(P) materials, which have lower bandgaps than InP and are used extensively in this invention as explained below, is in compression rather than tension, so lattice-mismatched $\text{InAs}_y\text{P}_{1-y}$ or GaInAs(P) grown on InP are not so likely to develop fissures or crack; and (v) Bulk InP crystals are less expensive than InAs and GaSb. Therefore, the InP substrate **26** is suitable in a monofacial, inverted PV converter **10** structure for any application in which the incident radiation R to be converted to electric energy has 0.93 μm and longer wavelengths, such as thermophotovoltaic (TPV) cells and some solar photovoltaic (SPV) cells as well as infrared detector devices and multi-bandgap infrared (IR) LID's. However, InP is susceptible to free carrier absorption of energy, which results in energy being lost in the form of heat. To minimize or prevent such free carrier absorption of energy, the InP substrate can be doped with deep acceptor atoms, such as iron (Fe) or chromium (Cr), to pin the Fermi level deeply within the bandgap, which makes the InP act more like an insulator or semi-insulator.

[0053] Subject to accommodations for a contact, buffer, cladding, optical control elements, and/or other auxiliary layers (not shown in **FIG. 1**), which will be described in more detail below, the first subcell **22** is deposited on substrate **26** with a bandgap E_{g1} designed to absorb the first desired wavelength or frequency band of the incident radiation R and convert such absorbed radiation to electricity. In the preferred embodiment, this first subcell **22** is a lattice-matched (LM), double-heterostructure (DH), $\text{InP}/\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{InP}/\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ with a desired bandgap E_{g1} , somewhere in a range that is less than the 1.35 eV bandgap of the InP substrate **26**. This first subcell **22** in **FIG. 1** is preferably grown epitaxially and is lattice-matched to the InP substrate **26**. Please note that "lattice-matched" when used in the context of a "lattice-matched, double-heterostructure" for a subcell generally means that the semiconductor materials within the subcell itself are lattice-matched to each other. Therefore, a subcell can be a lattice-matched, double-heterostructure, while such subcell may or may not be lattice-matched to a substrate or to another layer or material in the device that is not part of the subcell.

[0054] A particularly preferred subcell **22** lattice-matched to the InP substrate **26** comprises $\text{InP}/\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ with a bandgap of about 0.74 eV, because, as shown by the lines **12**, **14** in **FIG. 3**, $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ is the lowest bandgap Group III-V alloy that has the same lattice constant as the InP substrate **26**. Therefore, a $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** can make a transition from the lattice constant of InP (about 5.87 Å) to a lattice constant matching a $\text{Ga}_x\text{In}_{1-x}\text{As}$ alloy with a bandgap as low as about 0.52 eV, i.e., to a lattice constant as high as about 5.968 Å (see lines **15**, **17** in **FIG. 3**), and still be transparent to all infrared wavelengths that are longer than those absorbed by the 0.74 eV bandgap of the first subcell **22** (see line **14** in **FIG. 3**). Of course, the desired bandgap for the second subcell **24** could

also be anywhere between 0.74 eV and 0.52 eV, in which case the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** can be formulated to provide a back surface with whatever lattice constant is needed on which to grow the desired $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ that has such a desired bandgap.

[0055] An example second subcell **24** for use in conjunction with a first subcell **22** described above, therefore, can be a quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ or a ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ with a bandgap as low as 0.52 eV. A particular preferred example second cell **24** comprises a lattice-matched, double-heterostructure $\text{InAs}_y\text{P}_{1-y}/\text{Ga}_x\text{In}_{1-x}\text{As}$ with a bandgap **19** of 0.55 eV and a lattice constant **21** of about 5.952 Å.

[0056] The lattice constant transition layer **20**, as mentioned above, gradually makes a transition from the lattice constant of the first subcell **22** to the lattice constant of the second subcell **24**, preferably while remaining substantially transparent to all infrared radiation wavelengths that are not absorbed by the first subcell **22**, as illustrated by the example PV converter **10** of **FIG. 1**. In that specific example, the first subcell **22** has a bandgap (E_{g1}) **14** of about 0.74 eV and lattice constant of about 5.87 Å, while the second subcell **24** has a bandgap (E_{g2}) **19** of about 0.55 eV and lattice constant of about 5.952 Å, as explained above. Therefore, the lattice constant transition layer **20** has to make a transition of lattice constants gradually from about 5.87 Å to about 5.952 Å. As shown in **FIGS. 1 and 3**, adding As to InP to produce $\text{InAs}_y\text{P}_{1-y}$ increases the lattice constant of the $\text{InAs}_y\text{P}_{1-y}$ from about 5.87 Å to about 5.952 Å without decreasing the bandgap of the $\text{InAs}_y\text{P}_{1-y}$ to a level below the 0.74 eV $\text{Ga}_x\text{In}_{1-x}\text{As}$ ($x=0.47$) of the first subcell **22**. Therefore, the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** remains transparent to all of the remaining infrared radiation **R** that is not absorbed in the first subcell **22** so that it allows all of such remaining infrared radiation to reach the second subcell **24**.

[0057] As also mentioned above, such graded transition of the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** from the lattice constant of the first subcell **22** (e.g., 5.87 Å) to the lattice constant of the second subcell **24** (e.g., 5.952 Å) can be done by increasing the proportion of As on a gradual continuous basis or, preferably, in incremental discrete steps as illustrated by line **23** in the bandgap chart in **FIG. 1**. The stepped lattice constant transition **23** illustrated in **FIG. 1** seems to provide better experimental results than gradual, continuous grading.

[0058] A more specific example of the monofacial PV converter **10** of **FIG. 1** with auxiliary layers useful in actual implementation of such a device for high quality performance characteristics is shown diagrammatically in **FIG. 2**. Again, the thicknesses of the various layers are not illustrated in actual size or thickness proportions in relation to each other.

[0059] The substrate **26** is preferably InP doped with a deep acceptor element, such as Fe, (sometimes denoted as InP:Fe or as (Fe) InP) to trap electrons and thereby suppress or prevent free carrier absorption. The substrate **26** can be semi-insulating for isolation or p-type for conducting, as desired for a particular application, and other layers and components are designated as either n-type or p-type, accordingly to provide the n/p junctions **34**, **48** needed to convert the incident radiation **R** to electricity in the subcells **22**, **24**, respectively. However, p/n junctions would also work, as is understood by persons skilled in the art, so these

n-type and p-type designations could be reversed by substituting donor dopants, for acceptor dopants and vice versa, which would be considered equivalent for purposes of the invention.

[0060] While the subcells **22**, **24** can be simple shallow homojunctions, this invention is particularly conducive to the more efficient, lattice-matched, double-heterostructure subcells **22**, **24** illustrated in **FIG. 2**. Specifically, the example first subcell **22** illustrated in **FIG. 2** has a n/p homojunction **34** formed by a p-type $\text{Ga}_x\text{In}_{1-x}\text{As}$ base layer **38** grown epitaxially on an n-type $\text{Ga}_x\text{In}_{1-x}\text{As}$ emitter layer **36**, all of which is sandwiched between front and back cladding layers **40**, **42** of n-type InP and p-type InP, respectively. The InP in the cladding layers **40**, **42** is a different compound than the $\text{Ga}_x\text{In}_{1-x}\text{As}$ in the homojunction layers **36**, **38**, but it has the same lattice constant as the $\text{Ga}_x\text{In}_{1-x}\text{As}$. Therefore, the first subcell **22** is a lattice-matched, double-heterostructure. The cladding layers **40**, **42** passivate dangling bonds at terminated $\text{Ga}_x\text{In}_{1-x}\text{As}$ crystal structures at the front of layer **36** and at the rear of layer **38**, which otherwise function, at least to some extent, as unwanted recombination sites for minority carriers in the $\text{Ga}_x\text{In}_{1-x}\text{As}$. Also, the band offsets between the InP (bandgap of 1.35 eV) and the $\text{Ga}_x\text{In}_{1-x}\text{As}$ (bandgap of 0.74 eV in this example) repel minority carriers away from the InP/ $\text{Ga}_x\text{In}_{1-x}\text{As}$ interface, which further reduces such unwanted recombination of minority carriers. Therefore, a clad subcell, such as the lattice-matched (LM), double-heterostructure (DH), InP/ $\text{Ga}_{0.77}\text{In}_{0.53}\text{As}$ or optional InP/ $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ subcell **22** described above, is more efficient in converting radiant energy to electricity than non-clad subcells. This passivation and confinement of minority carriers by the cladding layers **40**, **42** is possible in the monolithic, multi-bandgap PV converter structures of this invention, because the cladding material, InP, has the same lattice constant (5.869 Å) as, and a higher bandgap than, the homojunction cell material, $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ ($\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ is lattice-matched to InP when $y \approx 2.2x$).

[0061] The second subcell **24** is also preferably a lattice-matched, double-heterostructure comprising a homojunction **48** formed by n-type and p-type layers **50**, **52** of either ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$, but its lattice constant is larger than the lattice constant of the first subcell **22** and of the InP substrate **26**, as explained above. Consequently, the second subcell **24** is lattice-mismatched (LMM) in relation to the InP substrate **26** and first cell **22**, and it cannot be clad with InP. However, as explained above in relation to the lattice constant transition layer **20**, $\text{InAs}_y\text{P}_{1-y}$ can be formulated to have the same lattice constant as the $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ homojunction layers **50**, **52**. Therefore, the passivation and confinement cladding layers **54**, **56** of the second subcell **24** comprise $\text{InAs}_y\text{P}_{1-y}$ that is lattice-matched to the $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ homojunction layers **50**, **52** to form the lattice-matched, double-heterostructure of that subcell **24**.

[0062] Prior to growing the first subcell **22**, a buffer layer **32** of n-InP about 300 Å thick is deposited first on a surface **25** of the InP substrate **26** to begin an epitaxial InP growth layer, if needed. If the InP substrate **26** is doped with a deep acceptor to be electrically insulating or semi-insulating as explained above, then provisions have to be made for a front electrical contact **29** and a conductive layer **33** for accommodating lateral flow of current produced by the subcells **22**,

24 to or from the contact **29**. Such a conductive layer **33** could be, for example, heavily n-doped InP or any other heavily doped material that is lattice-matched to the InP substrate **26** as well as transparent to all radiation wavelengths that are transmitted by the InP substrate **26**. Then, the first subcell **22** comprising the lattice-matched, double-heterostructure of n-Ga_{0.47}In_{0.53}As/p-Ga_{0.47}In_{0.53}As homo-junction layers **36**, **38** between the two cladding layers **40**, **42** of n-InP and p-InP, respectively. As is well-known in the art, semiconductor materials are usually doped with small amounts of elements from an adjacent group of the Periodic Table of the Elements to provide the majority carriers. Therefore, an appropriate donor dopant for the Group III-V semiconductor alloy used in this invention can be, for example, sulphur (S) from Group VI, and appropriate acceptor dopant can be, for example, zinc (Zn) from Group II. The InP buffer layer **32** grown epitaxially on the InP substrate **26** in this example is preferably heavily (10^{-18} - 10^{-20} cm⁻³) n-type doped with sulfur (S). Then, the InP front cladding layer **40** is grown epitaxially on the buffer layer **32** to a thickness of about 0.01-0.1 μm, but it is more lightly doped n-type with, for example, S to a dopant level of about 10^{16} - 10^{20} cm⁻³. The Ga_{0.47}In_{0.53}As homo-junction layers **36**, **38**, which lattice-match the InP substrate **26**, buffer layer **32**, and cladding layer **40**, are grown epitaxially. Therefore, the bandgap of the first subcell **22** is about 0.74 eV, which absorbs portions of the incident radiation R with wavelengths of about 1.67 μm and less, as explained above, although other values of x and other formulations would also work in this invention. Lattice-matching quaternary Ga In_{1-x}As_yP_{1-y} is also possible. The emitter layer **36** of subcell **22** is grown epitaxially to a thickness, preferably in a range of about 0.1-10 μm, and is doped n-type with, for example, S to a dopant level in a range of about 10^{16} - 10^{20} cm⁻³. The base layer **38** is then grown epitaxially to a thickness of about 0.01-10 μm, and doped p-type to create the n/p junction **34**. The p-type dopant, such as Zn in this example, is at a dopant level of about 10^{16} - 10^{20} cm⁻³. To complete the lattice-matched, double-heterostructure, first subcell **22**, the back cladding layer **42** is grown epitaxially on the base layer **38** to a thickness, preferably of about 0.01-0.1 μm, and is p-type doped, for example, with Zn, to a dopant level of about 10^{16} - 10^{20} cm⁻³. Each of the buffer layer **32**, conductive layer **33**, and/or cladding layer **40** can all serve any one or more of these functions, individually or together. Therefore, instead of the three distinct layers **32**, **33**, **40** shown in FIG. 2, one or two layers could serve those same functions, if desired.

[0063] The subcells **22**, **24** can be electrically connected together in series, or they can be electrically isolated from each other, as will be described in more detail below. For a monolithic, multi-bandgap, PV device **10** in which the subcells **22**, **24** are series connected, a tunnel junction comprising a layer **44** of heavily p-doped Ga_{0.47}In_{0.53}As or Ga_xIn_{1-x}As_yP_{1-y} followed by a heavily n-doped Ga_{0.47}In_{0.53}As or Ga_xIn_{1-x}As_yP_{1-y} layer **46** is deposited and grown epitaxially on the back cladding layer **42** of the first subcell **22** to facilitate low-resistive current flow in an ohmic manner between the first subcell **22** and the second subcell **24**. Again, if the preferred homo-junction layers **36**, **38** of subcell **22** comprise Ga_{0.47}In_{0.53}As, as discussed above, then it is also preferable that x=0.47 in the Ga_xIn_{1-x}As of the tunnel junction layers **44**, **46** in order to lattice-match them with the underlaying InP and Ga_{0.47}In_{0.53}As layers

described above, although other values of x and other formulations would also work in this invention. Tunnel junctions are well-known in the art, but, for purposes of this invention, each tunnel junction layer **44**, **46** can be about 0.01-0.1 μm thick and doped to a level of about 10^{-18} - 10^{-20} cm⁻³. Alternative monolithic, multi-bandgap, PV converters with the subcells **22**, **24** isolated electrically from each other will be described below.

[0064] The transparent, lattice constant transition layer **20** of this invention comprising gradually increasing lattice constants is deposited and grown epitaxially on the Ga_xIn_{1-x}As or Ga_xIn_{1-x}As_yP_{1-y} tunnel junction layer **46** in order to make the transition from the lattice constant of the InP substrate **26** and intervening layers described above to a lattice constant that matches the Ga_xIn_{1-x}As or Ga_xIn_{1-x}As_yP_{1-y} of the second subcell **24**, which is formulated to provide a desired bandgap E_{g2}, as described above. According to this invention, the bandgap E_{g2} is less than the bandgap E_{g1} of the first subcell **24** in the monofacial, inverted PV converter embodiment **10** of FIGS. 1 and 2 for the reasons explained above. InAs_yP_{1-y} is used for this lattice constant transition layer **20**, because it can be formulated to lattice match the lower bandgap E_{g2} of the Ga_xIn_{1-x}As of Ga_xIn_{1-x}As_yP_{1-y} of the second subcell **24**, while it also remains transparent to the longer infrared radiation R wavelengths that are not absorbed by the higher bandgap E_{g1} material of the first subcell **22**. This feature is important in order to ensure that substantially all of the longer wavelength radiation R, which is not absorbed in the first subcell **22**, reaches the second subcell **24**.

[0065] To form the lattice constant transition layer **20**, (As) is added to a growing layer of InP in increasing proportions so that the proportion of arsenic (As) increases in the resulting InAs_yP_{1-y} material, which increases the lattice constant of the InAs_yP_{1-y}. As mentioned above, this change can be accomplished continuously, but it is preferred that the changes in proportions be made in incremental steps. In the InAs_yP_{1-y} of the lattice constant transition layer **20** of this example PV converter **10**, y varies from zero (where it lattice-matches the Ga_{0.47}In_{0.53}As of the first subcell **22**) to about 0.44, where it lattice-matches to the Ga_xIn_{1-x}As of the second subcell **24**, in which x≈0.26 and the consequent bandgap E_{g2} is about 0.55 eV. That example bandgap E_{g2}=0.55 eV enables the second subcell **24** to absorb infrared radiation R with wavelengths up to about 2.25 μm. In general, the lattice-matching condition of Ga_xIn_{1-x}As to InAs_yP_{1-y} occurs when the crystal lattices of the epi-layers are fully relaxed, which is where y≈2.143x.

[0066] Of course, as mentioned above, the Ga_xIn_{1-x}As of the second subcell **24** can have x equal to some other value for a different desired bandgap E_{g2}, and the y in the InAs_yP_{1-y} of the lattice constant transition layer **20** can be varied or customized accordingly to make the necessary corresponding lattice constant transition. Also, as mentioned above, either or both of the subcell materials and/or the lattice constant transition materials could be quaternary Ga In_{1-x}As_yP_{1-y} with the x and y values customized to desired bandgaps and lattice constants within the physical constraints illustrated by the bandgap vs. lattice parameter chart of FIG. 3.

[0067] As explained above and shown in FIG. 2, the second subcell **24** comprises a lattice-matched, double-

heterostructure of n-type $\text{InAs}_y\text{P}_{1-y}$ front cladding layer **54**, n-type $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ emitter layer **50** and p-type $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ base **52** to form the homojunction **48**, and p-type $\text{InAs}_y\text{P}_{1-y}$ back cladding layer **56**, all grown epitaxially on the lattice constant transition layer **20**. As explained above for the first subcell **22**, the cladding layers **54**, **56** confine and passivate the front and back surfaces of the homojunction layers **50**, **52** to prevent recombination of minority carriers. The thicknesses and doping levels of the subcell **24** layers **50**, **52**, **54**, **56** can be similar to those described above for the first subcell **22**.

[0068] A back surface spectral control element **28**, which can also be used as a back electrical contact layer, can be deposited onto the back cladding layer **56** or onto an additional contacting layer (not shown) disposed atop the back cladding layer **56**. The nature of the back surface spectral element **28** may depend on the application of the device **10**. For example, if the device **10** is a SPV or TVP, the sole purpose of which is to convert radiation to electricity, then the back surface spectral element may comprise a reflector to reflect any remaining, unabsorbed radiation from the second subcell **24** back through the subcells **24**, **22**. Some of such reflected radiation could be absorbed in this second pass through the subcells, but most of it will continue propagating all the way back through the substrate **26** toward whatever radiator source (not shown) produces the incident radiation **R** in the first place. Adding such unabsorbed, back-reflected, radiation energy back into the radiator source may enable the radiator source to use such back-reflected energy in the production of new incident radiation **R** for conversion to electricity in the converter **10**. This feature is particularly appropriate for TPV configurations of converter **10** that are applied to convert infrared radiation **R** produced by a blackbody infrared radiation source (not shown) to electricity. Any radiation reflected back into the blackbody radiator adds energy to the blackbody radiator and thereby tends to raise the temperature of the blackbody radiator, which causes the blackbody radiator to produce more blackbody infrared radiation for the converter **10**. Therefore, such back-reflected radiation can help the blackbody radiator to produce more incident radiation **R** for the device **10** without having to use so much fuel.

[0069] On the other hand, some devices **10** are used both for producing electricity and gathering heat for an environment. In those applications, the back surface spectral control element **28** may be a material that is transparent to remaining infrared radiation that is not absorbed by the second subcell **24** so that such remaining infrared can be used as heat someplace behind the device **10**.

[0070] If the layer **28** is a back surface reflector (BSR), there can be several advantages to designing the last (second) subcell **24** with only one-half of its normal thickness, i.e., one-half the thickness that would be required for full absorption of radiation in the wavelengths that correspond to the bandgap, because any unabsorbed radiation will be reflected by the BSR **28** back into the last subcell **24**. The advantages of this kind of design include an enhanced photocurrent, higher operating voltage, and thinner structure that requires less growth time and provides easier device processing. Regardless of its optical characteristics, as described above, the layer **28** can also be a back surface electrical contact. Therefore, it is preferably electrically conductive. An optional, additional metallic contact **45** can

also be used on the conductive layer **28** for making an electrical connection, if desired.

[0071] The design of the front surface spectral control element **30** on the front surface **27** of the substrate **26** may also depend on usage of the device **10**. For example, if the device **10** is to be used only for producing electricity from blackbody radiation, the front surface spectral control element **30** may be a coating layer that transmits only shorter wavelength incident radiation **R** that can be absorbed and converted to electricity by the subcells **22**, **24** and that reflects all longer wavelength incident radiation **R** back into the blackbody radiator (not shown) for recovery and re-use. On the other hand, if the device **10** is to be used both for producing electricity and heat for an environment, then the front surface spectral control element **30** may be an antireflective coating to enhance transmission of all the incident radiation **R** into the device **10**.

[0072] As mentioned above, the monofacial PV converter **10** described above and illustrated in **FIGS. 1 and 2** is configured with the subcells **22**, **24** connected electrically in series facilitated by the tunnel junction layers **44**, **46**. An alternate embodiment monofacial, low-bandgap, monolithic, multi-bandgap, PV converter **110** is shown in **FIG. 4** with much the same first subcell **22**, second subcell **24**, and substrate **26** structures and materials described above for the PV converter **10**, but with the subcells **22**, **24** isolated electrically from each other. The electrical isolation instrumentality in the PV converter **110** is illustrated as a discrete electrical isolation layer **39** positioned between the first subcell **22** and the second subcell **24**. However, such electrical isolation function could be incorporated into other components, such as into the graded lattice constant transition layer **20**, as will be explained below.

[0073] There are a number of reasons that such electrical isolation of the subcells **22**, **24** may be desirable in some applications. For example, as mentioned above, current flow through series connected subcells **22**, **24** is limited by the lowest photocurrent producing subcell. Therefore, for series connected subcells, a number of subcell design factors, such as bandgaps, thicknesses, doping concentrations, and the like are used to optimize the operating characteristics of the series connected subcells **22**, **24**, so that electric power production from the tandem combination is maximized. In some designs and applications, however, more efficient conversion of radiant energy to electricity can be accomplished by extracting electric power from the individual subcells **22**, **24** separately or independently, or, in some applications, to design the subcells **22**, **24** for voltage matching. Such voltage matching techniques with subcells in other devices will be discussed in more detail below in relation to monolithic, integrated module (MIM) devices.

[0074] To isolate the subcells **22**, **24** electrically from each other, there has to be some material between them that inhibits electric current flow between the subcells **22**, **24**. However, such electrical isolation material cannot interfere with radiation transmission from one subcell **22** to the other subcell **24**. In the PV converter **110** of **FIG. 4**, a discrete isolation layer **39** is shown positioned between the first subcell **22** and the lattice constant transition layer **20**, although it could be positioned between the lattice constant transition layer **20** and the second subcell **24**.

[0075] An isolation material for isolation layer **39** can be fabricated in a number of ways. One such approach is to

fabricate the isolation layer **39** with a high-resistivity semiconductor material that has a high enough bandgap to be transparent to the longer wavelength radiation that is not absorbed in the first subcell **22** and is being transmitted to the second subcell **24**. Another such approach is to form the isolation layer **39** as an isolation diode, which, of course, must also be transparent to the radiation being transmitted from the first subcell **22** to the second subcell **24**. Also, such high-resistivity material or isolation diode material has to be lattice-matched to the materials in front and in back of it, which, in the position of isolation layer **39** shown in **FIG. 4**, has to be lattice-matched to the first cell **22** and substrate **26**.

[0076] As mentioned above, InP doped with a deep acceptor element, such as Fe or Cr, is a high-resistivity material and has a bandgap (1.35 eV) that makes it transparent to all radiation that is not absorbed by the first subcell **22**. It is also lattice-matched to the InP substrate **26** and to the ternary $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ of the first subcell **22**. Therefore, deep acceptor-doped InP can be used as the high-resistivity, isolation layer **39**. Such deep acceptor-doping of other lattice-matched semiconductor materials, such as ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$, quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$, or even AlGaInAs in some circumstances, with high enough bandgaps to be transparent to the radiation being transmitted, could also be used to provide suitable high-resistivity materials for the isolation layer **39**.

[0077] An isolation diode for isolation layer **39** can be provided by one or more doped junctions, such as an n-p junction or n-p-n junctions with high enough reverse-bias breakdown characteristics to prevent current flow between the subcells **22**, **24**. Again, lattice-matched semiconductor materials, such as InP, $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$, or even AlGaInAs, can be doped to provide an isolation diode structure for isolation layer **39**.

[0078] While a discrete isolation layer **39** is shown in the PV converter **110** of **FIG. 4**, it is possible to dope the lattice constant transition layer **20** to also function as an isolation layer between the two subcells **22**, **24**. The $\text{InAs}_y\text{P}_{1-y}$ of the lattice constant transition layer **20** can also be doped with a deep acceptor element, such as Fe or Cr, to make it highly-resistive, or discrete sublayers of the $\text{InAs}_y\text{P}_{1-y}$ can be n-p or n-p-n doped to form an isolation diode structure.

[0079] Of course, with each subcell **22**, **24** isolated electrically from each other, some additional provisions for electrical contacts are necessary to extract electric power independently from each subcell **22**, **24**. Persons skilled in the art will be able to design myriad structures for such contacts, once they understand the principles of this invention. The example additional contacts **27**, **42** for this purpose are shown fabricated on lateral current flow layers **39**, **41** respectively. Such lateral current flow layers **39**, **41** are lattice-matched to their respective subcells **22**, **24** and must be transparent to radiation being transmitted from the first subcell **22** to the second subcell **24**. Heavily doped $\text{GaIn}_{1-x}\text{As}_y\text{P}_{1-y}$ with $0 \leq x \leq 1$ and $0 \leq y \leq 1$ as necessary for lattice matching and transparency can be used for these lateral current flow layers **39**, **41**.

[0080] While the series connected PV converter **10** and isolated or independently connected PV converter **110** described above are illustrated with only two subcells **22**, **24**, and only one lattice constant transition layer **20** between them, any number of subcells with any number of lattice

constant transition layers can be included in a monolithic, multi-bandgap, optoelectronic device according to this invention. To illustrate this principle, a more complex monolithic, multi-bandgap, PV converter **112** is illustrated in **FIG. 5**.

[0081] In the PV converter **112**, an arbitrary number (five) subcells **114**, **116**, **118**, **120**, **122** are illustrated with arbitrary bandgaps $E_{g1} > E_{g2} > E_{g3} > E_{g4} > E_{g5}$. The substrate **124** is InP, and the first and second subcells **114**, **116** both have bandgaps E_{g1} , E_{g2} that can be ternary GaInAs or quaternary GaInAsP and are lattice-matched to the InP substrate **124** (see, e.g., lines **130**, **12**, **14** in **FIG. 3**). These first and second subcells **114**, **116** are preferably both lattice-matched (LM), double-heterostructures (DH) with junctions comprising n-type and p-type ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{GaIn}_{1-x}\text{As}_y\text{P}_{1-y}$ clad with n-type and p-type layers of InP, as described above for the other PV converter embodiment **10**. The third and fourth subcells **118**, **120** are LM, DH ternary or quaternary GaInAs(P) with bandgaps E_{g3} , E_{g4} that can be lattice-matched to each other, but not to the InP substrate (see, e.g., lines **12**, **132**, **134**, **136** in **FIG. 3**). Therefore, a lattice constant transition layer **126** of graded $\text{InAs}_y\text{P}_{1-y}$ is used to make the transition from the second subcell **116** to the lattice-mismatched subcell **118**. A fifth LM, DH subcell **122** of ternary or quaternary GaInAs(P) has a bandgap E_{g5} that cannot be lattice-matched to the fourth subcell **120**. Therefore, another lattice constant transition layer **128** is provided to make the transition from the fourth subcell **120** to the lattice-mismatched fifth subcell **122**.

[0082] As mentioned above, the numbers and combinations of subcells and lattice constant transition layers as well as the specific example bandgap values shown in the PV converter **112** of **FIG. 5** are selected arbitrarily to illustrate the principles of this invention. The only requirement is that the incident radiation reaches the subcells in order of decreasing bandgaps, so that the shorter wavelength radiation is absorbed and converted to electricity by higher bandgap subcells that will transmit unabsorbed, longer wavelength radiation to the next subcell(s). Other details, such as buffer layers, tunnel junction or isolation layers, contacts, optic control layers, etc., for fabricating a working PV converter can be similar to those described above for either the series connected subcell embodiments **10** of **FIGS. 1 and 2** or the independently connected subcell embodiment **110** of **FIG. 4**.

[0083] Now, as illustrated in another alternative inverted, monofacial, multi-bandgap, PV converter **140** in **FIG. 6**, the positions of the transparent lattice constant transition layer **20** and the first subcell **22** positions can be reversed from their positions shown in the **FIG. 1** embodiment **10**. Specifically, the lattice constant transition layer **20** can be grown epitaxially on the InP substrate **26** by gradually adding more and more As to the growing $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20**, as described above, until a desired lattice constant is attained for a desired $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{GaIn}_{1-x}\text{As}_y\text{P}_{1-y}$ semiconductor material with a desired bandgap to be grown on the InP substrate **26**. As explained above, the desired bandgap is chosen for absorbing and converting infrared radiation R of a desired wavelength or frequency band to electricity.

[0084] For example, but not for limitation, if it is desired to have the first subcell **22** in the PV converter **140** of **FIG.**

6 absorb and convert infrared radiation of at most 1.77 μm wavelength to electricity and to have the second subcell 24 absorb and convert infrared radiation in the range of 1.77 μm to 2.14 μm to electricity, the first subcell 22 would need a bandgap of about 0.70 eV, and the second subcell 24 would need a bandgap of about 0.58 eV. Therefore, an appropriate lattice constant transition layer 20 can be $\text{InAs}_{1-y}\text{P}_y$ with a gradually increasing proportion of As until an $\text{InAs}_y\text{P}_{1-y}$ semiconductor material having a lattice constant of about 5.94 \AA and a bandgap of about 0.90 eV, as illustrated in FIG. 7 by broken lines 60, 62, respectively. Therefore, a lattice constant transition layer 20 with those criteria will provide a transition of lattice constant 12 from the 5.87 \AA of the InP substrate to the 5.94 \AA of the terminal $\text{InAs}_y\text{P}_{1-y}$ material in the lattice constant transition layer 20. With a terminal bandgap of 0.90 eV, the lattice constant transition layer 20 is transparent to infrared radiation (IR) with wavelengths longer than about 1.38 μm .

[0085] The first subcell 22 with the example desired 0.70 eV bandgap can then be a lattice-matched (LM), double-heterostructure (DH) of, for example, $\text{InAs}_{1-y}\text{P}_y/\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ with the same lattice constant, 5.94 \AA , as the terminal $\text{InAs}_y\text{P}_{1-y}$ of the lattice constant transition layer 20 (see broken line 60 in FIG. 7). The $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ base of the subcell 22 can be formulated to have the desired bandgap of 0.70 eV (see broken line 64 in FIG. 7 and corresponding line 64 in FIG. 6), so it will absorb and convert 1.77 μm and shorter radiation R to electricity, but it will transmit and not absorb virtually all the incident infrared radiation (IR) that is longer wavelength than 1.77 μm . Such formulation of appropriate proportions of Group III-V elements in quaternary alloys, such as the $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ in this example, to achieve certain desired bandgap characteristics, such as the 0.70 eV in this example, is well-known and within the capabilities of persons skilled in the art, thus need not be explained in detail here to enable persons skilled in the art to understand and practice this invention.

[0086] The second subcell 24 in this example can be formulated with a lattice-matched (LM), double-heterostructure (DH) with the same lattice constant of 5.94 \AA as the first subcell 22 and still have a bandgap as low as 0.58 eV (see broken lines 60, 66 in FIG. 7). Therefore, if it is desired to formulate the second cell 24 to absorb and convert as much of the infrared radiation R, which passed through the first cell 22, as possible, and still be lattice-matched to the first cell 22, then $\text{Ga}_x\text{In}_{1-x}\text{As}$ with a bandgap of 0.58 eV can be used. This example second cell 24, with its 0.58 eV bandgap 66, would absorb and convert infrared radiation R of 2.14 μm wavelength and shorter to electricity. Of course, other auxiliary layers, such as buffers, cladding, tunnel junction or isolation layers, contacts, and antireflective or optical control layers can be used to make this structure a functioning device, as explained above, and as would be understood by persons skilled in the art.

[0087] While two lattice-mismatched (LM) subcells 22, 24 and one lattice constant transition layer 20 in any of a variety of ternary and/or quaternary formulations comprising Ga, In, As, and/or P provide wide flexibility in low bandgap designs for efficient absorption and conversion of desired infrared radiation wavelength bands to electricity, this invention also extends to three, four, five, or more subcells and bandgaps with one or more lattice constant transition layers, as needed. For example, there is no theo-

retical limit to the number of quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ formulations for different bandgaps between lines 13 and 14 (0.74 eV to 1.35 eV) in FIG. 3, which can be lattice-matched on line 12 (5.869 \AA). Likewise, there is no theoretical limit to the number of quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ formulations for different bandgaps between lines 14 and 17 (0.74 eV to 0.52 eV) in FIG. 3, which can be lattice-matched on line 15 (5.968 \AA). Further, there is no theoretical limit to the number of ternary and quaternary Ga, In, As, and/or P formulations for possible lattice constants between those of InP (5.869 \AA) and InAs (6.059 \AA), lines 12 and 23, respectively, in FIG. 3.

[0088] In other words, every ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ with a bandgap in the range between 0.74 eV and 0.355 eV (lines 14 and 31 in FIG. 3) can be lattice-matched to some higher bandgap $\text{InAs}_y\text{P}_{1-y}$, which is transparent to at least some infrared radiation that can be absorbed and converted to electricity by such ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ DH subcells. Further, any $\text{InAs}_y\text{P}_{1-y}$, which is used to make a transition between the lattice constant of such ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ to a larger lattice constant, also has a higher bandgap than such $\text{Ga}_x\text{In}_{1-x}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ thus is transparent to at least some infrared radiation that can be absorbed and converted to electricity by such ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ DH subcells. This invention utilized these characteristics of $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ ($0 \leq x \leq 1$, $0 \leq y \leq 1$) for the design, formulation, and fabrication of low bandgap (less than 1.35 eV, and preferably less than 0.74 eV), monolithic, multi-bandgap, photovoltaic converters, as described above, and as will be further described below.

[0089] This invention, as mentioned above, also extends to low bandgap, monolithic, multi-bandgap PV converters with more than one lattice constant transition layer. For example, referring again to FIG. 6, one or more additional subcells with even lower bandgap(s) than the 0.58 eV bandgap of the second subcell 24 can be grown on top of subcell 24. Such an example PV converter 150 with three subcells 22, 24, 72 is illustrated diagrammatically in FIG. 8. This example three-bandgap PV converter 150 is illustrated for convenience with the same substrate 26, first lattice constant transition layer 20, first subcell 22, and second subcell 24 as the two-bandgap embodiment 140 of FIG. 6, but it has a second lattice constant transition layer 70 positioned between the second subcell 24 and a third subcell 72.

[0090] As was explained above in relation to the inverted tandem (two-subcell) PV converter 140 in FIG. 6, the InP substrate 26 and the first lattice constant transition layer 20 are transparent to infrared radiation of longer wavelengths than can be absorbed by their respective bandgap characteristics. Therefore, in the examples of FIGS. 6 and 8, the lowest bandgap of the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer 20 is 0.90 eV (see line 62 in FIG. 7), which, of course, is also lower than the 1.35 eV bandgap of the InP substrate. Therefore, infrared radiation of wavelengths longer than 1.38 μm pass through both the InP substrate 26 and the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer 20. The first subcell 22, with its 0.70 eV bandgap, absorbs and converts infrared radiation R wavelengths of 1.77 μm and shorter to electricity, and it transmits infrared radiation R wavelengths longer than 1.77 μm to the second subcell 24. The 0.58 eV

bandgap of the $\text{Ga}_x\text{In}_{1-x}\text{As}$ second subcell **24** enables it to absorb and convert infrared radiation wavelengths of 2.14 μm and shorter to electricity, while infrared radiation R wavelengths greater than 2.14 μm pass through the second subcell **24**.

[0091] The energy in the infrared radiation R wavelengths longer than 2.14 μm , which are not absorbed in the second subcell **24** would be wasted in the PV converter **140** embodiment of **FIG. 6**, but adding one or more additional subcells, such as subcell **72** in the three-bandgap PV converter **150** in **FIG. 8**, can capture and convert significant amounts of that energy to electricity. However, as shown by line **60** in **FIG. 7**, there is no ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ or quaternary $\text{Ga}_{1-x}\text{In}_x\text{As}_y\text{P}_{1-y}$ with a bandgap below 0.58 eV (line **66**) that has the same lattice constant (5.94 Å) as the first and second subcells **22**, **24** in the example. Therefore, a second lattice constant transition layer **70** comprising $\text{InAs}_y\text{P}_{1-y}$ with gradually increasing proportions of arsenic (As) is positioned between the second subcell **24** and the third subcell **72**. The initial $\text{InAs}_y\text{P}_{1-y}$ in the second lattice constant transition layer **70** is formulated to have a bandgap of 0.90 eV, so that it has the same lattice constant (5.94 Å) as the second subcell **24**. Then, the subsequent $\text{InAs}_y\text{P}_{1-y}$ grown for the second lattice constant transition layer **70** decreases in bandgap in incremental steps or gradually toward, and preferably to, the same bandgap **66** as the second subcell **24**, which is 0.58 eV in the example described above. At that bandgap level, the $\text{InAs}_y\text{P}_{1-y}$ is still transparent to all of the infrared radiation R wavelengths that pass through the second subcell **24**. Therefore, the $\text{InAs}_y\text{P}_{1-y}$ second lattice constant transition layer **70** does not absorb or interfere with the infrared radiation R that has to reach the third subcell **72**, yet it provides a transition from the lattice constant of the second subcell **24** (line **60** in **FIG. 7**) to a new, larger lattice constant (line **74** in **FIG. 7**) for the third subcell **72**. In this example, the new lattice constant of 6.02 Å will match a ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ with a bandgap of 0.45 eV or quaternary $\text{Ga}_{1-x}\text{In}_x\text{As}_y\text{P}_{1-y}$ with a bandgap anywhere along line **94** between 0.58 eV and 0.45 eV, as shown in **FIG. 7**. Therefore, if the third subcell **74** in **FIG. 8** comprises, for example, $\text{Ga}_x\text{In}_{1-x}\text{As}$ formulated to have a bandgap of 0.45 eV, it will absorb and convert infrared radiation in wavelengths of 2.76 μm and shorter to electricity.

[0092] Again, as explained above for the first lattice constant transition layer **20**, the gradual change of lattice constant in the second lattice constant transition layer **70** can be graded gradually or in discrete stepped increments, the latter of which is preferred. Also, while not shown in detail in **FIG. 8**, the $\text{Ga}_x\text{In}_{1-x}\text{As}$ n/p junction in the third subcell **72** is preferably clad front and back with cladding layers of $\text{InAs}_y\text{P}_{1-y}$, which have the same lattice constant as the $\text{Ga}_x\text{In}_{1-x}\text{As}$ of the third subcell **74**, to form the third subcell **72** as a lattice-matched (LM), double-heterostructure (DH) subcell. Other auxiliary layers mentioned above can also be provided.

[0093] All of the PV converter embodiments **10**, **110**, **140**, **150** described above have been monofacial, i.e., grown on only one face of the substrate. A very significant feature of this invention is that it can also be implemented in bifacial or buried substrate structures, as illustrated diagrammatically by the example low bandgap, monolithic, multi-bandgap, PV converter **80** in **FIG. 9**. Essentially, in the PV converter **80** of **FIG. 9**, a lattice-matched (LM) first subcell

82 is grown epitaxially on a front surface **83** of a InP substrate **84**, and a lattice-mismatched (LMM) second subcell **86** with an intervening lattice constant transition layer **90** is grown epitaxially on a back surface **85** of the substrate **84**. An antireflective coating (ARC) **88** on the front surface **81** of the first subcell **82** and a back surface reflector (BSR) **89** on the back surface **87** of the second subcell **86** are shown, but they can be other optical control layer materials, as described above for PV converter **10**. Again, other auxiliary features, layers, and components that may be used to implement an actual device, such as buffers, contacts, deep acceptor doping of the InP substrate, tunnel junctions or isolation layers, and the like are not shown separately in **FIG. 9** in order to avoid unnecessary clutter and repetition, but persons skilled in the art can use the information herein to understand, design, and fabricate such components in PV converter devices according to this invention. Cladding layers (not shown separately in **FIG. 9**) can be used as part of the subcells **82**, **86** for lattice-matched (LM), double-heterostructure (DH) implementations of the subcells, as described above in relation to the PV converter **10**. Also, while only one lattice constant transition layer **90** and two subcells **82**, **86** with specific example bandgaps and lattice constants are illustrated in the example PV converter **80** in **FIG. 9**, other numbers of subcells, lattice constant transition layers, bandgaps, and/or lattice constants can also be used according to this invention, as explained above.

[0094] In the example bifacial PV converter **80** in **FIG. 9**, the first subcell **82** is lattice-matched to the InP substrate **84** (line **12** in **FIG. 10**). In this example, subcell **82** is formulated to have the lowest possible bandgap that can be lattice-matched to the InP substrate **84**, which is the ternary $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ with a bandgap of 0.74 eV (line **14** in **FIG. 8**), although many other formulations could be illustrated, as explained above. If it is desired to use a lattice-matched, double-heterostructure for the first subcell **82**, the $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ n/p junction material can be clad on both sides with lattice-matched, epitaxially grown, InP cladding layers, as described above.

[0095] In this example, any incident radiation R of wavelengths shorter than 1.67 μm will be absorbed by the 0.74 eV bandgap $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ in the first subcell **82**, and longer wavelength infrared radiation R will pass through the first subcell **82**. The InP substrate **84**, which has a much higher bandgap of 1.35 eV (line **13** in **FIG. 10**) is also transparent to any of such longer wavelength infrared radiation that passes through the first subcell **82**. Therefore, in order for the second subcell **86** to absorb and convert any of such longer wavelength infrared radiation R to electricity, it has to have a bandgap E_{g2} that is less than the bandgap E_{g1} of the first subcell **82**, i.e., less than 0.74 eV in this example. There are many considerations for selecting the lower bandgap for the second subcell **86**, such as targeting the concentrations of the infrared radiation in various wavelength or frequency bands, conversion efficiencies, and any additional subcells (not shown in **FIG. 9**). However, any bandgap less than 0.74 eV requires a $\text{Ga}_x\text{In}_{1-y}\text{As}$ or $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ that has a larger lattice constant than the InP substrate **84**, so it would not be possible for it to be lattice-matched to the InP substrate **84**. Therefore, a lattice constant transition layer **90** is needed, and it is preferred that the second subcell **86** should have a lattice constant that allows the $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **90** to be transparent to the longer infrared radiation wavelengths, which are not absorbed by, and pass

through, the first subcell **82**. In this example, a bandgap E_{g2} for the second subcell **86** is selected to be 0.55 eV, which can be provided with ternary $Ga_xIn_{1-x}As$ having a lattice constant of 5.972 Å, as illustrated by lines **92** and **93** in **FIG. 10**. However, a quaternary $Ga_xIn_{1-x}As_yP_{1-y}$ with a slightly larger lattice constant could also be used for the same bandgap and still be able to accommodate a transparent lattice constant transition layer **90**.

[0096] As shown by lines **12**, **93** in **FIG. 10**, the ternary $Ga_xIn_{1-x}As$ with its lattice constant of 5.972 Å requires the lattice constant transition layer **90** to make the transition between the lattice constant of the InP substrate (line **12**) to the 5.972 Å lattice constant (line **93**). As also illustrated in **FIG. 10**, increasing the proportion of As in an $InAs_yP_{1-y}$ lattice constant transition layer **90** reaches this 5.972 Å constant without its bandgap ever decreasing below about 0.82 eV (line **94**), which is still higher than the 0.74 eV bandgap (line **14**) of the first subcell **82**. Therefore, any infrared radiation R that is not absorbed by, thus passes through, the first subcell **82** will also not be absorbed by the $InAs_yP_{1-y}$ in the lattice constant transition layer **90**. Consequently, such infrared radiation will reach the second subcell **86**, where at least some of it can be absorbed and converted to electricity.

[0097] If the substrate **84** is doped with a deep acceptor element, such as Fe or Cr, to be an insulator or semi-insulator, as explained above, then the first subcell **82** and the second subcell **86** are electrically isolated from each other. Therefore, electricity has to be extracted independently from each subcell **82**, **86**, as described above for the electrically isolated subcells **22**, **24** of the PV converter device **110** in **FIG. 4**. This feature has advantages, such as in voltage-matching of multiple, series and/or parallel interconnected PV converter subcell circuits, especially in monolithic, integrated module (MIM) devices, as will be described in more detail below. In situations where the substrate **86** cannot be made as an insulator or semi-insulator, a separate isolation layer (not shown in **FIG. 9**) can be positioned anywhere between the two subcells **82**, **86**. For example, an isolation layer can be grown on either the front surface **83** or back surface **85** of the substrate **84** or between the lattice constant transition layer **90** and the second subcell **86**. Such an isolation layer can be made as desired above in relation to the isolation layer **39** in **FIG. 4**, i.e., a lattice-matched material that is transparent to wavelengths of radiation not absorbed by the first subcell **82** and doped to make the material highly-resistive or to create a diode barrier to the flow of electric current. Of course, there could also be applications that involve a series connection of subcell **82** on the front side of the substrate **84** with the subcell **86** on the back side of the substrate **84**, in which case the substrate **84** should be doped to conduct current, and appropriate tunnel junction layers may be added to allow current flow as explained above in relation to the PV converter device **10** of **FIG. 2**.

[0098] As explained above, any of a wide range of ternary or quaternary $GaInAs(P)$ alloys with any combinations of bandgaps and lattice constants can be used in subcells of tandem (more than one subcell) stacks of low-bandgap, monolithic, multi-bandgap, optoelectronic devices according to this invention. Another example of such combinations is illustrated in the alternate example bifacial PV converter device **160** in **FIG. 11**, where two lattice mismatched

(LMM) subcells **162**, **164** are grown on the front side **165** of an InP substrate **166** and another, even lower bandgap, subcell **168** is grown on the back side **167** of the substrate **166**. For purposes of this illustration, but not for limitation, the first subcell **162** is shown as LM, DH, quaternary $Ga_xIn_{1-x}As_yP_{1-y}$ with a bandgap of 1.1 eV, but lattice-matched to a LM, DH, ternary $Ga_xIn_{1-x}As$ second subcell **164** instead of to the InP substrate **166**, as shown by lines **170**, **172**, **174** in **FIG. 10**. Therefore, a lattice constant transition layer **176**, such as graded $InAs_yP_{1-y}$ is needed between the InP substrate **166** and the second subcell **164**, as shown in **FIG. 11**, to make the transition between the 5.869 Å lattice constant of the InP substrate **166** (line **12** in **FIG. 10**) and the 5.905 Å lattice constant of the ternary $Ga_xIn_{1-x}As$ of the second subcell **164** (line **174** in **FIG. 10**). Either an isolation layer **178**, as shown in **FIG. 11**, or a tunnel junction, can be positioned between the first subcell **162** and the second subcell **164**, depending on whether it is desired to connect the subcells **162**, **164** independently or in series, as explained above.

[0099] The third subcell **168** in the PV converter **160** in **FIG. 11** has an even lower bandgap, for example 0.55 eV, to absorb and convert longer wavelength radiation transmitted through the first and second subcells **162**, **164** to electricity, according to the principles explained above. Such a third subcell **168** can be, for example, a LM, DH, ternary $Ga_xIn_{1-x}As$ with a 0.55 eV bandgap, which is not lattice-matched to the InP substrate **166**, as shown by lines **12**, **93** in **FIG. 10**. Therefore, another lattice constant transition layer **180**, such as graded $InAs_yP_{1-y}$ is needed between the InP substrate **166** and the third subcell **168** to make the transition between the 5.869 Å lattice constant of InP (line **12** in **FIG. 10**) and the 5.952 Å lattice constant of the ternary $Ga_xIn_{1-x}As$ (line **93** in **FIG. 10**) of the third subcell **168**.

[0100] Again, if the InP substrate **166** is deep acceptor doped to be an insulator or semi-insulator, the third subcell **168** will be electrically isolated from the first and second subcells **162**, **164** and can be connected independently to other PV converters or subcells, such as in a MIM structure (described below). Otherwise, a separate isolation layer (not shown in **FIG. 11**) may be needed somewhere between the substrate **166** and the third subcell **168**, as explained above. Again, contacts, conductive layers, buffers, optical control layers, and the like, are not shown in **FIG. 11**, but can be provided as explained above for other embodiments.

[0101] Another interesting variation of the bifacial embodiment PV converter **80** in **FIG. 9** is the use of epitaxially grown InP for the higher bandgap first subcell **82** instead of a ternary or quaternary $GaInAs(P)$. This variation, with an appropriate lower bandgap (lower than the 1.35 eV bandgap of InP) second subcell **86**, can operate as a highly efficient, stand-alone, tandem solar cell. This bifacial or buried substrate configuration of the PV converter **80** is particularly advantageous for use as a solar cell, because the buried InP substrate **84** is not in a position to block or absorb shorter wavelength solar radiation before it reaches the first subcell **82**.

[0102] An illustration of this principle in a slightly more complex bifacial, monolithic, multi-bandgap, solar photovoltaic (SPV) converter device **190**, multiples of which can also be incorporated into a MIM structure, is shown in **FIG. 12**. In this example SPV device **190**, there are three lattice-

matched subcells **192**, **194**, **196** grown on the front side **197** of a InP substrate **198** and two, lower bandgap, lattice-mismatched (LMM) subcells **200**, **202** grown on the back side **199** of the substrate **198**. Again, isolation and/or tunnel junction layers **204**, **206** can be included between front-side subcells **192**, **194** and/or between subcells **194**, **196**, respectively, for either independent electrical connection or series electrical connection, respectively, within the SPV device **190**, as explained above. Similarly, either an isolation layer **208** or a tunnel junction can be provided between the back-side subcells **200**, **202**, depending on whether it is desired to electrically connect them independently or in series within the SPV device **190**.

[0103] In the example SPV device **190**, the first subcell **192** is shown as a LM, DH, InP subcell with a bandgap of 1.35 eV, while the bandgaps of the second and third subcells **194**, **196** have lower bandgaps, e.g., 1.0 eV, LM, DH, quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$ for the second subcell **194** and 0.74 eV, LM, DH, ternary $\text{Ga}_{0.47}\text{In}_{0.53}\text{As}$ for the third subcell **196**, which is the lowest bandgap GaInAs that can be lattice-matched to the InP substrate **198** (see lines **13**, **14**, **210** in **FIG. 13**). Since all the front-side subcells **192**, **194**, **196** are lattice-matched (line **12** in **FIG. 13**) to the InP substrate **198**, no lattice constant transition layer is needed on the front side of the substrate **198**.

[0104] Again, the variations of conductive or highly-resistive substrate **198**, isolation and/or tunnel junction layers, electrical contacts, buffer layers, optical control layers, more or fewer subcells, different bandgaps, and the like, as described above for other embodiments, are also applicable to the SPV device **190** described above.

[0105] Also, AlInAs in slightly higher bandgaps than the 1.35 eV bandgap of the InP can also be lattice-matched to InP, so a first subcell of such AlInAs lattice-matched to the InP substrate could also be used as part of a bifacial, monolithic, multi-bandgap, PV converter of this invention. Of course, Ga could be added to produce AlGaInAs, if a slightly lower bandgap than AlInAs is desired for either the first subcell or a subsequent subcell of a bifacial PV converter of this invention.

[0106] The PV converters described above can be used alone or in combinations with myriad other devices. For example, any of the PV converters, especially the SPV device **190**, but also, PV converters **10**, **110**, **112**, **140**, **150**, **80**, **160**, can be used for the bottom cell device in a mechanical stack of higher bandgap (higher than the 1.35 eV bandgap of InP) PV converters, such as GaAs based PV converters, in solar cell and other applications. Such other, higher bandgap, PV converters (not shown) can selectively absorb and convert shorter wavelength solar energy to electricity, while the lower bandgap PV converters, e.g., PV converters **10**, **110**, **112**, **150**, **80**, **160**, **190**, absorb and convert longer wavelength solar radiation to electricity.

[0107] As mentioned above, the bifacial, monolithic, multi-bandgap, optoelectronic devices of this invention, for example, the bifacial PV converters **80**, **160**, **190** shown in **FIGS. 9**, **11**, and **12** and described above, as well as myriad variations of such bifacial configurations, are particularly adaptable to use in monolithic, integrated modules (MIMs). An example MIM PV converter device **230** with a plurality of bifacial, monolithic, multi-bandgap, photovoltaic converters **190** of **FIG. 12** grown on a single substrate **198** is

shown in **FIG. 14**. Essentially, all of the PV converter subcell stacks **190** are grown in unison on the common substrate **198**, and then they are separated into a plurality of individual subcell stacks **190'** by etching away or otherwise removing material to form isolation trenches **232** between the front-side subcell stacks **190'** and to form isolation trenches **234** between the back-side subcell stacks **190''**. Then, various conductors **236**, **238**, **240**, **242**, **244**, **246**, **248**, **250**, **252**, **254**, **256**, **258**, **260**, and others are added in various electrical connection patterns to interconnect the subcells together, as will be described in more detail below. The spaces between the conductors are filled with insulator material, such as silicon nitride or any of a variety of other suitable insulator materials.

[0108] In the bifacial MIM PV converter device **230** illustrated in **FIG. 14**, there are twice as many, albeit smaller, back-side subcell stacks **190''** as front-face subcell stacks **190'**. Further, there can be any desired ratio of back-side subcell stacks **190''** to front-side subcell stacks **190'**. The ratio of two back-side subcell stacks **190''** to one front-side subcell stack **190'** shown in **FIG. 14** is only an example.

[0109] One advantage of being able to have different numbers of subcell stacks **190'**, **190''** on front and back of the substrate **198** is more flexibility to design voltage-matched subcell circuits. A schematic diagram of an equivalent electrical circuit corresponding to the example voltage-matched subcell circuits **262**, **264**, **266**, **270**, **272** of the MIM **230** of **FIG. 14** is shown in **FIG. 15**. According to fundamental electrical principles, a circuit comprising a plurality of subcells connected in parallel will have an output voltage equal to the subcell output voltage, but current from the parallel connected subcells add. Conversely, a circuit comprising a plurality of subcells connected in series will have a current output equal to the subcell output current, but the output voltages of the series connected subcells add. Therefore, connecting a plurality of higher voltage subcells together in parallel can build current as output voltage remains constant, while connecting a plurality of lower voltage subcells together in series can boost the voltage output of the subcell circuit to the level of the higher voltage subcell circuit. Also, higher bandgap subcells produce higher voltage than lower bandgap subcells. Therefore, if, for example, the voltage output of each of the lower bandgap subcell stacks **190''** in **FIG. 14** is half as much as the voltage output of each of the higher bandgap subcell stacks **190'**, and if all the higher bandgap subcell stacks **190'** are connected in series with each other while all the lower bandgap subcell stacks **190''** are connected in series with each other, then the total voltage output of the back-side subcell stacks **190''** circuits **270**, **272** would equal the total voltage output of the front-side subcell stacks **190'** circuits **262**, **264**, **266**, because there are twice as many low voltage subcell stacks **190''** as there are higher voltage subcell stacks **190'**.

[0110] However, the front-side subcells **192**, **194**, **196** of the front-side stacks **190'** can be connected in myriad combinations of series and/or parallel electrical connections, as illustrated in **FIGS. 14** and **15** to create voltage-matched subcell circuits **262**, **264**, **266**. The same goes for the back-side subcells **200**, **202** of the back-side stacks **190''** to create voltage-matched subcell circuits **270**, **272**. Such electrical connection options are facilitated by the isolation

layers **204**, **206**, **208** and highly-resistive substrate **198**, as described above. Additional options can be provided by tunnel junctions instead of isolation layers or even making the substrate **198** conductive rather than resistive for intra-subcell stack series connections, as explained above.

[0111] To illustrate several series and parallel connection options, the bifacial MIM PV converter device **230** in **FIGS. 14 and 16**, is shown, for example, with all of its highest bandgap, thus highest voltage, subcells **192** connected together in parallel to form the subcell circuit **262**. The next highest bandgap, thus next highest voltage, subcells **194** are connected together in a combination of parallel **244**, **246** and series **247** connections to form a subcell circuit **264** that is voltage-matched to the subcell circuit **262**. The subcells **196**, which are the lowest bandgap, thus lowest voltage, of the subcells on the front side of the substrate **198**, are shown in this example illustration of **FIGS. 14 and 15**, as all being connected in series in subcell circuit **266** by conductors **242** to add their voltages in order to match the output voltage of subcell circuit **266** to the output voltages of the subcell circuits **262**, **264**. These parallel and series-connected subcell circuits **262**, **264**, **266** are connected in parallel to each other at conductors **236**, **238**, **240** and at **236'**, **238'**, **240'** to add their respective current outputs.

[0112] The back-side subcells **200**, **202** are even lower voltage than the front-side subcells **196**, but there are more of them than the front-side subcells **192**, **194**, **196**, so the back-side voltage can be matched to the front-side voltage. In the example of **FIGS. 14 and 15**, the lowest voltage subcells **202** are connected together in series in the subcell circuit **272** by conductors **260** to add their voltages in order to match the output voltage of subcell circuit **272** to the output voltage of the parallel connected **256**, **258**, higher voltage subcells **200** in the subcell circuit **270**. Then, the subcell circuit **272** is connected in parallel to the subcell circuit **270** by conductors **252**, **254** and **252'**, **254'** to add their respective current outputs.

[0113] Finally, the front-side subcell circuits **262**, **264**, **266** are connected in parallel to the back-side subcell circuits **270**, **272** at terminal contacts **258**, **258'** to add their respective current outputs. Therefore, the bifacial MIM PV converter **230** can be connected electrically to other devices or loads via the two terminal contacts **256**, **258**, which is a very desirable feature of this invention. Other MIM structures, circuit connections, and advantages can be made according to these principles within this scope of this invention. For example, but not for limitation, the monofacial, monolithic, LM, DH, multi-bandgap, PV converters described above can also be incorporated into MIM structures (not shown), although the bifacial embodiments described above have the advantage of using the substrate **198** as a built-in isolation structure between subcells on the front side and subcells on the back side, as explained above.

[0114] Any of the PV converter embodiments **10**, **110**, **150**, described above and shown in **FIGS. 1, 2, 4**, and **6** can be modified to provide an ultra-thin, monolithic, multi-bandgap, PV converter by fabricating it in such a way as to enable removal of the InP substrate **26**. For example, as shown in **FIG. 16**, a monolithic, multi-bandgap (tandem), PV converter **100** is fabricated much the same as the PV converter **10** in **FIG. 2** on an InP substrate **26**, except that a stop-etch layer **98** is added between the buffer layer **32** and

the front cladding layer **40** of the first subcell **22**. The stop-etch layer **98** can be, for example, n-Ga_{0.47}In_{0.53}As with the same lattice constant as the InP substrate **26**, so that the subsequent layers of the first and second subcells **22**, **24**, tunnel junction **44**, **46**, (or isolation layer for independently connected subcells) and lattice constant transition layer **20** can be grown epitaxially, as described above.

[0115] The purpose of the stop-etch layer **98** is to enable the InP substrate **26** and buffer layer **32** to be removed by etching or other selective chemical removal to create an ultra-thin, monolithic, multi-bandgap (tandem) PV converter **100** without etching or damaging any of the first subcell **22**. After the several layers of the structure in **FIG. 16** are grown epitaxially on the InP substrate **26**, the structure **100** is top-mounted on another object **102**, such as a solar panel, heat sink, printed circuit board, or other useful platform. Then the substrate **26** and buffer layer **32** are removed by etching or other selective chemical removal, leaving the ultra-thin, monolithic, multi-bandgap, PV converter **100** mounted on the object **102**, as shown in **FIG. 17**. The stop-etch layer **98** can be an electrically conductive material, so it can also serve as a contact layer. If desired, part of such a conductive stop-etch layer **98** can be removed by etching or other selective chemical removal with a different chemical in which it is soluble to leave a grid pattern, which would be useful if the material of layer **98** is not transparent to the incident radiation **R**.

[0116] Mounting the PV converter **100** on the object **102** can be accomplished with a suitable adhesive or by any other suitable mounting mechanism. An anti-reflective coating **97** can be added to reduce reflection of incident radiation, or layer **97** can be any other optical control material for purposes described above for the PV converter **10**.

[0117] This ultra-thin, monolithic, multi-bandgap, PV converter **100** enables this device to be used as a solar cell, because elimination of the InP substrate **26** allows all of the incident solar radiation **SR** to reach the subcells **22**, **24**, which can convert it to electricity. Otherwise, the InP substrate **26**, which has a bandgap of 1.35 eV, would absorb large amounts of solar radiation **SR** in wavelengths shorter than 0.93 μm , before such solar radiation **SR** could reach the first subcell **22**. There is no n/p junction in the substrate **22**, and it cannot convert radiant energy to electricity, so any solar energy absorbed by the substrate **26** would be thermalized and wasted as heat.

[0118] Even without the InP substrate, however, there could be significant production of heat in the PV converter **100**, when it is used as a solar cell, because there is a substantial amount of energy in higher frequencies (shorter wavelengths) of the solar spectrum, where wavelengths are substantially shorter than the longest wavelength that can be absorbed by the first subcell **22**. Therefore, there is significant thermalization of excess energy that is not needed for carriers to transcend the bandgap E_{g1} of the first subcell **22**, thus a significant production of heat that must be dissipated from the PV converter **100**. However, the PV converter **100** is ultra-thin and has no thick substrate, so heat can flow through the PV converter **100** is substantially one-dimensional, and it can flow quickly and easily to the back surface **104**. If the object **102** on which the PV converter **100** is mounted is a good heat sink, i.e., good thermal conductivity and sufficient mass and/or surface area to conduct heat away

from the PV converter **100**, the combination provides very good thermal management and minimizes heat build-up in the PV converter **100**.

[0119] The ultra-thin, monolithic, multi-bandgap, PV converter **100** can also be grown in a polycrystalline form on less expensive substrates, such as graphite, which is amorphous and does not impose a lattice constant on the first subcell **22**, or in single-crystal form on compliant substrate or bonded substrate systems, which provide a lattice constant match to accommodate epitaxial growth. A typical compliant substrate may be made, for example, with an inexpensive substrate material, such as silicon, and with an amorphous oxide of the substrate material followed by a layer of perovskite oxide. Therefore, a first subcell **22** of InP, GaInAs, or GaInAsP will grow with its natural lattice constant. Such first subcell **22** can then be followed by a $\text{InAs}_y\text{P}_{1-y}$ lattice constant transition layer **20** and another, lower bandgap, second subcell **24**, as described above. Then, the resulting ultra-thin PV converter **100** is mounted on another object **102** and the compliant substrate is removed.

[0120] Compliant substrates can also be used on any of the monofacial PV converter embodiments **10**, **110**, **112**, **140**, **150** described above, and they can possibly be used for the bifacial embodiments **80**, **160**, **190**, **230**. Possible uses of compliant substrates in the embodiments of this invention depend on the transparency and other properties of the compliant substrate materials and systems being considered and/or applied.

[0121] While the description of this invention has focused primarily on photovoltaic converters, persons skilled in the art know that other optoelectronic devices, such as photodetectors and light-emitting diodes (LEDs) are very similar in structure, physics, and materials to PV converters with some minor variations in doping and the like. For example, photodetectors can be the same materials and structures as the PV converters described above, but perhaps more lightly-doped for sensitivity rather than power production. On the other hand LED's can also be much the same structures and materials, but perhaps more heavily-doped to shorten recombination time, thus radiative lifetime to produce light instead of power. Therefore, this invention also applies to photodetectors and LEDs with structures, apparatus, compositions of matter, articles of manufacture, and improvements as described above for PV converters.

[0122] Since these and numerous other modifications and combinations of the above-described method and embodiments will readily occur to those skilled in the art, it is not desired to limit the invention to the exact construction and process shown and described above. For example, accordingly, resort may be made to all suitable modifications and equivalents that fall within the scope of the invention as defined by the claims which follow. The words "comprise," "comprises," "comprising," "include," "including," and "includes" when used in this specification and in the following claims are intended to specify the presence of stated features or steps, but they do not preclude the presence or addition of one or more other features, steps, or groups thereof. Also, GaInAs(P) is used as a shorthand, generic term that includes any ternary $\text{Ga}_x\text{In}_{1-x}\text{As}$ and/or quaternary $\text{Ga}_x\text{In}_{1-x}\text{As}_y\text{P}_{1-y}$, and similar notation conventions apply to AlGaInAs(P).

1. A monolithic, multi-bandgap, photovoltaic converter, comprising:

a first subcell comprising GaInAs(P) with a first bandgap and a first lattice constant;

a second subcell comprising GaInAs(P) with a second bandgap and a second lattice constant, wherein the second bandgap is less than the first bandgap and the second lattice constant is greater than the first lattice constant, and further, wherein the second lattice constant is equal to a lattice constant of a $\text{InAs}_y\text{P}_{1-y}$ alloy with a bandgap greater than the first bandgap; and

a lattice constant transition material positioned between the first subcell and the second subcell, said lattice constant transition material comprising $\text{InAs}_y\text{P}_{1-y}$ alloy with a lattice constant that changes gradually from the first lattice constant to the second lattice constant.

2. The monolithic, multi-bandgap, photovoltaic converter of claim 1, wherein the lattice constant transition material is grown epitaxially on the first subcell with a gradually increasing value for y.

3. The monolithic, multi-bandgap, photovoltaic converter of claim w, wherein the second subcell is grown epitaxially on the lattice constant transition material.

4. The monolithic, multi-bandgap, photovoltaic converter of claim 1, wherein the first subcell is a lattice-matched, double-heterostructure, comprising homojunction layers of GaInAs(P) clad by $\text{InAs}_y\text{P}_{1-y}$ cladding layers wherein the $\text{InAs}_y\text{P}_{1-y}$ cladding has a value for y in a range of $0 \leq y < 1$, such that the $\text{InAs}_y\text{P}_{1-y}$ cladding layers of the first subcell have a lattice constant equal to the first lattice constant.

5. The monolithic, multi-bandgap, photovoltaic converter of claim 4, wherein the second subcell is a lattice-matched, double-heterostructure comprising homojunction layers of GaInAs(P) clad by $\text{InAs}_y\text{P}_{1-y}$ cladding layers, wherein the $\text{InAs}_y\text{P}_{1-y}$ cladding has a value for y in a range of $0 \leq y < 1$, such that the $\text{InAs}_y\text{P}_{1-y}$ cladding layer of the second subcell have a lattice constant equal to the second lattice constant.

6. The monolithic, multi-bandgap, photovoltaic converter of claim 1, including a InP substrate, and wherein the first subcell is grown epitaxially on the InP substrate.

7. The monolithic, multi-bandgap, photovoltaic converter of claim 1, including a tunnel junction positioned between the first subcell and the second subcell.

8. The monolithic, multi-bandgap, photovoltaic converter of claim 7, wherein the tunnel junction is positioned between the first subcell and the lattice constant transition layer.

9. The monolithic, multi-bandgap, photovoltaic converter of claim 1, wherein the lattice constant of the lattice constant transition material is graded.

10. The monolithic, multi-bandgap, photovoltaic converter of claim 1, wherein the lattice constant of the lattice constant transition material changes in steps of multiple, discrete, increments.

11. The monolithic, multi-bandgap, photovoltaic converter of claim 1, wherein the first bandgap is 0.74 eV.

12. The monolithic, multi-bandgap, photovoltaic converter of claim 6, wherein the first subcell is grown epitaxially on a front surface of the InP substrate, the lattice constant transition layer is grown epitaxially on a back surface of the InP substrate, and the second subcell is grown epitaxially on the lattice constant transition layer.

13. The monolithic, multi-bandgap, photovoltaic converter of claim 12, wherein the InP substrate is doped with

deep acceptor atoms to make the substrate more electrically insulating than InP, which is not doped with deep acceptor atoms.

14. The monolithic, multi-bandgap, photovoltaic converter of claim 1, including a InP substrate positioned between the first subcell and the second subcell.

15. The monolithic, multi-bandgap, photovoltaic converter of claim 14, wherein the InP substrate is positioned between the first subcell and the lattice constant transition material.

16. The monolithic, multi-bandgap, photovoltaic converter of claim 1, including an isolation layer positioned between the first subcell and the second subcell.

17. The monolithic, multi-bandgap, photovoltaic converter of claim 16, wherein the isolation layer is positioned between the first subcell and the lattice constant transition material.

18. The monolithic, multi-bandgap, photovoltaic converter of claim 16, including a InP substrate positioned between the first subcell and the second subcell.

19. The monolithic, multi-bandgap, photovoltaic converter of claim 18, wherein the InP substrate is positioned between the second subcell and the isolation layer.

20. The monolithic, multi-bandgap, photovoltaic converter of claim 18, wherein the InP substrate is positioned between the first subcell and the isolation layer.

21. The monolithic, multi-bandgap, photovoltaic converter of claim 14, including a first isolation layer positioned between the InP substrate and the first subcell, and including a second isolation layer positioned between the InP substrate and the second subcell.

22. A monolithic, multi-bandgap, photovoltaic converter, comprising:

- a InP substrate with a substrate lattice constant;
- a first subcell comprising GaInAs(P) with a first bandgap and a first lattice constant, wherein the first lattice constant is greater than the substrate lattice constant;
- a lattice constant transition material positioned between the InP substrate and the first subcell, said lattice constant transition material comprising $\text{InAs}_y\text{P}_{1-y}$ alloy with a lattice constant that changes from the substrate lattice constant to the first lattice constant; and
- a second subcell comprising GaInAs(P) positioned behind the first subcell, said GaInAs(P) of the second cell having a second bandgap, which is less than the first bandgap, and a second lattice constant.

23. The monolithic, multi-bandgap, photovoltaic converter of claim 22, wherein the second lattice constant is equal to the first lattice constant.

24. The monolithic, multi-bandgap, photovoltaic converter of claim 23, including a tunnel junction positioned between the first subcell and the second subcell.

25. The monolithic, multi-bandgap, photovoltaic converter of claim 23, including an isolation layer positioned between the first subcell and the second subcell.

26. The monolithic, multi-bandgap, photovoltaic converter of claim 22, wherein the first subcell is a lattice-matched, double-heterostructure comprising homojunction layers of GaInAs(P) clad by InP cladding layers.

27. The monolithic, multi-bandgap, photovoltaic converter of claim 22, wherein the second subcell is a lattice-matched, double-heterostructure comprising homojunction

layers of GaInAs(P) clad by $\text{InAs}_y\text{P}_{1-y}$ cladding has a lattice constant equal to the second lattice constant.

28. The monolithic, multi-bandgap, photovoltaic converter of claim 23, including:

- a third subcell behind the second subcell, said third subcell having a third bandgap, which is less than the second bandgap, and a third lattice constant, which is greater than the second lattice constant; and

- a second lattice constant transition material positioned between the second subcell and the first subcell, said second lattice constant transition material comprising $\text{InAs}_y\text{P}_{1-y}$ alloy with a lattice constant that changes from the second lattice constant to the third lattice constant.

29. The monolithic, multi-bandgap, photovoltaic converter of claim 22, wherein the second lattice constant is greater than the first lattice constant, and including a second lattice constant transition material positioned between the first subcell and the second subcell, said second lattice constant transition material comprising $\text{InAs}_y\text{P}_{1-y}$ alloy with a lattice constant that changes from the first lattice constant to the second lattice constant.

30. A monolithic, integrated, module (MIM), comprising:

- a plurality of monolithic, multi-bandgap, photovoltaic converters, each of which comprises: (i) a first subcell with a first bandgap and a first lattice constant; (ii) a second subcell with a second bandgap and a second lattice constant, wherein the second bandgap is less than the first bandgap and the second lattice constant is greater than the first lattice constant; and (iii) a lattice constant transition material positioned between the first subcell and the second subcell, said lattice constant transition material having a bandgap at least as large as the first bandgap and a lattice constant that changes from the first lattice constant to the second lattice constant; and
- a common substrate with a substrate bandgap and a substrate lattice constant, said common substrate being positioned between the first subcell and the lattice constant transition material of each of the monolithic, multi-bandgap, photovoltaic converters, wherein the substrate bandgap is at least as large as the first bandgap and the substrate lattice constant is equal to the first lattice constant.

31. The monolithic, integrated, module (MIM) of claim 30, wherein the first subcells are grown epitaxially on a front side of the substrate, and wherein the lattice constant transition materials and the second subcells are grown epitaxially on a back side of the substrate.

32. The monolithic, integrated, module (MIM) of claim 30, wherein the first subcell comprises GaInAs(P), the second subcell comprises GaInAs(P), the lattice constant transition material comprises $\text{InAs}_y\text{P}_{1-y}$, and the substrate comprises InP.

33. The monolithic, integrated, module (MIM) of claim 30, including a tunnel junction positioned between the first subcell and the second subcell of each of the monolithic, multi-bandgap, photovoltaic converters.

34. The monolithic, integrated, module (MIM) of claim 33, wherein the tunnel junction is positioned between the first subcell and the substrate.

35. The monolithic, integrated, module (MIM) of claim 30, including an isolation layer positioned between the first

subcell and the second subcell of each of the monolithic, multi-bandgap, photovoltaic converters.

36. A monolithic, integrated, module (MIM, comprising:

a plurality of monolithic, multi-bandgap, photovoltaic converters, each of which comprises: (i) a first subcell with a first bandgap and a first lattice constant; (ii) a second subcell with a second bandgap and a second lattice constant, wherein the second bandgap is less than the first bandgap and the second lattice constant is greater than the first lattice constant; and (iii) a lattice constant transition material positioned between the first subcell and the second subcell, said lattice constant transition material having a bandgap at least as large as the first bandgap and a lattice constant that changes from the first lattice constant to the second lattice constant; and

a common substrate with a substrate bandgap and a substrate lattice constant, said common substrate being positioned between the lattice constant transition material and the second subcell of each of the monolithic, multi-bandgap, photovoltaic converters, wherein the substrate bandgap is at least as large as the first bandgap and the substrate lattice constant is equal to the first lattice constant.

37. The monolithic, integrated, module (MIM) of claim 36, wherein the lattice constant transition layers and the first subcells are grown epitaxially on a front side of the substrate, and wherein the second subcells are grown epitaxially on a back side of the substrate.

38. The monolithic, integrated, module (MIM) of claim 36, wherein the first subcell comprises GaInAs(P), the second subcell comprises GaInAs(P), the lattice constant transition material comprises $\text{InAs}_y\text{P}_{1-y}$, and the substrate comprises InP.

39. The monolithic, integrated, module (MIM) of claim 36, including a tunnel junction positioned between the first subcell and the second subcell of each of the monolithic, multi-bandgaps, photovoltaic converters.

40. The monolithic, integrated, module (MIM) of claim 39, wherein the tunnel junction is positioned between the substrate and the second subcell.

41. The monolithic, integrated, module (MIM) of claim 36, including an isolation layer positioned between the first subcell and the second subcell of each of the monolithic, multi-bandgap, photovoltaic converters.

42. The monolithic, integrated, module (MIM) of claim 41, wherein a subcell circuit comprising the first subcells is voltage-matched to a subcell circuit comprising the second subcells.

43. A method of fabricating a monolithic, multi-bandgap, photovoltaic converter, comprising:

growing a first subcell comprising GaInAs(P) epitaxially on an InP substrate in a GaInAs(P) formulation that provides a first bandgap that is less than 1.35 eV and a first lattice constant, which equals in InP lattice constant;

growing a lattice constant transition layer on the first subcell, wherein the lattice constant transition layer comprises $\text{InAs}_y\text{P}_{1-y}$ with an increasing proportion of As and a decreasing proportion of P so that lattice constant of the $\text{InAs}_y\text{P}_{1-y}$ initially equals the first lattice constant and changes to a second lattice constant, which is greater than the first lattice constant, but also maintaining the proportions of As and P at levels that keep the lattice constant transition layer transparent to infrared radiation energy bands lower than infrared radiation energy that can be absorbed by the first subcell; and

growing a second subcell comprising GaInAs(P) epitaxially on the lattice constant transition layer in a GaInAs(P) formulation that has a lattice constant equal to the second lattice constant and a second bandgap that is less than the first bandgap.

43. A method of fabricating a monolithic, multi-bandgap, photovoltaic converter, comprising:

growing a first subcell comprising GaInAs(P) epitaxially on a front side of an InP substrate in a GaInAs(P) formulation that provides a first bandgap that is less than 1.35 eV and a first lattice constant, which equals an InP lattice constant;

growing a lattice constant transition layer comprising $\text{InAs}_y\text{P}_{1-y}$ on a back side of the InP substrate, including increasing proportion of As and decreasing proportion of P so that lattice constant of the $\text{InAs}_y\text{P}_{1-y}$ initially equals the lattice constant of the InP substrate and changes to a second lattice constant, which is greater than the first lattice constant, but also maintaining the proportions of As and P at levels that keep the lattice constant transition layer transparent to infrared radiation energy levels that are not absorbable by the first subcell.

* * * * *