

US 20070077884A1


(19) **United States**(12) **Patent Application Publication**
Regulinski et al.(10) **Pub. No.: US 2007/0077884 A1**(43) **Pub. Date: Apr. 5, 2007**(54) **COMMUNICATIONS APPARATUS AND METHOD**

continuation of application No. 09/835,066, filed on Apr. 16, 2001, now Pat. No. 6,950,625.

(75) Inventors: **Paul Lucian Regulinski**, London (GB);
Govindan Vishnu Nampoothiri,
Isleworth (GB); **Patrick Chomet**,
London (GB)(30) **Foreign Application Priority Data**Feb. 12, 2001 (EP) 0130126.5
Apr. 4, 2001 (GB) 0108501.8Correspondence Address:
DAVIS WRIGHT TREMAINE, LLP
2600 CENTURY SQUARE
1501 FOURTH AVENUE
SEATTLE, WA 98101-1688 (US)**Publication Classification**(51) **Int. Cl.**
H04B 7/185 (2006.01)
(52) **U.S. Cl.** **455/12.1; 455/427**(73) Assignee: **ICO Services Limited**, Uxbridge (GB)(57) **ABSTRACT**(21) Appl. No.: **11/524,388**(22) Filed: **Sep. 21, 2006****Related U.S. Application Data**

(63) Continuation of application No. 11/138,917, filed on May 26, 2005, now Pat. No. 7,155,161, which is a

A method of reusing frequency bands between base stations of a terrestrial mobile communications network and a satellite communications network, comprising allocating the frequency bands using integrated resource management and other mitigation techniques in a such a way as to minimise interference between both the systems, thus making optimum usage of valuable frequency spectrum.






Fig. 1




Fig. 2A




Fig. 3




Fig. 4A




Fig. 4B




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11

COMMUNICATIONS APPARATUS AND METHOD**FIELD OF THE INVENTION**

[0001] This invention relates to communications with a mobile user, and particularly to such communications in which links to mobile users are via a satellite or satellites, and also a relay station of a terrestrial network.

BACKGROUND OF THE INVENTION

[0002] Mobile satellite communication systems (MSSs) providing global coverage are known. One such is the Iridium™ system, others are the ICO™ system the Globalstar System™, and the Teledesic™ system.

[0003] Since such systems operate globally (or at least, over a large part of the Earth's surface) they need to use a band of frequencies which are available all round the Earth.

[0004] Such MSS systems have inherent limitations in their capability to provide services to users who are indoors and are in dense urban areas. Thus the available frequencies for these systems are wasted in dense urban areas and indoors.

[0005] Various Terrestrial mobile communications providing local geographic coverage are known. Known systems include GSM and its variants, CDMA, IS-136 and a variety of others using time division multiple access (TDMA) and code division multiple access (CDMA) techniques.

[0006] Code division multiple access is a so-called "spread spectrum" system, in which a given mobile device communicates using a relatively wide band, produced by multiplying the digital signal with a high bit rate ("chip rate") code sequence. Each code sequence defines a separate code channel.

[0007] Such systems, even though they are efficient and cost-effective in providing high capacity and coverage indoors and in dense urban areas, are not efficient and cost effective in terms of providing coverage to vast thinly populated rural areas.

[0008] Ideally, the satellite and terrestrial communications systems could be allocated completely separately frequency ranges, and they would then not interfere with each other.

[0009] Known systems like Iridium™ and Globalstar™ rely on roaming between satellite and terrestrial systems, and use completely different frequency spectrum for accessing the satellite and terrestrial systems. However, roaming between satellite and terrestrial systems would be a waste of valuable spectrum, considering that the spectrum used for Satellite communication system cannot be used in dense urban areas and indoors, while spectrum allocated for terrestrial use is not deployed in rural and ocean areas.

[0010] Accordingly, the present invention is designed to increase the possibilities for reusing the same channels (for example frequency channels) between terrestrial and satellite mobile communication systems.

[0011] U.S. Pat. No.5,394,561 discloses a mechanism for networking satellite and terrestrial networks in which the power levels of the satellite and terrestrial communications are controlled so as to minimise co-channel interference.

SUMMARY OF THE INVENTION

[0012] In one aspect, the invention provides a communications system comprising a satellite mobile communications network which comprises a plurality of satellites and a plurality of user terminals communicating on satellite uplink and downlink bands; and a terrestrial mobile communications network which comprises a plurality of base stations and a plurality of user terminal communicating on terrestrial uplink and downlink bands; characterised in that at least one of the terrestrial bands at least partly reuses at least one of the satellite bands.

[0013] Preferably, an embodiment provides a communication system where the resource management, allocation and planning functions of the satellite and terrestrial systems are linked together in such a way as to allow planned reuse of the spectrum.

[0014] In another aspect, the present invention provides a frequency reuse system comprising means for reducing localised reuse of said satellite uplink and/or downlink in regions around one of said base stations.

[0015] Where the satellite downlink (typically the mobile link) shares the same frequencies as the land network, dual mode terminals will be able to use the terrestrial network instead of the satellite network, and interference from the satellite downlink into the land network is reduced. Indirectly, interference from the satellite uplink is also reduced since terminals cease to use the satellite service in the absence of downlink.

[0016] In another aspect, the present invention provides a frequency reuse system, comprising means for transmitting a control signal to satellite user terminals in regions around one of said base stations to cause said user terminals to reduce (if necessary, to zero) use of said satellite uplink.

[0017] In another embodiment, the present invention provides a frequency reuse system, comprising means for transmitting a control signal to satellite user terminals in regions around one of said base stations to cause said user terminals to use channels which are non-interfering with said terrestrial network.

[0018] The control signal may be transmitted by the satellite. It may be a modified version of a predetermined common control signal.

[0019] In another embodiment, the control signal may be transmitted by the land network. As in the preceding embodiment, where the satellite uplink shares channels with the terrestrial network, interference from the satellite uplink is mitigated. Additionally, in this case, since the user terminal responds to a signal transmitted by the terrestrial network itself, rather than by the satellite as in the previous aspect, use of the shared spectrum on the satellite uplink is only suppressed when the user terminal is actually within range of the terrestrial network.

[0020] In another aspect, the invention provides a dual mode user terminal in which the satellite system shares frequencies with the terrestrial system, and in which the user terminal is arranged to detect downlink or uplink transmission on the terrestrial network, and to cease use of the shared part of the satellite spectrum on detection thereof. Again, the terminal may cease transmission on the satellite system, but alternatively it may be switched to a non-interfering satellite channel.

[0021] In one particular aspect, the uplink and downlink frequencies of a terrestrial network reuse the same frequencies as the satellite downlink but not the satellite uplink. This has the substantial advantage that no uplink or downlink transmissions from the terrestrial network are received by the satellite; such transmissions from a base station or a large number of terrestrial handsets could be more powerful than the weak signals transmitted by a satellite handset and hence could potentially cause significant interference.

[0022] In the reverse direction, the satellite downlink is low power because: firstly, the battery and solar cell power available on the satellite is limited; secondly, the path length travelled is long; and thirdly, satellite terminals typically have higher sensitivity. Thus, the total power in the satellite downlink is low and causes minimal interference.

[0023] In a particular preferred embodiment, this aspect of the invention is employed with a satellite using narrowband frequency, or frequency and time, division multiplexing and a terrestrial network employing CDMA. Where only a small number of satellite downlink transmissions are taking place, the effect of these on each CDMA signal is limited since they occupy only a small part of the CDMA spectrum. The interference from the satellite is thus even less intrusive in this embodiment.

[0024] This aspect is particularly preferably employed with the first aspect of the invention, in which case because the terrestrial network uses the satellite frequencies in shadowed areas (such as urban areas and indoors), the satellite downlink effect is reduced still further since the satellite signal is frequently shadowed.

[0025] In another aspect, the invention provides a satellite system which reuses radio spectrum with a terrestrial communications network, in which the satellite uplink shares spectrum with the terrestrial uplink and the satellite downlink shares spectrum with the terrestrial downlink. In this case, and particularly when this aspect is combined with the first, the satellite uplink causes relatively little interference at the terrestrial handset (and particularly when the terrestrial network uses spread spectrum communication and the satellite uses narrowband frequency division or frequency and time division multiplexing).

[0026] Also, in this embodiment or others it is particularly convenient to provide a dual mode user terminal having common elements of the radio frequency transmit and receive circuit, to which a separate terrestrial (for example CDMA) and satellite (for example FDMA/TDMA) decoder and demodulator are coupled.

[0027] In another aspect, the invention provides a satellite system which reuses radio spectrum with a terrestrial communications network, in which the uplink and downlink frequencies of the terrestrial network reuse the same frequencies as the satellite uplink but not the satellite downlink.

[0028] This is particularly advantageous where data terminal equipment is connected to the mobile terminals, since it is found that typical use of such data terminal equipment is heavily asymmetrical; that is, much more information is downloaded on the downlink (for example as a result of downloading emails, and browsing or downloading files from the Internet) than is transmitted on the uplink (which typically carries only selection and navigation commands).

There is therefore spare capacity on the satellite uplink which can be reused for terrestrial communications.

[0029] Other aspects and preferred embodiments of the invention are as described or claimed hereafter, with advantages which will be apparent from the following.

BRIEF DESCRIPTION OF THE DRAWINGS

[0030] Embodiments of the invention will now be described, by way of example only, with reference to the accompanying drawings, in which:

[0031] FIG. 1 is a block diagram showing schematically the elements of a first communications system embodying the present invention;

[0032] FIG. 2a is an illustrative diagram showing schematically the elements of mobile terminal equipment suitable for use with the present invention; and

[0033] FIG. 2b is a corresponding block diagram;

[0034] FIG. 3 is a block diagram showing schematically the elements of an Earth station node forming part of the embodiment of FIG. 1;

[0035] FIG. 4a illustrates schematically the beams produced by a satellite in the embodiment of FIG. 1;

[0036] FIG. 4b illustrates schematically the disposition of satellites forming part of FIG. 1 in orbits around the earth;

[0037] FIG. 5 shows the arrangement of terrestrial base stations in the first embodiment;

[0038] FIG. 6 shows the frequency allocation in the first embodiment;

[0039] FIG. 7 shows the frequency allocation in the second embodiment;

[0040] FIG. 8 is a block diagram showing the user terminal of the second embodiment;

[0041] FIG. 9 shows the frequency allocation in the third embodiment;

[0042] FIG. 10 shows the frequency allocation in the fourth embodiment; and

[0043] FIG. 11 illustrates the uplinks and downlinks present in the invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

First Embodiment

[0044] Referring to FIG. 1, a satellite communications network according to this embodiment comprises satellite mobile user terminal equipment 2a, 2b (e.g. handsets 2a and 2b); orbiting relay satellites 4a, 4b; satellite earth station nodes 6a, 6b; satellite system gateway stations 8a, 8b; terrestrial (e.g. public switched) telecommunications networks 10; and fixed telecommunications terminal equipment 12; terrestrial (e.g. public land) mobile telecommunications networks (PLMNs) 110 and terrestrial mobile terminal equipment 112.

[0045] Interconnecting the satellite system gateways 8a, 8b with the earth station nodes 6a, 6b, and interconnecting the nodes 6a, 6b with each other, is a dedicated ground-

based network comprising channels **14a**, **14b**, **14c**. The satellites **4**, earth station nodes **6** and lines **14** make up the infrastructure of the satellite communications network, for communication with the mobile terminals **2**, and accessible through the gateway stations **8**.

[0046] A central database station **15** is connected, via a signalling link **60** (e.g. within the channels **14** of the dedicated network) to the gateway station, earth stations **6**, and PLMN **110** (as discussed below).

[0047] The PSTNs **10** comprise, typically, local exchanges **16** . . . to which the fixed terminal equipment **12** . . . is connected via local loops **18**; and international switching centres **20** . . . connectable one to another via national and transnational links **21** (for example, satellite links or subsea optical fibre cable links). The PSTNs **10** and fixed terminal equipment **12** (e.g. telephone instruments) are well known and almost universally available today.

[0048] The PLMNs **110** comprise, typically, mobile switching centres (MSCs) **116** to which the terrestrial mobile terminals **112** are connected via local radio paths **118** and base stations **119**; and international gateways **20b**.

[0049] In this embodiment, most or all of the satellite user terminals **2** are dual mode and hence are also connectable via the terrestrial base stations **119**.

[0050] For voice communications via the satellite network, each satellite mobile terminal apparatus **2** is in communication with a satellite **4** via a full duplex channel (in this embodiment) comprising a downlink (to-mobile) channel and an uplink (from-mobile) channel, for example (in each case) a TDMA time slot on a particular frequency allocated on initiation of a call, as disclosed in UK patent applications GB 2288913 and GB 2293725. The satellites **4** in this embodiment are non geostationary, and thus, periodically, there is handover of the user terminal from one satellite **4** to another.

[0051] For voice communications via the PLMN, each mobile terminal apparatus **2**, **112** is in communication with a mobile switching centre **116** via a base station **119** using an uplink frequency band and a downlink frequency band.

Mobile Terminal **2**

[0052] Referring to FIGS. **2a** and **2b**, a dual mode mobile terminal handset equipment **2a** of FIG. **1** is shown.

[0053] It comprises a combination of a satellite handset, similar to those presently available for use with the GSM system, and a terrestrial handset suitable for third generation (3G) CDMA, W-CDMA or CDMA 2000. communications.

[0054] The user interface components (microphone **36**, loudspeaker **34**, display **39** (for example a liquid crystal display) and keypad components **38**) and power supply (battery **40**) are shared, i.e. used in both modes.

[0055] Apart from such common components (omitted for clarity from FIG. **2b**), the terminal comprises a CDMA functional unit **200a** and a satellite functional unit **200b**. Each comprises a digital coder/decoder **30a**, **30b**; modem **32a**, **32b**; control circuit **37a**, **37b**; radio frequency (RF) interface **32a** and **32b**, and antennas **31a** and **31b**, suitable for satellite and terrestrial mobile communications respectively. The satellite antenna **31a** has some gain in directions

above the horizon (it may be a Quadrifilar Helix or QFH antenna). The terrestrial antenna **31b** is roughly omnidirectional.

[0056] A 'smart card' reader **33** receiving a smart card (subscriber identity module or SIM) **35** storing user information are also provided, connected to communicate with the satellite control circuit **37b**. Specifically, the SIM **35** includes a processor **35a** and permanent memory **35b**.

[0057] The control circuits **37a**, **37b** (in practice integrated with the respective codec **30**) consist of a suitably programmed microprocessor, microcontroller or digital signal processor (DSP) chip. Each control circuit **37** performs various functions including framing speech and data into TDMA time frames for transmission (and likewise demultiplexing received TDMA frames) or CDMA sequences respectively; and performing encryption or enciphering.

[0058] Separate chipsets may be provided, each for implementing one of the terrestrial and satellite system functionalities **200a**, **200b**. Alternatively, a single processor may be programmed to perform the coding and control for both functionalities. In each case, in this embodiment separate RF components are provided, but user interface components are shared.

[0059] The mobile phone will then operate either as a satellite telephone or as terrestrial phone, with the relevant functional unit **200a** or **200b** working substantially independently and as it would do in a single mode phone.

[0060] The coder/decoder (codec) **30**, **30b** in this embodiment comprise a coder, generating a speech bit stream at around 3.6 kilobits per second, together with a channel coder **30b** applying error correcting encoding, to generate an encoded bit stream, and corresponding decoders.

[0061] In this embodiment the modems can support data rates of up to 384 kbps also.

[0062] A single mode satellite handset **2** would be as described, but lacking the section **200b**; and a terrestrial handset **112** is as described but lacking section **200a**.

Earth Station Node **6**

[0063] The earth station nodes **6** are arranged for communication with the satellites.

[0064] The Earth stations **6** are positioned dispersed about the Earth such that for any orbital position, at least one Earth station **6** is in view of a satellite **4**.

[0065] Each earth station node **6** comprises, as shown in FIG. **3**, a conventional satellite earth station **22** consisting of at least one satellite tracking antenna **24** arranged to track at least one satellite **4**, RF power amplifiers **26a** for supplying a signal to the antenna **24**, and **26b** for receiving a signal from the antenna **24**; and a control unit **28** for storing the satellite ephemeris data, controlling the steering of the antenna **24**, and effecting any control of the satellite **4** that may be required (by signalling via the antenna **24** to the satellite **4**).

[0066] The earth station node **6** further comprises a mobile satellite switching centre **42** comprising a network switch **44** connected to the trunk links **14** forming part of the dedicated network. A multiplexer **46** is arranged to receive switched calls from the switch **44** and multiplex them into a composite

signal for supply to the amplifier **26** via a low bit-rate voice codec **50**. Finally, the earth station node **6** comprises a local store **48** storing details of each mobile terminal equipment **2a** within the area served by the satellite **4** with which the node **6** is in communication.

Gateway **8**

[0067] The gateway stations **8a**, **8b** comprise, in this embodiment, commercially available mobile switch centres (MSCs) of the type used in digital mobile cellular radio systems such as GSM systems.

[0068] The gateway stations **8** comprise a switch arranged to interconnect incoming PSTN lines from the PSTN **10** with dedicated service lines **14** connected to one or more Earth station nodes **6**.

Database Station **15**

[0069] The database station **15** comprises a digital data store, a signalling circuit, a processor interconnected with the signalling circuit and the store, and a signalling link **60** interconnecting the database station **15** with the gateway stations **8** and Earth stations **6** making up satellite system network, for signalling or data message communications.

[0070] It stores data for terminal apparatus **2**, for example position data, billing data, authentication data and so on, like the Home Location Register (HLR) of a GSM system.

[0071] Thus, in this embodiment the database station **15** acts to fulfil the functions of a home location register (HLR) of a GSM system, and may be based on commercially available GSM products.

[0072] Periodically, the Earth station nodes measure the delay and Doppler shift of communications from the terminals **2** and calculate the rough terrestrial position of the mobile terminal apparatus **2** using the differential arrival times and/or Doppler shifts in the received signal. The position is then stored in the database **48**.

[0073] The database station **15** in this embodiment also performs frequency planning, to determine the frequencies to be used for communicating via the satellites **4** with each of the satellite user terminals **2**, and to control the use of uplink and downlink frequencies thereby as further discussed below. The database station **15** is accordingly connected additionally with the radio spectrum allocation components of the PLMN **110** via the signalling link **60**; it can thereby communicate with the Mobile Switching Centre (MSC) or Base Station Control centre which controls the frequencies used by the base stations **119b** of the PLMN.

[0074] Periodically, the database station **15** transmits frequency allocation information to the Earth stations **6** for use in the satellites **4**, and PLMNs **110**.

Satellites **4**

[0075] The satellites **4a**, **4b** comprise generally conventional communications satellite buses such as the HS601 available from Hughes Aerospace Corp, California, US, and the payload may be as disclosed in GB 2288913. Each satellite **4** is arranged to generate an array of beams covering a footprint beneath the satellite, each beam including a number of different frequency channels and time slots, as described in GB 2293725 and illustrated in FIG. **4a**.

[0076] On each beam, the satellite therefore transmits a set of downlink frequencies. The downlink frequencies on adjacent beams are different, so as to permit frequency re-use between beams. Each beam therefore acts somewhat in the manner of a cell of a conventional terrestrial cellular system. For example, there may be 61, 121 or 163 beams.

[0077] In this embodiment each downlink frequency carries a plurality of time division channels, so that each mobile terminal **2** communicates on a channel comprising a given time slot in a given frequency.

[0078] The satellites **4a** are arranged in a constellation in sufficient numbers and suitable orbits to cover a substantial area of the globe (preferably to give global coverage).

[0079] Referring to FIG. **4b**, a global coverage constellation of satellites is provided, consisting of a pair of orbital planes each inclined at 45 degrees to the equatorial plane, spaced apart by 90 degrees around the equatorial plane, each comprising ten pairs of satellites **4a**, **4b**, (i.e. a total of 20 operational satellites) the pairs being evenly spaced in orbit, with a phase interval of zero degrees between the planes (i.e. a 10/2/0 constellation in Walker notation) at an altitude of about 10,500 km (6 hour orbits).

[0080] Thus, neglecting blockages, a UT **2** at any position on Earth can always have a communications path to at least one satellite **4** in orbit ("global coverage").

Base Station **119**

[0081] The base station **119** comprises a CDMA base station having transmit and receive antennas which are arranged to transmit signals on downlink CDMA channels to mobile terminals, and to receive signals from mobile terminals on uplink CDMA channels. The downlink channels are provided, in this embodiment, in a downlink frequency band and the uplink signals in an uplink frequency band. At the base station **119**, there is further provided a conventional demodulator for demodulating the uplink signals to provide digital data and for modulating digital data onto the downlink signals. Each code channel may spread across the entire uplink or downlink spectrum in known fashion.

[0082] Referring to FIG. **5**, the base stations **119** of this embodiment comprise first base stations **119a**, each of which define a reception cell around it, which are deployed in suburban and rural areas as well as in urban areas. In such cases, the effective radio coverage of the cell will be of the order of several kilometres or even tens of kilometres, depending upon the line of sight visibility.

[0083] This embodiment also provides a second set of base stations **119b** which are provided in urban or built up areas. Each defines a "microcell" or "picocell" around it, to provide coverage in heavily shadowed or built up urban areas. For example, within a building such as an airport or a train station, or along an underground railway, a number of such picocell base stations **119b** are provided. Cover is therefore provided in areas where the base stations **119a** usually cannot communicate and satellites **4** will almost never communicate.

[0084] The base stations **119** include base station control circuits which allocate frequencies for communicating with mobile terminals **112**.

[0085] The transmit and receive antennas at the base stations **119a** are generally constrained to broadcast prefer-

entially in the azimuthal plane, for example by using a suitable “apple core” torroidal or conical reflector antenna, or are provided with some other beam shaping or directing means which reduces the gain above the azimuth (i.e. the horizon) so that the beam shaping effectively mitigates the interference to the satellites; the transmit and receive antennas of the terrestrial handsets **112** are generally omnidirectional to permit the handset to be used in any orientation.

Frequency Allocation

[0086] FIG. 6 shows the frequency allocations in this embodiment. The feeder link frequencies will not be discussed further in the following embodiments, and the terms “satellite uplink” and “satellite downlink” hereafter will refer to the mobile links.

[0087] The satellite uplink bands may be within the 1985-2014 MHz range and the satellite downlink bands within the 2170-2200 MHz band range. These frequencies are generally referred to as S-band frequencies.

[0088] It will be seen that the satellite uplink frequency band occupies spectrum not shared by the terrestrial network. Thus, the (relatively powerful) transmission from the terrestrial base stations (and terminals) will not interfere with the (relatively weak) uplink signals received at the satellite from the satellite mobile terminals.

[0089] Any non-urban base stations **119a** may also have allocated uplink and downlink bands which do not interfere with the satellite uplink or downlink bands. As is conventional in cellular mobile systems, this spectrum is reused in geographically separate cells. In urban areas, there is a requirement for additional capacity since more users are present per square kilometre.

[0090] In this embodiment, the additional capacity is provided by reusing the satellite downlink, as shown in FIG. 6, to provide additional terrestrial uplink and downlink bands. In this embodiment, the terrestrial uplink and downlink each occupy the same frequencies but are separated by a frequency space to permit frequency duplex separation within the base stations and the mobile terminals.

[0091] These are used by the base stations **119b** in micro-cells and picocells; for the purpose of this embodiment, these are cells located inside buildings or tunnels. (For reasons discussed further below, additional frequencies are present within the satellite downlink band which are not occupied by the additional terrestrial uplink and downlink frequencies.)

[0092] In such areas, the satellite downlink is frequently attenuated by ceilings or walls. Since the power radiated by the satellite is relatively low and the path length is relatively long, and the antenna used by a terrestrial user terminal has a relatively low gain (and/or G/T measure) as it is omnidirectional, the level of interference from the satellite into the terrestrial terminal is minimal.

[0093] Referring to FIG. 5, in this embodiment one or more of the base stations **119a** which are located in urban areas may also make use of the additional frequency bands used by the pico base stations **119b**. This is because, as shown in FIG. 5, the level of shadowing by buildings makes communication with satellites **4a**, **4b** difficult; only on the rare occasions when a satellite **4c** is in an unobstructed line of sight to a user terminal will the user terminal be affected by the satellite downlink.

[0094] Thus, to sum up, in this embodiment, the frequencies used by the terrestrial base stations **119** are allocated so that in urban or other shadowed areas, the additional terrestrial uplink and downlink bands lying within the satellite downlink band are utilised. The specific frequency channels within the satellite downlink band are reused for uplink and downlink of the terrestrial basestations located in urban and suburban areas.

[0095] In this embodiment, as the satellite communicates with each user on a narrow frequency channel, even if communication with a relatively small number of satellite users continues in the urban area, the interference with the terrestrial uplink and downlink frequencies will be minor because, due to the spectrum spreading of CDMA, the interference on one particular frequency is (up to a certain level) absorbed in the CDMA error correction decoding. Thus, small numbers of (inherently low) satellite channels merely slightly raise the noise floor.

[0096] Likewise, as the CDMA signals are spread over a wide spectrum, the noise power contributed by the PLMN **110** into any one of the narrow satellite communication frequency channels is low.

[0097] In this embodiment, however, the effects of such residual interference are reduced yet further by controlling the broadcast from the satellites **4**. The orbits of each of the satellites **4** are characterised to a high degree of accuracy, and their inclinations are actively controlled to maintain their beam directions accurately pointing to Earth. Each of the satellite spot beams has a radius of the order of some tens or hundreds of kilometres. The spot beams of each satellite overlap, and those of one satellite overlap with those of another in the most regions of the Earth and at most times.

[0098] In this embodiment, the database station **15** maintains a database recording the positions of base stations **119b** using the additional frequency bands which lie within the satellite downlink. The frequencies allocated to a given spot beam (which are dictated by a routing table held within each satellite and periodically reprogrammed from within the data base station **15**) are controlled so that the frequencies first allocated (i.e. preferentially allocated when available) are those from the region of the satellite downlink not in use by terrestrial base stations **119**. Thus, a number of satellite handsets may be operated without any possibility of interference with the terrestrial network.

[0099] As the database station **15** communicates with the PLMNs **110** periodically, it is able to vary the frequency allocations depending on the instantaneous loads (i.e. demand for service) on the terrestrial and satellite networks.

[0100] Frequencies are preferentially allocated from opposite ends of the shared frequency band; thus, for example, each time a new satellite communication channel is to be added, the next available frequency down from the high frequency end of the band may be allocated, whereas where additional terrestrial capacity is to be allocated, then frequencies may be allocated from the next available frequency up from the low end of the band.

[0101] Where such frequencies are exhausted, the next to be allocated to calls may be those which overlap with the terrestrial uplink band. In this embodiment it is easier to mitigate interference on the terrestrial uplink, since each

base station **119b** can be provided with sophisticated interference reduction techniques to reduce the effect of such interference.

[0102] Finally, the last to be allocated are the frequencies sharing the terrestrial downlink frequency band in any spot beam which covers the area overlying one of the base stations **119b**.

[0103] When the interference due to the above allocation exceeds a certain limit in such a way that this affects the capacity of the terrestrial network, dynamic reallocation of the uplink and downlink frequencies used by a number of terrestrial stations and the satellite network is performed so that the overall interference is kept to a minimum. For example, the set of frequencies used by one spot beam of the satellite and its neighbours, and/or by one of the base stations and its neighbours, are varied to allocate non-interfering channels to the satellite or the base station or both, exchanging those channels with those of a neighbour.

[0104] The control channels of the satellite and/or the base station may reallocate channels used on existing calls, by signalling to the terminals to hand over to a new frequency channel.

[0105] Thus, in the preferred arrangement of this embodiment, the satellite downlink signals are selectively controlled to areas of coverage which include base stations **119b** which are reusing the satellite downlink frequency, so as to mitigate the interference with the terrestrial system.

[0106] Under circumstances where it is impossible to allocate non-interfering spectrum to satellite users, it would be possible for the satellite system to signal terminals to cease use of the satellite network. It might be thought that the loss of satellite capacity would preclude economic operation of a satellite system in this case. However, according to this embodiment it is envisaged that the vast majority of satellite user terminals **2** will be dual mode terminals as illustrated in FIG. 2. Accordingly, in areas where the satellite has shut down service, coverage through the terrestrial base stations **119** will be available.

Second Embodiment

[0107] Referring to FIG. 7, in this embodiment, the satellite uplink is reused by the second set of base stations **119b** in urban areas as a terrestrial uplink, and the satellite downlink is reused by those base stations as a terrestrial downlink.

[0108] As in the preceding embodiment, the between the satellite system and the terrestrial system is similarly small because of the blocking and shadowing effects of buildings.

[0109] In this embodiment, additional measures are taken to limit the interference from the satellite user terminals into terrestrial base stations (satellite uplink into terrestrial uplinks), by providing that the satellite user terminals detect a signal indicating the possibility of interference, and in response cease to transmit satellite signals on the interfering channels and use non-interfering channels where available. Again, in this embodiment, it is envisaged that most of the satellite user terminals are dual mode terminals. Referring to FIG. 8, in this embodiment, as distinct from the preceding embodiment, since the satellite uplink and downlink spectra are the same as the additional terrestrial uplink and downlink spectra, some of the radio frequency components can be

reused. FIG. 8 is based on FIG. 2b, and like components are omitted from FIG. 8 for clarity.

[0110] In this embodiment, separate satellite and terrestrial antennas **31a**, **31b** are maintained, since although the area of spectrum occupied is the same, the satellite antenna preferably has a higher gain above the horizon whereas the terrestrial antenna will generally be omnidirectional.

[0111] A common RF amplifier block **52** comprising a low noise amplifier **54b** on the downlink and power amplifier **54a** on the uplink is provided, connected switchably to either of the antennas **31a**, **31b**. The amplifier section **52** is connected to a common up/down converter block **58** consisting of an up converter converting from baseband to RF and a down converter converting from RF to base band with a pair of switchable bandwidths corresponding to those of the satellite communications channels (which are relatively narrow) and terrestrial communications channels (which are relatively broad).

[0112] At base band frequency, the signal is then routed between the converter block **58** and the separate codecs etc as discussed in relation to FIG. 2b. Thus, the expensive RF components need not be duplicated, resulting in reduced cost, weight and power consumption. Single mode satellite handsets **2** would omit the CDMA codec portion shown in FIG. 8.

[0113] In this embodiment, a special code indicating the frequency channels used and the location of the terrestrial base station is defined for transmission on the broadcast common control channel in each spot beam. When a spot beam overlies a base station **119b**, which reuses the satellite frequencies, the code is broadcast. When it is received by any satellite user terminal **2**, the user terminal **2** responds by ceasing all uplink transmissions in shared channels by the satellite codec, until a control channel is detected in a satellite downlink spot beam on which the control signal is not being broadcast or the contents of the control signal indicates a different frequency (indicating that the user terminal is now within coverage of a spot beam that does not overlap the terrestrial base stations **119b**).

[0114] The above described embodiment has the effect of causing all satellite user terminals **2** which can receive the downlink on a beam which overlies one of the base stations **119b** to cease to generate satellite signals on the shared frequency channels. However, firstly, since the beam may cover a wider area than the cell surrounding the base station **119b**, many satellite user terminals **2** which could otherwise communicate with the satellite without interfering with the terrestrial base station **119** are adversely affected. Secondly, satellite user terminals **2** which cannot receive the signal concerned (for example because of fading or blockage) may nonetheless broadcast on the satellite uplink channel and hence interfere with the terrestrial base station **119**.

[0115] To resolve the first of these problems, rather than sending a broadcast mode control signal which is to be acted upon by all satellite user terminals **2** within the beam, the position of each satellite user terminal **2** is registered with the data base station **15** (either by incorporating a GPS receiver within each user terminal which reports its data to the satellite periodically, or by using a range and Doppler position sensing technique as described above).

[0116] The data base station **15** compares the position of each to data defining the coverage area of each of the base

stations **119b**, and when a satellite user terminal **2** is detected to be within one of the coverage areas, a control signal of the type discussed above is transmitted specifically to that satellite user terminal on a dedicated control channel therefore, or on a broadcast channel with a user terminal address decodable thereby. Thus, only those terminals which are detected as being likely to interfere cease to be able to use the satellite system.

[0117] Alternatively, where the handsets are aware of their own positions (for example each is equipped with a GPS receiver), the control signal may specify the co-ordinates of the coverage area of the base station **119b** and each satellite user terminal **2** may be arranged to terminate uplink transmissions on shared frequency channels only if it lies within that coverage area.

[0118] To deal with the second problem identified above, in an alternative embodiment, rather than making the satellite user terminals responsive to a control signal broadcast in the downlink from the satellite to cease satellite mode transmissions, the terrestrial base stations **119b** which reuse the satellite uplink and downlink are equipped with a transmitter arranged to transmit the control signals.

[0119] The satellite codec within each satellite user terminal **2** which can receive transmissions from the base station **119b** (and hence might generate uplink transmissions which would interfere with reception by that base station) is arranged, on detecting the control signal, to cease transmissions by the satellite system codec on shared frequency channels.

[0120] The control signal might simply be a beacon, broadcast at a predetermined frequency. Alternatively, it might emulate one of the satellite broadcast control channels.

[0121] Thus, in this embodiment, with some small modification to the base stations **119b**, only those satellite user terminals **2** which are actually within range of the base station **119b** are made unable to communicate with the satellite **4** using shared frequency channels, and this is achieved regardless of whether the satellite downlink can be received by them or not. The terrestrial mobile codec of the dual mode terminal **2** in this embodiment (as in the last) does not require modification. This embodiment is effective not only with dual mode satellite terminals sets **2** but also with satellite user terminals which lack a terrestrial mobile codec, because the broadcast signal from the base station **119b** is received and acted upon by the satellite system codec.

[0122] Finally, rather than modifying the base stations **119b**, it is possible instead to modify the terrestrial mobile codecs of dual mode satellite user terminals **2**, so that such terminals continuously monitor the downlink for signals from a terrestrial base station **119b**. On detection of a CDMA downlink signal, the terrestrial codec sends a control signal to the satellite system codec indicating the detected terrestrial frequencies, to cause the satellite system codec to cease its transmission on shared channels, and switch to free satellite channels. On loss of signal from the base station **119**, after a predetermined time without signal from the base station, the terrestrial system codec issues a control signal to the satellite system codec permitting use once more on the shared channels when necessary.

[0123] This embodiment therefore has the advantage that minimal modifications to the terrestrial base stations **119** are required.

[0124] It will be seen that this embodiment, in which the satellite uplink spectrum is also available for terrestrial mobile uplink and the satellite downlink spectrum is also available for terrestrial mobile downlink, provides more bandwidth to the terrestrial network for sharing than the preceding embodiment, and enables common RF components to be used in the satellite user terminal **2**.

[0125] Unlike the preceding embodiment there is also the possibility of interference on the satellite uplink and the terrestrial uplink.

[0126] Since satellite uplink channels are on narrow frequency bands, the effect on the broadband terrestrial CDMA uplink channels of any residual satellite uplink transmissions is merely to increase slightly the noise floor experienced.

Third Embodiment

[0127] Referring to FIG. 9, in this embodiment, the frequency reuse of the previous embodiment is reversed. That is to say, the satellite uplink is reused by the terrestrial downlink and vice versa. Thus, transmissions in the downlink from the satellite do not affect the terrestrial handsets, but could be received by the terrestrial base stations **119b**. Each such base station can, however, be protected from transmission from above by an overlying metal plate, or by suitably designing the antennas to reduce the gain and sidelobes in higher elevation angles and also by pointing the antennas tilted down from the horizontal.

[0128] Thus, such shielding or beam shaping, in addition to the shadowing and blockage caused by the deployment of the base stations **119b** indoors and in urban areas, substantially reduces the power levels on the satellite downlink reaching the base stations **119b**.

[0129] For similar reasons, and because the antennas of the base stations **119b** are intended to broadcast predominantly in the azimuthal plane, the impact of the terrestrial downlink on the satellite uplink is minimal.

[0130] As in the preceding embodiments, the antennas of the base stations may either broadcast preferentially in the azimuthal plane or in all directions other than above the azimuth, so as to reduce the power broadcast towards, and reduce the sensitivity to signals from, the satellite **4**.

[0131] Although the signals transmitted on the terrestrial and satellite uplink by user terminals are of lower amplitude due to the lower power available in the user terminals, it is noted that the terrestrial uplink signals transmitted by terrestrial handsets could interfere with the satellite downlink signals received by satellite mode handsets, and vice versa, where active terrestrial **112** and satellite mode **2** handsets are close to each other.

[0132] Accordingly, in this embodiment, the techniques discussed in the above first and second embodiments in reducing satellite transmissions on the satellite downlink and handset transmissions on the satellite uplink are preferably employed.

[0133] Alternatively, each dual mode handset **2** of this embodiment may be arranged to detect CDMA transmission on the terrestrial uplink (i.e. the terrestrial uplink frequency

used by other terrestrial handsets) through the satellite receiver. On detection of the frequency of transmissions from a terrestrial handset **112**, the satellite system codec is instructed to cease transmissions on any shared frequency channels on the satellite uplink. Thus, where a dual mode terminal **2** is close enough to a terrestrial mode terminal **112** to detect transmission from it (and hence is likely to interfere with it) potentially interfering transmissions from the dual mode handset **2** are terminated.

[0134] This embodiment has the advantage that the relatively powerful satellite and terrestrial downlink transmissions are received at the satellite **4** and the base station **119**, rather than at the user terminals **2**, **112**, making interference at the user terminals less likely than interference at the satellite **4** and base station **119**. Since it is easier to provide sophisticated interference mitigation and cancellation techniques, of the type described in our earlier applications WO 00/48333, WO 00/49735 or WO 00/35125 for example, at the network side rather than within the user terminals, the effects of any such interference can more easily be mitigated.

Fourth Embodiment

[0135] Referring to FIG. **10**, in this embodiment, as in the first, the terrestrial uplink and downlink frequency bands both occupy one of the satellite frequency bands. In this embodiment, however, it is the satellite uplink frequency band which is shared. This can be accomplished by placing a frequency gap between the terrestrial uplink and downlink bands, allowing a frequency division duplexer to separate the bands in the handsets and the base stations.

[0136] This embodiment is advantageous in situations where many satellite user terminals **2** are connected to data terminal equipment such as personal computers, personal digital assistants or other devices. Typically, such devices are used to download emails; or to download files via the Internet using either file transfer protocol (FTP) or hyper text transfer protocol (i.e. "web browsing").

[0137] In such uses, the uplink needs to carry only occasional control and navigation commands specifying files to be downloaded, or acknowledging receipt of data, relative to the heavy usage of the satellite downlink. There is, therefore, considerable scope for reusing the satellite uplink.

[0138] As the data rate on satellite uplink channels will be low, they are inherently more immune to the additional noise generated by the wide band CDMA PLMN traffic if each satellite uplink channel is allowed to occupy the same bandwidth as the satellite downlink channel. Alternatively, the satellite uplink channels may be allocated a narrower bandwidth, for example by time division multiplexing a higher number of uplink channels together. The unused uplink channel frequencies thus released are available for terrestrial reuse.

Summary Of Interference Modes And Effects

[0139] FIG. **11** shows the satellite and terrestrial uplink and downlinks.

TABLE 1

	Interference Modes			
	1 st Embodiment	2 nd Embodiment	3 rd Embodi- ment	4 th Embodi- ment
Satellite into Terrestrial Base	POTENTIAL		POTEN- TIAL	
Satellite into Terrestrial UT	POTENTIAL	POTENTIAL		
Satellite UT into Terrestrial Base		POTENTIAL		POTEN- TIAL
Satellite UT into Terrestrial UT			POTEN- TIAL	POTEN- TIAL
Terrestrial Base into Satellite Terrestrial	POTENTIAL	POTENTIAL	POTEN- TIAL	POTEN- TIAL
Base into Satellite UT Terrestrial		POTENTIAL		POTEN- TIAL
UT into Satellite Terrestrial UT into Satellite UT	POTENTIAL		POTEN- TIAL	

[0140] Referring to Table 1, the potential modes of interference in each of the above embodiments are briefly discussed, together with the techniques preferred for mitigation thereof. It will be seen that in the first embodiment there is potential interference from the satellite into the terrestrial base station **119** and user terminal **112**; and from the terrestrial base station **119** and user terminal **112** into the satellite user terminal **2**. In the second embodiment there is potential interference from the satellite **4** into the terrestrial user terminal **112** and vice versa, and from the base station **119** into the satellite user terminal **2** and vice versa.

[0141] In the third embodiment there is potential interference from the satellite **4** into the terrestrial base station **119** and vice versa, and from the satellite user terminal **2** into the terrestrial user terminal **112** and vice versa.

[0142] In the fourth embodiment there is potential interference in the satellite user terminal **2** into the terrestrial base station **119** and user terminal **112**, and from the terrestrial base station **119** and user terminal **112** into the satellite **4**.

Satellite **4** into Base Station **119**

[0143] Using representative figures, providing a substantial number of continuous satellite downlink channels (of the order of **40**) would increase the noise level, and hence reduce the effective cell size allowable for the terrestrial base station **119** by the order of 60%. To reduce this impact on the PLMN **110**, the following measures are proposed:

[0144] Providing suitable gain reduction above azimuth (for example by shielding, beam shaping or both) as discussed above can provide up to 25 dB discrimination, halving the reduction in cell size.

[0145] As disclosed above, initial allocation by the data-base station **15** of non-interfering channels to the satellite

and terrestrial networks reduces the impact of the interference. Subsequently, shared frequency channels are only allocated up to a predefined limit, which is decided by the amount of interference. Finally, dynamically controlling the number of channels which overlap the PLMN bandwidth which can be allocated to satellite uplinks and downlinks depending on the relative loading of the two networks, further assists in reducing the impact. As most or all satellite terminals **2** will be dual mode, they can also operate on the terrestrial PLMN **110** where needed.

[0146] In combination, these techniques greatly mitigate the impact of interference between the terrestrial and satellite systems.

Satellite **4** Into Terrestrial Mobile Terminal **112**

[0147] Using similar figures, it is estimated that up to 40 satellite downlink channels could reduce the effective terrestrial cell size by of the order of 50% where these interfere with the terrestrial downlink.

[0148] To mitigate this, as above, the data base station **15** initially preferentially allocates channels to the satellite terminals **2** which do not overlap with the terrestrial spectrum, and dynamically controls the number of satellite channels sharing the spectrum where it is not possible to avoid overlap. The combination of these techniques effectively mitigates potential interference.

Satellite User Terminal **2** Into Terrestrial Base Station **119**

[0149] The radio horizon experienced between the base station antenna and the user terminal will prevent interference from user terminals more than, say, 30 km from the base station. However, within that distance, and to the extent not obstructed by obstacles, user terminals **2** can interfere into the terrestrial base station **119b** where the uplink spectra are shared.

[0150] To mitigate the interference, firstly, the satellite terminals **2** are made dual mode, and are controlled as described above to operate as terrestrial mobile terminals and consequently to inhibit satellite uplink transmissions while within the coverage of terrestrial base stations **119**. This virtually eliminates the interference except where a satellite user terminal **2** is outside the coverage of a base station **119b** but close enough to interfere with it, or where the satellite terminal is single mode only.

[0151] Secondly, as discussed above, the database station **15** takes advantage of its knowledge of the locations of the base stations **119** and the user terminals **2**, to dynamically limit the uplink frequency assignments for user terminals **2** close to a base station **119**, to channels which do not overlap the base station receive band. As the maximum interference range is estimated to be around 30 km, different allocations can be made within different parts of each satellite beam.

[0152] The combination of these techniques virtually eliminates the potential interference in this mode.

Satellite User Terminal **2** Into Terrestrial Mobile Terminal **112**

[0153] The radio horizon between two handheld terminals is only around 8 km, so that terminals further away from this will not interfere with each other even where the uplink spectra are shared.

[0154] To mitigate this interference, the same techniques as in the previous interference mode are operated, with the same results.

Terrestrial Base Station **119** Into Satellite **4**

[0155] As noted above, shadowing substantially reduces the direct line of sight from urban base stations to the satellite. Further, as discussed above, the base station antennas are preferably designed to minimise gain at angles above the horizon, giving up to 25 dB discrimination in the direction of the satellites. Further, the database station **15** initially assigns satellite uplink channels which do not overlap with the base station emission bandwidth for satellite beams which overlap terrestrial base stations **119b**; shared channels are only assigned as necessary.

[0156] Thirdly, as discussed above, dynamic control of the number of shared channels allocated to satellite uplinks depending on relative loading of the two networks is performed.

Terrestrial Base Station **119** Into Satellite User Terminal **2**

[0157] The interference situation is essentially the reverse of that for satellite user terminal interference into the terrestrial base station, and the same techniques are used to mitigate interference.

Terrestrial Mobile Terminal **112** Into Satellite **4**

[0158] To mitigate this interference, the data base station **15** initially assigns satellite uplink channels which do not overlap with the base station downlink bandwidth in areas where satellite beams overlap cells of base stations **119b**; shared channels are only assigned as the satellite or terrestrial systems reach capacity. Secondly, the number of channels shared is dynamically controlled in dependence on the relative loading of the two networks and thereby the interference between both the networks are minimised.

Terrestrial Mobile Terminal **112** Into Satellite User Terminal **2**

[0159] As above, the maximum interference range between the two user terminals is only 8 km. To mitigate interference, firstly, as above, the fact that the satellite terminals **2** are dual mode causes them to operate whenever within range of a base station **119b** as terrestrial mobile terminals, which eliminates most of interference except where the terrestrial terminal **112** is in communication with a base station **119b** and is within range of a satellite user terminal **2** which is blocked or otherwise prevented from communicating with the terrestrial network **119b**.

[0160] Secondly, the data base station **15** in conjunction with the MSC **116** dynamically allocates the satellite and terrestrial uplink and downlink frequency assignments for satellite user terminals near a base station **119** to channels that do not overlap each other.

Other Embodiments

[0161] It will be clear from the foregoing that the above described embodiments are merely a few ways of putting the invention into effect. Many other alternatives will be apparent to the skilled person and are within the scope of the present invention.

[0162] For example, although the above-described embodiments mention base stations sited indoors or in urban

areas, and thus make use of the potential shadowing there, it will be clear that the various interference mitigation techniques and spectrum reuse techniques described could also be used with base stations sited additionally or alternatively in suburban or rural areas.

[0163] Although in the above embodiments a limit is set on the number of interfering frequencies used, a limit based on other criteria such as the total interfering power (calculated for example taking into account path loss and power used on each channel, and/or other criteria), may instead be used.

[0164] Whilst in certain of the above embodiments, frequency duplexing is used to share satellite spectrum between the terrestrial uplink and downlink, time division duplex between the terrestrial uplink and downlink could alternatively be used (as in certain existing terrestrial networks).

[0165] It will be clear that other possibilities for reuse by terrestrial networks of the satellite spectrum exist, making use of the above described observations and techniques. Further, the above described techniques may be combined.

[0166] Further, it will be clear that each of the above described techniques for reducing the interference between the satellite and terrestrial systems, or for detection techniques to do so, may be employed separately of the others, in other similar interference scenarios.

[0167] Whereas in the above described embodiments a dual mode user terminal comprises a common housing and user interface containing separate satellite system and terrestrial codecs, other constructions are possible; for example it could comprise separate single mode terminals interconnected by a wire or a wireless interface.

[0168] The CDMA can be third generation wide band CDMA (W-CDMA) or CDMA 2000.

[0169] Whereas a TDMA/FDMA satellite system and CDMA terrestrial system are described above, in principle the satellite system could be CDMA and the terrestrial system TDMA/FDMA or FDMA.

[0170] The numbers of satellites and satellite orbits indicated are purely exemplary. Smaller numbers of geostationary satellites (for regional coverage), or satellites in higher altitude orbits, could be used; or larger numbers of low earth orbit (LEO) satellites could be used, as disclosed in EP 0365885, or publications relating to the Iridium or Teledesic systems, for example. Equally, different numbers of satellites in intermediate orbits could be used. In principle, even flying platforms such as balloons or aircraft are not excluded.

[0171] It will be understood that components of embodiments of the invention may be located in different jurisdictions or in space. For the avoidance of doubt, the scope of the protection of the following claims extends to any part of a telecommunications apparatus or system or any method performed by such a part, which contributes to the performance of the inventive concept.

1-31. (canceled)

32. A communications system, comprising:

a satellite communications network having a satellite communicating using a first air interface on satellite uplink and downlink bands;

a terrestrial communications network having base stations configured to communicate using a second air interface on terrestrial uplink and downlink bands; and

a plurality of user terminals capable of communicating with the satellite communications network and/or the terrestrial communications network.

33. The communications system of claim 32, wherein the satellite bands and the terrestrial bands do not overlap.

34. The communications system of claim 32, wherein at least one of the plurality of user terminals is a dual mode user terminal and is further configured to communicate with both the satellite communications network on the satellite uplink and downlink bands and the terrestrial communications network on the frequency uplink and downlink bands.

35. The communications system of claim 32, wherein the terrestrial uplink and downlink bands at least partly reuse the satellite uplink band.

36. The communications system of claim 32, wherein the terrestrial uplink and downlink bands at least partly reuse the satellite downlink band.

37. The communications system of claim 32, wherein the terrestrial uplink band at least partly reuses the satellite uplink band and the terrestrial downlink band at least partly reuses the satellite downlink band.

38. The communications system of claim 32, wherein the terrestrial downlink band at least partly reuses the satellite uplink band and the terrestrial uplink band at least partly reuses the satellite downlink band.

39. The communications system of claim 32, wherein the satellite uplink and downlink bands use channels that are divided by a code.

40. The communications system of claim 39, wherein the channels use code division multiple access communications protocol.

41. The communications system of claim 40, wherein the terrestrial uplink and downlink band use time divided channels and/or frequency divided channels.

42. The communications system of claim 32, wherein the satellite uplink and downlink bands time divided channels and/or frequency divided channels.

43. The communications system of claim 42, wherein the terrestrial uplink and downlink bands use code division multiple access communications protocol.

44. The communications system of claim 32, wherein the terrestrial uplink and downlink bands do not share or reuse satellite uplink and downlink bands.

45. The communications system of claim 32, wherein the satellite uplink and downlink bands contain relatively narrow frequency channels, and the terrestrial uplink and downlink bands contain relatively wide frequency channels.

46. The communications system of claim 32, wherein the satellite uplink and downlink bands contain relatively wide frequency channels, and the terrestrial uplink and downlink bands contain relatively narrow frequency channels.

47. The communications system of claim 32, wherein at least one of the terrestrial bands at least partly reuses at least one of the satellite bands.

48. The communications system of claim 32, further comprising:

an integrated frequency controller for allocating channels within the satellite uplink and downlink bands and the terrestrial uplink and downlink bands.

49. The communications system of claim 32, further comprising:

means for transmitting a control signal to a user terminal communicating with the satellite communications network using a channel that is non-interfering with the terrestrial communications network.

50. The communications system of claim 32, further comprising:

means for transmitting a control signal to a user terminal communicating with the terrestrial communications system using a channel that is non-interfering with the satellite communications network.

51. The communications system of claim 32, further comprising:

a satellite controller configured to determine available channels to use in the satellite uplink and downlink bands for communications between at least one of the user terminals and the satellite.

52. The communications system of claim 51, further comprising:

a terrestrial controller configured to determine available channels to use in the terrestrial uplink and downlink bands for communications between at least one of the user terminals and one of the base stations.

53. The communications system of claim 52, wherein the satellite controller and the terrestrial controller operate substantially independently.

54. The communications system of claim 32, further comprising:

a controller configured to determine available channels to use in the satellite bands for communications between at least one of the user terminals and the satellite, and available channels for use in the terrestrial bands between at least one of the user terminals and one of the base stations.

55. The communications system of claim 32, wherein the first interface and the second interface use relatively wide frequency channels within the bands.

56. The communications system of claim 32, wherein the first interface and the second interface use relatively narrow frequency channels within the bands.

57. The communications system of claim 32, wherein the first air interface is a CDMA based air interface or a derivative thereof, and the second air interface is a CDMA based air interface or a derivative thereof.

58. The communications system of claim 32, wherein the first air interface is a CDMA based air interface or a derivative thereof, and the second air interface is a TDMA based air interface or a derivative thereof.

59. The communications system of claim 32, wherein the first air interface is a TDMA based air interface or a derivative thereof, and the second air interface is a CDMA based air interface or a derivative thereof.

60. The communications system of claim 32, wherein the first air interface is a TDMA based air interface or a derivative thereof, and the second air interface is a TDMA based air interface or a derivative thereof.

61. The communications system of claim 32, wherein the first air interface is a CDMA based air interface or a derivative thereof, and the second air interface is a FDMA/TDMA based air interface or a derivative thereof.

62. The communications system of claim 32, wherein the first air interface is a FDMA/TDMA based air interface or a derivative thereof, and the second air interface is a CDMA based air interface or a derivative thereof.

63. The communications system of claim 32, wherein the first air interface is a FDMA/TDMA based air interface or a derivative thereof, and the second air interface is a FDMA/TDMA based air interface or a derivative thereof.

64. A dual mode user terminal for use in a communications system having a satellite portion and a terrestrial portion, comprising:

a satellite interface configured to communicate with a satellite in the satellite portion on satellite uplink and downlink bands using satellite channels; and

a terrestrial interface configured to communicate with a base station in the terrestrial portion of the communications system on terrestrial uplink and downlink bands using terrestrial channels.

65. The dual mode user terminal of claim 64, wherein at least one of the terrestrial uplink or downlink bands share or reuse frequencies with at least one of the satellite uplink or downlink bands.

66. The dual mode user terminal of claim 64, wherein the terrestrial uplink and downlink bands do not share or reuse frequencies with satellite uplink and downlink bands.

67. The dual mode user terminal of claim 65, further comprising:

a detector for detecting interference, and when such interference is above a predetermined threshold, ceasing use of any shared at least one of the satellite uplink or downlink bands.

68. The dual mode user terminal of claim 64, wherein the terrestrial uplink and downlink bands at least partly reuse the satellite uplink band.

69. The dual mode user terminal of claim 64, wherein the terrestrial uplink and downlink bands at least partly reuse the satellite downlink band.

70. The dual mode user terminal of claim 64, wherein the terrestrial uplink band at least partly reuses the satellite uplink band and the terrestrial downlink band at least partly reuses the satellite downlink band.

71. The dual mode user terminal of claim 64, wherein the terrestrial downlink band at least partly reuses the satellite uplink band and the terrestrial uplink band at least partly reuses the satellite downlink band.

72. The dual mode user terminal of claim 64, wherein the satellite uplink and downlink bands use channels that are divided by a code.

73. The dual mode user terminal of claim 72, wherein the channels use code division multiple access communications protocol.

74. The dual mode user terminal of claim 72, wherein the terrestrial uplink and downlink band use time divided channels and/or frequency divided channels.

75. The dual mode user terminal of claim 64, wherein the satellite uplink and downlink bands use time divided channels and/or frequency divided channels.

76. The dual mode user terminal of claim 75, wherein the terrestrial uplink and downlink bands use code division multiple access communications protocol.

77. The dual mode user terminal of claim 64, wherein the terrestrial uplink and downlink bands do not share or reuse satellite uplink and downlink bands.

78. The dual mode user terminal of claim 64, wherein the satellite uplink and downlink bands contain relatively narrow frequency channels, and the terrestrial uplink and downlink bands contain relatively wide frequency channels.

79. The dual mode user terminal of claim 64, wherein the satellite uplink and downlink bands contain relatively wide frequency channels, and the terrestrial uplink and downlink bands contain relatively narrow frequency channels.

80. The dual mode user terminal of claim 64, wherein at least one of the terrestrial bands at least partly reuses at least one of the satellite bands.

81. The dual mode user terminal of claim 64, further comprising:

a receiver for receiving a control signal to use a channel that is non-interfering with the terrestrial communications network.

82. The dual mode user terminal of claim 64, further comprising:

a receiver, for receiving a control signal to use a channel that is non-interfering with the satellite communications network.

83. The dual mode user terminal of claim 64, wherein the terrestrial interface and satellite interface comprise at least one common element consisting of a microphone, display, codec, control circuit, modem, RF interface, or antenna.

84. The dual mode user terminal of claim 64, wherein the satellite interface comprises:

a digital coder/decoder;

a control circuit;

a modem; and

an RF interface.

85. The dual mode user terminal of claim 64, wherein the terrestrial interface uses at least one of the digital coder/decoder, the control circuit, and the modem.

86. The dual mode user terminal of claim 85, wherein the terrestrial interface comprises:

a second digital coder/decoder;

a second control circuit;

a second modem; and

a second RF interface.

87. A communications system, comprising:

a satellite portion having a satellite configured to receive communications from user terminals over an uplink satellite frequencies and to transmit communications to the user terminals over a downlink satellite frequencies; and

an ancillary terrestrial portion configured to transmit communications to, and receive wireless communications from, the plurality of user terminals over the satellite uplink frequencies.

88. The communications system of claim 87, wherein at least one of the plurality of user terminals is a dual mode user terminal and is further configured to communicate with both the satellite communications network on the satellite uplink and downlink frequencies and the terrestrial communications network over the satellite uplink frequencies.

89. The communications system of claim 87, wherein the satellite portion uses channels in the satellite that are divided by a code.

90. The communications system of claim 89, wherein the channels use code division multiple access communications protocol.

91. The communications system of claim 90, wherein the terrestrial uplink portion uses time divided channels and/or frequency divided channels.

92. The communications system of claim 87, wherein the satellite portion uses time divided channels and/or frequency divided channels.

93. The communications system of claim 92, wherein the terrestrial portion uses code division multiple access communications protocol.

94. The communications system of claim 87, wherein the satellite portion contains relatively narrow frequency channels, and the terrestrial portion contains relatively wide frequency channels.

95. The communications system of claim 87, wherein the satellite portion contains relatively wide frequency channels, and the terrestrial uplink portion contain relatively narrow frequency channels.

96. The communications system of claim 87, further comprising:

an integrated frequency controller for allocating channels within the satellite portion and the terrestrial portion.

97. The communications system of claim 87, further comprising:

a satellite controller configured to determine available channels to use in the satellite portion for communications between at least one user terminal and the satellite.

98. The communications system of claim 97, further comprising:

a terrestrial controller configured to determine available channels to use in the terrestrial portion for communications between at least one user terminals and the base station.

99. The communications system of claim 98, wherein the satellite controller and the terrestrial controller operate substantially independently.

100. The communications system of claim 87, further comprising:

a controller configured to determine available channels to use in the satellite portion for communications between at least one of the user terminals and the satellite, and determining available channels for use in the terrestrial bands between at least one of the user terminals and the base station.

101. A communications system, comprising:

a satellite portion having a satellite configured to receive communications from user terminals over an uplink satellite frequency and to transmit communications to the user terminals over a downlink satellite frequency;

an ancillary terrestrial portion configured to transmit communications to, and receive wireless communications from, the user terminals over the satellite downlink frequency.

102. The communications system of claim 101, wherein at least one of the user terminals is a dual mode user terminal and is further configured to communicate with both the satellite communications network on the satellite uplink and downlink frequencies and the terrestrial communications network over the satellite uplink frequencies.

103. The communications system of claim 101, wherein the satellite portion uses channels in the satellite that are divided by a code.

104. The communications system of claim 103, wherein the channels use a code division multiple access communications protocol.

105. The communications system of claim 104, wherein the terrestrial uplink portion uses use time divided channels and/or frequency divided channels.

106. The communications system of claim 101, wherein the satellite portion uses use time divided channels and/or frequency divided channels.

107. The communications system of claim 106, wherein the terrestrial portion uses code division multiple access communications protocol.

108. The communications system of claim 101, wherein the satellite portion contains narrow frequency channels, and the terrestrial portion contains wide frequency channels.

109. The communications system of claim 101, wherein the satellite portion contains wide frequency channels, and the terrestrial uplink portion contain narrow frequency channels.

110. The communications system of claim 101, further comprising:

an integrated frequency controller for allocating channels within the satellite portion and the terrestrial portion.

111. The communications system of claim 101, further comprising:

a satellite controller configured to determine available channels to use in the satellite portion for communications between at least one user terminal and the satellite.

112. The communications system of claim 111, further comprising:

a terrestrial controller configured to determine available channels to use in the terrestrial portion for communications between at least one user terminals and the base stations.

113. The communications system of claim 112, wherein the satellite controller and the terrestrial controller operate substantially independently.

114. The communications system of claim 101, further comprising:

a controller configured to determine available channels to use in the satellite portion for communications between at least one of the user terminals and the satellite, and determining available channels for use in the terrestrial bands between at least one of the user terminals and the base station.

* * * * *