

US 20100225272A1

(19) **United States**

(12) **Patent Application Publication**
Kirby et al.

(10) **Pub. No.: US 2010/0225272 A1**

(43) **Pub. Date: Sep. 9, 2010**

(54) **WIRELESS POWER FOR CHARGEABLE AND CHARGING DEVICES**

Related U.S. Application Data

(75) Inventors: **Miles A. Kirby**, San Diego, CA (US); **Matthew S. Grob**, La Jolla, CA (US)

(60) Provisional application No. 61/152,359, filed on Feb. 13, 2009.

Correspondence Address:
QUALCOMM INCORPORATED
5775 MOREHOUSE DR.
SAN DIEGO, CA 92121 (US)

Publication Classification

(51) **Int. Cl.**
H02J 7/00 (2006.01)

(52) **U.S. Cl.** **320/108**


(57) **ABSTRACT**

(73) Assignee: **QUALCOMM INCORPORATED**, San Diego, CA (US)

Exemplary embodiments are directed to wireless power. A method may comprise detecting one or more transmit elements positioned within an associated charging region. The method may further comprise selecting at least one transmit element of the detected one or more transmit elements to receive wireless power therefrom to enable for optimal charging of a charging device.

(21) Appl. No.: **12/695,911**

(22) Filed: **Jan. 28, 2010**






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6



FIG. 8




FIG. 7




FIG. 9







FIG. 10

**FIG. 11**



**FIG. 13**




FIG. 14






FIG. 15



**FIG. 17**

WIRELESS POWER FOR CHARGEABLE AND CHARGING DEVICES

CLAIM OF PRIORITY UNDER 35 U.S.C. §119

[0001] This application claims priority under 35 U.S.C. §119(e) to:

[0002] U.S. Provisional Patent Application 61/152,359 entitled “UNIVERSAL WIRELESS AND WIRED CHARGER (MULTI-FREQUENCY, MULTI-VERSION AND MULTI-REVISION)” filed on Feb. 13, 2009, the disclosure of which is hereby incorporated by reference in its entirety.

BACKGROUND

[0003] 1. Field

[0004] The present invention relates generally to wireless electronic devices, and more specifically to electronic devices configured for wireless communication, wireless charging, and enabling for an optimal charging scenario.

[0005] 2. Background

[0006] Typically, each battery powered device requires its own charger and power source, which is usually an AC power outlet. This becomes unwieldy when many devices need charging.

[0007] Approaches are being developed that use over the air power transmission between a transmitter and the device to be charged. These generally fall into two categories. One is based on the coupling of plane wave radiation (also called far-field radiation) between a transmit antenna and receive antenna on the device to be charged which collects the radiated power and rectifies it for charging the battery. Antennas may be of resonant length in order to improve the coupling efficiency. This approach suffers from the fact that the power coupling falls off quickly with distance between the antennas. So charging over reasonable distances (e.g., >1-2 m) becomes difficult. Additionally, since the system radiates plane waves, unintentional radiation can interfere with other systems if not properly controlled through filtering.

[0008] Other approaches are based on inductive coupling between a transmit antenna embedded, for example, in a “charging” mat or surface and a receive antenna plus rectifying circuit embedded in the host device to be charged. This approach has the disadvantage that the spacing between transmit and receive antennas must be very close (e.g. mms). Though this approach may have the capability to simultaneously charge multiple devices in the same area, this area is typically small, hence the user must locate the devices to a specific area.

[0009] A need exists for wireless power devices configured for detecting other wireless power devices and determining optimal charging solutions. More specifically, a need exists for a chargeable device configured to detect one or more wireless chargers and, thereafter, determine an optimal charging solution for receiving a charge. Further, a need exists for a wireless charger configured to detect one or more chargeable devices and, thereafter, determine an optimal charging solution for charging at least one of the one or more detected chargeable devices.

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] FIG. 1 shows a simplified block diagram of a wireless power transfer system.

[0011] FIG. 2 shows a simplified schematic diagram of a wireless power transfer system.

[0012] FIG. 3 shows a schematic diagram of a loop antenna for use in exemplary embodiments of the present invention.

[0013] FIG. 4 is a simplified block diagram of a transmitter, in accordance with an exemplary embodiment of the present invention.

[0014] FIG. 5 is a simplified block diagram of a receiver, in accordance with an exemplary embodiment of the present invention.

[0015] FIG. 6 shows a simplified schematic of a portion of transmit circuitry for carrying out messaging between a transmitter and a receiver.

[0016] FIG. 7 illustrates a chargeable device, in accordance with an exemplary embodiment of the present invention.

[0017] FIG. 8 illustrates another chargeable device, according to an exemplary embodiment of the present invention.

[0018] FIG. 9 illustrates a system including a wireless charger and a chargeable device, according to an exemplary embodiment of the present invention.

[0019] FIG. 10 illustrates a system including a plurality of wireless chargers and a chargeable device, in accordance with an exemplary embodiment of the present invention.

[0020] FIG. 11 illustrates a chargeable device having a plurality of receive antennas, according to an exemplary embodiment of the present invention.

[0021] FIG. 12 illustrates a system including a plurality of wireless chargers and a chargeable device having a plurality of receive antennas, according to an exemplary embodiment of the present invention.

[0022] FIG. 13 is a flowchart illustrating a method, according to an exemplary embodiment of the present invention.

[0023] FIG. 14 illustrates a wireless charger, according to an exemplary embodiment of the present invention.

[0024] FIG. 15 illustrates a system including a wireless charger and a plurality of chargeable devices, according to an exemplary embodiment of the present invention.

[0025] FIG. 16 illustrates another system including a wireless charger and a plurality of chargeable devices, in accordance with an exemplary embodiment of the present invention.

[0026] FIG. 17 is a flowchart illustrating another method, according to an exemplary embodiment of the present invention.

DETAILED DESCRIPTION

[0027] The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any embodiment described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments.

[0028] The detailed description set forth below in connection with the appended drawings is intended as a description of exemplary embodiments of the present invention and is not intended to represent the only embodiments in which the present invention can be practiced. The term “exemplary” used throughout this description means “serving as an example, instance, or illustration,” and should not necessarily be construed as preferred or advantageous over other exemplary embodiments. The detailed description includes specific details for the purpose of providing a thorough understanding of the exemplary embodiments of the invention. It will be apparent to those skilled in the art that the exemplary embodiments of the invention may be practiced without these specific details. In some instances, well-known structures and

devices are shown in block diagram form in order to avoid obscuring the novelty of the exemplary embodiments presented herein.

[0029] The words “wireless power” is used herein to mean any form of energy associated with electric fields, magnetic fields, electromagnetic fields, or otherwise that is transmitted between from a transmitter to a receiver without the use of physical electromagnetic conductors.

[0030] FIG. 1 illustrates a wireless transmission or charging system 100, in accordance with various exemplary embodiments of the present invention. Input power 102 is provided to a transmitter 104 for generating a radiated field 106 for providing energy transfer. A receiver 108 couples to the radiated field 106 and generates an output power 110 for storing or consumption by a device (not shown) coupled to the output power 110. Both the transmitter 104 and the receiver 108 are separated by a distance 112. In one exemplary embodiment, transmitter 104 and receiver 108 are configured according to a mutual resonant relationship and when the resonant frequency of receiver 108 and the resonant frequency of transmitter 104 are very close, transmission losses between the transmitter 104 and the receiver 108 are minimal when the receiver 108 is located in the “near-field” of the radiated field 106.

[0031] Transmitter 104 further includes a transmit antenna 114 for providing a means for energy transmission and receiver 108 further includes a receive antenna 118 for providing a means for energy reception. The transmit and receive antennas are sized according to applications and devices to be associated therewith. As stated, an efficient energy transfer occurs by coupling a large portion of the energy in the near-field of the transmitting antenna to a receiving antenna rather than propagating most of the energy in an electromagnetic wave to the far field. When in this near-field a coupling mode may be developed between the transmit antenna 114 and the receive antenna 118. The area around the antennas 114 and 118 where this near-field coupling may occur is referred to herein as a coupling-mode region.

[0032] FIG. 2 shows a simplified schematic diagram of a wireless power transfer system. The transmitter 104 includes an oscillator 122, a power amplifier 124 and a filter and matching circuit 126. The oscillator is configured to generate a signal at a desired frequency, which may be adjusted in response to adjustment signal 123. The oscillator signal may be amplified by the power amplifier 124 with an amplification amount responsive to control signal 125. The filter and matching circuit 126 may be included to filter out harmonics or other unwanted frequencies and match the impedance of the transmitter 104 to the transmit antenna 114.

[0033] The receiver 108 may include a matching circuit 132 and a rectifier and switching circuit 134 to generate a DC power output to charge a battery 136 as shown in FIG. 2 or power a device coupled to the receiver (not shown). The matching circuit 132 may be included to match the impedance of the receiver 108 to the receive antenna 118. The receiver 108 and transmitter 104 may communicate on a separate communication channel 119 (e.g., Bluetooth, zig-bee, cellular, etc).

[0034] As illustrated in FIG. 3, antennas used in exemplary embodiments may be configured as a “loop” antenna 150, which may also be referred to herein as a “magnetic” antenna. Loop antennas may be configured to include an air core or a physical core such as a ferrite core. Air core loop antennas may be more tolerable to extraneous physical devices placed

in the vicinity of the core. Furthermore, an air core loop antenna allows the placement of other components within the core area. In addition, an air core loop may more readily enable placement of the receive antenna 118 (FIG. 2) within a plane of the transmit antenna 114 (FIG. 2) where the coupled-mode region of the transmit antenna 114 (FIG. 2) may be more powerful.

[0035] As stated, efficient transfer of energy between the transmitter 104 and receiver 108 occurs during matched or nearly matched resonance between the transmitter 104 and the receiver 108. However, even when resonance between the transmitter 104 and receiver 108 are not matched, energy may be transferred at a lower efficiency. Transfer of energy occurs by coupling energy from the near-field of the transmitting antenna to the receiving antenna residing in the neighborhood where this near-field is established rather than propagating the energy from the transmitting antenna into free space.

[0036] The resonant frequency of the loop or magnetic antennas is based on the inductance and capacitance. Inductance in a loop antenna is generally simply the inductance created by the loop, whereas, capacitance is generally added to the loop antenna’s inductance to create a resonant structure at a desired resonant frequency. As a non-limiting example, capacitor 152 and capacitor 154 may be added to the antenna to create a resonant circuit that generates resonant signal 156. Accordingly, for larger diameter loop antennas, the size of capacitance needed to induce resonance decreases as the diameter or inductance of the loop increases. Furthermore, as the diameter of the loop or magnetic antenna increases, the efficient energy transfer area of the near-field increases. Of course, other resonant circuits are possible. As another non-limiting example, a capacitor may be placed in parallel between the two terminals of the loop antenna. In addition, those of ordinary skill in the art will recognize that for transmit antennas the resonant signal 156 may be an input to the loop antenna 150.

[0037] Exemplary embodiments of the invention include coupling power between two antennas that are in the near-fields of each other. As stated, the near-field is an area around the antenna in which electromagnetic fields exist but may not propagate or radiate away from the antenna. They are typically confined to a volume that is near the physical volume of the antenna. In the exemplary embodiments of the invention, magnetic type antennas such as single and multi-turn loop antennas are used for both transmit (Tx) and receive (Rx) antenna systems since magnetic near-field amplitudes tend to be higher for magnetic type antennas in comparison to the electric near-fields of an electric-type antenna (e.g., a small dipole). This allows for potentially higher coupling between the pair. Furthermore, “electric” antennas (e.g., dipoles and monopoles) or a combination of magnetic and electric antennas is also contemplated.

[0038] The Tx antenna can be operated at a frequency that is low enough and with an antenna size that is large enough to achieve good coupling (e.g., >-4 dB) to a small Rx antenna at significantly larger distances than allowed by far field and inductive approaches mentioned earlier. If the Tx antenna is sized correctly, high coupling levels (e.g., -2 to -4 dB) can be achieved when the Rx antenna on a host device is placed within a coupling-mode region (i.e., in the near-field) of the driven Tx loop antenna.

[0039] FIG. 4 is a simplified block diagram of a transmitter 200, in accordance with an exemplary embodiment of the present invention. The transmitter 200 includes transmit cir-

cuitry **202** and a transmit antenna **204**. Generally, transmit circuitry **202** provides RF power to the transmit antenna **204** by providing an oscillating signal resulting in generation of near-field energy about the transmit antenna **204**. By way of example, transmitter **200** may operate at the 13.56 MHz ISM band.

[0040] Exemplary transmit circuitry **202** includes a fixed impedance matching circuit **206** for matching the impedance of the transmit circuitry **202** (e.g., **50** ohms) to the transmit antenna **204** and a low pass filter (LPF) **208** configured to reduce harmonic emissions to levels to prevent self-jamming of devices coupled to receivers **108** (FIG. 1). Other exemplary embodiments may include different filter topologies, including but not limited to, notch filters that attenuate specific frequencies while passing others and may include an adaptive impedance match, that can be varied based on measurable transmit metrics, such as output power to the antenna or DC current draw by the power amplifier. Transmit circuitry **202** further includes a power amplifier **210** configured to drive an RF signal as determined by an oscillator **212**. The transmit circuitry may be comprised of discrete devices or circuits, or alternately, may be comprised of an integrated assembly. An exemplary RF power output from transmit antenna **204** may be on the order of 2.5 Watts.

[0041] Transmit circuitry **202** further includes a controller **214** for enabling the oscillator **212** during transmit phases (or duty cycles) for specific receivers, for adjusting the frequency of the oscillator, and for adjusting the output power level for implementing a communication protocol for interacting with neighboring devices through their attached receivers.

[0042] The transmit circuitry **202** may further include a load sensing circuit **216** for detecting the presence or absence of active receivers in the vicinity of the near-field generated by transmit antenna **204**. By way of example, a load sensing circuit **216** monitors the current flowing to the power amplifier **210**, which is affected by the presence or absence of active receivers in the vicinity of the near-field generated by transmit antenna **204**. Detection of changes to the loading on the power amplifier **210** are monitored by controller **214** for use in determining whether to enable the oscillator **212** for transmitting energy to communicate with an active receiver.

[0043] Transmit antenna **204** may be implemented as an antenna strip with the thickness, width and metal type selected to keep resistive losses low. In a conventional implementation, the transmit antenna **204** can generally be configured for association with a larger structure such as a table, mat, lamp or other less portable configuration. Accordingly, the transmit antenna **204** generally will not need “turns” in order to be of a practical dimension. An exemplary implementation of a transmit antenna **204** may be “electrically small” (i.e., fraction of the wavelength) and tuned to resonate at lower usable frequencies by using capacitors to define the resonant frequency. In an exemplary application where the transmit antenna **204** may be larger in diameter, or length of side if a square loop, (e.g., **0.50** meters) relative to the receive antenna, the transmit antenna **204** will not necessarily need a large number of turns to obtain a reasonable capacitance.

[0044] The transmitter **200** may gather and track information about the whereabouts and status of receiver devices that may be associated with the transmitter **200**. Thus, the transmitter circuitry **202** may include a presence detector **280**, an enclosed detector **290**, or a combination thereof, connected to the controller **214** (also referred to as a processor herein). The controller **214** may adjust an amount of power delivered by

the amplifier **210** in response to presence signals from the presence detector **280** and the enclosed detector **290**. The transmitter may receive power through a number of power sources, such as, for example, an AC-DC converter (not shown) to convert conventional AC power present in a building, a DC-DC converter (not shown) to convert a conventional DC power source to a voltage suitable for the transmitter **200**, or directly from a conventional DC power source (not shown).

[0045] As a non-limiting example, the presence detector **280** may be a motion detector utilized to sense the initial presence of a device to be charged that is inserted into the coverage area of the transmitter. After detection, the transmitter may be turned on and the RF power received by the device may be used to toggle a switch on the Rx device in a predetermined manner, which in turn results in changes to the driving point impedance of the transmitter.

[0046] As another non-limiting example, the presence detector **280** may be a detector capable of detecting a human, for example, by infrared detection, motion detection, or other suitable means. In some exemplary embodiments, there may be regulations limiting the amount of power that a transmit antenna may transmit at a specific frequency. In some cases, these regulations are meant to protect humans from electromagnetic radiation. However, there may be environments where transmit antennas are placed in areas not occupied by humans, or occupied infrequently by humans, such as, for example, garages, factory floors, shops, and the like. If these environments are free from humans, it may be permissible to increase the power output of the transmit antennas above the normal power restrictions regulations. In other words, the controller **214** may adjust the power output of the transmit antenna **204** to a regulatory level or lower in response to human presence and adjust the power output of the transmit antenna **204** to a level above the regulatory level when a human is outside a regulatory distance from the electromagnetic field of the transmit antenna **204**.

[0047] As a non-limiting example, the enclosed detector **290** (may also be referred to herein as an enclosed compartment detector or an enclosed space detector) may be a device such as a sense switch for determining when an enclosure is in a closed or open state. When a transmitter is in an enclosure that is in an enclosed state, a power level of the transmitter may be increased.

[0048] In exemplary embodiments, a method by which the transmitter **200** does not remain on indefinitely may be used. In this case, the transmitter **200** may be programmed to shut off after a user-determined amount of time. This feature prevents the transmitter **200**, notably the power amplifier **210**, from running long after the wireless devices in its perimeter are fully charged. This event may be due to the failure of the circuit to detect the signal sent from either the repeater or the receive coil that a device is fully charged. To prevent the transmitter **200** from automatically shutting down if another device is placed in its perimeter, the transmitter **200** automatic shut off feature may be activated only after a set period of lack of motion detected in its perimeter. The user may be able to determine the inactivity time interval, and change it as desired. As a non-limiting example, the time interval may be longer than that needed to fully charge a specific type of wireless device under the assumption of the device being initially fully discharged.

[0049] FIG. 5 is a simplified block diagram of a receiver **300**, in accordance with an exemplary embodiment of the present invention. The receiver **300** includes receive circuitry

302 and a receive antenna **304**. Receiver **300** further couples to device **350** for providing received power thereto. It should be noted that receiver **300** is illustrated as being external to device **350** but may be integrated into device **350**. Generally, energy is propagated wirelessly to receive antenna **304** and then coupled through receive circuitry **302** to device **350**.

[0050] Receive antenna **304** is tuned to resonate at the same frequency, or near the same frequency, as transmit antenna **204** (FIG. 4). Receive antenna **304** may be similarly dimensioned with transmit antenna **204** or may be differently sized based upon the dimensions of the associated device **350**. By way of example, device **350** may be a portable electronic device having diametric or length dimension smaller than the diameter or length of transmit antenna **204**. In such an example, receive antenna **304** may be implemented as a multi-turn antenna in order to reduce the capacitance value of a tuning capacitor (not shown) and increase the receive antenna's impedance. By way of example, receive antenna **304** may be placed around the substantial circumference of device **350** in order to maximize the antenna diameter and reduce the number of loop turns (i.e., windings) of the receive antenna and the inter-winding capacitance.

[0051] Receive circuitry **302** provides an impedance match to the receive antenna **304**. Receive circuitry **302** includes power conversion circuitry **306** for converting a received RF energy source into charging power for use by device **350**. Power conversion circuitry **306** includes an RF-to-DC converter **308** and may also include a DC-to-DC converter **310**. RF-to-DC converter **308** rectifies the RF energy signal received at receive antenna **304** into a non-alternating power while DC-to-DC converter **310** converts the rectified RF energy signal into an energy potential (e.g., voltage) that is compatible with device **350**. Various RF-to-DC converters are contemplated, including partial and full rectifiers, regulators, bridges, doublers, as well as linear and switching converters.

[0052] Receive circuitry **302** may further include switching circuitry **312** for connecting receive antenna **304** to the power conversion circuitry **306** or alternatively for disconnecting the power conversion circuitry **306**. Disconnecting receive antenna **304** from power conversion circuitry **306** not only suspends charging of device **350**, but also changes the "load" as "seen" by the transmitter **200** (FIG. 2).

[0053] As disclosed above, transmitter **200** includes load sensing circuit **216** which detects fluctuations in the bias current provided to transmitter power amplifier **210**. Accordingly, transmitter **200** has a mechanism for determining when receivers are present in the transmitter's near-field.

[0054] When multiple receivers **300** are present in a transmitter's near-field, it may be desirable to time-multiplex the loading and unloading of one or more receivers to enable other receivers to more efficiently couple to the transmitter. This "unloading" of a receiver is also known herein as a "cloaking." A receiver may also be cloaked in order to eliminate coupling to other nearby receivers or to reduce loading on nearby transmitters. Furthermore, this switching between unloading and loading as controlled by receiver **300** and detected by transmitter **200** provides a communication mechanism from receiver **300** to transmitter **200** as is explained more fully below. Additionally, a protocol can be associated with the switching which enables the sending of a message from receiver **300** to transmitter **200**. By way of example, a switching speed may be on the order of 100 μ sec.

[0055] In an exemplary embodiment, communication between the transmitter and the receiver refers to a device

sensing and charging control mechanism, rather than conventional two-way communication. In other words, the transmitter uses, for example, on/off keying of the transmitted signal to adjust whether energy is available in the near-field. The receivers interpret these changes in energy as a message from the transmitter. From the receiver side, the receiver uses tuning and de-tuning of the receive antenna to adjust how much power is being accepted from the near-field. The transmitter can detect this difference in power used from the near-field and interpret these changes as signal forming a message from the receiver.

[0056] Receive circuitry **302** may further include signaling detector and beacon circuitry **314** used to identify received energy fluctuations, which may correspond to informational signaling from the transmitter to the receiver. Furthermore, signaling and beacon circuitry **314** may also be used to detect the transmission of a reduced RF signal energy (i.e., a beacon signal) and to rectify the reduced RF signal energy into a nominal power for awakening either un-powered or power-depleted circuits within receive circuitry **302** in order to configure receive circuitry **302** for wireless charging.

[0057] Receive circuitry **302** further includes processor **316** for coordinating the processes of receiver **300** described herein including the control of switching circuitry **312** described herein. Cloaking of receiver **300** may also occur upon the occurrence of other events including detection of an external wired charging source (e.g., wall/USB power) providing charging power to device **350**. Processor **316**, in addition to controlling the cloaking of the receiver, may also monitor beacon circuitry **314** to determine a beacon state and extract messages sent from the transmitter. Processor **316** may also adjust DC-to-DC converter **310** for improved performance.

[0058] FIG. 6 shows a simplified schematic of a portion of transmit circuitry for carrying out messaging between a transmitter and a receiver. In some exemplary embodiments of the present invention, a means for communication may be enabled between the transmitter and the receiver. In FIG. 6 a power amplifier **210** drives the transmit antenna **204** to generate the radiated field. The power amplifier is driven by a carrier signal **220** that is oscillating at a desired frequency for the transmit antenna **204**. A transmit modulation signal **224** is used to control the output of the power amplifier **210**.

[0059] The transmit circuitry can send signals to receivers by using an ON/OFF keying process on the power amplifier **210**. In other words, when the transmit modulation signal **224** is asserted, the power amplifier **210** will drive the frequency of the carrier signal **220** out on the transmit antenna **204**. When the transmit modulation signal **224** is deactivated, the power amplifier will not drive any signal on the transmit antenna **204**.

[0060] The transmit circuitry of FIG. 6 also includes a load sensing circuit **216** that supplies power to the power amplifier **210** and generates a receive signal **235**. In the load sensing circuit **216**, a voltage drop across resistor R_s develops between the power in signal **226** and the power supply **228** to the power amplifier **210**. Any change in the power consumed by the power amplifier **210** will cause a change in the voltage drop that will be amplified by differential amplifier **230**. When the transmit antenna is in coupled mode with a receive antenna in a receiver (not shown in FIG. 6) the amount of current drawn by the power amplifier **210** will change. In other words, if no coupled mode resonance exist for the transmit antenna **204**, the power required to drive the radiated

field will be a first amount. If a coupled mode resonance exists, the amount of power consumed by the power amplifier **210** will go up because much of the power is being coupled into the receive antenna. Thus, the receive signal **235** can indicate the presence of a receive antenna coupled to the transmit antenna **235** and can also detect signals sent from the receive antenna. Additionally, a change in receiver current draw will be observable in the transmitter's power amplifier current draw, and this change can be used to detect signals from the receive antennas.

[0061] Details of some exemplary embodiments for cloaking signals, beacon signals, and circuits for generating these signals can be seen in U.S. Utility patent application Ser. No. 12/249,873, entitled "REVERSE LINK SIGNALING VIA RECEIVE ANTENNA IMPEDANCE MODULATION" filed on Oct. 10, 2008; and in U.S. Utility patent application Ser. No. 12/249,861, entitled "TRANSMIT POWER CONTROL FOR A WIRELESS CHARGING SYSTEM" filed on Oct. 10, 2008, both herein incorporated by reference in their entirety.

[0062] Details of exemplary communication mechanisms and protocols can be seen in U.S. Utility patent application Ser. No. 12/249,866 entitled "SIGNALING CHARGING IN WIRELESS POWER ENVIRONMENT" filed on Oct. 10, 2008, the contents of which is incorporated by reference herein in its entirety.

[0063] FIG. 7 depicts a chargeable device **700** that may comprise any known and suitable chargeable device. As non-limiting examples, chargeable device **700** may comprise a cellular telephone, a portable media player, a camera, a gaming device, a navigation device, a headset (e.g., a Bluetooth headset), a tool, a toy, or any combination thereof. Chargeable device **700** may include at least one receive antenna **702**, at least one coil **705**, or any combination thereof. Each of receive antenna **702** and coil **705** may be configured to receive power wirelessly transmitted from a suitable wireless power source. More specifically, according to one exemplary embodiment, antenna **702** and an associated receiver, such as receiver **108** of FIG. 2, may be configured to receive wireless power transmitted from a wireless power source within an associated near-field region. Further, according to another exemplary embodiment, coil **705** and an associated receiver, such as receiver **108** of FIG. 2, may be configured to receive wireless power transmitted from a wireless power source via inductive coupling. Additionally, chargeable device **700** may be configured to store received power within a battery (e.g., battery **136** of FIG. 2) of chargeable device **700**. It is noted that the terms "receive antenna" and "coil" may each be referred to herein as a "receive element."

[0064] Furthermore, in accordance with various exemplary embodiments, chargeable device **700** may be configured to detect one or more wireless chargers, which are positioned within a charging region of chargeable device **700** and include one or more wireless transmit elements (e.g., a wireless transmit antenna or a coil). More specifically, chargeable device **700** may be configured to detect one or more wireless chargers according to one or more specific protocols and/or one or more specific frequencies. For example only, chargeable device **700** may be configured to detect one or more wireless chargers by sampling for wireless chargers operating with one or more specific wireless charging protocols, sampling for wireless chargers resonating at one more specific frequencies, or both. As described more fully below, upon detection of a wireless charger, chargeable device **700** may be config-

ured to determine an amount of power received from the detected wireless charger, including at each frequency and with each protocol that the detected wireless charger is configured to transmit.

[0065] According to one exemplary embodiment, chargeable device **700** may be configured to detect a wireless charger, which is positioned within a near-field region of chargeable device **700** and is configured to wirelessly transmit power at one or more suitable frequencies (e.g., unlicensed ISM bands) via a near-field resonance protocol. It is noted that various frequencies may be suitable for wireless power transmission in one location (e.g., a first country) but not suitable in another location (e.g., a second country). As such, according to one exemplary embodiment, chargeable device **700** may be configured to determine its location via a location device **701**, and, thereafter, determine which one or more frequencies are suitable for wireless power transmission. For example only, location device **701** may comprise a Global Positioning System (GPS) device. By way of example only, chargeable device **700** may be configured to detect a wireless charger positioned within an associated near-field region and configured to transmit wireless power, via near-field resonance, at one or more of 6.78 MHz, 13.56 MHz, 27.12, and 40.68 MHz. Further, according to one exemplary embodiment, chargeable device **700** may be configured to detect a wireless charger positioned within an associated charging region and configured to convey wireless power via an inductive coupling protocol.

[0066] Moreover, chargeable device **700** may be configured to establish a communication link with a detected wireless charger and, upon establishing the communication link, may wirelessly receive data (e.g., audio files, data files, or video files) from the detected wireless charger, wirelessly transmit data to the detected wireless charger, or both. It is noted that chargeable device **700** may be configured to detect and receive wireless power from multiple versions of wireless chargers. It is noted further that chargeable device **700** may be configured to identify a version of a detected wireless charger and, as a result, may receive wireless power from and communicate with the detected wireless charger accordingly. Additionally, upon establishing the communication link, chargeable device **700** may be configured to control an operation of a detected wireless charger (e.g., transmission of power, synchronization of data, displaying media, or any user-interface functionality).

[0067] Upon detection of one or more wireless chargers, chargeable device **700** may be further configured to select at least one of the detected one or more wireless charging to receive power therefrom for optimizing an amount of power received by chargeable device **700**. A method of optimizing an amount of power received by chargeable device **700** may be based on at least one of one or more charging protocols of each detected wireless charger, one or more charging frequencies of each detected wireless charger, a position of each detected wireless charger relative to chargeable device **700**, and a version of each detected wireless charger. It is noted that relatively small chargeable devices (e.g., a Bluetooth headset) may charge more efficiently at a higher frequency (e.g., 40.68 MHz) in comparison to a lower frequency (6.78 MHz). On the other hand, relatively large chargeable devices (e.g., a camera) may charge more efficiently at a lower frequency (e.g., 6.78 MHz) in comparison to a higher frequency (40.68 MHz).

[0068] FIG. 8 illustrates a chargeable device **700A**, which is similar to chargeable device **700** of FIG. 7 and, therefore,

will not be explained again. However, in FIG. 8, chargeable device 700A does not include a coil and only includes one receive antenna 702. It is noted that in an embodiment wherein chargeable device 700A includes a single receive element (i.e., receive antenna 702), chargeable device 700A may be configured to receive wireless power from only one wireless transmit element at any one time. Accordingly, in this exemplary embodiment, chargeable device 700A may be configured to determine which detected wireless charger may enable for optimal charging. Stated another way, chargeable device 700A may be configured to determine which detected wireless charger and, more specifically, which transmit element of the one or more detected wireless chargers may enable for maximum efficiency, maximum charging rate, minimum interference, or any combination thereof. Further, according to another exemplary embodiment, chargeable device 700A may be configured to determine which plurality of transmit elements of the one or more detected wireless chargers, utilizing a time domain multiplexing method based upon allocated activation time slots for each selected transmit element, may enable for maximum efficiency, maximum charging rate, minimum interference, or any combination thereof.

[0069] FIG. 9 illustrates a system 730 including chargeable device 700A and a wireless charger 732. Wireless charger 732 includes a first transmit antenna 734 configured to transmit wireless power at a frequency of, for example only, 13.56 MHz. Further, wireless charger 732 includes a second transmit antenna 736 configured to transmit wireless power at a frequency of, for example only, 6.78 MHz. According to one contemplated operation of system 730, chargeable device 700 may detect wireless charger 732, which is positioned within an associated charging region and operating with one or more specific protocols (e.g., near-field resonance) and/or resonating at one or more specific frequencies (e.g., 6.78 MHz and 13.56 MHz). Further, upon detection of wireless charger 732, a communication link 733 between chargeable device 700A and wireless charger 732 may be established. Moreover, after wireless charger 732 has been detected, an optimal scenario for charging chargeable device 700A with wireless charger 732 may be determined.

[0070] According to one exemplary embodiment, determining an optimal charging scenario may include determining which single protocol (i.e., either near-field resonance via transmit antenna 734 or near-field resonance via transmit antenna 736) enables for optimal charging (e.g., maximum efficiency, maximum charging rate, minimum interference, or any combination thereof) of chargeable device 700A. As an example, chargeable device 700A, wireless charger 732, or a combination thereof, may determine that transmit antenna 736 enables for optimal charging of chargeable device 700A. As a more specific example, chargeable device 700A may receive wireless power from transmit antenna 734 at a first frequency (e.g., 13.56 MHz.), determine an amount of power received from transmit antenna 734 and, thereafter, provide this information to wireless charger 732. Further, chargeable device 700A may receive wireless power from transmit antenna 736 at a second frequency (e.g., 6.78 MHz.), determine an amount of power received from transmit antenna 736 and, thereafter, provide this information to wireless charger 732. Wireless charger 732 may then inform chargeable device 700A, via communication link 733, which protocol (i.e., either near-field resonance via transmit antenna 734 or near-field resonance via transmit antenna 736) facilitates optimal

charging by wireless charger 732. After determining which transmit element facilitates optimal charging, chargeable device 700A, wireless charger 732, or a combination thereof, may select the transmit element, and wireless power may be transmitted to chargeable device 700A.

[0071] It is noted that upon receiving information from chargeable device 700A relating to an amount of power received from a specific transmit element (e.g., transmit antenna 734 or transmit antenna 736), wireless charger 732 may be configured to increase or decrease an amount of power transmitted from the specific transmit element. It is further noted that depending on the type of device (i.e., whether chargeable device 700A is, for example only, a mobile telephone, a media player, or a Bluetooth headset) and/or a type of battery within chargeable device 700A, wireless charger 732 may be configured to increase or decrease an amount of power transmitted from a specific transmit element.

[0072] According to another exemplary embodiment, determining an optimal charging scenario may include determining which plurality of transmit elements, utilizing a time domain multiplexing method, may provide for optimal charging. As an example, chargeable device 700A, wireless charger 732, or a combination thereof, may determine that transmit antenna 734 may be time multiplexed with transmit antenna 736 to enable for optimized charging of chargeable device 700A.

[0073] FIG. 10 illustrates another system 750 including chargeable device 700. System 750 further includes a first wireless charger 752, a second wireless charger 754, and a third wireless charger 756, each of which is positioned within an associated charging region of chargeable device 700. As illustrated in FIG. 10, first wireless charger 752 includes a transmit antenna 760 and may be configured to transmit wireless power at a frequency of, for example only, 40.68 MHz. Further, second wireless charger 754 includes a first transmit antenna 762 configured to transmit wireless power at a frequency of, for example only, 27.12 MHz., and a second transmit antenna 764 configured to transmit wireless power at a frequency of, for example only, 6.78 MHz. Moreover, third wireless charger 756 includes a transmit antenna 766 configured to transmit wireless power at a frequency of, for example only, 13.56 MHz. Third wireless charger 756 further includes a coil 768 configured to transmit power, via inductive coupling, to a coil (e.g., coil 705) adequately aligned therewith.

[0074] According to one contemplated operation of system 750, chargeable device 700 may detect one or more wireless chargers positioned within an associated charging region and operating with one or more specific protocols (e.g., near-field resonance and/or inductive coupling) and/or resonating at one or more specific frequencies (e.g., unlicensed ISM bands). Accordingly, chargeable device 700 may detect each of first wireless charger 752, second wireless charger 754, and third wireless charger 756. Moreover, upon detection, respective communication links 735, 737, and 739 may be established between chargeable device 700 and first wireless charger 752, second wireless charger 754, and third wireless charger 756.

[0075] Furthermore, upon detection of first wireless charger 752, second wireless charger 754, and third wireless charger 756, an optimal charging scenario for charging chargeable device 700 may be determined. Determining an optimal charging scenario may include, as noted above, determining an optimal charging scenario for one or more detected wireless chargers that may include one or more protocols

and/or are configured to transmit wireless power at one or more frequencies. Furthermore, determining an optimal charging scenario may include determining which plurality of transmit elements within one or more detected wireless chargers, utilizing a time domain multiplexing method, may provide for optimal charging. For example, according to one exemplary embodiment, chargeable device **700** may be configured to sequentially receive wireless power from each individual transmit element within system **750**. Further, after receiving wireless power from each individual transmit element within system **750**, chargeable device **700** may be configured to determine which one or more transmit elements enable for optimal charging.

[0076] More specifically, for example, receive antenna **702** may be configured to receive wireless power from transmit antenna **760**, via near-field resonance, at a frequency (e.g., 40.68 MHz.), and an amount of power received from transmit antenna **760** may be determined by chargeable device **700**. In addition, receive antenna **702** may be configured to receive wireless power from transmit antenna **762**, via near-field resonance, at a frequency (e.g., 27.12 MHz.), and chargeable device **700** may determine an amount of power received from transmit antenna **762**. Further, receive antenna **702** may be configured to receive wireless from power transmit antenna **764**, via near-field resonance, at a frequency (e.g., 6.78 MHz.), and an amount of power received from transmit antenna **764** may be determined by chargeable device **700**. Moreover, transmit antenna **700** may be configured to receive wireless power from transmit antenna **766**, via near-field resonance, at a frequency (e.g., 6.78 MHz.), and an amount of power received from transmit antenna **766** may be determined by chargeable device **700**. Furthermore, coil **705** may be configured to receive wireless power, via inductive coupling, from coil **768** of wireless charger **756** and chargeable device **700** may determine an amount of received from coil **768**. Thereafter, chargeable device **700** may determine which one or more transmit elements enable for maximum efficiency, maximum charging rate, minimum interference, or any combination thereof. Accordingly, as an example, chargeable device **700** may determine that wireless charger transmit antenna **762** of wireless charger **754** and coil **768** of wireless charger **756** enable for optimal charging. After determining which one or more transmit elements enable for an optimal charging scenario, chargeable device **700** may select the one or more transmit elements and wireless power may be transmitted to chargeable device **700A** accordingly.

[0077] Furthermore, as noted above, a time domain multiplexing method may be utilized to provide for optimal charging. As such, chargeable device **700** may be configured to determine an optimal charging scenario by utilizing a time domain multiplexing method based upon allocated activation time slots for two or more transmit elements. Accordingly, as an example, chargeable device **700** may determine that, in addition to receiving wireless power from coil **768**, transmit antenna **760** of wireless charger **752** may be time multiplexed with transmit antenna **766** of wireless charger **756** to enable for optimized charging.

[0078] FIG. 11 depicts a chargeable device **700B**, which is similar to chargeable device **700** of FIG. 7 and, therefore, will not be explained again. However, in FIG. 11, chargeable device **700B** includes a plurality of receive antennas **702**. Although chargeable device **700B** is depicted as having only two receive antennas **702**, chargeable device **700B** may include any number of receive antennas **702**. Similarly to

chargeable device **700**, chargeable device **700B** may be configured to detect one or more wireless chargers positioned within an associated charging region and including one or more transmit elements. Furthermore, upon detection of one or more wireless chargers, chargeable device **700B** may be configured to optimize an amount of power received from the one or more wireless chargers and, more specifically, the one or more transmit elements. It is noted that in an embodiment wherein chargeable device **700B** includes multiple receive antennas, chargeable device **700B** may be configured to receive wireless power from multiple transmit antennas associated with one or more wireless chargers at any one time.

[0079] Determining an optimal charging scenario may include determining an optimal charging scenario for one or more detected wireless chargers that may include one or more protocols and/or may be configured to transmit wireless power at one or more frequencies. More specifically, determining an optimal charging scenario may include determining which plurality of transmit elements associated with one or more detected wireless chargers enables for optimal charging of chargeable device **700B**. It is noted that in an embodiment wherein chargeable device **700B** includes multiple antennas, a time domain multiplexing method, as mentioned above, may still be used.

[0080] FIG. 12 illustrates a system **780** including chargeable device **700B**. System **780** further includes first wireless charger **752**, second wireless charger **754**, and third wireless charger **756**, each of which is positioned within an associated charging region of chargeable device **700B**. First wireless charger **752**, second wireless charger **754**, and third wireless charger **756** have been described above and, therefore, will not be explained again. However, it is noted that first wireless charger **752** includes a coil **763**. According to one contemplated operation of system **780**, chargeable device **700B** may detect one or more wireless chargers within an associated charging region and operating with one or more specific protocols (e.g., near-field resonance and/or inductive coupling) and/or resonating at one or more specific frequencies (i.e., unlicensed ISM bands). Accordingly, chargeable device **700B** may detect each of first wireless charger **752**, second wireless charger **754**, and third wireless charger **756**.

[0081] Moreover, upon detection thereof, respective communication links **765**, **767**, and **769** may be established between chargeable device **700B** and first wireless charger **752**, second wireless charger **754**, and third wireless charger **756**. As noted above with respect to chargeable device **700**, upon establishing a communication link with a detected wireless charger, chargeable device **700B** may be configured to control an operation of a detected wireless charger (e.g., transmission of power, synchronization of data, displaying media, or any user-interface functionality). Further, upon detection of first wireless charger **752**, second wireless charger **754**, and third wireless charger **756**, chargeable device **700B** may be configured to determine an optimal charging scenario.

[0082] For example, with reference to FIG. 12, chargeable device **700B** may be configured to sequentially receive wireless power from each individual transmit element (i.e., transmit antenna **760**, transmit antenna **762**, transmit antenna **764**, transmit antenna **766**, coil **763**, and coil **768**). Furthermore, chargeable device **700B** may be configured to sequentially receive wireless power from every possible and suitable combination of two or more transmit elements. It is noted that chargeable device **700B** may only simultaneously receive

power from a number of transmit antennas equal to a number of receive antennas **702**. For example, if chargeable device **700B** comprises two receive antennas **702**, chargeable device **700B** may be configured to simultaneously receive wireless power from every possible combination of two transmit antennas. However, it is noted that coil **705** may simultaneously receive wireless power from both coil **763** and **768**, so long as coil **763** and **768** are each in phase with coil **705**.

[0083] After determining an amount of power received from each suitable combination of transmit elements, and optionally each transmit element individually, chargeable device **700B** may be configured to identify one or more transmit elements for optimal charging. By way of example, in an embodiment wherein chargeable device **700B** includes two antennas **702**, charging device **700B** may identify transmit antenna **764**, transmit antenna **766**, and coil **763** as transmit elements for enabling an optimal charging scenario. As another example, charging device **700B** may identify transmit antenna **766**, transmit antenna **762**, and coil **768** as transmit elements for enabling an optimal charging scenario. Further, chargeable device **700B** may be configured to determine an optimal charging scenario by utilizing a time domain multiplexing method based upon allocated activation time slots for two or more transmit antennas.

[0084] FIG. 13 is a flowchart illustrating a method **680**, in accordance with one or more exemplary embodiments. Method **680** may include detecting one or more transmit elements positioned within an associated charging region (depicted by numeral **682**). Method **680** may further include selecting at least one transmit element of the detected one or more transmit elements to receive wireless power therefrom to enable optimal charging of the chargeable device (depicted by numeral **684**).

[0085] FIG. 14 depicts a charger **900** that may comprise any known and suitable charger configured to transmit wireless power. Charger **900** may include at least one transmit antenna **704** configured to wirelessly transmit power to at least one chargeable device (e.g., chargeable device **700**). More specifically, transmit antenna **704** and an associated transmitter, such as transmitter **104** of FIG. 2, may be configured to transmit wireless power at a frequency (e.g., an unlicensed ISM band) to a receiver within an associated near-field region. Further, charger **900** may include at least one coil **902** configured to transmit wireless power to a chargeable device (e.g., chargeable device **700**) via inductive coupling.

[0086] Furthermore, in accordance with various exemplary embodiments of the present invention, charger **900** may be configured to detect one or more chargeable devices, which are positioned within a charging region of charger **900** and are configured to receive wireless power via a suitable protocol. More specifically, charger **900** may be configured to detect one or more chargeable devices according to one or more specific protocols, one or more specific frequencies, or both. For example only, charger **900** may be configured to detect chargeable devices within a charging region by sampling for chargeable devices operating with specific wireless charging protocols, sampling for chargeable devices resonating at specific wireless charging frequencies, or both.

[0087] According to one exemplary embodiment, charger **900** may be configured to detect one or more chargeable devices positioned within an associated near-field region and configured to receive wireless power at one or more frequencies via near-field resonance. For example only, charger **900** may be configured to detect one or more chargeable devices

positioned within an associated near-field region and configured to receive wireless power, via near-field resonance, at a suitable frequency, such as an unlicensed ISM band (e.g., 13.56 MHz). It is noted that various frequencies may be suitable for wireless power transmission in one location (e.g., a first country) but not suitable in another location (e.g., a second country). As such, according to one exemplary embodiment, charger **900** may be configured to determine its location via a location device **901** and, thereafter, determine which one or more frequencies are suitable for wireless power transmission. For example only, location device **901** may comprise a Global Positioning System (GPS) device. Further, according to one exemplary embodiment, charger **900** may be configured to detect one or more chargeable devices positioned within an associated charging region and configured to receive wireless power via an inductive coupling protocol.

[0088] Moreover, charger **900** may be configured to establish a communication link with a detected chargeable device and, upon establishing the communication link, may wirelessly receive data (e.g., audio files, data files, or video files) from the chargeable device, wirelessly transmit data to the chargeable device, or both. Additionally, it is noted that charger **900** may be configured to perform various operations (e.g., synchronizing data and/or displaying media) while transmitting power to one or more chargeable devices. Furthermore, charger **900** may be configured to detect and transmit wireless to multiple versions of chargeable devices. Accordingly, charger **900** may be configured to identify a version of a detected chargeable device and transmit power to and communicate with the detected chargeable device in a suitable manner. It is further noted that charger **900** may attempt to communicate with each detected chargeable device according to a common version protocol. However, in the event that a detected chargeable device is not compatible with the common version protocol, charger **900** may be configured to communicate with the chargeable device in a suitable manner using a suitable version protocol.

[0089] Additionally, upon detection of one or more chargeable devices, charger **900** may be configured to determine an optimal charging solution which may maximize efficiency, maximize charging rates, minimize interference, or any combination thereof, for charging the one or more detected chargeable devices. More specifically, for example, charger **900** may be configured to determine an optimal solution for providing wireless power to one or more of the detected chargeable devices for a given set of conditions (e.g., the number of available transmit elements within charger **900** compared to the number of detected chargeable devices, the charging levels of each of the detected chargeable devices, or the amount of power received by each detected chargeable devices (i.e., the charging efficiency between charger **900** and each of the detected chargeable devices)).

[0090] FIG. 15 illustrates a system **910** including a charger **900A**, a first chargeable device **902**, and a second chargeable device **903**. As illustrated, each of first chargeable device **902** and second chargeable device **903** include a receive antenna **702** and each are configured to receive wireless power transmitted at a specific frequency via near-field resonance. It is noted that charger **900A** is similar to charger **900** of FIG. 13 and, therefore, will not be described in detail. However, it is noted that charger **900A** does not include a coil and only includes a single transmit antenna **704**.

[0091] According to one contemplated operation of system **910**, charger **900A** may detect each of first chargeable device

902 and second chargeable device **903** via any suitable manner. According to one contemplated operation of system **910**, charger **900A** may detect each of first chargeable device **902** and second chargeable device **903**, each of which being positioned within an associated charging region and operating with one or more wireless power protocols (e.g., near-field resonance) and/or resonating at one or more wireless power frequencies (e.g., unlicensed ISM bands). Moreover, upon detection thereof, respective communication links **905** and **907** may be established between charger **900A** and each of first chargeable device **902** and second chargeable device **903**. Furthermore, upon detection of first chargeable device **902** and second chargeable device **903**, charger **900A** may determine an optimal charging solution for system **910**. It is noted that in an embodiment wherein charger **900A** includes a single transmit element (i.e., transmit antenna **704**), charger **900A** may be configured to transmit wireless power to only one chargeable device at any one time.

[0092] As such, according to one exemplary embodiment, charger **900A** may be configured to determine which single detected chargeable device (i.e., either first chargeable device **902** or second chargeable device **903**) should be charged to enable for an optimal charging solution. As one example, charger **900A** may be configured to determine charging efficiencies between charger **900A** and each of first chargeable device **902** and second chargeable device **903**. Thereafter, to reduce power loss, charger **900A** may be configured to convey wireless power to the device that has the highest charging efficiency. More specifically, for example, charger **900A** may be configured to sequentially transmit wireless power to each of first chargeable device **902** and second chargeable device **903**. Further, charger **900A** may be configured to request and receive a signal from each of first chargeable device **902** and second chargeable device **903** identifying an amount of power received by each of first chargeable device **902** and second chargeable device **903**. Thereafter, charger **900A** may determine which chargeable device has a higher charging efficiency and, thereafter, convey power thereto. By way of example, charger **900A** may determine that a charging efficiency with first chargeable device **902** is greater than a charging efficiency with second chargeable device **903** and, therefore, charger **900A** may select first chargeable device **902** and convey power thereto.

[0093] As another example, charger **900A** may be configured to charge a device having the greatest need for a charge. More specifically, for example, charger **900A** may be configured to determine, via communication means, a charging level of each of first chargeable device **902** and second chargeable device **903** and, thereafter, select and convey wireless power to the device that has the least charged battery. By way of example, charger **900A** may determine that a battery of second chargeable device **903** has a lower charging level than a battery of first chargeable device **902** and, as a result, charger **900A** may select and convey wireless power to second chargeable device **903**. Furthermore, after a charging level of the battery of second chargeable device **903** has reached an acceptable status, charger **900A** may convey wireless power to first chargeable device **902**. Further, according to another exemplary embodiment, charger **900A** may be configured to determine whether a time domain multiplexing method, based upon allocated activation time slots for each of first chargeable device **902** and second chargeable device **903**, may enable for an optimal charging solution.

[0094] FIG. 16 illustrates a system **950** including charger **900B**, a first chargeable device **911**, a second chargeable device **912**, a third chargeable device **913**, and a fourth chargeable device **914**. As illustrated, each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914** include an antenna **702** configured to receive wireless power transmitted at a specific frequency via near-field resonance. Furthermore, each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914** include a coil **909** configured to receive wireless power via inductive coupling. It is noted that charger **900B** is similar to charger **900** of FIG. 13 and, therefore, will not be described in detail. However, it is noted that charger **900B** includes two transmit antennas **704**. According to one contemplated operation of system **950**, charger **900B** may detect each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914** via any suitable means. According to one contemplated operation of system **950**, charger **900B** may detect each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914**, each of which being positioned within an associated charging region and operating with one or more wireless power protocols (e.g., near-field resonance) and/or resonating at one or more wireless power frequencies (e.g., unlicensed ISM bands).

[0095] Moreover, upon detection thereof, respective communication links **970**, **971**, **972**, and **973** may be established between charger **900** and each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and a fourth chargeable device **914**. Furthermore, upon detection of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914**, charger **900B** may determine an optimal charging solution for system **950**.

[0096] It is noted that charger **900B** may simultaneously transmit power to a number of receive antennas (i.e., receive antenna **702**) equal to a number of transmit antennas (i.e., transmit antennas **704**). For example, in the embodiment illustrated in FIG. 15, charger **900B** may be configured to simultaneously transmit wireless power to two transmit antennas **704**. Furthermore, it is noted that coil **902** may simultaneously transmit wireless power to multiple coils **909**, so long as the coils **909** are in phase with coil **902**.

[0097] According to one exemplary embodiment, charger **900B** may be configured to determine which one or more detected chargeable devices should be charged to enable for an optimal charging solution. As one example, charger **900B** may be configured to determine a charging efficiency between charger **900B** and each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914**. Thereafter, to reduce power loss, charger **900B** may be configured to convey wireless power to one or more chargeable devices that have the highest charging efficiency. More specifically, for example, charger **900B** may be configured to sequentially transmit wireless power to each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914** according to various protocols and frequencies. Further, charger **900B** may be configured to request and receive a signal from each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and fourth chargeable device **914** identifying an amount of power received by each of first chargeable device

911, second chargeable device **912**, third chargeable device **913**, and forth chargeable device **914** according to each suitable protocol and frequency. Thereafter, charger **900B** may determine which one or more chargeable devices should be charged with which protocols and frequencies to enable for an optimal charging scenario of system **950**.

[0098] As another example, charger **900B** may be configured to convey power to one or more chargeable devices that have the greatest need for a charge. More specifically, for example, charger **900B** may be configured to determine, via communication means, a charging level of each of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and forth chargeable device **914** and, thereafter, convey wireless power to the one or more chargeable devices having the least charged batteries. Further, according to another exemplary embodiment, charger **900B** may be configured to determine whether a time domain multiplexing method, based upon allocated activation time slots for two or more of first chargeable device **911**, second chargeable device **912**, third chargeable device **913**, and forth chargeable device **914**, may enable for an optimal charging solution.

[0099] It is noted that charger **900** and, more specifically, at least one antenna **704** of charger **900** may include additional functionality. As one example, antenna **704** may be configured to transmit radio frequencies. Furthermore, for example, antenna **704** may be configured to operate as a RF repeater, a femtocell, a WiFi access point (AP), or any combination thereof. Additionally, antenna **704** may positioned remotely from and connected to charger **900** via a coax, an RF conductor, an IP connection, or any other suitable connector. In this example, antenna **704** may configured to operate as a remote antenna for an RF repeater, a femtocell, a WiFi access point (AP), or any combination thereof.

[0100] FIG. 17 is a flowchart illustrating a method **690**, in accordance with one or more exemplary embodiments. Method **690** may include detecting one or more receive elements positioned within an associated charging region (depicted by numeral **692**). Method **690** may further include selecting at least one receive element of the detected one or more receive elements to transmit wireless power thereto to enable for an optimal charging solution of one or more chargeable devices associated with the one or more receive elements (depicted by numeral **694**).

[0101] Those of skill in the art would understand that information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

[0102] Those of skill would further appreciate that the various illustrative logical blocks, modules, circuits, and algorithm steps described in connection with the exemplary embodiments disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. To clearly illustrate this interchangeability of hardware and software, various illustrative components, blocks, modules, circuits, and steps have been described above generally in terms of their functionality. Whether such functionality is implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system. Skilled artisans may implement the described

functionality in varying ways for each particular application, but such implementation decisions should not be interpreted as causing a departure from the scope of the exemplary embodiments of the invention.

[0103] The various illustrative logical blocks, modules, and circuits described in connection with the exemplary embodiments disclosed herein may be implemented or performed with a general purpose processor, a Digital Signal Processor (DSP), an Application Specific Integrated Circuit (ASIC), a Field Programmable Gate Array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

[0104] The steps of a method or algorithm described in connection with the exemplary embodiments disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in Random Access Memory (RAM), flash memory, Read Only Memory (ROM), Electrically Programmable ROM (EPROM), Electrically Erasable Programmable ROM (EEPROM), registers, hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage medium is coupled to the processor such that the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. The processor and the storage medium may reside in an ASIC. The ASIC may reside in a user terminal. In the alternative, the processor and the storage medium may reside as discrete components in a user terminal.

[0105] In one or more exemplary embodiments, the functions described may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Computer-readable media includes both computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code in the form of instructions or data structures and that can be accessed by a computer. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and blu-ray disc where disks usually reproduce data magnetically, while discs

reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media.

[0106] The previous description of the disclosed exemplary embodiments is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these exemplary embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without departing from the spirit or scope of the invention. Thus, the present invention is not intended to be limited to the exemplary embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

What is claimed is:

1. A chargeable device, comprising:
at least one receive element configured to receive wireless power;
wherein the chargeable device is configured to:
detect one or more transmit elements positioned within an associated charging region; and
select at least one transmit element of the detected one or more transmit elements to receive wireless power therefrom to enable for optimal charging of the charging device.
2. The chargeable device of claim 1, wherein the chargeable device is configured to detect the one or more transmit elements according to at least one of one or more specific protocols and one or more specific frequencies.
3. The chargeable device of claim 2, further configured to detect the one or more transmit elements by sampling for transmit elements operating with at least one of the one or more specific protocols.
4. The chargeable device of claim 3, further configured to detect the one or more transmit elements by sampling for transmit elements operating with at least one of a near-field resonance protocol and an inductive coupling protocol.
5. The chargeable device of claim 2, further configured to detect the one or more transmit elements by sampling for transmit elements resonating at the one or more specific frequencies.
6. The chargeable device of claim 5, further configured to detect the one or more transmit elements by sampling for transmit elements resonating at one or more unlicensed ISM band frequencies.
7. The chargeable device of claim 1, further comprising a location device configured for determining a location thereof.
8. The chargeable device of claim 1, wherein the at least one receive element comprises at least one of a receive antenna and a coil.
9. The chargeable device of claim 1, further configured to wirelessly communicate with one or more wireless chargers associated with the detected one or more transmit elements.
10. The chargeable device of claim 1, further configured to control at least one operation of one or more wireless chargers associated with the detected one or more transmit elements.
11. A method of operating a chargeable device, comprising:
detecting one or more transmit elements positioned within an associated charging region; and
selecting at least one transmit element of the detected one or more transmit elements to receive wireless power therefrom to enable for optimal charging of the chargeable device.

12. The method of claim 11, wherein detecting one or more transmit elements comprises detecting one or more transmit elements according to at least one of a near-field resonance protocol and an inductive coupling protocol.

13. The method of claim 11, wherein detecting one or more transmit elements comprises detecting one or more transmit elements resonating at least one unlicensed ISM band frequency.

14. The method of claim 11, wherein selecting comprises:
sequentially receiving wireless power from each transmit element of each detected one or more transmit elements;
and
measuring an amount of power received from each transmit element of each of the detected one or more transmit elements.

15. The method of claim 11, wherein selecting comprises selecting a plurality of transmit elements of the detected one or more transmit elements to receive wireless power therefrom in a time-domain multiplexing method.

16. The method of claim 11, further comprising detecting a version of one or more wireless chargers associated with at least one of the detected one or more transmit elements.

17. A chargeable device, comprising:
means for detecting one or more transmit elements positioned within an associated charging region; and
means for selecting at least one transmit element of the detected one or more transmit elements to receive wireless power therefrom to enable for optimal charging of the chargeable device.

18. A charger, comprising:
at least one transmit element configured to wirelessly transmit power;
wherein the charger is configured to:

detect one or more receive elements positioned within an associated charging region; and
select at least one receive element of the detected one or more receive elements to transmit wireless power thereto to enable for an optimal charging solution of one or more detected chargeable devices associated with the one or more receive elements.

19. The charger of claim 18, further configured to detect the one or more receive elements according to at least one of one or more wireless power protocols and one or more wireless power frequencies.

20. The charger of claim 19, further configured to detect the one or more receive elements by sampling for receive elements operating with at least one of the one or more specific protocols.

21. The charger of claim 20, further configured to detect the one or more receive elements by sampling for receive elements operating with at least one of a near-field resonance protocol and an inductive coupling protocol.

22. The charger of claim 19, further configured to detect the one or more receive elements by sampling for receive elements resonating at least one of the one or more specific frequencies.

23. The charger of claim 18, further configured to detect the one or more receive elements by sampling for receive elements resonating at least one unlicensed ISM band.

24. The charger of claim 18, further comprising a location device configured for determining a location thereof.

25. The charger of claim 18, wherein the at least one transmit element comprises at least one of a transmit antenna and a coil.

26. A method of operating a wireless charger, comprising:
 detecting one or more receive elements positioned within
 an associated charging region; and
 selecting at least one receive element of the detected one or
 more receive elements to transmit wireless power
 thereto to enable for an optimal charging solution of one
 or more chargeable devices associated with the one or
 more receive elements.

27. The method of claim **26**, wherein detecting one or more
 receive elements comprises detecting one or more receive
 elements according to at least one of a near-field resonance
 protocol and an inductive coupling protocol.

28. The method of claim **26**, wherein detecting one or more
 receive elements comprises detecting one or more receive
 elements resonating at least one unlicensed ISM band fre-
 quency.

29. The method of claim **26**, wherein selecting comprises
 selecting a plurality of receive elements of the detected one or
 more receive elements to transmit wireless power thereto in a
 time-domain multiplexing method.

30. The method of claim **26**, further comprising detecting a
 version of at least one chargeable device associated with the
 one or more receive elements.

31. The method of claim **26**, wherein selecting comprises
 selecting the at least one receive elements of the detected one
 or more receive elements having the highest charging effi-
 ciency with the wireless charger.

32. The method of claim **26**, wherein selecting comprises
 selecting the at least one receive element having the lowest
 charging level of the detected one or more receive elements.

33. The method of claim **26**, further comprising receiving
 a signal from one or more wirelessly chargeable devices
 indicative of an amount of power received at each associated
 one or more receive elements.

34. A wireless charger, comprising:

means for detecting one or more receive elements posi-
 tioned within an associated charging region; and

means for selecting at least one receive element of the
 detected one or more receive elements to transmit wire-
 less power thereto to enable for an optimal charging
 solution of one or more chargeable devices associated
 with the one or more receive elements.

* * * * *