US 20230021292A1

(19) **United States**

(12) **Patent Application Publication**

Watkins et al.

(10) **Pub. No.: US 2023/0021292 A1**

(43) **Pub. Date: Jan. 19, 2023**

(54) **ELECTRICAL SENSING, TRACKING, AND ACTUATION OF DROPLETS**

(71) Applicant: **Lawrence Livermore National Security, LLC**, Livermore, CA (US)

(72) Inventors: **Nicholas Watkins**, Brentwood, CA (US); **N. Reginald Beer**, Pleasanton, CA (US); **Melinda Simon**, Fremont, CA (US)

(21) Appl. No.: **17/818,759**

(22) Filed: **Aug. 10, 2022**

Related U.S. Application Data

(62) Division of application No. 16/150,059, filed on Oct. 2, 2018, now Pat. No. 11,440,007.

Publication Classification

(51) **Int. Cl.**
B01L 3/00 (2006.01)

(52) **U.S. Cl.**
CPC ***B01L 3/50273*** (2013.01); ***B01L 3/5025*** (2013.01); *B01J 19/0093* (2013.01)

(57) **ABSTRACT**

Devices, techniques, and processes are disclosed that use electrical impedance to detect of the presence and contents of droplets including cells, nucleic acids, proteins, or solute concentrations in an array of retrievable, trackable, trapped droplets in a fluidic system. Electrodes may be positioned underneath individual droplet traps in a microchannel to assay droplet contents and/or actuating droplets for the release of the droplets from corresponding traps. The disclosed technology may be used for detection of the results of solvent extraction processes including time-dependent quantification of metal ion concentration in the aqueous and organic phases, for wastewater treatment, heavy metal detection, pharmaceutical industry, and/or biotechnology, or for environmental monitoring of wastewater for toxic metal, monitoring of biological cell viability and proliferation, monitoring of extraction processes used in heavy metal mining, monitoring of extraction processes used in nuclear fuel processing, monitoring kinetics of enzyme processes, and/or assessing pharmacodynamics and drug efficacy.




104
120
125
130
135
110
115
112A
$R_{droplet}$
$C_{droplet}$
C_{int}
C_{dl}
C_{st}
R_{lead}
Sensing electrode
400
Excitation electrode
102
106
140
145
150
R_{shell}
C_{shell}
R_{core}
C_{stray}

FIG. 1


220
MasterMix
Model
MasterMix
model
210
212
C_{st}, C_{sol}
R_{sol}
|Z| (ohm)
frequency (Hz)

FIG. 2


300
310
315
microfluidic channel width
320
gap
325
width
330
340
X
Y
Z

FIG. 3


430
455
445
435
450
440
460
410
Channel top view
422/424
426
412
416
414
420
Channel side view
422
426
424
Facing
480
416
412
414
Coplanar
470

FIG. 4


530
Lock-in Amplifier
Signal out
Signals in
Current Amplifier
540
1
2
3
522
524
526
510
Sense electrode
Actuation electrode
Electrical sensing region of microfluidic device
550
Signal delivered to chip from lock-in amplifier
Microfluidic channel
Signal from chip to current amplifier
560
Signal delivered to chip from lock-in amplifier
Microfluidic channel
Signal from chip to current amplifier

FIG. 5


600
685
End of extraction
670
660
655
650
610
675
625
630
665
645
640
635
620
680
Beginning of extraction
Droplet Sensing (Hi BW): $\Delta Z_{begin} = Z_{12} - Z_{23}$ $\Delta Z_{end} = Z_{45} - Z_{56}$
Extraction Sensing (Lo BW): $Z_{begin} = Z_{12}$ or Z_{23} $Z_{end} = Z_{45}$ or Z_{56}

FIG. 6


770
Provide real-time monitoring
• Current/end-point detection
(start & finish)
• Continuous analyzers provide
more data points before end
of extraction (in progress)
760
Target specific extraction processes/components
• Interrogation frequencies
(3 for each analyzer)
• Applied voltage
• Electrode material and/or geometry
750
Detect changes in electrical impedance from extraction
• Resistance (ions)
• Capacitance (dipoles)
• Inductance (metals)
705
710
720
725
ΔIZI
time
impedance (|Z|)
Exit Analyzer
670
Entrance Analyzer
665
685
Extraction
Finish
660
655
650
630
645
640
635
680
Extraction
Start

FIG. 7


800
Input
Droplet Size/Length
Size/Length Variability
Droplet Frequency
Frequency Variability
850
860
870
880
Pump
820
Evaluator
830
Flow Speed, Flow Ratios
840
Entrance
Analyzer
812
810
815
890
Exit analyzer feedback
Exit impedance values can be monitored to find optimal extraction and measurement parameters before droplet collection
Parameters: droplet size and velocity, fluid ratios, interrogation frequencies and voltages, etc
Size/Length
Frequency
835

FIG. 8



FIG. 9


1010
R, Amplitude (V)
Duration (s)
1020
#Events:
Amplitude (mV)
Event Width (ms)
Length (mm)
R, Amplitude (V)
#Events
1040
#Events:
Amplitude (mV)
Event Width (ms)
Length (mm)
Volume (pL)
#Events

FIG. 10


Signal amplitude @ 27 Hz (mV)
12
10
8
6
4
2
0
-2
1
10
100
1000
10000
[Fe2+] (ppm)
X (mV)
Y (mV)
R (mV)

FIG. 11


1200
1240
Impedance Analyzer
Control and Data
1220
Computer
Analog In Signal
Analog Out Signal
Control to valves
Control to pumps
Control
Switching ACB
Constant Scan Mode
1230
1210
Generated droplets enter
Ejected droplets exit
Direction of droplet flow
1
2
3
4
5
6
7
8
9
10

FIG. 12


Iteration 1: Droplet composition A
Scan Results: Traps 1, 5, 6 and 9 newly occupied
Iteration 2: Droplet composition B
Scan Results: Traps 2, 7, 8, and 10 newly occupied
Iteration 3: Droplet composition C
Scan Results: Traps 3 and 4 newly occupied
Droplet Composition
Occupied Traps
A 1,5,6,9
B 2,7,8,10
C 3,4

FIG. 13


1402
1450
1405
1410
1 mm
1442
1443
150 µm
1440
1450
1445
1430
1450
200 µm
1452
400 µm
1450
1409
1407
1420
1409
1450
A
B
C
D
144
2144
3

FIG. 14


1500
1510
Lock-in Amplifier
1520
1530A
1530B
1530C
1530O
1530P
1540
DUT
40-pin Ribbon Cable Connectors to DUT
Signals 1 - 40
Signals 41 - 80
Signals 81 - 120
Signals 121 - 160
Signals 161 - 200
Signals 201 - 240
Signals 241 - 256
S1-16
S9-16
S1-8
S1
S2
S3
S15
S16
In from DUT
Out to Switching Network (SMB jack on PCB)
TTL Logic Control Lines from CU Board
DI1-4
DI5-8
DI1 to DI8
8-pin Ribbon Cable Connector to DUT

FIG. 15


Top View – DEP trapping
1610
1612
1615
1613
Isometric View – DEP trapping
1620
1622
1612
1613
Top View – DEP trapping
1630
1632
1639
Droplet trap structure
Side View – EWOD droplet trapping
1635
1633
1637
Side View – EWOD droplet release
1640
1632
1639
1635
1633
1637

FIG. 16


1) Droplet flows into trap
2) Electrodes actuated to pin droplet to channel surface
3) Microfluidic device is inverted; droplet held in place by DEP force
4) Electrode is de-actuated; droplet falls due to higher density
5) Pressure-driven flow transports drop downstream.

FIG. 17


1800
Chip outlet
1810
1830
1820
1830
Droplets collected here
by reversing flow
Org. inlet
Aq. inlet
1810
1810
1810

FIG. 18


1900
1905
Receive droplet criteria
1910
Look-up-table and/or calculation
1915
Set initial flow conditions
1920
Wait x seconds
1925
Start impedance data collection
1930
Wait y seconds
1935
Evaluate impedance data
1940
Impedance Data
1945
Data within criteria?
Yes
No
1950
Success, use pump settings
1955
Increment time or # iterations
1960
Timeout/max iterations reached?
Yes
No
1965
Turn off pumps
1970
Report Failure
1975
Modify flow/pressure of pump(s)
1980
Look-up table and/or calculation
1985
Past Impedance Data

FIG. 19


Provide an electrical signal at one or more predetermined frequencies to a first electrode of the microfluidic device, the first electrode positioned within a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel
2002
Sense electrical signals from at least a second electrode of the microfluidic device, the second electrode positioned within the microfluidic channel and configured to produce an electrical signal upon making physical contact with, or upon being in close proximity to, a first droplet
2004
Obtain at least one impedance value based on the sensed electrical signals
2006
Determine at least one characteristic of the first droplet based on the at least one impedance value
2008

FIG. 20

ELECTRICAL SENSING, TRACKING, AND ACTUATION OF DROPLETS

CROSS REFERENCE TO RELATED APPLICATION(S)

[0001] This patent document is a division of and claims the benefit of priority to U.S. patent application Ser. No. 16/150,059, filed Oct. 2, 2018. The before-mentioned patent application is incorporated by reference as part of the disclosure of this application it its entirety.

FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

[0002] This invention was made with Government support under Contract No. DE-AC52-07NA27344 awarded by the United States Department of Energy. The Government has certain rights in the invention.

TECHNICAL FIELD

[0003] The present disclosure relates to detecting the contents and controlling the movement of droplets.

BACKGROUND

[0004] Microfluidic droplets provide advantages in heat and mass transport to conduct chemical and biological reactions. Typically, microfluidic systems rely on optical (e.g., fluorescence-based) methods to analyze reaction products in the microfluidic device, or instead transport the droplets out of the microfluidic device for offline analysis. Fluorescence-based detection methods suffer from common drawbacks such as their inherently qualitative nature, effects of pH, fluorophore concentration, and temperature on fluorescence intensity, and spectral overlap that limits the number of simultaneous measurements that can be made. These techniques also require steps to include labels in the system, which requires preparation, adds to the system expense, and potentially affects the function of biological entities. Such techniques are also dependent on the availability of a fluorescent label to detect the desired product. Frequently, the instrumentation used to detect fluorescence is bulky and expensive, requiring a light source, multiple filters, lenses and mirrors, and a detector. New techniques and devices are needed for detecting the contents of droplets.

SUMMARY

[0005] The disclosed technology overcome the above deficiencies and provide additional features and benefits in generation, sensing, sorting and manipulation of droplets in microfluidic devices by relying on electrical impedance values to, inter alia, detect the presence and contents of droplets.

[0006] One aspect of the disclosed technology relates to a microfluidic measurement device that includes a microfluidic device including a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel. The microfluidic device also includes a plurality of electrodes coupled to the microfluidic channel configured to make physical contact with, or to be in close proximity to, the one or more of the droplets, where at least a first electrode from the plurality of electrodes is configured to receive an electrical signal at one or more frequencies. The microfluidic measurement device also includes a detector coupled to the first electrode and at least a second electrode, where the detector is configured to sense electrical signals from the plurality of electrodes at the one or more frequencies, and to enable a determination of one or more impedance values associated with the sensed electrical signals.

[0007] Another aspect of the disclosed technology relates to a microfluidic device, that includes a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel, and a plurality of traps positioned in the microfluidic channel. Each trap is configured to trap a droplet and arrest the trapped droplet's movement, and is configured to allow the trapped droplet to make physical with or become close enough in proximity to be electrically detected by a first electrode and a second electrode in each trap. At least the first electrode is configured to receive an electrical signal at one or more frequencies. The microfluidic device also includes a detector that is coupled to at least the second electrode of each trap and is configured to sense electrical signals at the one or more frequencies from the one or more traps to enable a determination of one or more impedance values associated therewith.

[0008] The above and other aspects and features of the disclosed technology are described in greater detail in the drawings, the description and the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] FIG. **1** depicts examples of equivalent circuits for droplets in a microchannel;

[0010] FIG. **2** depicts an example of electrical impedance as a function of frequency for a conductive solution and examples of properties of the system such as the resistance and capacitance of droplet contents;

[0011] FIG. **3** depicts a top-down view of an example of a two-electrode sensor in a coplanar configuration;

[0012] FIG. **4** depicts examples of electrode configurations including a coplanar configuration and a facing configuration;

[0013] FIG. **5** depicts an example of a measurement system;

[0014] FIG. **6** depicts measuring extraction via impedance in a microfluidic channel, in accordance with some example embodiments;

[0015] FIG. **7** depicts measuring extraction via impedance in a microfluidic channel, in accordance with some example embodiments;

[0016] FIG. **8** shows depicts an example of a system using electrical impedance feedback control for droplet generation;

[0017] FIG. **9** depicts an example of a picture showing a droplet passing a three-electrode impedance sensor;

[0018] FIG. **10** depicts examples of impedance pulses caused by the passage of droplets through a impedance sense region;

[0019] FIG. **11** depicts an example of determining a concentration of iron in nitric acid droplets;

[0020] FIG. **12** depicts an example embodiment of a droplet tracking system;

[0021] FIG. **13** depicts an example method using impedance sensing to track the position of droplets in a static array;

[0022] FIG. **14** depicts examples of pictures of a microfluidic structure at different optical zoom levels in each picture.

[0023] FIG. **15** depicts an example of a demultiplexer for selecting measurement of one of a plurality of traps;

[0024] FIG. **16** depicts a diagram showing the release of a droplet using dielectrophoresis and electrowetting-on-dielectric (EWOD), in accordance with some example embodiments;

[0025] FIG. **17** depicts density-assisted separation for droplets that are denser than the continuous phase, in accordance with some example embodiments.

[0026] FIG. **18** depicts an example of a microfluidic design for collection of select droplets via flow reversal; and

[0027] FIG. **19** depicts a set of operations for adjusting pump flow and/or pressure to generate droplets within predetermined criteria, in accordance with some example embodiments.

[0028] FIG. **20** depicts a set of operations for determining a droplet's characteristic in a microfluidic device, in accordance with some example embodiments.

DETAILED DESCRIPTION

[0029] As noted earlier, some microfluidic systems transport droplets out of the microfluidic system for analysis using conventional analytical techniques, such as liquid chromatography-mass spectrometry (LC-MS) or inductively coupled plasma-mass spectrometry (ICP-MS). However, offline analysis of droplet contents still requires some preparation steps such as coalescence of the emulsion and separation of the immiscible phases, and can require dilution of the sample to an acceptable range for the analytical equipment. In addition, the low flow rates of microfluidic systems (nL-μL/min) can result in lengthy system run times to collect sufficient sample volume for analysis in conventional analytical equipment. These conditions add significantly to the time and labor required to analyze the results of a reaction.

[0030] The devices, techniques, methods, and processes disclosed in this patent document use electrical impedance to detect the presence and contents of droplets. As disclosed herein electrical impedance is used to detect the presence of cells, nucleic acids, proteins, or solute concentrations in an array of retrievable, trackable, and trapped droplets in a fluidic system such as a closed fluidic system. Electrodes may be positioned underneath individual droplet traps in a microchannel for the purpose of assaying droplet contents and/or actuating the one or more droplets for the release of the one or more droplets from one or more corresponding traps.

[0031] Example applications of the disclosed technology include detection of the results of solvent extraction processes including time-dependent quantification of metal ion concentration in the aqueous and organic phases. The disclosed subject matter may be used in wastewater treatment, heavy metal detection, pharmaceutical industry, and/or biotechnology. For example, the disclosed technology may be used for environmental monitoring of wastewater for toxic metal; monitoring of biological cell viability and proliferation; monitoring of extraction processes used in heavy metal mining; monitoring of extraction processes used in nuclear fuel processing and reprocessing monitoring kinetics of enzyme processes; and/or assessing pharmacodynamics and drug efficacy.

[0032] In this disclosure, an electrical impedance-based sensor in a microfluidic system is disclosed with configurations including: (1) providing sensing or actuation of a droplet or droplet contents as droplets flow past a stationary electrical impedance sensor in a microchannel; and (2) providing sensing or actuation of a droplet or droplet contents that are stationary in a microfluidic structure, such as a trap.

[0033] Using an integrated sensor permits real-time sensing of ion concentration internal or external to the droplets in the microfluidic channel, and provides information on the progress of a chemical reaction or separation such as for solvent extraction. Electrodes can also be actuated to deliver energy within the droplets (e.g., electroporate cells within droplets) or to move the droplets.

[0034] Integrating multiple electrode sensing units onto the same chip provides time-dependent data on the progress of a reaction, enabling facile extraction of kinetic information (e.g., determination of mass transfer or enzymatic rate constants).

[0035] In the disclosed subject matter, electrical impedance is used to detect the presence and contents of droplets. The disclosed subject matter includes the use of electrical impedance to detect the presence of cells, nucleic acids, proteins, or solute concentrations in an array of retrievable, trackable, and trapped droplets in a closed fluidic system. Also disclosed is using electrodes positioned underneath individual droplet traps in a microchannel for assaying droplet contents and/or actuating the droplet for release from the trap.

[0036] In one aspect, the disclosed electrical impedance techniques and devices overcome the limitations of optical methods that are currently used to analyze reactions. For instance, the disclosed approach provides quantitative measurements, and is immune to the effects of variables such as pH, temperature, and label on the measurement. Since no label is required in the disclosed subject matter, it is simpler, cheaper, and avoids the deleterious effect of a label on the biological activity of a molecule. The disclosed approach allows for an automated, robust emulsion analysis system that can be used at a small scale for portable "in the field" sample analysis or used as a microfluidic pilot plant to tailor the chemistry and reaction prior to the expense of scaling up to the bulk process. Because of the disclosed microfluidic architecture, reaction parameters can be varied and the reaction measured and observed so that optimization can occur faster and cheaper than traditional approaches. Given the ubiquity of chemical extractions in industry, this is very valuable.

[0037] In another aspect, a method is disclosed to generate microdroplets reliably, accurately, and precisely without a user's intervention; this can be used anywhere where emulsions are employed (industrial production, biomedical and biotechnology, nanomaterials fabrication, pharmaceuticals, research, etc.).

[0038] In yet another aspect, a pathway is disclosed for multiplexed drug target discovery of single cells in their microenvironments that is readily scalable from hundreds to tens of thousands or more microreactors. This is, for example, applicable to the study of heterogeneity of tumor cells and the immune system cells in tumor microenvironment. The disclosed technology may be used in downstream analysis and/or the culture of responsive assay elements on the same fluidic platform, without the need for human interaction. The disclosed method allows for the controlled assessment of statistically-relevant populations of cellular host/target interactions and therapies. The system may be used for observing cellular evolution or morphology

changes under induced pressures, whether they be environmental, therapeutic, or pathogenic. Using a loaded array, statistical significance of the platform will provide a ready study of lethal dose levels and scales for individual target types.

[0039] Single-cell analysis has numerous advantages: (i) biological systems are intrinsically heterogeneous, thus being able to accurately characterize cellular homeostasis is only possible if single cells are analyzed, (ii) single-cell analysis can provide insights into disease mechanisms which are difficult to obtain from bulk cell populations, (iii) in the context of disease intervention, such as tumor cell populations, studying single cells can help disambiguate potentially targetable tumor subpopulations, (iv) studying single cells provides a unique opportunity to map the dynamic regulatory landscape of cells in heterogeneous populations, (v) single cell technologies lend themselves to high-resolution imaging and control of subcellular mechanistic processes, and (vi) single cell immunophenotyping of clinical specimens can significantly advance biomarker discovery for diagnosis, prognosis, assessment of treatment efficacy and patient stratification strategies. Additionally, droplet or single-cell analysis enables analysis of enzymes, including cell-expressed enzymes with applications in a directed evolution context in laboratory settings.

[0040] As noted earlier, the disclosed subject matter has numerous applications including: (i) detection of the results of solvent extraction processes (time-dependent quantification of metal ion concentration in the aqueous and organic phases), (ii) environmental monitoring of wastewater for toxic metal, (iii) monitoring of biological cell viability and proliferation, (iv) monitoring of extraction processes used in heavy metal mining, (v) monitoring of extraction processes used in nuclear fuel processing and reprocessing, (vi) monitoring kinetics of enzyme processes, (vii) assessing pharmacodynamics and drug efficacy, and (viii) study of tumor cell as well as stromal cell heterogeneity in a tumor sample.

Example Electrical Measurements of Droplets

[0041] To measure the internal or external contents of a droplet using electrical impedance, appropriate frequency (or frequencies) are selected. A droplet in a microchannel can be modeled using an equivalent circuit.

[0042] FIG. **1** depicts three configurations of equivalent circuits for droplets in a microchannel in accordance with example embodiments. The three circuits in FIG. **1** show example equivalent circuit models of a solution **102**, a droplet **104**, and a core-shell particle (or double emulsion) **106** (bottom) in a microchannel, respectively. The model components of the circuit include capacitances such as C_{dl}=double layer capacitance **110**, C_{st}=stray capacitance **115**, C_{int}=interfacial capacitance **130**, R_{lead}=the resistance of the electrical leads **135**, and $R_{droplet}$=the droplet resistance **120** and $C_{droplet}$ the droplet capacitance **125**. The circuit model for the core-shell particle at **106** includes R_{shell}=the shell resistance **145**, C_{shell}=the shell capacitance, and R_{core}=the resistance **140** of the core droplet. The foregoing properties are related to the droplet's electrical conductivity and permittivity.

[0043] FIG. **2** at **210** depicts an example of impedance measured in ohms as a function of frequency for a conductive solution in a microchannel, which allows identification of optimal frequency regions for sensing with and external to droplet contents. The roll-off in the impedance plot at the left-hand side of FIG. **2** starts at approximately 10^6 Hz that is caused by the capacitive effects attributed to the stray and solution capacitances (C_{st} and C_{sol}). The roll off continues and a minimum impedance is reached around the frequency region **212**. FIG. **2** at **220** depicts properties of the system such as the resistance and capacitance of the droplet contents that can be obtained by fitting an equation for the overall impedance of the system, derived from the equivalent circuit model to measured data of electrical impedance as a function of frequency.

[0044] For the system in FIG. **2**, the double layer capacitance and the stray capacitance may dominate the impedance at low and high frequency values, respectively. For example, in the example plots of FIG. **2**, the impedance value is at a high value and starts to roll off at approximately 10^6 Hz, reaching a region with minimum values at approximately 10^7 to 10^8 Hz, before ramping back up to the high impedance region. To accurately measure properties of the droplet or solution inside a microfluidic channel requires selection of a frequency between these regions, where the impedance values are lower.

[0045] The system may drive a droplet at one or more frequencies to collect data about the droplet or system. Examples include:

[0046] (1) A first frequency selected to obtain data about the phase surrounding the droplet and a second frequency selected to obtain data about the contents of the droplet;

[0047] (2) A first frequency selected to obtain data about the inner contents of the droplet and a second frequency selected to obtain data about the droplet-outer phase interface;

[0048] (3) For systems of double- or higher-order emulsions: A first frequency selected to obtain data about the contents of the innermost compartment, a second frequency selected to obtain data about the contents of a shell around the innermost compartment, and a third frequency selected to obtain data about the solution external to the droplet. For the case of a core-shell or W/O/W (water/oil/water) capsule or droplet, the first frequency can be selected to obtain information about the core water component of the capsule, while the second frequency can be selected to obtain information about the oil or lipophilic shell component of the capsule. In such a system, the electrical impedance measurements can provide information about the thickness of the shell or information about the transport of materials into or out of the capsule; and

[0049] (4) A first frequency selected to obtain information about a droplet (such as the droplets size), and a second frequency selected to obtain information about the contents of the droplet, such as biological cells. Additional frequencies can be used to obtain information of the interior of said cells.

[0050] The impedance may be expressed or measured as a magnitude and a phase or as a complex impedance with a real and an imaginary component.

[0051] The electrical sensing system includes sets of 2 to 3 electrodes per sensing site. Each set of 2 to 3 electrodes provides one measurement point, and multiple electrode sets may be placed in a single microfluidic device to provide measurement points in different areas of a microfluidic device, which for example provides time-dependent information about a reaction's progress. FIG. **3** at **300** depicts a top-down view of an example of a two-electrode sensor in a coplanar configuration. The electrodes are positioned in

microfluidic channel (the center section of the configuration in FIG. **3**) so as to make contact with a droplet in the channel. A droplet can flow in microfluidic channel **315** (e.g., from left to right) making contact with one or both electrodes **330** and **340**. As the droplet flows in the channel, it makes contact with a first electrode **330**, then as the droplet flows further the droplet makes contact with both the first electrode **330** and a second electrode **340**, and when the droplet flows further still, contact with the first electrode **330** is lost and the droplet is only in contact with the second electrode **340**. Electrodes **330** and **340** comprise a conductive material and have a width **325**. The electrodes are spaced apart by gap **320**. The electrode width **325** and the gap **320** between adjacent electrodes are chosen based on the size of the droplets and can be scaled to accommodate a wide range of droplet sizes. The gap between adjacent electrodes **320** may be smaller than the droplet size which may increase the sensitivity of the sensor. Electrode width **325** may be chosen to be approximately the same as, or greater than, the gap between adjacent electrodes. Representative values for electrode widths range from 10 nm-100 μm, and corresponding typical electrode gaps range from 10 nm-100 μm as well. It should be further noted that in some examples, the measurement of impedance values can be conducted while the droplet is in close proximity to the electrodes without making actual physical contact. In this case for example, an immiscible carrier medium with low electrical resistivity (e.g., ionic liquid) may be used to ensure negligible resistive drop between the sense electrodes and the free-floating droplets (in contrast to mineral oil whose high resistivity requires the droplets to be in physical contact with the electrodes to ensure successful electrical droplet interrogation). A change in a capacitance value, for example, can be sensed as a droplet passes across the electrodes, thereby causing a change in the sensed impedance value.

[0052] Microelectrodes such as electrodes **330** and **340** can comprise different conductive materials, using a variety of techniques for their construction. The type of material selected for the electrode may depend on the particular sensing application For example, gold is etched by nitric acid, so for a system where the droplet contents will include nitric acid, a material that is more resistant to nitric acid attack, such as titanium, may be selected. Example materials for electrode construction include metals such as gold, platinum, chrome, titanium, palladium, or indium tin oxide, which can be patterned using photolithographic procedures such as lift-off, wet metal etching, and sputtering. Electrodes may be constructed from any conductive material (e.g., boron diamond, graphene, etc.).

[0053] Electrodes may be positioned in various configurations such as a coplanar configuration **470** or facing configuration **480**, as shown in FIG. **4**. In the coplanar configuration (left hand side of FIG. **4**), two electrodes are positioned side-by-side on an upper or lower layer. In the facing configuration (right hand side of FIG. **4**), one electrode is positioned on an upper layer and the other electrode on the lower layer. In the facing configuration, electrodes may be placed either at the top and bottom of a microfluidic channel, or along either side of a microfluidic channel. Shown at **430** is a top view diagram of a droplet **450** trapped in a microfluidic channel structure **435** over a set of coplanar electrodes **440** and **445**. The depicted microfluidic channel structure **435** includes a first end that allows the droplet to enter the structure, and a second tapered end that allows the droplet to be trapped.

[0054] In the coplanar configuration, electrodes can be patterned from thin (typically <1 μm thick) metal films using photolithographic processes such as lift-off or wet etching of the metal. Coplanar electrodes may be placed in various orientations. For example, a pair of electrodes may be positioned parallel or perpendicular to the primary direction of flow, or may be positioned at an arbitrary angle with respect to the primary direction of flow. For the facing electrode configuration, electrodes may be patterned on the top and bottom of a microfluidic channel using a thin-film of metal and a process such as lift-off or wet etching, or may be patterned along the sides of channel using methods including 3D printing or electroplating. In some example embodiments, a structure within the microfluidic channel such as a droplet trap **435** may be comprised of a conductive material, rendering these structures usable as electrodes. The term "trap" here refers to a structure to arrest the movement of a droplet in a microchannel via a structure that counterbalances the hydrostatic pressure driving droplet movement with capillary, or Laplace, pressure on the droplet. However, the sensing and actuation methods discussed here are not limited to traps that are physical in nature. Such droplet traps may arrest droplets by other means, such as optical (e.g., optical tweezers) or electrical (e.g., dielectrophoresis).

System Diagram and Measurement Configuration

[0055] FIG. **5** depicts a measurement system, in accordance with some example embodiments. The example measurement system includes a microfluidic device **510** containing integrated electrodes such as electrodes **522**, **524**, and **526**, an impedance analyzer **530** (e.g., Zurich Instruments HF2LI lock-in amplifier), and an amplifier such as current amplifier **540** (e.g., Zurich Instruments HF2TA current amplifier). An output signal of one or more frequencies from the impedance analyzer **530** or a function generator (not shown in FIG. **5**) is delivered to one of the electrodes in each of the electrode sets. In a measurement set including 3 electrodes as shown at **550**, this signal can be delivered to the middle electrode; in a measurement set including 2 electrodes as shown at **560**, this signal can be delivered to either electrode. The other electrode(s) sense the signal that is then amplified by the current amplifier **540** before it reaches the impedance analyzer **530** (lock-in amplifier in FIG. **5**).

[0056] In the system of FIG. **5**, an output signal (label 1) including one or more frequencies is delivered to the actuation electrode(s) on the microfluidic device **510**. A signal from the droplets in the microfluidic channel is sensed using one or more electrodes and input to the current amplifier **540**, and then to the lock-in amplifier **530**. Labels 2 and 3 indicate separate inputs to the current amplifier and lock-in amplifier from different electrodes. If only one electrode is used for sensing just one of these channels may be used. External, custom Wheatstone or Maxwell bridge circuits can be used to enhance impedance measurement precision or to find the ab solute impedance values of droplets or the baseline signal (i.e., when no droplet is present within the sense region). It should be noted that the use of a lock-in amplifier in this example embodiment is intended to facilitate the recovery of the sensed signal based on the known carrier frequency at low signal-to-noise ratio values. It is,

however, understood that other devices, such as different amplifiers and detection circuitry can be used to generate signals at desired frequencies, and detect the signals associated with the droplets.

[0057] In the 3-electrode sensing system at **550**, the middle electrode is actuated with a signal from the lock-in amplifier. The outer two electrodes are used to sense and carry the detected signal from the microfluidic chip to the current amplifier. In a 2-electrode sensing system shown at **560**, either of the two electrodes can serve as the actuated electrode, and sensing is done from the remaining electrode.

[0058] FIG. **6** at **600** depicts measuring extraction via impedance in a microfluidic channel, in accordance with an example embodiment. Microfluidic tube **610** has a hollow center **620** in which a liquid **625** flows. The liquid includes particles or droplets **630** (referred to hereinafter as "droplets"). For example, droplets **630** may be aqueous droplets that include iron and the liquid **625** may be kerosene. As the droplet **630** flows from the beginning of the extraction **680** to the end of the extraction **685**, the iron may be caused to migrate to the exterior of the droplet **630**. At the beginning of the extraction **680**, droplet **630** passes electrodes **635**, **640** and **645**; first contacting electrode **635**, then contacting electrodes **635** and **640**, and last in contact with just electrode **645**, as detailed above. Signal **665** with a predetermined frequency is provided to electrode **640** (label 2) and impedances are measured between electrodes **635** (label 1) and **640** (label 2) which is referred to as impedance Z_{12}, and between electrodes **640** (label 2) and **645** (label 3) which is referred to as impedance Z_{23}. A measure of how much the impedance changes, and thus extraction changes to droplet **630**, as the droplet moves from being in contact with **635** and **640** to being in contact with **640** and **645** may be expressed as $\Delta Z_{begin=Z_{12}-z_{23}}$. Another measure is the impedance Z_{12} or Z_{23}. Similarly, signal **670** with a predetermined frequency is provided to electrode **655** (label 5) and impedances are measured between electrodes **650** (label 4) and **655** (label 5) which is referred to as impedance Z_{45}, and between electrodes **655** (label 5) and **660** (label 6) which is referred to as impedance Z_{56}. A measure of how much the impedance changes, and thus changes to droplet **630**, as the droplet moves from being in contact with **650** and **655** to being in contact with **655** and **660** may be expressed as $\Delta Z_{end=Z_{45}-z_{56}}$. Another measure is the impedance Z_{45} or Z_{56}. Another measure of the extraction is the change in impedance from electrodes **635** and **640** or **640** and **645** to electrodes **650** and **655** or **655** and **660**. Compared with configurations that use two electrodes, configurations that use three electrodes can improve the sensitivity and/or reliability of measurements. In some implementations, more than three electrodes may be used. Pillars **675** may be periodically or intermittently spaced along the inside of microfluidic tube **610** to facilitate movement/rotation of the particles, and to facilitate the associated measurements. For example, the physical contact between the droplets and the pillars **675** can cause the droplets to spin, creating forces that facilitate movement of ions (e.g., iron) to the outer surface of the droplets and extraction thereof.

[0059] FIG. **7** depicts measuring extraction via impedance in a microfluidic channel, in accordance with an example embodiment. FIG. **7** depicts the same measurement set-up as FIG. **6**. FIG. **7** at **705** depicts an example of a graph of impedance over time. The impedance at **710** is an example of impedance at the extraction start **680**. The impedance at **710** may be impedance Z_{12} or Z_{23} in FIG. **6**. The impedance at **720** is an example of impedance at the extraction finish **680**. The impedance at **720** may be impedance Z_{45} or Z_{56} in FIG. **6**. AO at **725** is the difference between the impedance at the extraction start **680** and the impedance at the extraction finish **685**. $\Delta|Z|$ is a measure of the change in impedance due to the droplet **630** as extraction proceeds from the electrodes **635**, **640**, and **645** at the extraction start **680** to the extraction finish at electrodes **650**, **655**, and **660**. The top section of FIG. **7** illustrates example changes in impedance caused by different factors, examples of how specific extraction processes or components can be targeted, and example monitoring locations or set ups. In particular, at **750**, detection of changes in impedance of the droplet from extraction can include resistance changes such as resistance changes due to ions moving within the droplets, capacitance changes such as capacitance changes due to dipoles in the droplet, and inductance changes such as inductance changes due to metals in the droplets. At **760**, specific extraction processes may be targeted by selection of interrogation frequencies **665** and **670**, an applied voltage across the electrodes, and selection of the electrode material and/or geometry. At **770**, real-time monitoring may be provided by electrode sets at the start and finish. Additional electrode sets may be provided along the path from the start to the finish. Note that in FIG. **7**, the droplets are in physical contact with the microfluidic channel surfaces, which similar to the configuration of FIG. **6**, can facilitate the extraction process via the generation of vortices.

[0060] FIG. **8** depicts a system using electrical impedance feedback control for droplet generation in accordance with an example embodiment. An interface allows for determining the characteristics of droplets based on various target criteria values, including target mean and allowed variation from the mean. The evaluator module **830**, which may include hardware and/or software components, calculates flow rates for each pump based on a look-up-table and/or pre-defined algorithm and sends the appropriate commands to the pumps **820** to initiate droplet generation. Once droplets are generated, the evaluator receives real-time streaming data from the impedance analyzer and calculates the mean and variation for each droplet criterion. If the mean and/or variation of the droplets are outside of the criteria target values, the evaluator varies the pump flow rates to meet the criteria. This feedback loop of adjusting pump flowrates and receiving the resulting droplet characteristics may be continued until all criteria target values are satisfied. If the criteria are not satisfied after adjustments are made, the system determines that a failure has occurred and reports possible causes (e.g., bad microfluidic chip surface coating, clogged chip, etc.). Executable code consistent with the disclosed subject matter controls all fluidics and electrical impedance measurements and feedback, and provides/records emulsion statistics of the generated droplets (e.g., production rate, mean diameter/volume, monodispersity, etc.).

[0061] In some embodiments, an additional set or sets of electrodes and impedance analyzer can be used to evaluate the droplets farther downstream to provide a secondary form of feedback on subsequent processing occurring to the droplets. This feedback can be used to automatically find optimal droplet processing parameters that are related to droplet generation or other components for the manipulation and/or interrogation of the droplets.

[0062] FIG. **8** further depicts an example of a droplet impedance analyzer **800**, in accordance with some example embodiments. At **810** is an entrance impedance analyzer with electrodes **815** similar to the three electrode examples shown in FIGS. **5-7**. Signal source **840** provides a signal at one or more predetermined frequencies. The impedance of droplet **812** passing by electrodes **810** of entrance analyzer **810** is measured by evaluator **830**. Evaluator **830** stores impedance values from multiple droplets and may generate histograms **835** of various measurements such as the size or length of droplets based on a flow rate. An exit analyzer **890** similar to entrance analyzer **810** may be included in the analyzer **800**. The exit impedance values can be monitored to determine optimal extraction and measurement parameters before droplet collection. Parameters that can be adjusted in the analyzer **800** include droplet size, droplet velocity, fluid ratios, interrogation frequencies, and applied voltages, as well as others. Inputs to the evaluator **830** can include, but are not limited to, droplet size/length **850**, droplet size/length variability over multiple droplets **860**, the frequency of droplets **870**, and a variability in the frequency of droplets **880**.

[0063] FIG. **9** depicts a picture showing a droplet passing a three-electrode impedance sensor, in accordance with some example embodiments. Microdroplet passing through three-electrode sensing region that is narrowed-down to create a slug that will contact the electrode interface. As a droplet flows over the sensing region **815**, a peak in the signal is detected (see, e.g., FIG. **10**). The peak magnitude is extracted and can be compared to the peak magnitude from droplets generated from many different samples. It may be useful to analyze the real or imaginary components of the impedance signal, or both, depending on the nature of the compounds being detected.

[0064] FIG. **10** at **1010** depicts examples of impedance pulses caused by the passage of phosphate-buffered saline (PBS) droplets (in organic continuous phase) through a microfabricated impedance sense region. In this example, the electrodes are driven with a 200 kHz signal. Shown at **1020** are examples of a real-time display of events, statistics, and population distributions.

[0065] The statistics shown in FIG. **10** at **1040** were obtained by a high density of impedance pulses caused by the passage of ferric nitrate droplets (in organic continuous phase). Impedance signals were observed at three discrete frequencies (200 kHz, 2 MHz, and 20 MHz). Shown at **1040** is a display of events, statistics, and population distributions for each frequency. As evident from the statistics at **1020** and **1040**, the disclosed technology can be readily used to detect impedance changes for droplets having different characteristics, including different lengths, widths, composition and number.

[0066] FIG. **11** shows example plots that allow the concentration of iron to be determined electrically in nitric acid droplets (formed in kerosene continuous phase) at an interrogation frequency of 20 MHz. The change in impedance trend at 10,000 ppm may be due to effects of Fe^{2+} saturation, giving the upper limit of detection. Signal values of various impedance components for different Fe^{2+} concentrations in nitric acid droplets are represented by: X (real), Y (imaginary), R (magnitude, $\sqrt{X^2+Y^2}$). In this experiment, the phase angle (θ) did not show a trend and was omitted. Error bars are a single standard deviation from the mean of at least 10,000 impedance pulses (droplets) collected for each data point.

[0067] Electrodes for Sensing and/or Actuation of Stationary or TrappedDroplets

[0068] A. Tracking Droplet Position

[0069] In some embodiments, a separate electrical impedance sensor can be positioned in each trap of an array to detect the occupancy of the trap by a droplet to track the order in which traps are loaded. Droplets comprising different contents can be trapped in the array and their identity preserved using this approach.

[0070] FIG. **12** shows an example embodiment **1200** of a droplet tracking system. A microfluidic chip **1210** comprising a chamber of droplet traps is overlaid onto a network of microscale electrodes, with one set of electrodes per trap. A computer **1220** controls the fluidic actuation via valves and pumps. The computer **1220** communicates with a switching board **1230** that electrically connects the impedance analyzer to each trap for a certain duration. This provides the ability to scan large numbers of traps with a single impedance analyzer **1240** at rates much faster than 1 trap per second. As the traps fill with droplets, the occupancy of a particular trap by a droplet is detected by a change in impedance from the corresponding electrode set under the trap.

[0071] Below is an example method using impedance sensing to track the position of droplets in a static array. See FIG. **13**.

[0072] 1. Single or multiple-emulsion droplets of composition A are created using any of a variety of methods known in the art.

[0073] 2. Once droplet creation is stable and with correct size, length, impedance, etc., a valve is switched to direct the droplets toward an array of traps instead of into waste.

[0074] 3. A custom PCB switching board continually scans the impedance values of each trap which is addressed using an independent set of electrodes for each trap. When a droplet docks at a trap, the trap's impedance value changes. The program controlling the pumps, valves, impedance analyzer, and switching board detects this change and notes the trap's position and that it is filled with a droplet of composition A.

[0075] 4. Once a sufficient number of droplets of composition A are created, the valve is switched to release the droplets (e.g., direct the droplets back to waste).

[0076] 5. Droplets of a different composition (composition B) are generated using a combination of different biological, biochemical, or chemical solutions.

[0077] 6. Same as step 2.

[0078] 7. Same as step 3, but the program now records the newly-trapped droplets as those of composition B.

[0079] 8. Same as step 4, but for droplets of composition B.

[0080] Steps 4 through 8 show how this iterative process of steps 1 through 4 can repeat N times to create N compositions of droplets. This process can stop at the user's request, when the program detects that all traps are filled or when all droplet compositions of interest have been created and trapped.

[0081] After droplet trapping and tracking, long-term impedance evaluations of each droplet composition are performed simultaneously or nearly simultaneously in similar conditions, creating a controlled experiment platform for

detecting changes in chemical, biological, or biochemical reactions. A custom program can be used to dynamically find the most sensitive interrogation frequency to impedance changes caused by a particular assay. The program can sequentially scan each droplet's impedance and/or phase angle over a range of frequencies and can determine the frequency that provides the largest change of a particular component of impedance (i.e., X, Y, R, phase angle, or a combination thereof) over time. This "auto-tuning" can provide the most detection sensitivity for various assay conditions with the least user interaction, which is amenable to large-scale, heterogenous assays.

[0082] A method similar to the one used to track the capture of the droplets may be used to ensure droplets are ejected out of traps (droplet actuation may be performed through various means). If a droplet shows all the criteria for ejection for downstream analysis, the program/user, knowing its position in the trap array, can initiate the ejection procedure (e.g., mechanical, electrical, optical, etc.). Ejection should happen at a slow enough rate to ensure that each ejected droplet is accounted for in downstream analysis or manipulation. Ejected droplets may be subsequently directed through a subsequent network of trapped arrays and valves, providing a highly-specialized, dynamic testing platform that can precisely interrogate droplet populations based on upstream results.

[0083] FIG. **14** illustrates an example of a fabricated device which includes a chamber with **120** traps and electrical impedance sensing for the **120** traps that are individually addressable.

[0084] Sections identified as A, B, C and D at **1410**, **1420**, **1430**, and **1440** are at successive magnifications to show trap layout and geometry. At **1440** (D) a ~75 picoliter fluorescein droplet captured in an impedance trap is depicted; the captured droplet is centered over a pair of coplanar electrodes that detect the presence of the droplet. The substrate of this device is comprised of glass and micropatterned platinum electrodes. The on-chip fluidics are created via polydimethylsiloxane (PDMS) that can be formed by, for example, curing over a microfabricated mold using a photoresist such as SU-8. The device can track droplet location, and be used to perform long-term studies on the changes of droplets (and their contents) via electrical impedance spectroscopy. The platinum sensing electrodes of this geometry or another can also be used to actuate the droplets to release them from their respective traps. Electrical contact to instrumentation in this device may be made through POGO (spring loaded contact pins), but other technologies can be used, including edge card, wire bonding, flip chip, and ball grid array, and others. Flip chip and ball grid array allow a higher density of traps per device area since the electrical contacts is underneath the fluidics, requiring little additional device area, if any.

[0085] At **1410** (A), an array of droplet traps is shown in a microfluidic channel **1405** (1 millimeter scale). A fluid including droplets flows from fluid input **1402**, through microfluidic channel **1405**, to fluid output **1407**. Each trap includes two electrodes. One electrode from each trap is connected to a common conductor **1409** (see section B). The second conductor from each trap is an independent contact that is connected to a demultiplexer (see, FIG. **15**). An example trap is shown at **1450**. Fifteen columns of traps are shown with each column having eight traps. Other number of columns and other numbers of traps per column can be implemented within the scope of the disclosed technology.

[0086] At **1420** (B), a zoomed-in section with a 400-micrometer scale shows the lower right portion of the section **1410**. More details can be seen of the traps, such as the trap **1450**, the connections to the common conductor **1409**, and the independent conductors such as conductor **1452** associated with the trap **1450**.

[0087] At **1430** (C), a zoomed-in section with a 200-micrometer scale shows the lower right portion of the section **1420** (and **1410**). More details can be seen of the traps, such as the trap **1450**, including the electrodes **1442** and **1443** associated with the trap **1450**. Electrode **1442** connects to common conductor **1409** and the electrode **1443** is the independent conductor fed to a demultiplexer and impedance analyzer.

[0088] At **1440** (D), a zoomed-in picture with a 150-micrometer scale shows the lower right portion of the section **1430** (and **1420** and **1410**). The details of the traps, such as the trap **1450** can be seen, including the electrodes **1442** and **1443** associated with the trap **1450**. Droplet **1445** is trapped in the trap **1450**. Electrodes **1442** and **1443** contact the droplet **1445**. Through the electrodes **1442** and **1443**, common conductor **1409** to an impedance analyzer and independent conductor **1443** through a demultiplexer to the impedance analyzer, the impedance of the droplet **1445** can be measured.

[0089] B. Detection of Droplet Contents

[0090] In some embodiments, separate electrical impedance sensors for each trap in an army of traps can be used to detect properties of trapped droplets, including pH and conductivity. In addition, when the droplets encapsulate biological cells, the impedance sensors can be used to detect the presence of the cell, cell viability, monitor cell growth, and characterize the cell's membrane properties. Disclosed herein is the use of electrical impedance to detect the presence of cells, nucleic acids, proteins, or solute concentrations in an array of retrievable, trackable, and trapped droplets in a closed fluidic system. The electrical impedance sensors can be used to measure properties of core-shell particles or multiple emulsions, including several layers of immiscible phases. The disclosed subject matter can be used to quantify the thickness of the shell of such particles, or to dynamically monitor a process occurring within or external to a droplet in which a reaction product moves into or out of the particle over time, as well as other features.

[0091] C. Actuation of Droplets/Droplet Contents

[0092] In addition to using electrodes for detection of droplet or capsule/particle contents, electrodes can be configured to enable actuation of droplet or droplet contents for purposes including:

[0093] (1) electroporation of a cell within a droplet to introduce nucleic acids or proteins into the cell;

[0094] (2) electrophoresis to purify or selectively remove compounds from trapped droplets; and/or

[0095] (3) movement of the droplet or release of the droplet from a trapped position;

[0096] The ability to release individual droplets via individual electrode traps as disclosed herein is an enabling technology for studies linking the genotype and phenotype of biological cells. The phenotype of a cell may be observed inside of a trapped droplet, and then importantly may be selected and collected for further study by releasing a single droplet from an array of trapped droplets.

[0097] Actuation of a droplet with DC or AC electrical fields can be used to introduce material to cells via electroporation. With the technology outlined above with the aid of figures, including FIG. **14**, the contents of droplets in an array can be monitored and select cells can be chosen for electroporation/transformation.

[0098] FIG. **15** shows an example of a demultiplexer for selecting measurement of one of a plurality of traps, in accordance with some example embodiments. Illustrated are 16 demultiplexers **1530**A to **1530**P, each having 16 outputs. The input of each demultiplexer **1530**A to **1530**P is connected to one of 16 outputs of demultiplexer **1520** having an input that is connected to an output of the lock-in amplifier **1510**. The demultiplexer in FIG. **15** includes 256 outputs (Signals 1 to 256) for connection to device under test **1540**; such outputs can be used to activate, release, sense or otherwise control an individual trap in the device under test **1540**.

[0099] DC electrical actuation can be used to induce electrophoresis in droplets trapped in an array. Following cell lysis by any number of methods, select sets of electrodes can be actuated with a DC field to remove nucleic acids from select droplets by electrophoresis. Using this approach, the DNA from a select subset of cells can be isolated from the droplets and analyzed for the expression of a phenotypic characteristic of interest.

[0100] Example mechanisms by which actuation with microelectrodes can be used to move and remove individual droplets from an array, include dielectrophoresis (DEP) and electrowetting-on-dielectric (EWOD) technology. Examples of the use of these physics to move a droplet from a trapped position are shown in FIG. **16**.

[0101] Time-averaged DEP force may be expressed by Equation (1) as:

$$\langle F_{DEP} \rangle = 2\pi r^3 \varepsilon_m \mathrm{Re}(CM) \nabla |E_{rms}|^2 \quad \text{Equation (1),}$$

where $\langle F_{DEP} \rangle$ is the time averaged force, ε_m is the permittivity of the media, $|E_{rms}|$ is the magnitude of the applied electric field, and CM is the Clausius-Mossotti factor, given by:

$$CM = \left(\frac{\varepsilon_p^* - \varepsilon_m^*}{\varepsilon_p^* + 2\varepsilon_m^*} \right), \quad \text{Equation (2)}$$

where ε_m^* is the complex conjugate of the permittivity of the media, and ε_p^* is the complex conjugate of the permittivity of the particle

[0102] An aqueous droplet in an organic or non-polar medium may (given the dielectric constants of most common organic and non-polar fluids used in microfluidics) experience positive electrophoresis due to the positive value of the Clausius-Mossotti factor and trap at the point of the strongest electrical field gradient, which is at the center of the electrode structure indicated by the arrows **1615** in section **1610** of FIG. **16**. To release a droplet trapped, the electrode pair containing the trapped droplet is de-actuated. A modest flow rate of the surrounding phase fluid may transport the droplet away from the trap. Depending on the permittivity values of the droplet and the medium, there may be a frequency range where the droplet experiences negative DEP. In these cases, changing the frequency from one in the positive DEP range to one in the negative DEP range for that particular set of electrodes can result in the release of the trapped droplet. In the presence of flow in the microfluidic channel, the droplet can be carried downstream in the channel and transported to another part of the device, or off of the device for further analysis.

[0103] When the complex permittivity of the media (ε_m) is greater than the complex permittivity of the particle (ε_p), for example, when working with a water/oil/water, or W/O/W capsule, the particle can experience negative DEP. In these cases, DEP can be used to eject a droplet from a trap when the droplet has been passively trapped (e.g., by capillary pressure in a microfluidic channel or array).

[0104] FIG. **16** also depicts diagrams illustrating electrowetting-on-dielectric (EWOD), which along with DEP, are two example mechanisms that can be used to remove a droplet from a trap in a microfluidic channel. At **1610** and **1620** electrodes **1612** and **1613** can be used to trap a droplet **1622** in one position using dielectrophoresis. Once trapped, the droplet **1622** can be released by de-actuating the electrodes **1612** and/or **1613**, and the flow of the continuous phase around the droplet **1622** will transport it away from the trap. At **1630**, a droplet **1632** is trapped. At **1640** the droplet **1632** is released from the trap using the EWOD. EWOD can be used for droplet manipulation in the disclosed system where droplets are transported by pressure-driven flow. In some example embodiments, pressure driven flow may be used to position droplets in traps, and EWOD actuation may be used to remove a selected droplet from its trap. This is illustrated at **1630** and **1640** in FIG. **16**. In this configuration, the bottom of a microfluidic channel **1635** is patterned with an array of electrodes **1633** and **1637**, while the top plate **1639** of the microfluidic channel is an electrically conductive substrate. Actuation of an electrode adjacent to a droplet causes the droplet to move to the energized electrode. Using this scheme, a selected droplet can be moved out of a trap and carried out of the microfluidic device by pressure-driven flow.

[0105] DEP or other electrical-based forces can be combined with other methods to ensure droplets are ejected from traps. Another example method is creating cavitation bubbles underneath (or over if the bubbles are positively buoyant and resting on the ceiling of the chamber) droplets via focused laser beam.

[0106] Once removed from a trap, a droplet can be retrieved from the microfluidic device using a variety of mechanisms. Depending on the trap structure, forward flow through the microfluidic channel after droplet release may be sufficient to carry the droplet downstream past the trap. For other trap geometries, this method may result in re-trapping of the released droplet. In these situations, there are several mechanisms that can be employed to release the trapped droplets after actuation, including the following:

[0107] (1) Density-assisted separation—by constructing a microfluidic channel that is taller than the diameter of a droplet and the trap structures, the droplet may be manipulated vertically above or below the trap structures. Depending on the ratio of the density of the droplet or particle and continuous phase around the droplet or particle, the droplet may settle to the bottom of the microfluidic channel or float to the top. The procedure to employ density-assisted separation involves trapping the droplet, then actuating an electrode or set of electrodes above or below the droplet to pin them to either the top or bottom surface of the channel, depending on whether the density dictates that the droplet floats or sinks. Before selection of the droplets for retrieval,

the device is then inverted so that the trapping force provided by the electrodes holds the droplet to the opposite surface of the channel from the original orientation. Finally, selected droplets can be released from their traps simply by de-actuating the electrodes that address the droplets. See, for example FIG. **17**. FIG. **17** depicts density-assisted separation for droplets that are denser than the continuous phase. The droplet flows into the trap of a microfluidic device and is held there when the electrodes are actuated (left diagram in FIG. **17**). The microfluidic device is inverted but the droplet is still held in place due to, e.g., DEP force (middle diagram). When the electrode is de-actuated, the droplet falls due to having a higher density, and can be transported downstream due to, e.g., pressure driven flow (right diagram). If droplets were less dense than continuous phase (positive buoyancy), the droplet, traps, and electrodes would initially be at the ceiling of the microchannel before inverting the device.

[0108] (2) Flow reversal—following any method for droplet release from traps, including de-actuation of electrodes, or a change in the frequency applied to the electrodes, flow through the microfluidic device can be reversed to collect these droplets without the risk of re-trapping. This is illustrated in an example device design in FIG. **18**. FIG. **18** depicts a microfluidic design for collection of select droplets via flow reversal. Droplets are created and loaded into traps in the direction indicated by arrows **1810** and **1820**. Once selected droplets have been removed from their traps, flow is reversed according to the direction arrows **1830** and these droplets can be collected at a separate outlet as shown in the diagram above.

[0109] Electrical Impedance Feedback for Optical-Free Droplet Creation

[0110] Microdroplet generation may involve a feedback loop in determining if the generated droplets have acceptable criteria (e.g., size, length, volume, inter-droplet spacing, frequency, etc.). The feedback loop may include optical determination via a microscope or other optical device and adjusting the pumping flow rate and/or pressure for one or more fluidic phases. This feedbackloop may be iterated until the droplets meet acceptable criteria as defined by one or more criteria. This practice may become impractical with the increase in the number of droplet generators (e.g., scaling up parallel droplet generators for high-throughput droplet studies or manufacturing processes). Automatic optical detection methods of droplet criteria can be employed to improve the process but may still rely on expensive optics and cameras that provide a limited field of view (i.e., would be a limit to the number of droplet generators that could be observed simultaneously), may provide relatively low-resolution, high noise data (depending on optics, camera pixel size, background noise, etc.), may require a camera with high shutter speed (<0.5 ms) and high frame rate (>2,000 fps) to capture fast-moving droplets without motion blur, and may require that every droplet generator be in good focus to ensure accurate droplet evaluation.

[0111] Measuring the electrical impedance of droplets can be included in an automated droplet generator that avoids issues related to optical detection methods. A two- or three-electrode system (see, e.g., FIG. **5**) placed immediately after a droplet generator module can electrically measure all criteria needed to generate desired droplets. For example, the Coulter principle in a direct current (DC) or alternating current (AC) regime may be employed to determine droplet frequency (i.e., number of impedance pulses per second, with each pulse representing a droplet passing through the sense region), droplet size/volume (i.e., positive correlation with change in impedance from baseline with size/volume of droplet), velocity (i.e., how long the droplet takes to pass through the electrical sense region of known length), physical length (i.e., how long the droplet takes to pass through the sense region at a known velocity and/or flow rate), and inter-droplet spacing (i.e., time between the exit of one droplet from the sense region and the entrance of a subsequent droplet, multiplied by the average velocity of the droplets). The disclosed electrical impedance method provides more information related to the characteristics and contents of multiple emulsions. The mechanical characteristics of a single emulsion droplet (e.g., size, spacing, frequency, etc.) and some internal characteristics (e.g., conductivity, pH, electrical permittivity, etc.) can be determined with low frequency impedance measurement of the droplet. For multiple emulsion droplets (e.g., capsules), the shell of the outside emulsion may block low frequency interrogation of the contents of the interior emulsion(s), providing only the mechanical characteristics of the capsule. The shell may be electrically shorted at higher frequencies, thereby providing access to the electrical characteristics of the interior emulsion(s) (e.g., conductivity, pH, electrical permittivity, etc.). Electrical shorting can occur by simply increasing the interrogation frequency past a point that the shell material cannot electrically polarize fast enough to shield the electric field from the droplet's interior. This phenomenon is called dielectric relaxation or dispersion and determined by a shell's dielectric properties. Impedance analysis within a droplet is now possible since electrical current can now flow within the droplet's interior. The electrical characteristics may be correlated to physical characteristics within each emulsion (whether single or multiple), such as density and bioparticle/nanoparticle concentration. Such a scheme can also be used to determine the thickness of the particle's shell, or the size of the core of these particles, and can improve the process and quality control for large-scale, automated production of these particles.

[0112] FIG. **19** at **1900** depicts an example of set of operations **1900** for generating droplets within predetermined criteria. For example, the predetermined criteria may include a droplet impedance, droplet size (e.g., diameter, length, volume), droplet generation frequency, velocity, and/or droplet-electrode physical contact duration. A similar process can be used to ensure that droplets continue to be within the desired criteria over the duration of an experiment after initial success (e.g., mitigating for experimental drift, possible clogging, modified droplet/surface dynamics, etc.).

[0113] At **1905**, droplet criteria are received. At **1915** initial flow conditions are set using the received droplet criteria (from **1905**) and a look-up table and/or calculation based an algorithm (from **1910**). At **1920**, the process waits a for predetermined amount of time, x seconds. At **1925**, impedance data collection is started. At **1930**, the process waits for a predetermined amount of time, y seconds. At **1935**, the collected impedance data is evaluated. For example, the collected impedance data can be compared to stored impedance data at **1940**. At **1945**, if the impedance data is within the received criteria, the process is complete and the pump settings are used. At **1955**, if the impedance is not within the received criteria, the number of iterations or time is incremented. At **1960**, if a timeout has occurred or a

maximum number of iterations has been reached, the pumps are turned off at **1965**, and a failure is reported at **1970**. If no timeout or the maximum number of iterations has not been reached, the flow and/or pressure of the pump(s) is adjusted automatically through the user-controlled program. For example, if the droplet generation frequency is too high, the program will decrease the total flow rate of the pump(s) while keeping the flow ratio between the carrier phase and the droplet phase the same. In another example if the droplets are too large, the program will decrease the droplet-to-carrier flow rate ratio while still meeting the droplet velocity criterion. The pressure or flow is adjusted according to past impedance data at **1985** and from the look-up table and/or calculation from **1980**. The modified pressure and/or flow is fed back to **1920** and the process from **1920** is repeated until either the impedance meets the criteria or a timeout/maximum number of iterations is reached.

[0114] FIG. **20** illustrates a set of operations for determining a droplet's characteristic in a microfluidic device in accordance with an example embodiment. At **2002**, an electrical signal at one or more predetermined frequencies is provided to a first electrode of the microfluidic device, where the first electrode is positioned within a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel. At **2004**, electrical signals from at least a second electrode of the microfluidic device are sensed. The second electrode is positioned within the microfluidic channel and is configured to produce an electrical signal upon making physical contact with, or upon being in close proximity to, a first droplet. At **2006**, at least one impedance value is obtained based on the sensed electrical signals, and at **2008**, at least one characteristic of the first droplet is determined based on the at least one impedance value.

[0115] It is evident that the disclosed technology includes many aspects and embodiments, and finds many applications that can benefit from generation, detection, and manipulation of droplets in a microfluidic environment. For example, one aspect of the disclosed technology relates to a microfluidic measurement device that includes a microfluidic device including a microfluidic channel that is configured to allow fluid including one or more droplets to pass through the microfluidic channel. The microfluidic device also includes a plurality of electrodes coupled to the microfluidic fluidic channel configured to make physical contact with, or to be in close proximity to, the one or more of the droplets. At least a first electrode from the plurality of electrodes is configured to receive an electrical signal at one or more frequencies. The microfluidic measurement device further includes a detector coupled to the first electrode and at least a second electrode from the plurality of electrodes. The detector is configured to sense electrical signals from the plurality of electrodes at the one or more frequencies as the one or more droplets make physical contact with, or come to within proximity to, the first or the second electrode, and to enable a determination of one or more impedance values associated with the sensed electrical signals.

[0116] In one example embodiment, the first electrode is configured to operate as an excitation electrode to receive an input signal from the electrical source and to exert a force onto the one or more droplets that pass through the microfluidic channel in a vicinity of the first electrode. Further, the second electrode is configured to operate as a sensing electrode to produce electrical signals in response to sensing of the one or more droplets that pass through the microfluidic channel in the vicinity of the second electrode. In one example embodiment, the first and the second electrodes are spaced apart at a predetermined distance that is selected based on at least a physical size of the one or more droplets. In another example embodiment, the predetermined gap is less than a diameter of at least one droplet of the one or more droplets. In still another example embodiment, the first and the second electrodes are positioned at a coplanar configuration within the microfluidic channel such that the first electrode and the second electrode are positioned at one side of the microfluidic channel. In yet another example, embodiment, the first and the second electrodes are positioned at a facing configuration within the microfluidic channel such that the first electrode and the second electrode are positioned at opposite sides of the microfluidic channel facing each other.

[0117] According to one example embodiment, the detector is coupled to the first, the second and the third electrodes to enable a determination of the one or more impedance values that include: an impedance value between the second and the first electrode, or an impedance value between the third and the second electrode. In another example embodiment, the microfluidic measurement device includes a processor and memory including processor executable code, where the processor executable code upon execution by the processor causes the processor to determine or analyze the one or more impedance values that correspond to sensing of the one or more droplets. In one example embodiment, the processor executable code upon execution by the processor causes the processor to identify the one or more droplets based on detected changes in the one or more impedance values. In yet another example embodiment, the processor executable code upon execution by the processor causes the processor to determine a composition of the one or more droplets.

[0118] In one example embodiment, the microfluidic measurement device includes at least two sets of electrodes, and the first set of electrodes includes the first and the second electrode that are positioned at a first location within microfluidic channel, and the second set of electrodes positioned at a second location within the microfluidic channel downstream from the first set of electrodes. In another example embodiment, each of the first and the second set of electrodes includes at least two electrodes. In yet another example embodiment, each of the first and the second set of electrodes has three electrodes. In still another example embodiment, the microfluidic channel includes a plurality of pillars positioned at different locations within the microfluidic channel and are configured to make physical contact with the one or more droplets as the one or more droplets flow though the microfluidic channel.

[0119] In another example embodiment, the detector is configured to sense the electrical signals from the first set of electrodes corresponding to sensing of a first droplet at the first location within the microfluidic channel, and from the second set of electrodes corresponding to sensing of the first droplet at the second location within the microfluidic channel. In one example embodiment, the electrical signals sensed from the first and the second locations enable a determination of an extraction process. In still another example embodiment, the one or more frequencies are in the range 1 kilohertz to 100 megahertz. In another example embodiment, the one or more impedance values include a

magnitude, a phase, a value of a real component or a value of an imaginary component of the one or more impedance values. In yet another example embodiment, the microfluidic measurement device includes an electrical signal source operable at one or more frequencies and coupled to at least the first electrode.

[0120] In another example embodiment, the microfluidic measurement device includes a plurality of traps positioned in the microfluidic channel. In this example embodiment, the first electrode and the second electrode are part of a first trap of the plurality of traps, each trap is configured to trap a single droplet and arrest the trapped droplet's movement, and each trap is configured to allow the trapped droplet to make physical with or become close enough in proximity to be electrically detected by at least two electrodes in each trap. Additionally, at least one of the two electrodes is configured to receive the electrical signal at one or more frequencies, and the detector is configured to sense the electrical signals at the one or more frequencies from one or more traps to enable a determination of the one or more impedance values associated the trapped droplet or droplets in the at least first trap.

[0121] In one example embodiment, the at least two electrodes in each trap are positioned at an angle with respect to each other such that one end of each trap has a larger opening compared to the other end of the trap. In another example embodiment, the plurality of traps is configured to include a plurality of rows and columns to allow a plurality of droplets that flow through the microfluidic channel be intercepted by the plurality of traps. In yet another example embodiment, at least one trap is configured to arrest the trapped droplet's movement based on a received alternating current (AC) or direct current (DC) electric field. In still another example embodiment, at least one trap is configured to release the trapped droplet based on a received alternating current (AC) or direct current (DC) electric field.

[0122] According to one example embodiment, the microfluidic device includes a processor and memory including processor executable code, where the processor executable code upon execution by the processor causes the processor to determine or analyze the one or more impedance values that correspond to the trapped droplet or droplets. In one example embodiment, the processor executable code upon execution by the processor causes the processor to determine, using the one or more impedance values, (a) a size of the trapped droplet, (b) a number of trapped droplets having a particular size, or (c) a content of the trapped droplet or droplets. In another example embodiment, the processor executable code upon execution by the processor causes the processor to selectively actuate or de-actuate any one of the plurality of traps. In still another example embodiment, the microfluidic device includes a demultiplexer configured to allow each trap to be selectively controlled by the processor. In yet another example embodiment, the one or more impedance values include a magnitude, a phase, a value of a real component or a value of an imaginary component of the one or more impedance values

[0123] Another aspect of the disclosed technology relates to a microfluidic device that includes a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel, and a plurality of traps positioned in the microfluidic channel. Each trap is configured to trap a droplet and arrest the trapped droplet's movement and is further configured to cause the trapped droplet to make physical and electrical contact with a first electrode and a second electrode in each trap. At least the first electrode is configured to receive an electrical signal at one or more frequencies. The microfluidic device also includes a detector coupled to at least the second electrode of each trap and configured to sense electrical signals at the one or more frequencies from the one or more traps to enable a determination of one or more impedance values associated therewith.

[0124] Another aspect of the disclosed technology relates to an apparatus for generating droplets that includes a microfluidic entrance analyzer including a microfluidic channel and a plurality of entrance electrodes, where the microfluidic channel has a first input and a first output, and the plurality of entrance electrodes are positioned between the first input and the first output. The apparatus for generating droplets also includes one or more microfluidic pumps coupled to the first input of the microfluidic channel and configured to control a flow speed of a liquid that travels in the microfluidic channel and a flow ratio of droplet-to-liquid in the microfluidic channel. The apparatus for generating droplets further includes an evaluator including a processor and a memory comprising processor executable instructions. The evaluator is electrically coupled to the entrance analyzer and to the one or more microfluidic pumps, and the processor executable instructions when executed by the processor cause the processor to receive and process one or more impedance values at the plurality of entrance electrodes associated with droplets that flow through the microfluidic channel and adjust the one or more microfluidic pumps according to one or more droplet criteria.

[0125] In one example embodiment, the apparatus for generating droplets includes an exit analyzer including a plurality of exit electrodes positioned to allow a determination of one or more impedance values associated with droplets that reach the microfluidic exit analyzer section of the microfluidic device. In another example, embodiment, the apparatus for generating droplets is configured to determine an entrance impedance between the plurality of entrance electrodes and an exit impedance between the plurality of exit electrodes. In yet another example, embodiment, the entrance impedance and the exit impedance are determined at a predetermined frequency in the range 1 kilohertz and 100 megahertz. In still another example embodiment, the one or more droplet criteria include a droplet size or a droplet velocity. In another example embodiment, the exit analyzer is configured to provide a feedback based on the one or more impedance values associated with droplets that reach the microfluidic exit analyzer. For example, the feedback is indicative that droplet formation has a poor quality. According to an example embodiment, determination of the one or more impedance values includes determining a peak impedance value and comparing the peak impedance value to known values associated with a particular composition of matter.

[0126] Another aspect of the disclosed technology relates to a method for determining a droplet's characteristic in a microfluidic device. Such a method includes providing an electrical signal at one or more predetermined frequencies to a first electrode of the microfluidic device, where the first electrode is positioned within a microfluidic channel that is configured to allow fluid including one or more droplets to pass through the microfluidic channel. The method further includes sensing electrical signals from at least a second

electrode of the microfluidic device, where the second electrode is positioned within the microfluidic channel and configured to produce an electrical signal upon making physical contact with (or coming to within a close proximity to) a first droplet. The method additionally includes obtaining at least one impedance value based on the sensed electrical signals, and determining at least one characteristic of the first droplet based on the at least one impedance value.

[0127] In one example embodiment, at least one characteristic of the first droplet includes one of a size or a content of the droplet. In another example embodiment, the above noted method includes providing the electrical signal at a first frequency and determining one of the size or the content of the first droplet based on the at least one impedance value obtained at the first frequency, and providing the electrical signal at a second frequency and determining the other of the size or the content of the first droplet based on the at least one impedance value obtained at the second frequency. In another example embodiment, the first and the second electrode are part of a first set of electrodes, and the method further includes allowing the first droplet to travel through the microfluidic channel to reach a second set of electrodes, and obtaining at least one additional impedance value from electrical signals sensed from the second set of electrodes. In such an embodiment, determining the at least one characteristic of the first droplet includes determining an extraction associated with the first droplet based on impedance changes in the at least one additional impedance value obtained based on electrical signals sensed at the second set of electrodes compared to the at least one impedance value obtained based on electrical signals sensed at the first set of electrodes.

[0128] In another example embodiment, the impedance changes caused by changes in a resistance value are indicative of extraction of ions, the impedance changes caused by changes in a capacitance value are indicative of extraction of dipoles, and the impedance changes caused by changes in an inductance value are indicative of extraction of metals. In yet another example embodiment, the first and the second electrode are part of a first set of electrodes, the first set of electrodes further includes a third electrode, and obtaining the at least one impedance value includes obtaining one or both of: an impedance value between the second electrode and the first electrode, or an impedance value between the third electrode and the second electrode. In one example embodiment, each of the first and the second set of electrodes include at least three electrodes. In another example embodiment, obtaining the at least one impedance value includes obtaining one or more of: a magnitude, a phase, a value of a real component or a value of an imaginary component of the at least one impedance value.

[0129] According to another example embodiment, the microfluidic device comprises a plurality of traps and the first and the second electrodes are part of a first trap of the plurality of traps, where each trap is configured to arrest a movement of a droplet that makes physical contact with the trap. In this example embodiment, the above noted method further includes actuating at least the first trap to determine an impedance value of the trapped first droplet. In another example embodiment, the method incudes de-actuating at least the first trap to release the trapped droplet.

[0130] Another aspect of the disclosed technology relates to a method for generating a plurality of droplets in a microfluidic device. Such a method includes (a) receiving droplet criteria indicative of specific characteristics of the plurality of droplets; (b) determining initial flow conditions in a microfluidic channel of the microfluidic device, where the microfluidic channel includes at least a first electrode and second electrode positioned in the microfluidic channel to allow determination of impedance values for droplets that flow through the microfluidic channel and come in physical contact with at least the second electrode; (c) obtaining impedance values associated with particles that come in physical contact with at least the second electrode; (d) determining whether the obtained impedance values meet the droplet criteria; and upon a determination that the obtained impedance values meet the droplet criteria, retaining the initial flow conditions as correct conditions for sustained generation of the plurality of droplet; (e) upon a determination that the obtained impedance values do not meet the droplet criteria, modifying the initial flow conditions based on new values of one or both of a flow rate or a pressure value, and repeating operations (c) though (e). In one example embodiment, upon a determination that the obtained impedance values do not meet the droplet criteria for a predetermined number of iterations, halting operations (a) through (e).

[0131] From the foregoing, it will be appreciated that specific embodiments of the invention have been described herein for purposes of illustration, but that various modifications may be made without deviating from the scope of the invention. Accordingly, the invention is not limited except as by the appended claims.

[0132] The subject matter described herein may be embodied in systems, apparatus, methods, and/or articles depending on the desired configuration. For example, the systems, apparatus, methods, and/or articles described herein can be implemented using one or more of the following materials such as glass, metals, or any other mechanical material, electronic components such as transistors, inductors, capacitors, resistors, and the like, a processor executing program code, an application-specific integrated circuit (ASIC), a digital signal processor (DSP), an embedded processor, a field programmable gate array (FPGA), and/or combinations thereof. These various example embodiments may include implementations in one or more computer programs that are executable and/or interpretable on a programmable system including at least one programmable processor, which may be special or general purpose, coupled to receive data and instructions from, and to transmit data and instructions to, a storage system, at least one input device, and at least one output device. These computer programs (also known as programs, software, software applications, applications, components, program code, or code) include machine instructions for a programmable processor, and may be implemented in a high-level procedural and/or object-oriented programming language, and/or in assembly/machine language.

[0133] As used herein, the term "machine-readable medium" refers to any computer program product, computer-readable medium, computer-readable storage medium, apparatus and/or device (for example, magnetic discs, optical disks, memory, Programmable Logic Devices (PLDs)) used to provide machine instructions and/or data to a programmable processor, including a machine-readable medium that receives machine instructions. In the context of this document, a "machine-readable medium" may be any non-transitory media that can contain, store, communicate,

propagate or transport the instructions for use by or in connection with an instruction execution system, apparatus, or device, such as a computer or data processor circuitry. A computer-readable medium may comprise a non-transitory computer-readable storage medium that may be any media that can contain or store the instructions for use by or in connection with an instruction execution system, apparatus, or device, such as a computer. Furthermore, some of the embodiments disclosed herein include computer programs configured to cause methods as disclosed herein (see, for example, FIGS. **7**, **8**, **10-13**, **15**, **16** and/or the process **1900** in FIG. **19**).

[0134] Although a few variations have been described in detail above, other modifications or additions are possible. In particular, further features and/or variations may be provided in addition to those set forth herein. Moreover, the example embodiments described above may be directed to various combinations and subcombinations of the disclosed features and/or combinations and subcombinations of several further features disclosed above. In addition, the logic flow depicted in the accompanying figures and/or described herein does not require the particular order shown, or sequential order, to achieve desirable results. Other embodiments may be within the scope of the following claims.

[0135] Similarly, while operations are depicted in the drawings in a particular order, this should not be understood as requiring that such operations be performed in the particular order shown or in sequential order, or that all illustrated operations be performed, to achieve desirable results. Moreover, the separation of various system components in the embodiments described in this patent document should not be understood as requiring such separation in all embodiments.

[0136] Only a few implementations and examples are described and other implementations, enhancements and variations can be made based on what is described and illustrated in this patent document.

What is claimed is:

1. A method for determining a droplet's characteristic in a microfluidic device, the method comprising:

providing an electrical signal at one or more predetermined frequencies to a first electrode of the microfluidic device, the first electrode positioned within a microfluidic channel configured to allow fluid including one or more droplets to pass through the microfluidic channel;

sensing electrical signals from at least a second electrode of the microfluidic device, the second electrode positioned within the microfluidic channel and configured to produce an electrical signal upon making physical contact with, or upon being in close proximity to, a first droplet;

obtaining at least one impedance value based on the sensed electrical signals; and

determining at least one characteristic of the first droplet based on the at least one impedance value, wherein the microfluidic device comprises a plurality of traps and the first and the second electrodes are part of a first trap of the plurality of traps, each trap configured to arrest a movement of a droplet that makes physical contact with the trap, and wherein obtaining the at least one impedance value comprises actuating at least the first trap to determine the at least one impedance value of the trapped first droplet.

2. The method of claim **1**, wherein the at least one characteristic includes one of a size or a content of the droplet.

3. The method of claim **2**, comprising:

providing the electrical signal at a first frequency and determining one of the size or the content of the first droplet based on the at least one impedance value obtained at the first frequency, and

providing the electrical signal at a second frequency and determining the other of the size or the content of the first droplet based on the at least one impedance value obtained at the second frequency.

4. The method of claim **1**, wherein the first and the second electrode are part of a first set of electrodes, and the method further comprises:

allowing the first droplet to travel through the microfluidic channel to reach a second set of electrodes, and

obtaining at least one additional impedance value from electrical signals sensed from the second set of electrodes, wherein:

determining the at least one characteristic of the first droplet includes determining an extraction associated with the first droplet based on impedance changes in the at least one additional impedance value obtained based on electrical signals sensed at the second set of electrodes compared to the at least one impedance value obtained based on electrical signals sensed at the first set of electrodes.

5. The method of claim **4**, wherein:

the impedance changes caused by changes in a resistance value are indicative of extraction of ions,

the impedance changes caused by changes in a capacitance value are indicative of extraction of dipoles, and

the impedance changes caused by changes in an inductance value are indicative of extraction of metals.

6. The method of claim **1**, wherein:

the first and the second electrode are part of a first set of electrodes,

the first set of electrodes further includes a third electrode, and

obtaining the at least one impedance value includes obtaining one or both of: an impedance value between the second electrode and the first electrode, or an impedance value between the third electrode and the second electrode.

7. The method of claim **4**, wherein each of the first and the second set of electrodes include at least three electrodes.

8. The method of claim **1**, wherein obtaining the at least one impedance value includes obtaining one or more of: a magnitude, a phase, a value of a real component or a value of an imaginary component of the at least one impedance value.

9. The method of claim **1**, further comprising de-actuating at least the first trap to release the trapped droplet.

10. The method of claim **1**, comprising, for each trap, providing the electrical signal at one or more frequencies, and allowing the trapped droplet to make physical contact with or become close in proximity to be electrically detected by at least two electrodes in each trap.

11. The method of claim **1**, wherein the plurality of traps includes a plurality of rows and columns, and a plurality of droplets that flow through the microfluidic channel are intercepted by the plurality of traps.

12. The method of claim **1**, comprising selectively actuating or de-actuating any one of the plurality of traps.

13. The method of claim **1**, comprising using a demultiplexer to selectively control one or more of the plurality of traps.

14. The method of claim **1**, comprising releasing the trapped droplet in response to an alternating current (AC) or direct current (DC) electric signal.

15. The method of claim **1**, obtaining the at least one impedance value includes obtaining one or more of a magnitude, a phase, a value of a real component or a value of an imaginary component of the at least one impedance value.

* * * * *