



US007515149B2

(12) **United States Patent**
Kerr et al.

(10) **Patent No.:** **US 7,515,149 B2**
(45) **Date of Patent:** **Apr. 7, 2009**

(54) **DISPLAY WITH WIRELESSLY CONTROLLED ILLUMINATION**
(75) Inventors: **Roger S. Kerr**, Brockport, NY (US);
Timothy J. Tredwell, Fairport, NY (US)
(73) Assignee: **Eastman Kodak Company**, Rochester, NY (US)
(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 686 days.

5,904,916 A	5/1999	Hirsch	
5,986,401 A	11/1999	Thompson et al.	
5,998,803 A	12/1999	Forrest et al.	
6,013,538 A	1/2000	Burrows et al.	
6,046,543 A	4/2000	Bulovic et al.	
6,048,573 A	4/2000	Tang et al.	
6,048,630 A	4/2000	Burrows et al.	
6,066,357 A	5/2000	Tang et al.	
6,125,226 A	9/2000	Forrest et al.	
6,137,223 A	10/2000	Hunt et al.	
6,242,115 B1	6/2001	Thomson et al.	
6,274,980 B1	8/2001	Burrows et al.	
6,559,825 B2 *	5/2003	Jacobsen et al.	345/102
6,661,563 B2 *	12/2003	Hayashi et al.	359/296
7,016,701 B2 *	3/2006	Colorado	455/550.1
7,286,105 B2 *	10/2007	Akimoto et al.	345/82
7,299,005 B1 *	11/2007	Yarkosky et al.	455/7

(21) Appl. No.: **11/015,904**
(22) Filed: **Dec. 17, 2004**

(65) **Prior Publication Data**
US 2006/0131504 A1 Jun. 22, 2006

* cited by examiner

Primary Examiner—Abbas I Abdulsalam
(74) *Attorney, Agent, or Firm*—Roland R. Schindler

(51) **Int. Cl.**
G09G 5/00 (2006.01)
(52) **U.S. Cl.** **345/207**; 345/82; 250/201.1;
340/825.72
(58) **Field of Classification Search** 345/211,
345/82, 39, 74.1, 79, 204, 207; 455/566,
455/426.1; 368/67, 68, 226; 428/690; 340/815.45,
340/525, 825.72; 250/370.01, 201.1, 203.2,
250/338.1; 349/62; 438/473; 257/E27.111;
362/552, 559; 385/116; 235/440; 348/14.01
See application file for complete search history.


(57) **ABSTRACT**


Image forming displays is provided. The display has a first layer having imaging elements positioned thereon; and a power circuit to provide electrical energy for the imaging elements. Wherein each imaging element comprises: an illumination circuit having an illumination element adapted so that the illumination element generates light at an intensity that is based upon a control signal, and a wireless communication circuit adapted to detect a wireless communication signal and to generate the control signal. A body contains the wireless communication circuit and the illumination circuit with the body occupying a space that is less than about five cubic millimeters. Imaging elements can also be adapted to sense radiation and provide wireless signals having data therein said data being based upon the amount of sensed radiation.

(56) **References Cited**
U.S. PATENT DOCUMENTS

5,545,291 A	8/1996	Smith et al.
5,707,745 A	1/1998	Forrest et al.
5,721,160 A	2/1998	Forrest et al.
5,757,026 A	5/1998	Forrest et al.
5,834,893 A	11/1998	Bulovic et al.
5,861,219 A	1/1999	Thompson et al.

29 Claims, 19 Drawing Sheets





20
FIG. 1A








FIG. 1C






FIG. 5A




FIG. 5B




FIG. 6




FIG. 7




FIG. 8




FIG. 9





FIG. 10



20 FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 20




FIG. 21




FIG. 22




FIG. 23





FIG. 24



20 FIG. 25

1

**DISPLAY WITH WIRELESSLY
CONTROLLED ILLUMINATION**CROSS-REFERENCE TO RELATED
APPLICATIONS

This application is related to U.S. Ser. No. 11/016,377 entitled IMAGING ELEMENT, in the name of Kerr et al.; and U.S. Ser. No. 11/016,459 entitled METHODS FOR MAKING DISPLAY, in the name of Kerr et al., all filed concurrently herewith.

Reference is made to commonly assigned, co-pending application U.S. Ser. No. 10/631,092, entitled A DIGITAL IMAGING ELEMENT in the name of Daniel Haas, filed on Jul. 31, 2003 and incorporated herein by reference.

FIELD OF THE INVENTION

The invention relates generally to the field of light emitting image displays.

BACKGROUND OF THE INVENTION

There is a general desire in the art of display technology to provide displays with high-resolution as measured in a number of imaging elements per unit area of the display surface and to provide displays that are low in cost. These objectives can be difficult to achieve in a single display. In particular, it is conventionally known to form a display device by depositing a plurality of individual light emitting materials in a pattern on a surface. These deposits of light emitting material are adapted to radiate light when exposed to electrical energy and are referred to herein as light emitting elements. Control electronics are also deposited on the surface of such a display that enable a controller to selectively provide a controlled amount power to each image display element. Such control circuits are generally known in the art as a "backplane".

It will be appreciated that both the light emitting elements and backplane require a certain amount of the space on the surface. As the number of light emitting elements increases, there is a concomitant need for an ever-larger number of control lines in the backplane. However, as the number of light emitting elements per unit area on a display increases, there is a decrease in available space between light emitting elements for the control lines and other circuits of the backplane. Therefore, as the number of light emitting elements in the display increases, it becomes substantially more difficult to define a backplane on the same surface as the light emitting elements.

One way to solve this problem is to form a display using a plurality of layers. In a first layer formed on the surface, light emitting elements are formed on the surface in a first layer and a second layer is overlaid onto the first layer with the second layer having backplane circuits arranged to cooperate with the light emitting elements of the imaging plane. This approach can cause a variety of problems. For example, inter-layer registration problems become difficult to solve in high-resolution displays. This is because as the size of the light emitting elements is reduced it becomes increasingly difficult to align the circuits of the backplane with appropriate light emitting elements formed as another layer on the surface. Further, the forming of multiple layers adds assembly steps and introduces the possibility of damaging the light emitting elements in the process of applying the backplane. It will be appreciated that, even a single damaged light emitting element in a display can introduce an artifact in a displayed image that renders the display unsatisfactory for use by a consumer.

2

There is also desire in the art to form displays using non-conventional surfaces such as flexible substrates. One barrier to the development of displays on flexible substrates is that it is difficult to maintain the integrity of the relationship between the backplane and the light emitting elements when the surface upon which they are formed can be deformed. Further, there is a desire to form displays using non-flat surfaces such as curved or non-flat contours, fabrics, bottles, and the like as substrates, however, it is difficult to form backplanes using such surfaces.

Accordingly what is needed in the art is a display that is substantially different from those that are currently known in the art and that enables images to be presented thereon and optionally captured thereby but that does not require the use of complex backplanes. There is a further need in the art for a display that can be provided in a convenient manner on a flexible or non-conventionally shaped surface.

SUMMARY OF THE INVENTION

In one aspect of the present invention a display is provided. The display has a first layer having imaging elements positioned thereon; and a power circuit to provide electrical energy for the imaging elements. Wherein each imaging element comprises: an illumination circuit having an illumination element adapted so that the illumination element generates light at an intensity that is based upon a control signal, and a wireless communication circuit adapted to detect a wireless communication signal and to generate the control signal. A body contains the wireless communication circuit and the illumination circuit with the body occupying a space that is less than about five cubic millimeters.

In another aspect of the invention, an imaging surface is provided. The imaging surface has a surface comprising a two-dimensional array of imaging elements for providing pixel image data for capturing an image of the subject, each imaging element comprising: an illumination element for providing an electromagnetic radiation in response to a control signal; a radiation sensor for providing a sensed-level signal corresponding to the amount of radiation sensed during a sampling period; and a wireless communication circuit adapted to detect a wireless communication signal having an illumination value therein and to generate a control signal based upon the illumination value. The wireless communication circuit is further adapted detect a wireless signal with a sensing command to cause the radiation sensor to sense radiation, to encode said sensed-level signal in the form of sensed radiation data and to transmit a wireless output signal having the sensed radiation data in response thereto.

BRIEF DESCRIPTION OF THE DRAWINGS

While the specification concludes with claims particularly pointing out and distinctly claiming the subject matter of the present invention, it is believed that the invention will be better understood from the following description when taken in conjunction with the accompanying drawings, wherein:

FIG. 1A shows top cutaway view of a one embodiment of an imaging element of the present invention;

FIG. 1B shows top cutaway view of another embodiment of an imaging element of the present invention;

FIG. 1C shows top cutaway view of another embodiment of an imaging element of the present invention;

FIG. 2 shows a top partial section view of another embodiment of an imaging element of the present invention;

FIG. 3 shows exterior view of one embodiment of the embodiment of FIG. 2;

FIG. 4 shows a partial cross-section view of the embodiment of FIG. 2;

FIG. 5A illustrates a sectional view of a first embodiment of a display using imaging elements;

FIG. 5B illustrates a sectional view of a second embodiment of a display using image elements;

FIG. 6 shows the display section of FIG. 5A having a top surface adapted with the microlenses;

FIG. 7 shows an embodiment of an imaging element having a memory;

FIG. 8 illustrates one embodiment of an imaging element having a radiation sensor;

FIG. 9 shows a block diagram schematic of one example of an imaging element having a light sensor and a sensor driver circuit and transmitter;

FIG. 10 is a block diagram schematic of an imaging element adapted for use in sensing x-ray radiation;

FIG. 11 illustrates an embodiment of an imaging element having wireless communication system that receives light signals;

FIG. 12 illustrates an embodiment of an imaging element having wireless communication system that receives and transmits light signals;

FIG. 13 illustrates a block diagram view of an imaging system using a sensing display;

FIG. 14 illustrates a display having a scintillator plate having grouping transceivers;

FIG. 15 illustrates a display having grouping transceivers and intermediate grouping transceivers;

FIG. 16 shows a partial side view of the formation of a sensing display formed using fluidic self-assembly techniques;

FIG. 17 illustrates the use of an electromagnetic field to help orient imaging elements to engage cavities in a display formed using fluidic self-assembly techniques;

FIG. 18 is a side illustration an embodiment of a display formed by coating techniques;

FIG. 19 is a top plane view of the display of FIG. 18;

FIG. 20 shows an embodiment of a display having a overcoat layer;

FIG. 21 shows an embodiment of the sensing display having imaging elements on two sides of a substrate;

FIG. 22 illustrates one embodiment of a method for determining locations of imaging elements on a display;

FIG. 23 illustrates another embodiment of a method for determining locations of imaging elements on a display;

FIG. 24 illustrates another embodiment of an imaging element; and

FIG. 25 shows another embodiment of an element having a multiple part illumination element.

To facilitate understanding, identical reference numerals have been used, where possible, to designate identical elements that are common to the figures.

DETAILED DESCRIPTION OF THE INVENTION

The present description is directed in particular to elements forming part of, or cooperating more directly with, apparatus in accordance with the invention. It is to be understood that elements not specifically shown or described may take various forms well known to those skilled in the art.

FIGS. 1A-1C show top cutaway views of one embodiment of an imaging element 20 of the present invention. In the embodiment of FIGS. 1A, imaging element 20 comprises a wireless communication circuit 22, an illumination circuit 24 and a support 26. Wireless communication circuit 22 comprises, in this embodiment, a radio frequency receiver circuit

30 and an antenna 32. Antenna 32 is adapted to receive radio frequency signals and to provide the received signals to radio frequency receiver circuit 30. Radio frequency receiver circuit 30 is adapted to process the radio frequency signals received by antenna 32 and, in certain embodiments, to extract energy for operation from the radio frequency signal received by antenna 32.

Radio frequency receiver circuit 30 has an identification code associated therewith and is adapted to sense whether a received signal has the associated identification code. When radio frequency receiver circuit 30 detects a radio frequency signal having the associated identification code, radio frequency receiver circuit 30 is adapted to generate an illumination control signal having a value that is based upon an illumination value that is encoded in the received wireless communication signal. Radio frequency receiver circuit 30 provides the illumination control signal to illumination circuit 24. In certain embodiments, radio frequency receiver circuit 30 can also be adapted to receive certain radio frequency signals that contain generic instruction codes to which radio frequency receiver circuit 30 will react despite the absence of an identification code specific to imaging element 20. For example, in such embodiments, radio frequency receiver circuit 30 can be adapted to receive codes such as "all off" or "reduce brightness" that generically apply to an entire set of imaging elements 20 when such imaging elements 20 are used collectively in a display as will be described in greater detail below.

Illumination circuit 24 has an illumination control circuit 36 and an illumination element 38. Illumination control circuit 36 is an electrical circuit that is adapted to control an amount of electrical energy passing from a power source to the illumination element 38 based upon the control signal received from radio frequency receiver circuit 30. Illumination element 38 can comprise any material that is adapted to receive electrical energy and to generate an amount of light in proportion to the amount of received electrical energy. In this regard, illumination element 38 can comprise, for example, a light emitting diode, an organic light emitting diode element, a florescent or incandescent light element, or an electroluminescent element. Illumination element 38 can be adapted to provide one wavelength, frequency, or color of light or multiple wavelengths, frequencies or colors of light.

Illumination element 38 can take on any of a variety of shapes, including, for example, the rectangular shape illustrated in FIG. 1A as well as circular, square or other convenient shapes.

In one embodiment, radio frequency receiver circuit 30 is adapted to provide an illumination control signal in the form of a voltage signal having an amplitude that varies in accordance with the illumination value in a received radio frequency signal. In this embodiment, illumination control circuit 36 comprises a voltage-controlled gate such as a transistor that is electrically in series between the power source and the illumination element 38. Illumination control circuit 36 is adapted to receive a control signal having a voltage within a range and to control the amount of energy passing to the illumination element 38 based upon the control signal.

In another example embodiment, radio frequency receiver circuit 30 is adapted to receive a radio frequency signal that contains an illumination value and a light characteristic value that defines a characteristic of the light to be emitted by illumination circuit 24. The light characteristic value can define, for example, a preferred wavelength, frequency or color for the light. In response to this, radio frequency receiver circuit 30 generates an illumination control signal

5

that is based upon both of illumination control value and the light characteristic value. In such an embodiment, illumination circuit 24 has an illumination control circuit 36 and an illumination element 38 that are capable of selectively generating light in more than one wavelength, frequency, or color. For example, illumination control circuit 36 can be adapted to drive illumination element 38 in a variety of different manners to achieve different colors. In another example, illumination element 38 can be provided with a combination of separate areas that are each adapted to radiate light having a particular wavelength, frequency or color and that can be selectively actuated by illumination control circuit 36 to provide light having characteristics called for in the illumination control value and/or light characteristic value in the radio frequency signal.

It will also be appreciated, from this embodiment, that the combination of wireless communication circuit 22 and illumination circuit 24 provide an imaging element 20 that generates an amount of light that is based upon the illumination value contained in a wireless signal received by radio frequency receiver circuit 30 and addressed to radio frequency receiver circuit. By using the codes, a transmitter (not shown) can transmit signals that individually address single imaging elements 20 in an array comprising a plurality of imaging elements 20 for purposes including but not limited to controlling the amount of light emitted by each imaging element 20 without need for backplane control wires.

In FIGS. 1A-1C, embodiments of imaging element 20 are shown that comprise a body 40 for the wireless communication circuit 22 and the illumination circuit 24. Body 40 provides protection for wireless communication circuit 22 and illumination circuit 24 and defines an outer surface 42 for light emitting element 20. In the embodiment shown in FIGS. 1A and 1B, body 40 is shown in a circular form. However, this is not necessary. Body 40 can have a variety of shapes as desired by the functional and/or aesthetic requirements of the use to which imaging element 20 is put. For example, such as the shape illustrated in FIG. 1C. Typically, body 40 will completely enclose wireless communication circuit 22 and illumination circuit 24.

Generally speaking, body 40 can be made from a wide variety of materials. For example, body 40 can comprise a thermoplastic, a glass, an organic material, or an inorganic material. Typically, body 40 is provided on imaging element 20 so as to provide protection to prevent materials in an environment within which the imaging element 20 is placed from contacting wireless communication circuit 22 or illumination circuit 24 to thereby protect wireless communication circuit 22 and illumination circuit 24 or any other circuits or systems of imaging element 20 from environmental degradation. For example, body 40 can be formed as a material that is applied to communication circuit 22 and/or illumination circuit 24 so as to provide a barrier to prevent environmental contaminants from contacting communication circuit 22 or illumination circuit 24. Examples of such materials include moisture resistant barrier materials, thermally resistant barrier materials, shock resistant materials, particulate matter resistant materials, biocidal materials, radiation resistant materials and materials adapted for electrical field insulation. Alternatively, body 40 can be adapted with such materials such as by coating or otherwise applying barrier layers of such materials on or in body 40. Further, body 40 can be adapted with combinations of such materials.

Body 40 can also be formed from or adapted with materials that are adapted to prevent unwanted migration of materials from within body 40 into the environment. For example, body 40 can be formed from materials or otherwise adapted to prevent

6

migration of materials used in the formation of wireless communication circuit 22 or illumination circuit 24 so as to extend the life of these components. Body 40 can completely encapsulate communication circuit 22, illumination circuit 24 and support 26. Alternatively, body 40 can be formed at least in part using support 26 so that support 26 comprises at least part of an outer surface 42 of body 40 and support 26 combined to form an outer surface 42.

Imaging element 20 is generally small sized, occupying space that is less than about 5 cubic mm. However, the overall size and shape of imaging element 20 can be defined in any number of ways. When imaging element 20 is adapted for use in relatively high resolution displays, imaging element 20 can have a size that is substantially less than about 5 cubic mm and can have, for example and without limitation, a size that is, the order of less than 0.001 cubic mm.

Typically, body 40 can be made from transparent or translucent materials so that light emitted by the illumination circuit 24 can be seen outside of outer surface 42. In one embodiment, body 40 is formed from a material that is adapted to absorb selected wavelengths, frequency, or colors of light. In another embodiment, body 40 is made of a transparent material such as a glass or clear thermoplastic.

In the embodiment of FIG. 1B, body 40 is formed in part from a deposit a light emitting material 37 that emits light when exposed to energy, and such material is used to form an illumination element 38 within body 40. In this embodiment, illumination control circuit 36 is adapted with electrodes 35 that apply electrical energy to the deposit of light emitting material 37. As is shown in FIG. 1C, deposit of light emitting material 37 is applied within a matrix of material forming body 40.

Imaging element 20 can derive power for operation from a variety of sources. In the embodiments shown in FIG. 1A-1C, imaging element 20 has a radio frequency receiver circuit 30 that is adapted to derive operational power from radio frequency signals that are broadcast proximate to the radio frequency receiver circuit 30. For example, radio frequency signals that can be received by a radio frequency receiver circuit 30 and used to provide the power for operational purposes including, but not limited to, signals used to send illumination values to the imaging element 20 and signals intended for transmission to other imaging elements 20 in an array of such elements. Alternatively, radio frequency receiver circuit 30 and antenna 32 can be adapted to detect a wireless signal that is adapted to provide power to imaging elements 20 for operation and illumination without such signal necessarily having illumination values encoded therein. Power obtained for operational purposes can be used for purposes including but not limited operating wireless communication circuit 22, radio frequency receiver circuit 30,

Turning now to FIGS. 2-4 what is shown, respectively, is a top partial section view, an exterior side view, and a partial cross-section of another embodiment of imaging element 20. In this embodiment, imaging element 20 has a body 40 with a first electrically conductive portion 44 on outer surface 42, a second electrically conductive portion 46 and an electrical insulator 48 therebetween. Electrical conductors 52 and 54 provide electrical pathways from first electrically conductive portion 44 and from second electrically conductive portion 46 to wireless communication circuit 22 and/or illumination circuit 24. This allows a power supply that is separate from imaging element 20 to provide power for use in operating any or all of radio frequency receiver circuit 30, illumination control circuit 36, or illumination element 38.

FIG. 5A shows one section of a display 60 that is adapted to use the imaging elements 20 of the embodiment of FIGS.

2-4. As is shown in FIG. 5A, a first layer 62 of display 60 is provided and a first conductive layer 64 is formed thereon. A plurality of imaging elements is provided in an array 71 on first conductive layer 64 with second electrically conductive portion 46 thereon. A second conductive layer 66 is formed separate from first conductive layer 64 and in contact with the first electrically conductive portion 44 thereon. The conductive layers 64 and 66 can be formed of conventional conductive material such as a metal deposits or metallic coatings, a semi-conductor coating and the like. In certain embodiments, it may be useful to provide a conductive layer that is essentially transparent. For such purposes a material such as Indium Tin Oxide, pentazine and the like. This listing of such essentially transparent conductive materials is illustrative only and is not limiting.

In the embodiment shown, an electrically insulative layer 72 is disposed between first conductive layer 64 and second conductive layer 66. The electrically insulative layer 72 can comprise, generally, any dielectric material including, but not limited to, air, inert gasses, and other gasses, that generally that are not conductive with a range of expected operating conditions. Other materials such as thermoplastic materials, organic materials having dielectric properties, and inorganic materials having dielectric properties can be used

As shown in FIG. 5A, a power supply 74 provides electrical energy to imaging elements 20 by way of electrically conductive layers 64 and 66. Power supply 74 can comprise, for example, a battery, fuel cell, line voltage, rectified line voltage or any other conventional source of electrical energy. In the embodiment shown in FIG. 5, a power supply 74 is provided in the form of a battery formed on a layer 76 on display 60. Layer 76 is electrically connected to second conductive layer 66 directly, and is connected to first electrically conductive layer 64 (as necessary) by an interlayer power connector 78 that is insulated from contact with second electrically conductive layer 66. Such a battery can be of a rechargeable type. Power supply 74 can be formed as a part of display 60 in ways other than providing a battery layer, can be external to display 60 with connectors adapted to join power supply 74 to first conductive layer 64 and second conductive layer 66.

It will be appreciated from the above that because the amount of light emitted by imaging elements 20 of display 60 is controlled by way of wireless signals it is not necessary to separately control the amount of electrical energy actually delivered to each imaging element 20. Accordingly, power supply 74 can provide electrical energy in a common fashion to all of imaging elements 20 in an array 71 by way of first conductive layer 64 and second conductive layer 66 that do not have individual paths to each imaging element. This greatly simplifies assembly and design of display 60 as, in some embodiments, first conductive layer 64 and second conductive layer 66 can comprise layers of conductive material that do not have a predetermined pattern of conductive material and therefore do not require registration with individual imaging elements 20.

In other embodiments electrically conductive layers 64 and 66 can be patterned as desired. However, as there is no need to individually regulate the amount of energy flowing to each element in a patterned conductive layer, larger conductors can be used and registration problems between the conductive layers and the imaging elements 20 are greatly reduced. This reduces the challenge properly assembling display 60 and provides a display 60 with increased durability.

In still other embodiments, a single conductive layer such as first conductive layer 64 can be provide with a pattern of alternating conductors adapted to engage first electrically conductive portion 44 and second electrically conductive por-

tion 46 to define a difference of potential to provide power thereto. Here too, because there is no need to define individually patterned conductors for each individual imaging element 20, a display 60 of this type can be more easily manufactured and can offer greater durability than existing displays.

In a further embodiment shown in FIG. 5B, imaging elements 20 are disposed between a first layer 62 and a second layer 64 of a display 60 that is adapted to provide a fluid around imaging elements 20, with fluid 65 that is adapted so that a difference of potential between a first electrically conductive portion 44 and disposed in one portion of fluid 65 and a second electrically conductive portion 46 of imaging elements 20 disposed in a different portion of a fluid 65. Fluid 65 can be provided as a static fluid in a liquid form, gel form or in the form of a flow of fluid.

In certain embodiments, the orientation of imaging element 20 with respect to support 26 can be of importance. Further, the orientation of imaging element 20 relative to contacts adapted to engage first and second conductive portions 44 and 46 can be of importance. In the embodiment shown in FIG. 5A, each imaging element 20 is shown optionally adapted with a magnetic polarity so that when it is exposed to a magnetic field, imaging element 20 will orient itself in accordance with such a field. Such magnetic orientation can be used to properly align with imaging elements 20 of array 71 to ensure that light radiated by each imaging element 20 in array 71 is radiated in a desired manner or in a desired direction and/or to ensure that the first electrically conductive portion 44 and second electrically conductive portion 46 are properly aligned to engage contacts such as a conductive layer 64 or 66 that provide electrical energy from power supply 74. In this regard, body 40 can be formed of or otherwise provided with a coating of a material that allows imaging element 20 to react to an applied electric field. Other forms of electromagnetic bias can be introduced into an illumination element 38 for this purpose including but not limited to an electrostatic bias.

A second layer 68 is shown in FIG. 5A. Second layer 68 can be used to secure imaging elements 20, and conductive layer 64 and optionally, to also secure conductive layer 66, insulative layer 72, power supply 74, battery layer 76 and interlayer power connector 78 as desired. Further, second layer 68 can be adapted to join with first layer 62 to provide an enclosure to encapsulate imaging element 20, and conductive layer 64 and optionally, to also secure conductive layer 66, insulative layer 72, power supply 74, battery layer 76 and interlayer power connector 78 as desired.

In the embodiment that is shown in FIG. 5A, second layer 68 is optionally applied to form a top surface 69 of display that does not have protrusions caused by imaging elements 20, and conductive layer 64 and optionally, to also secure conductive layer 66, insulative layer 72, power supply 74, battery layer 76 and/or interlayer power connector 78.

There is a general desire in the art for the displays 60 that are the relatively thin. Using imaging elements 20 in the present invention, it is possible to form a display having the very little thickness. In this regard, the size of imaging elements 20 makes it possible to form a display 60 having a first layer and a second layer that are separated by distance of less than 1 mm. Thus, imaging elements 20 of the present invention can be used to form both displays having conventional thicknesses, as well as displays having greatly reduced thicknesses. Further, it will be appreciated that a thickness of a display 60 that can be formed from imaging elements 20 is also reduced because a display 60 formed using imaging

elements 20 can have fewer layers of the type that are used for a backplane purposes in conventional imaging technologies.

As shown in FIG. 6, top surface 69 can also be patterned or otherwise adapted with for example, micro-lenses M to focus light traveling to or from, imaging elements. As is also illustrated in FIG. 6, in one embodiment, an optional overcoat layer 70 can be provided on top surface 69, imaging elements 20 and/or other portions of display 60

In one embodiment, first layer 62, second layer 68 and/or overcoat layer 70 can comprise a transparent material or a nearly transparent material. In some embodiments, first layer 62, second layer 68 and/or overcoat layer 70 can comprise any of a number of less than transparent materials such as diffusion materials, filtering material and the like. Additionally, first layer 62, second layer 68 and/or overcoat layer 70 can also optionally be formed from materials that can prevent display 60 from damage that can occur when it is exposed to thermal, electrical, magnetic or other forms of energy such as materials that block the flow of ultraviolet or other forms of radiation or from damage that can occur because of exposure to environments that can damage the components, or because of damage that can occur during handling or manipulation of a display 60 or that provides protection against mechanical, thermal, chemical or other factors that may damage imaging elements 20 or other components of display 60.

FIG. 7 shows yet another embodiment of an imaging element 20 in accordance with the present invention. In the embodiment of FIG. 7, imaging element 20 can comprise any of the above-described embodiments and also incorporates an optional memory 80. Memory 80 is adapted to store at least one illumination control signal for use in controlling the light emitted by the illumination circuit 24. This additional stored illumination control signal can be used as a default condition so that as display 60 is activated, an initial image or default image will be presented by an array of imaging elements 20 in display 60. Alternatively, memory 80 can have the capability of storing a plurality of illumination control signals. In such an embodiment, wireless signals can be provided to select one of the stored illumination control signals for presentation using the imaging element 20. Further, wireless control signals can be generated that cause wireless communication circuit 22 to store new illumination control signals in memory 80.

Referring now to FIG. 8, what is shown is an embodiment of imaging element 20 of FIG. 7 further comprising a radiation sensor 90 and sensor driver 92. Radiation sensor 90 is adapted to sense at least one form of electromagnetic radiation by converting such forms of energy into a sensed radiation signal. Such forms of radiation can include, but are not limited to, visible light, x-ray radiation, ultraviolet light, and infrared light.

Sensor driver 92 is adapted to monitor the sensed radiation signal and to provide a sensed value signal that indicates an amount of radiation incident on radiation sensor 90 during an exposure time. In one embodiment, the exposure time is a predetermined period of time. In another embodiment, the exposure time is determined dynamically with sensor driver 92 establishing an exposure time based upon the amount radiation incident on radiation sensor 90 during a pre-sampling period, or even during an initial portion of the exposure time. In still another embodiment, the exposure time can be defined by a device that is external to an imaging element 20, with the external device (not shown) transmitting a wireless signal to cause radio frequency receiver circuit 30 to transmit a sensor driver control signal. Sensor driver 92 receives the sensor driver control signal and can determine the exposure time therefrom.

In one embodiment of imaging element 20, radiation sensor 90 is adapted to sense an amount of light radiated by illumination element 38 during an exposure time and sensor driver 92 is adapted to provide a feedback signal that can be used to help guide operation of illumination control circuit 36. In this embodiment, illumination control circuit 36 receives this feedback signal and compares the amount of light sensed by radiation sensor 90 to an amount of light that illumination control circuit 36 should be causing illumination element 38 to radiate in response to an illumination control signal in use at the time that the light is sensed. Illumination controller circuit 36 can use this comparison to make automatic adjustments to the amount of energy applied to illumination element 38 so that illumination element 38 radiates a desired amount of light in response to an illumination value received by illumination control circuit 36.

In other embodiments, sensor driver 92 and radiation sensor 90 can be adapted to sense light emitted by adjacent imaging elements in a display and/or ambient levels, and an optional adjustment circuit 97 can be provided that is adapted to adjust the amount of light emitted by an imaging element in response to a control signal, with such adjustments being based upon the sensed amount of light from the adjacent light levels and or the ambient light levels.

In another embodiment, sensor driver 92 provides the feedback signal to wireless communication circuit 22 which provides a wireless signal to an external calibration device (not shown) that is adapted to compare the light emitted by an imaging element 20 as indicated by the feedback signal and an actual amount of light measured by the external calibration system so that the external calibration system can transmit a correction factor for use by illumination control circuit 36 in controlling light emitting operations of imaging element 20.

In this way, imaging element 20 can compensate for variations in the efficiency of illumination circuit 24 that arise as a result of manufacturing variations and/or variations that can occur in illumination circuit 24 as a result of use or exposure to environmental irritants over the course of the useful life of imaging element 20. Where advantageous, compensation can also be provided to compensate for variations in the alignment of imaging elements 20.

Alternatively, imaging element 20 can provide a radiation sensor 90 that senses little or no light radiated by illumination element 38. This can be done by the providing a radiation sensor 90 that is not adapted to sense specific types of light emitted by illumination element 38 or by applying filter materials within body 40 between illumination element 38 and radiation sensor 90 so that light emitted by illumination element 38 is absorbed by such filter materials. In another embodiment, radiation sensor 90 can be adapted to sense light that is incident upon imaging element 20 from a range of areas that are largely unaffected by the light emitted by illumination element 38. For example, radiation sensor 90 can be directed away from illumination element 38 such as by being positioned on a side of support 26 that is opposite from a side of support 26 having illumination element 38.

In one embodiment, sensor driver 92 is adapted to generate a data signal that can be stored in memory 80 that is indicative of an amount of radiation incident upon radiation sensor 90 during exposure time. Memory 80 and sensor driver 92 also can be adapted so that sensor driver 92 can store multiple sensed radiation data signals in memory 80. In this embodiment, wireless communication circuit 22 can be adapted to transmit a wireless signal providing stored sends radiation signals to a remote device so that it is not necessary to immediately upload stored sensed radiation signals. This can be

11

used, for example, to allow a number of images to be captured in quick succession and then uploaded at a later time.

In the embodiment of FIG. 8, wireless communication circuit 22 can have a radio frequency transmitter 94. Radio frequency transmitter 94 can be used to transmit a radio frequency signal having data therein. Examples of data that can be transmitted by radio frequency transmitter 94 include but are not limited to data stored in memory 80, sensed radiation signals from sensor driver 92 and identification code data.

FIG. 9 shows a block diagram schematic of one example of an imaging element 20 having a radiation sensor 90, sensor driver 92 and radio frequency transmitter 94 in accordance with the embodiment of FIG. 7. In this embodiment, radiation sensor 90 comprises photovoltaic surface for converting radiation that is incident on the photovoltaic surface into an electrical output signal. In the configuration of FIG. 9, radiation sensor 90 provides a voltage across a capacitor 96 to an optional amplifier 98. An optional analog to digital converter 99 accepts the output of amplifier 98 as input and provides, as an output, a corresponding digital sensed value signal. In this embodiment, radio frequency transmitter 94 accepts the digital value from analog to digital converter 99 as input and in combination with antenna 32 generates and transmits an encoded electromagnetic signal conditioned by the sensed value signal.

Referring to FIG. 10, there is shown a block diagram schematic of imaging element 20 shown in FIG. 8 and adapted for use in sensing x-ray radiation. In this embodiment, X-rays 93 are directly incident on a scintillator element 95 such as a phosphor material that radiates visible light when exposed to X-ray radiation. In this embodiment, the scintillator element 95 is within imaging element 20 a coating of a photosensor or as a deposit of a photosensor in a material forming body 40. In response to the level of radiation received, scintillator element 95 provides light which is then sensed by a photosensitive radiation sensor 90, buffered by amplifier 98, converted by analog to digital converter 99, and encoded, available for transmission by transmitter 94.

Referring now to FIG. 11, still another embodiment of imaging element 20 is provided. In the embodiment of FIG. 11, an imaging element 20 is shown having an embodiment of wireless communication circuit 22 that is adapted to receive wireless signals in the form of visible or non-visible light having an illumination value therein and to generate a control signal based thereupon. In the embodiment of FIG. 11, wireless communication circuit comprises radiation sensor 90, and an embodiment of sensor driver 92 that is adapted to sense light signals having illumination values therein and to provide an illumination control signal to operate illumination control circuit 36. Optionally, illumination control circuit 36 can be adapted to modulate light emitted by illumination element 38 to transmit data.

In an alternative embodiment, shown in FIG. 12, wireless communication circuit 22 comprises a light sensor 100 such as a photodiode, OLED, PLED or other sensor of a type that can be used to sense visible light, infrared light, ultraviolet light or other non-visible light and to convert the sensed light into a sensed light signal and a light receiver circuit 102. Light signal receiver circuit 102 is adapted to receive the sensed light signal and to interpret the sensed light signal. Light signal receiver circuit 102 has an identification code that performs the same function described above with regard to detecting any illumination values stored in the sensed light and to providing an illumination control signal having a value that is based upon the illumination value when the light signal has the identification code therein. In such an embodiment,

12

light receiver circuit 102 will provide illumination control signal to illumination control circuit 36.

In any embodiment of the invention, radiation sensor 90 and radiation controller 92 and/or light sensor 100 and light receiver circuit 102 and can be adapted to extract operational power from sensed radiation. Further, light receiver circuit 102 can also be used to extract operational power from the sensed radiation. Such extracted power can be applied for use by any energy consuming circuit or system in such an imaging element 20. It will also be appreciated that such a radiation sensor 90 or light sensor 100 can also be capable of extracting power from energy radiated by ambient sources including but not limited to solar radiation.

In the embodiment shown in FIG. 12, wireless communication circuit 22 also comprises a light transmitter circuit 103 that can be used to transmit light signals in the visible or invisible spectrum to a remote receiver (not shown). In the embodiment of FIG. 12, a light transmitter circuit 103 drives a light source 104 to generate data modulated light. However, in other embodiments, light transmitter circuit 103 can provide modulation or other instructional signals to illumination control circuit 36 causing illumination element 38 to be modulated in a manner that conveys data. In certain embodiments, this is done in a manner that is not readily apparent to an observer, such as by encoding the signal using minor variations in the power supplied to illumination element 38.

Referring to FIG. 13, there is shown a block diagram view of an imaging system 105 comprising a sensing display 106 having a plurality of imaging elements 20 having a radiation sensor 90 and a sensor driver 92 as described above. In this embodiment, a radiation source 107 such as the sun provides light that strikes an object 108. Light reflected by the object 108 is sensed by radiation sensors 90 of imaging elements 20. A transceiver 109, controlled by a control logic processor 110, sends and receives wireless signals to and from imaging elements 20. In this embodiment, the wireless signals 112 and 114 are radio frequency signals.

Transceiver 109 is adapted to generate radio frequency signals having generic commands to which all imaging elements 20 in display 106 will respond. For example, when transceiver 109 is used with an imaging element 20 having illumination values stored in memory 80, transceiver 109 can transmit a "present stored image" signal that causes all of the imaging elements 20 in sensing display 106 to emit an amount of light determined by the stored illumination value. Similarly, transceiver 109 can cause an image to be captured by imaging elements 20 of the type having radiation sensors 90 by transmitting a generic "capture" signal to each of the imaging elements 20 in sensing display 106 causing the sensor drivers 92 therein to monitor the amount of radiation sensed by radiation sensors 90 for a common exposure period.

Transceiver 109 is also adapted to generate radio frequency signals that contain identification codes therein which cause only one of the imaging elements 20 to respond. For example, transceiver 109 can transmit signals individually addressed to individual imaging elements 20 causing the individual imaging elements 20 to emit specific amount of light so that an image that has not yet been stored in memories 80 of imaging elements 20 can be presented on sensing display 106. Similarly, transceiver 109 can transmit signals individually addressed to imaging elements 20 to individually poll imaging elements 20 so that sensed radiation values can be obtained therefrom in a logical manner. These sensed radiation values can be assembled by control logic processor 110 to form an electronic image 116 for presentation on a separate display monitor 118. Alternatively, transceiver 109 can trans-

13

mit signals causing imaging elements **20** to radiate light in proportion to an amount of light sensed during the exposure period. In this way, an image can be captured and presented using sensing display **106**. In one embodiment, sensing display **106** can be used to cause illumination elements **38** of imaging elements **20** to act as radiation sources **107** to emit light that is reflected, for example, by object **108** and sensed by radiation sensors **90**.

Among the useful applications for a sensing display **106** of imaging elements **20** is the capture of images of non-visible light. Specifically, as shown above, it is possible to use imaging elements **20** that are of a type that is specially adapted for the purpose of sensing x-ray light. However, as shown in FIG. **14**, imaging elements **20** that are adapted for capturing visible light can be used for such a purpose when a scintillator plate **120** is positioned proximate to be imaging elements **20**. Scintillator plate **120**, can be for example as a fluorescent screen that emits a pattern of visible light **121** when exposed to a pattern of x-ray light **122**. As shown in FIG. **14**, sensing display **106** is positioned proximate to scintillator plate **120** in an arrangement suitable for obtaining a high-resolution image. An image sensing operation is then performed as described above.

Communications Schemes

It can readily be appreciated that the use of miniaturized imaging elements **20**, while eliminating the need to form a complex backplane, imposes a requirement for a significant amount of wireless communication in order to read or write data to each of the imaging elements **20** useful in a sensing display **106**. Even with a sensing display **106** having a 200 dpi resolution, display **106** of the present invention would have 200×200=40,000 RF devices, that is, 40,000 imaging elements **20**, per square inch. To make communication more efficient, various types of polling and grouping schemes may be employed.

Referring again to FIG. **14**, there is shown an arrangement of grouping transceivers **124** on a sensing display **106** for communicating with imaging elements **20**. Each grouping transceiver **124** communicates with a set of imaging elements **20**. Such a set can comprise for example between 2 and 2000 imaging elements. This arrangement reduces the number of RF transactions that must then be executed between transceiver **109** and components within sensing display **106**.

Referring to FIG. **15**, there is shown another arrangement that extends the use of grouping transceivers **124** on an embodiment of sensing display **106** further having one or more sets of intermediate grouping transceivers **126**. These intermediate transceivers **126** are deployed for further relaying of the image-bearing RF signals on sensing display **106**. By cascading grouping transceivers **124** in this fashion, the transfer of a complete image between a transceiver **109** and imaging elements **20** of sensing display **106** can be performed in a fraction of the time that would be required for individual polling of imaging elements **20**. It will also be appreciated that grouping transceivers **124** and intermediate grouping transceivers **126** can be used with a display **60**.

Fabrication Using Fluidic Self Assembly

Referring to FIG. **16**, there is shown, in a partial side view representation, a placement arrangement for imaging elements **20** on sensing display **106** using Fluidic Self-Assembly (FSA) as described in U.S. Pat. No. 5,545,291 entitled "Method for fabricating self-assembling microstructures" and filed by Smith et al. on Dec. 17, 1993. In conventional FSA techniques, a substrate such as substrate **128** is provided having a plurality of cavities **130** on a surface **132** such as first layer **62**. A liquid **134** is combined with items such as imaging

14

elements **20** to form a slurry **136**. Slurry **136** is applied to surface **132** and the suspended items flow into the cavities and assemble thereto. Liquid **134** is then evaporated or may be retained, such as sealed within sensing display **106**, for example. At the end of the assembly process, each cavity **130** in a surface **132** has at least one imaging element deposited therein.

FSA techniques allow a fairly accurate placement of individual imaging elements **20** into individual cavities **130**; however, it is possible that a small percentage of cavities **130** are empty. In a preferred embodiment, cavity **130** is dimensioned to allow, at most, a single imaging element **20**; however, there may be applications for which larger cavities **130** may be more desirable, even at the risk of multiple imaging elements **20** in a single cavity **130**. In such a case, duplicate imaging elements **20** could be detected and disabled.

Where imaging elements **20** have a preferred orientation it will be necessary to provide systems that are compatible with FSA techniques to ensure that imaging elements **20** are fixed in such an orientation. FSA techniques may provide the preferred orientation, such as by shaping walls **138** of each cavity **130** to have a shape that corresponds to a shape of an engagement surface **83** on body **40** of each imaging element **20** so that each imaging element **20** can engage cavity **130** in only one orientation.

As noted above, in an alternative embodiment, imaging elements **20** can be adapted to positionally react when exposed to an electromagnetic field such as by magnetically polarizing the imaging elements **20** in slurry, and then applying a magnetic field orient imaging elements **20**. Referring to FIG. **17**, one example of this is shown. In the example of FIG. **17**, a magnet **140** that is passed along surface **136** of substrate **128** in order to correctly orient imaging elements **20**. Magnet **140** could be any of a number of types of magnets, such as permanent or electromagnetic types, for example.

In an alternate embodiment, body **40** of imaging element **20** is adapted to diffuse, reflect, or otherwise modify received and/or transmitted radiation and/or light so that orientation is not critical. For example, body **40** can be defined to have an arrangement of walls **146** that are at least partially reflective, in a pattern that allows any light incident on any portion of body **40** to be distributed for sensing by radiation sensor **90** without regard to the orientation of radiation sensor. Similarly body **40** can have an arrangement of outer surface **42** that is defined to have a pattern that causes light emitted by illumination element **38** to be distributed so that the light is evenly distributed to provide generally uniform illumination despite the orientation of display element **30**.

Imaging Elements Applied in a Coating

An alternate embodiment for manufacturing a display **60** or sensing display **106** uses a coating process to apply imaging elements **20**. Miniaturization of imaging element **20** components allows these components to be suspended within a liquid coating medium **142** for application to a surface **144** such as first layer **62** or some other substrate **146** in one or more coats without necessarily creating cavities **130** in first layer **62**.

FIG. **18** shows an embodiment in which a display **60** or a sensing display **106** is fabricated using coating methods to deposit imaging elements **20** onto substrate **128**. Coating methods can be similar to applying a paint or other finish, with the additional requirement for having imaging elements **20** suspended within the coating medium **142**. Conventional binder types can be used in coating medium **142** for suspending imaging elements **20** during coating and for securing imaging elements **20** into place on substrate **128**. Typical

binder types include conventional polymeric binders used for paint and finish coatings. Any of a variety of binder types including acrylic, alkyds, epoxies, polyester urethane, or vinyl resins could be used, for example. As is shown in FIG. 18, some irregularity in the distribution of imaging elements 20 can be anticipated. Following the coating process, a number of imaging elements 20 may be oriented at a variety of angles with respect to surface 132 of substrate 126. There may be other irregularities in distribution, such as gaps and overlaps, as is shown in the plane view of FIG. 19, and the sectional view of FIG. 20.

In order to provide a suitable image and represent the image in an array of unevenly spaced pixels, using conventional imaging methods, various types of imaging algorithms can be employed. Imaging algorithms, for example, would apply interpolation to determine the value of a pixel based upon nearby values. Where imaging elements 20 overlap, it may even be necessary to apply an averaging algorithm or to disable the unneeded imaging element 20, depending on the requirements of the imaging application. Thus, while it would be optimal to provide a uniform density coverage for imaging elements 20 over a unit area of substrate 128, there are various methods available for effectively smoothing out distribution irregularities of imaging elements 20.

Coating medium 142 may itself provide a protective layer over imaging elements 20 once they are applied to substrate 146. Optionally, as is shown in FIG. 20, a separate display overcoat 148 could be applied atop imaging elements 20 and/or coating medium 142. Display overcoat 148 could be any number of materials. In one embodiment, display overcoat 148 is a transparent polyurethane; however, display overcoat 148 could have various properties for handling light, including diffusive or filtering properties. Display overcoat 148 could act as a type of color filter, for example, blocking light of certain wavelengths, so that only light of a selected wavelength is sensed by imaging elements 20. Display overcoat 148 could also be a phosphorescent material for absorbing and radiating light energy at certain useful wavelengths, for example. Use of a diffusive phosphorescent material could be advantageous, for example, where imaging elements 20 are skewed at angles rather than parallel to the surface of substrate 126 as was shown in FIGS. 18 and 19.

Multiple coating layers could be applied to obtain improved uniformity or to apply different types of components with each coating operation providing layer and components as described generally above with respect to FIG. 5. For example, a first coating could be applied for positioning grouping transceivers 124 on one layer. A second coating could be applied atop this first layer to position imaging elements 20 on sensing display 106.

Double-Sided Embodiments for Sensing Display

Referring to FIG. 21, there is shown an embodiment in which a display 60 or sensing display 106 is double-sided, having imaging elements 20 disposed on first side 150 and second side 152 of substrate 128. This arrangement allows a number of options for use of display 60 or sensing display 106. Optionally, where substrate 146 is transparent, imaging elements 20 on both sides of sensing display 106 could be used to capture an image of the same scene at higher resolution.

As shown in FIG. 21, imaging elements 20, first conductors 64 and second conductors 66 and second layer 68 can be provided on one side of substrate 128 with first conductors 155 and second conductors 157 and an insulator layer 153 having imaging elements 20 therein can be formed on another side of substrate 128. Additional layers, such as second layer

68 and additional second layer 159, can also be applied as needed. In another optional embodiment, both first side 150 and second side 152 of sensing display 106 could be provided with a phosphor coating for absorbing radiation energy for subsequent scanning and sensing using imaging elements 20.

Calibration of Displays

Whether or not imaging elements 20 are arranged in an orderly matrix arrangement, using cavities 130 as was described with reference to FIGS. 16 and 17 or randomly distributed using the coating method described with reference to FIGS. 18 and 19, each display 60 or sensing display 106 should have some mechanism for determining location information that associates each imaging element 20 with the location of each imaging element 20 on display 60 and sensing display 106. This can be done, for example by assigning Cartesian (x,y), polar coordinates or other logical two-dimensional or even three dimensional location information for each imaging element 20.

FIG. 22 illustrates another embodiment of a method for determining location information for associating each imaging element 20 with a location on a sensing display 106. This embodiment, an external calibration system applies a radiation pattern 162 to known locations on sensing display 106. The radiation pattern 162 can be a single point 164, or it can comprise multiple points. The imaging elements 20 on sensing display 106 are polled during exposure. Each imaging element 20 and 20a-20d that is exposed to the radiation can respond to the polling with signals indicative of such exposure and address information. Where grouping transceivers 124 and/or intermediate grouping transceivers 126 are used for example in a sensing display 106 having imaging elements 20, a responsive signal can be received therefrom that provides address information or other information that identifies the grouping transceiver and the intermediate grouping transceiver.

Because the location on the sensing display 106 that is exposed radiation is known, it can be determined that the imaging element 20 or imaging elements 20a-20d that respond with signals indicative of each such exposure are located at the position of exposure. Location information that links each such location with responsive imaging elements 20a-20d is stored. The pattern of radiation 162 is swept across sensing display 106 following a sweep path 166, one example of which is shown in FIG. 23, until imaging elements 20 are identified for each location in a display area of sensing display 106. Conversely, a similar approach can be used in which signals are sent causing individual ones of the imaging element 20 to radiate light, and by determining the location of the light radiating imaging element 20.

The method outlined above also allows a type of calibration for each imaging element 20. The radiation pattern 162 provides a signal of known strength to known areas of display 106. However, in other embodiments, radiation source 152 can comprise other light sources such as line arrays. The response signal may indicate, for example, the angular position of imaging element 20, which may not be at the angle of surface 132 as was described with reference to FIG. 18. Alternatively, the response can be a function of the efficiency of illumination elements 38 of imaging elements 20. This information can be used to provide calibration information for each imaging element 20. In embodiments wherein imaging element 20 has a radiation sensor 90 that is adapted to sense radiation emitted by illumination element 38, radiation sensor 90 and sensor driver 92 can provide such a signal for

communication to an external device which can use this signal to determine calibration information based upon this signal.

In another embodiment, a different method for determining location information associating a position of any individual imaging element **20** on the surface of a sensing display **106** is to use triangulation. With this method, each point is located based on its relative distance from and direction from a set of three reference points. Referring to FIG. **22**, there is shown sensing display **106** having a randomized array of imaging elements **20**. Imaging elements **20a**, **20b**, and **20c** serve as reference points for the triangularization process. Based on the coordinates of reference points **20a**, **20b**, and **20c**, any fourth point can be located, as is represented by point **20d**, for example. The triangularization process can be carried out iteratively for all imaging elements **20** on the surface of sensing display **106**, using the same reference points of imaging elements **20a**, **20b**, and **20c**. Optionally, different sets of reference points can be used for obtaining relative coordinates for other imaging elements **20** on the surface of sensing display **106**. Triangularization logic can use methods to determine relative distance based on comparative signal strength or may use methods for determining the angular direction of a signal source.

There are a variety of forms in which the grain location information can be stored. The stored imaging element **20** location information could comprise, in one specific embodiment, a data Look-Up Table (LUT) correlating a imaging element **20** identifier to a coordinate position (x,y) could be maintained. Using this method, imaging element **20** does not need to store its coordinate position data in an internal memory. For example, each imaging element **20** can be pre-programmed with a unique address that is provided each time that the imaging element **20** responds to the polling signal. In this embodiment, the imaging element location data comprises a look-up table that associates each address of a imaging element **20** with the location on display **106** that energy was applied to add a point when the respective imaging element **20** provided a signal indicative of exposure to the energy.

In another embodiment, each imaging element **20** is adapted to receive and store location information indicating the location on sensing display **106** at which energy was applied at a time when the respective imaging element **20** provided a signal indicative of exposure to such energy. In this embodiment, therefore, each time, after calibration, that the imaging elements **20** of sensing display **106** are polled, such digital imaging elements **20** will respond with a signal indicating the intensity of the exposure and the location of the grain reporting the intensity signal. This allows for rapid reconstruction of a digital image using the information provided in response to the polling signal.

It will be appreciated that while these methods have been described with reference to a sensing display **106**, they are equally applicable to determining the location of imaging elements **20** that are not adapted to sense radiation.

In still another embodiment, imaging element location information can, at least in part, be stored in memories in a grouping transceiver **124** and/or intermediate grouping transceiver **126**.

Sensing/Display Element Embodiment

In certain of the above described embodiments, imaging elements **20** have been described that incorporate illumination element **38** and a radiation sensor **90** that are provided in the form of separate components. However, in the embodiment shown in FIG. **24**, an imaging element **20** is provided

that is adapted to use a single material for both light emission and radiation sensing. In the embodiment shown in FIG. **24** an imaging element is provided having an anode layer **170**, a diode layer **172** and a substantially transparent conductive layer **174** assembled about a substrate **26** having a communication circuit **22**, an illumination control circuit **24** and a sensor driver **92**. In this embodiment, both of illumination control circuit **24** and sensor driver **92** are adapted with electrical connections to a combined illumination element **38** and radiation sensor **90** having the anode layer **170**, diode layer **172** and/or conductive layer **174** so that electrical signals can be provided to or received from the anode layer **170**, diode layer **172** and/or conductive layer **174**. In this embodiment, the material for the diode layer comprises an organic or inorganic diode material that is capable of emitting light when driven in a first manner by illumination control circuit **24** and capable of sensing light when driven by or otherwise interacting with sensor driver **92**. Examples of material that can be used in this fashion include OLED and PLED materials. When a potential difference is applied across a cathode and anode disposed about a supply of such material, electrons from the electron injecting layer and holes from the hole injecting layer are injected into the light emitting layer, they recombine, emitting light. This process can be reversed so that exposure of such materials to light causes such materials to generate a difference in potential across the cathode and anode when exposed to light. Examples of such OLEDs and PLEDs are described in the following United States patents, all of which are incorporated herein by this reference: U.S. Pat. No. 5,707,745 to Forrest et al., U.S. Pat. No. 5,721,160 to Forrest et al., U.S. Pat. No. 5,757,026 to Forrest et al., U.S. Pat. No. 5,834,893 to Bulovic et al., U.S. Pat. No. 5,861,219 to Thompson et al., U.S. Pat. No. 5,904,916 to Tang et al., U.S. Pat. No. 5,986,401 to Thompson et al., U.S. Pat. No. 5,998,803 to Forrest et al., U.S. Pat. No. 6,013,538 to Burrows et al., U.S. Pat. No. 6,046,543 to Bulovic et al., U.S. Pat. No. 6,048,573 to Tang et al., U.S. Pat. No. 6,048,630 to Burrows et al., U.S. Pat. No. 6,066,357 to Tang et al., U.S. Pat. No. 6,125,226 to Forrest et al., U.S. Pat. No. 6,137,223 to Hung et al., U.S. Pat. No. 6,242,115 to Thompson et al., and U.S. Pat. No. 6,274,980 to Burrows et al.

Another example of a material that can be used in this fashion is an inorganic LED material such as a material fabricated from III-V compound semi-conductors and a material II-VI semi-conductors. When a forward difference of potential is applied across junctions formed in these devices electron in holes injected into the device recombine, emitting light. This process can be reversed so that the exposure of such materials to light causes generation of electron hole pairs; these electron hole pairs, known in the art as carriers can be sensed either as a current or as change in potential.

Those of skill in the art will recognize that a variety of other types of materials and devices are known that have the capability to both emit and sense light and can be used in like fashion.

It will be appreciated that this embodiment, the size of a sensing and light emitting imaging element **20** can be reduced as compared to the size of a sensing and light emitting imaging element that requires a separate illumination element **38** and radiation sensor **90**. It will also be appreciated that embodiments such as the embodiments of FIGS. **1B** and **1C** can be adapted with such a light emitting and sensing material and a radiation sensor **92** for use in a sensing and emitting embodiment of imaging element **20**.

In this or other embodiments, an imaging element **20** having a radiation sensor **90**, communication circuit **22** can be adapted to receive illumination values or to transmit a signal

based on sensed radiation using digital or analog wireless communication schemes. In an analog example, communication circuit **22** can have a voltage controlled oscillator and a mixer that adjust the frequency of radio frequency signals to provide a sensed voltage level signal that can be detected, for example by a grouping transceiver **124** which then converts this signal into a digital signal for transmission to a transceiver as generally described above.

Multiple Part Illumination Element

As is shown in FIG. **25**, in certain applications, it can be useful to provide an illumination element **38** that is capable of emitting more than one separately controllable type of light. For example, it can be useful to provide an imaging element **20** that is capable of generating multiple colors of light, or of generating light that is both in the visible and non-visible bands. In the example shown in FIG. **25**, imaging element **20** has three parts, a red part **38a** that emits red light, a blue part **38b** that emits blue light, and a green part **38c** that emits green light. By controlling the amount of light emitted by each of parts **38a**, **38b** and **38c**, a wide range of colors can be emitted.

The invention has been described with reference to a preferred embodiment. However, it will be appreciated that variations and modifications can be effected by a person of ordinary skill in the art without departing from the scope of the invention.

PARTS LIST

20 imaging element
22 wireless communication circuit.
24 light source
26 support
30 radio frequency receiver circuit
32 antenna
35 electrodes
36 illumination control circuit
37 deposit of light emitting material
38 illumination element
38a-38c illumination element parts
40 body
42 outer surface of body
44 first electrically conductive portion
46 second electrically conductive portion
48 electrical insulator
52 electrical conductor
54 electrical conductor
60 display
62 first layer
64 first conductive layer
66 second conductive layer
68 second layer
69 top surface
70 overcoat layer
71 array
72 insulative layer
74 power supply
76 battery layer
78 interlayer power connector
80 memory
90 radiation sensor
92 sensor driver
93 X-rays
94 radio frequency transmitter
95 scintillator element
96 capacitor
97 adjustment circuit

98 amplifier
99 analog to digital converter
100 light sensor
102 light receiver circuit
103 light transmitter circuit
104 light source
105 imaging system
106 sensing display device
107 radiation source
108 object
109 transceiver
110 control logic processor
112 wireless signal
114 wireless signal
116 electronic image
118 display monitor
120 scintillator plate
121 visible light
122 X-ray light
124 grouping transceiver
126 intermediate grouping transceiver
128 substrate
130 cavity
132 surface
134 liquid
138 wall
140 magnet
142 coating medium
144 surface
146 walls
148 overcoat
150 first side
152 second side
153 insulator layer
155 first conductor
157 second conductor
159 additional second layer
162 radiation pattern
164 point
166 sweep path
170 anode layer
172 diode layer
174 transport conductive layer
M Microlens

The invention claimed is:

1. A display comprising: a first layer having imaging elements positioned thereon; and a power circuit to provide electrical energy for the imaging elements, wherein each one of said imaging elements comprises: an illumination circuit having an illumination element for generating an amount of light in proportion to the amount of electrical energy received and based upon a control signal that controls the amount of electrical energy passing to the illumination element; and a wireless communication circuit for receiving a wireless communication signal encoded with an illumination value and for setting the control signal to have an energy value that controls the amount of electrical energy passing to the illumination element based upon the illumination value, and wherein the power circuit comprises a first electrically conductive layer on the first layer contacting a first portion of each imaging element and a second electrically conductive layer contacting a second portion of each imaging element with an electrical insulator disposed between the first electrically conductive layer and the second electrically conductive layer.
2. The display of claim 1, wherein each imaging element is associated with an address code, and further comprising a memory associated with the display, said memory having

21

location information stored therein that associates each of a plurality of image forming locations on the display with at least one address code for at least one imaging element located proximate to each image forming location.

3. The display of claim 2, wherein the memory is associated with the display by incorporating at least one of a combination of discrete memory circuits, an application specific control circuit, a semi-conductor memory, a magnetic memory, and an optical memory with the display.

4. The display of claim 2, wherein the memory is associated with the display by storing the location data in a location in which a device for using said display can access the location information.

5. The display of claim 2, further comprising a transmitter circuit for receiving illumination values for presenting an image on the display and using the location information to transmit wireless signals having addresses and illumination values for each of the imaging elements used in forming an image.

6. The display of claim 1, wherein each imaging element has an address code that is programmed in accordance with the location of the imaging element in the display so that a transmitter can transmit wireless signals having location information and at least one control value and an wireless communication circuit having an address code programmed in accordance with the location of the imaging element will respond thereto by generating a control value.

7. The display of claim 1, wherein the power circuit comprises a fluid around the imaging elements, said fluid defining a difference of potential in the fluid between power supply contacts on an outside of each imaging element.

8. The display of claim 1, wherein the power circuit further comprises battery layer between the first layer and the first conductive layer.

9. The display of claim 1, wherein the power circuit further comprises at least one power signal antenna and conversion circuits for convening electro-magnetic signals into power for use by light sources of the light emitting elements in generating light.

10. The display of claim 1, wherein the power circuit further comprises at least one light converter and conversion circuits for converting light signals into power for use by light sources of the light emitting elements in generating light.

11. The display of claim 1, wherein the imaging elements are polarized so that the imaging elements can be aligned on the first layer by an applied electromagnetic field.

12. The display of claim 1, wherein the first layer comprises a pattern of cavities on the first layer for receiving and positioning said imaging elements.

13. The display of claim 1, further comprising a binder to hold the imaging elements in a location on the first layer that can be applied to the first layer as a fluidic material to harden to hold the imaging elements to the first layer.

14. The display of claim 1, further comprising a binder to hold the imaging elements in a location on the first surface comprising a second surface joined to the first surface with said imaging elements held therebetween.

15. The display of claim 1, further comprising radio frequency repeaters to facilitate communication between sets of the imaging elements and a transceiver that transmits wireless signals that can be received by the repeater and provided by the repeater by way of appropriate wireless signals to a receiver.

16. The display of claim 1, wherein the display is exposes a light sensitive media to an illumination pattern.

17. A display comprising: a first layer having imaging elements positioned thereon; and a power circuit to provide

22

electrical energy for the imaging elements, wherein each imaging element comprises: an illumination circuit having an illumination element for generating light at an intensity based upon a control signal; a wireless communication circuit for detecting a wireless communication signal and generating the control signal; and wherein at least some of the imaging elements further comprise a light sensor for sensing light that is incident on the light sensor during an exposure period, wherein each wireless communication circuit generates a wireless communication signal indicative of the amount of sensed light during an exposure period, and wherein the power circuit comprises a first electrically conductive layer on the first layer contacting a first portion of each imaging element and a second electrically conductive layer contacting a second portion of each imaging element with an electrical insulator disposed between the first electrically conductive layer and the second electrically conductive layer.

18. The display of claim 1, wherein the first layer has a first side and a second side and wherein the imaging element is positioned so that the light sensing element confronts the same side as a light source.

19. The display of claim 18, wherein said first layer is joined to a second layer to form a baffle to protect the imaging elements from alteration caused by shock, moisture, particles, chemical agents, light, or electromagnetic fields.

20. The display of claim 1, wherein the first layer has a first side and a second side and wherein the imaging element is positioned so that the light sensing element confronts a different side than a light source.

21. The display of claim 20, wherein the imaging elements sense radiation incident thereon, and wherein the first surface is transparent so that light that is not incident on the imaging elements of one side can be sensed by the radiation sensors of imaging elements of the other side.

22. The display of claim 1, wherein the first layer has a first side and a second side and the first side and second side both have imaging elements thereon.

23. The display of claim 22, wherein at least some of the imaging elements are able to sense light.

24. The display of claim 23, wherein imaging elements on both sides of the first layer are able to sense light and the first layer is transparent so that an image can be captured of a scene using imaging elements from both sides.

25. The display of claim 1, wherein said imaging elements are positioned on both of a first side of the first layer and a second side of the first layer.

26. The display of claim 1, wherein location information is stored in a memory of the imaging elements so that the imaging elements will respond to location.

27. An imaging surface comprising: a radiation source for providing electromagnetic radiation; and a surface comprising a two-dimensional array of imaging elements positioned on a first layer for providing pixel image data for capturing an image, wherein each one of said imaging elements comprises: a radiation sensor for providing a sensed-level signal corresponding to an amount of electromagnetic radiation sensed; an illumination circuit having an illumination element for generating light at an intensity based upon a control signal; and a wireless communication circuit for detecting a wireless communication signal encoded with an illumination value and generating the control signal based upon the wireless communication signal, for detecting a wireless communication signal with a sensing command to cause the radiation sensor to sense electromagnetic radiation, to encode said sensed-level signal in the form of sensed radiation data and to transmit a wireless output signal having the sensed radiation data in response thereto; and wherein a power circuit is pro-

23

vided to supply power to the imaging elements, the power circuit including a first electrically conductive layer on the first layer contacting a first portion of each imaging element and a second electrically conductive layer contacting a second portion of each imaging element with an electrical insulator disposed between the first electrically conductive layer and the second electrically conductive layer.

28. The imaging surface of claim **27**, wherein said wireless communication circuit detects a wireless communication signal having an address for the wireless communication circuit and having an illumination value, generates the control sig-

24

nal, detects a wireless communication signal addressed thereto with the sensing command, causes the radiation sensor to sense electromagnetic radiation and encodes said sensed-level signal in the form of sensed radiation data and an address signal in a wireless output signal in response thereto.

29. The imaging surface of claim **28**, further comprising a memory associated with a display and having imaging element location information stored therein that associates an address of each imaging element with a location in an image capture area.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 7,515,149 B2
APPLICATION NO. : 11/015904
DATED : April 7, 2009
INVENTOR(S) : Roger S. Kerr et al.

Page 1 of 1

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Issued Patent		Description of Error
Column	Line	
21	37	In Claim 9, delete “convening” and insert -- converting --, therefor.
21	64	In Claim 16, before “exposes” delete “is”.
22	7	In Claim 17, delete “comprise” and insert -- comprise: --, therefor.
22	8	In Claim 17, after “period,” insert -- and --.
22	23	In Claim 19, delete “baffler” and insert -- barrier --, therefor.

Signed and Sealed this

Twenty-fifth Day of August, 2009



David J. Kappos
Director of the United States Patent and Trademark Office