

US00RE42627E

(19) **United States**  
(12) **Reissued Patent**  
**Neuhauser et al.**

(10) **Patent Number:** **US RE42,627 E**  
(45) **Date of Reissued Patent:** **Aug. 16, 2011**

(54) **ENCODING AND DECODING OF INFORMATION IN AUDIO SIGNALS**

(75) Inventors: **Alan R. Neuhauser**, Silver Spring, MD (US); **Wendell D. Lynch**, East Lansing, MI (US); **James M. Jensen**, Shelton, WA (US)

(73) Assignee: **Arbitron, Inc.**, Columbia, MD (US)

(21) Appl. No.: **11/726,762**

(22) Filed: **Mar. 22, 2007**

**Related U.S. Patent Documents**

Reissue of:

(64) Patent No.: **6,871,180**  
Issued: **Mar. 22, 2005**  
Appl. No.: **09/318,045**  
Filed: **May 25, 1999**

(51) **Int. Cl.**  
**H04Q 11/04** (2006.01)  
**H04N 9/00** (2006.01)  
**H04L 1/08** (2006.01)  
**H04L 27/26** (2006.01)

(52) **U.S. Cl.** ..... **704/500; 380/205; 725/14; 725/18**

(58) **Field of Classification Search** ..... **704/200, 704/200.1, 201, 205, 206, 270, 273, 501, 704/502, 503, 504; 380/201, 202, 205, 3, 380/4, 6; 375/355, 362, 365, 366, 132; 348/1; 725/14, 18; 370/511**

See application file for complete search history.

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

2,470,240 A 5/1949 Crosby  
2,573,279 A 10/1951 Scherbatskoy

2,630,525 A 3/1953 Tomberlin et al.  
2,660,511 A 11/1953 Scherbatskoy et al.  
2,660,662 A 11/1953 Scherbatskoy  
2,662,168 A 12/1953 Scherbatskoy  
2,766,374 A 10/1956 Hoffmann  
3,004,104 A 10/1961 Hembrooke  
3,397,402 A 8/1968 Schneider  
3,492,577 A 1/1970 Reiter et al.  
3,760,275 A 9/1973 Ohsawa et al.  
3,803,349 A 4/1974 Watanabe  
3,845,391 A 10/1974 Crosby  
3,919,479 A 11/1975 Moon et al.  
4,025,851 A 5/1977 Haselwood et al.  
4,225,967 A 9/1980 Miwa et al.  
4,230,990 A 10/1980 Lert, Jr. et al.  
4,238,849 A 12/1980 Gassmann  
4,306,308 A \* 12/1981 Nossen ..... 375/275

(Continued)

**FOREIGN PATENT DOCUMENTS**

CA 1 208 761 A 7/1986

(Continued)

**OTHER PUBLICATIONS**

Definition of Checksum. Wikipedia.

(Continued)


*Primary Examiner* — Martin Lerner

(74) *Attorney, Agent, or Firm* — Barnes & Thornburg LLP

(57) **ABSTRACT**

Systems and methods are provided for decoding a message symbol in an audio signal. This message symbol is represented by first and second code symbols displaced in time. Values representing the code signals are accumulated and the accumulated values are examined to detect the message symbol.

**112 Claims, 10 Drawing Sheets**



# US RE42,627 E

Page 2

## U.S. PATENT DOCUMENTS

4,425,642 A 1/1984 Moses et al.  
 4,450,531 A 5/1984 Kenyon et al.  
 4,547,804 A 10/1985 Greenberg  
 4,554,669 A \* 11/1985 Deman et al. .... 375/133  
 4,599,732 A \* 7/1986 LeFever ..... 375/346  
 4,613,904 A 9/1986 Lurie  
 4,618,995 A 10/1986 Kemp  
 4,626,904 A 12/1986 Lurie  
 4,639,779 A 1/1987 Greenberg  
 4,677,466 A 6/1987 Lert, Jr. et al.  
 4,697,209 A 9/1987 Kiewit et al.  
 4,703,476 A 10/1987 Howard  
 4,718,106 A 1/1988 Weinblatt  
 4,739,398 A 4/1988 Thomas et al.  
 4,771,455 A 9/1988 Hareyama et al.  
 4,805,020 A 2/1989 Greenberg  
 4,843,562 A 6/1989 Kenyon et al.  
 4,876,617 A 10/1989 Best et al.  
 4,918,730 A 4/1990 Schulze  
 4,930,011 A 5/1990 Kiewit  
 4,942,607 A 7/1990 Schroder et al.  
 4,943,973 A 7/1990 Werner  
 4,945,412 A 7/1990 Kramer  
 4,955,070 A 9/1990 Welsh et al.  
 4,967,273 A 10/1990 Greenberg  
 4,972,471 A 11/1990 Gross et al.  
 5,023,929 A 6/1991 Call  
 5,113,437 A 5/1992 Best et al.  
 5,191,593 A \* 3/1993 McDonald et al. .... 375/130  
 5,213,337 A 5/1993 Sherman  
 5,214,788 A \* 5/1993 Delaperriere et al. .... 375/132  
 5,214,793 A 5/1993 Conway et al.  
 5,311,541 A \* 5/1994 Sanderford, Jr. .... 375/131  
 5,319,735 A 6/1994 Preuss et al.  
 5,379,345 A 1/1995 Greenberg  
 5,394,274 A 2/1995 Kahn  
 5,404,377 A 4/1995 Moses  
 5,408,496 A \* 4/1995 Ritz et al. .... 375/132  
 5,425,100 A 6/1995 Thomas et al.  
 5,450,490 A \* 9/1995 Jensen et al. .... 380/253  
 5,461,390 A 10/1995 Hoshen  
 5,481,294 A 1/1996 Thomas et al.  
 5,483,276 A 1/1996 Brooks et al.  
 5,510,828 A 4/1996 Lutterbach et al.  
 5,512,933 A 4/1996 Wheatley et al.  
 5,526,427 A \* 6/1996 Thomas et al. .... 725/18  
 5,541,585 A 7/1996 Duhame et al.  
 5,574,962 A 11/1996 Fardeau et al.  
 5,579,124 A 11/1996 Aijala et al.  
 5,581,800 A 12/1996 Fardeau et al.  
 5,594,934 A 1/1997 Lu et al.  
 5,612,729 A 3/1997 Ellis et al.  
 5,612,741 A 3/1997 Loban et al.  
 5,687,191 A \* 11/1997 Lee et al. .... 375/216  
 5,737,025 A 4/1998 Dougherty et al.  
 5,758,315 A 5/1998 Mori  
 5,761,240 A \* 6/1998 Croucher, Jr. .... 375/224  
 5,764,763 A \* 6/1998 Jensen et al. .... 380/253  
 5,768,680 A 6/1998 Thomas  
 5,787,334 A 7/1998 Fardeau et al.  
 5,796,785 A 8/1998 Spiero  
 5,809,013 A \* 9/1998 Kackman ..... 370/253  
 5,828,325 A 10/1998 Wolosewicz et al.  
 5,848,129 A 12/1998 Baker  
 5,848,391 A 12/1998 Bosi et al.  
 5,923,252 A 7/1999 Sizer et al.  
 5,945,932 A 8/1999 Smith et al.  
 5,960,048 A \* 9/1999 Haartsen ..... 375/366  
 5,966,696 A 10/1999 Giraud  
 6,005,598 A 12/1999 Jeong  
 6,148,020 A \* 11/2000 Emi ..... 375/132  
 6,154,484 A 11/2000 Lee et al.  
 6,175,627 B1 1/2001 Petrovic et al.  
 6,252,522 B1 6/2001 Hampton et al.  
 6,266,442 B1 7/2001 Laumeyer et al.  
 6,286,005 B1 9/2001 Cannon  
 6,330,293 B1 \* 12/2001 Klank et al. .... 375/344  
 6,360,167 B1 3/2002 Millington et al.

6,396,413 B2 5/2002 Hines et al.  
 6,421,445 B1 \* 7/2002 Jensen et al. .... 380/253  
 6,424,939 B1 7/2002 Herre et al.  
 6,484,148 B1 11/2002 Boyd  
 6,507,802 B1 1/2003 Payton et al.  
 6,519,769 B1 2/2003 Hopple et al.  
 6,546,257 B1 4/2003 Stewart  
 6,571,279 B1 5/2003 Herz et al.  
 6,580,916 B1 6/2003 Weisshaar et al.  
 6,597,405 B1 7/2003 Iggulden  
 6,647,269 B2 11/2003 Hendrey  
 6,647,548 B1 \* 11/2003 Lu et al. .... 725/20  
 6,675,383 B1 \* 1/2004 Wheeler et al. .... 725/19  
 6,720,876 B1 4/2004 Burgess  
 6,735,775 B1 5/2004 Massetti  
 6,845,360 B2 \* 1/2005 Jensen et al. .... 704/500  
 6,862,355 B2 3/2005 Kolessar et al.  
 6,871,180 B1 \* 3/2005 Neuhauser et al. .... 704/500  
 6,934,508 B2 8/2005 Ceresoli et al.  
 6,958,710 B2 10/2005 Zhang et al.  
 6,996,237 B2 \* 2/2006 Jensen et al. .... 380/252  
 7,006,982 B2 2/2006 Sorensen  
 7,015,817 B2 3/2006 Copley  
 7,222,071 B2 \* 5/2007 Neuhauser et al. .... 704/231  
 2001/0053190 A1 12/2001 Srinivasan  
 2002/0097193 A1 7/2002 Powers  
 2002/0107027 A1 8/2002 O'Neil  
 2003/0005430 A1 1/2003 Kolessar  
 2003/0055707 A1 3/2003 Busche et al.  
 2003/0097302 A1 5/2003 Overhultz et al.  
 2003/0110485 A1 6/2003 Lu et al.  
 2003/0122708 A1 7/2003 Percy et al.  
 2003/0170001 A1 9/2003 Breen  
 2003/0171833 A1 9/2003 Crystal et al.  
 2003/0171975 A1 9/2003 Kirshenbaum  
 2004/0019675 A1 1/2004 Hebel, Jr. et al.  
 2004/0102961 A1 5/2004 Jensen et al.  
 2004/0122727 A1 6/2004 Zhang et al.  
 2004/0127192 A1 7/2004 Ceresoli et al.  
 2004/0170381 A1 9/2004 Srinivasan  
 2005/0035857 A1 2/2005 Zhang et al.  
 2005/0159863 A1 7/2005 Howard  
 2005/0201826 A1 9/2005 Zhang et al.  
 2006/0222179 A1 10/2006 Jensen et al.

## FOREIGN PATENT DOCUMENTS

CA 2036205 C 12/1991  
 DE 3806411 A1 9/1989  
 EP 0372601 A1 6/1990  
 FR 2559002 A1 8/1985  
 WO 91/11062 A1 7/1991  
 WO WO 91/11062 7/1991  
 WO 9307689 A1 4/1993  
 WO WO 93/07689 4/1993  
 WO 95/12278 A1 5/1995  
 WO 96/27264 A1 9/1996  
 WO 98/10539 A2 3/1998  
 WO 98/26529 A2 6/1998  
 WO 98/32251 A1 7/1998  
 WO 99/59275 A1 11/1999  
 WO 00/04662 B2 1/2000  
 WO 00/72309 A1 11/2000  
 WO 2006/14362 A1 2/2006

## OTHER PUBLICATIONS

Definition of Checksum. SearchSecurity.  
 Namba, Seiichi, et al., "A Program Identification Code Transmission System Using Low-Frequency Audio Signals"; NHK Laboratories Note; Ser. No. 314, Mar. 1985.  
 McGraw-Hill Encyclopedia of Science & Technology, 6th Edition, McGraw-Hill Book Company, 1987, vol. 8, pp. 328-341.  
 Rossing, The Science of Sound, Addison-Wesley Publishing Company, 1990, Chapters 5 and 6 (pp. 65-108) and section 16.4 (pp. 336-338).  
 Zwislocki, J.J. "Masking: Experimental and Theoretical Aspects . . .", 1978, in Carterette, et al., ed., Handbook of Perception vol. IV, pp. 283-316, Academic Press, New York .

## US RE42,627 E

Page 3

---

Bender, et al., "Techniques for Data Hiding", IBM Systems Journal, vol. 35, Nos. 3 & 4, 196.

Rabinowitz, M. et al, A New Positioning System Using Television Synchronization Signals, date unknown, pp. 1-11.

Rabinowitz, M. et al, Is a Next Generation Positioning Technology Necessary?, Jun. 17, 2002, 22 pages.

www.rosun.com, various pages from website, Rosun TV-GPS, printed Feb. 16, 2005, 13 pages total.


Apr. 22, 2009 Complaint in *Arbitron Inc., v. John Barrett Kiefl* in United States District Court for the Southern District of New York. Case 1:09-cv-04013-PAC.

Apr. 8, 2009 Letter from John S. Macera (representing Kiefl) to Michael Skarzynski (of Arbitron) re: alleged patent infringement. (Exhibit 1 of the Apr. 22, 2009 Complaint in *Arbitron Inc., v. John Barrett Kiefl* in United States District Court for the Southern District of New York. Case 1:09-cv-04013-PAC.).

Apr. 24, 2009 Letter from Michael Skarzynski (of Arbitron) to John S. Macera (representing Kiefl) re: alleged patent infringement.

\* cited by examiner

FIG. 1



*FIG. 2*

INFORMATION SIGNAL	SYMBOL
COPYRIGHTED WORK	S <sub>1</sub>
AUTHOR	S <sub>2</sub>
BROADCASTING STATION	S <sub>3</sub>
DATE	S <sub>4</sub>

FIG. 3A




FIG. 3B




FIG. 3C





FIG. 4

		SYMBOL												
		S <sub>A</sub>	S <sub>B</sub>	S <sub>1</sub>	S <sub>2</sub>	S <sub>3</sub>	S <sub>4</sub>	.	.	.	S <sub>N-1</sub>	S <sub>N</sub>		
1	FREQUENCY COMPONENT	f <sub>1A</sub>	f <sub>1B</sub>	f <sub>11</sub>	f <sub>12</sub>	f <sub>13</sub>	f <sub>14</sub>	.	.	.	f <sub>1(N-1)</sub>	f <sub>1N</sub>		
2		f <sub>2A</sub>	f <sub>2B</sub>	f <sub>21</sub>	f <sub>22</sub>	f <sub>23</sub>	f <sub>24</sub>	.	.	.	f <sub>2(N-1)</sub>	f <sub>2N</sub>		
3		f <sub>3A</sub>	f <sub>3B</sub>	f <sub>31</sub>	f <sub>32</sub>	f <sub>33</sub>	f <sub>34</sub>	.	.	.	f <sub>3(N-1)</sub>	f <sub>3N</sub>		
4		f <sub>4A</sub>	f <sub>4B</sub>	f <sub>41</sub>	f <sub>42</sub>	f <sub>43</sub>	f <sub>44</sub>	.	.	.	f <sub>4(N-1)</sub>	f <sub>4N</sub>		
.		.	.	.	.	.	.	.	.	.	.	.		
.		.	.	.	.	.	.	.	.	.	.	.		
.		.	.	.	.	.	.	.	.	.	.	.		
N-1		f <sub>(N-1)A</sub>	f <sub>(N-1)B</sub>	f <sub>(N-1)1</sub>	f <sub>(N-1)2</sub>	f <sub>(N-1)3</sub>	f <sub>(N-1)4</sub>	.	.	.	f <sub>(N-1)(N-1)</sub>	f <sub>(N-1)N</sub>		
M		f <sub>MA</sub>	f <sub>MB</sub>	f <sub>m1</sub>	f <sub>m2</sub>	f <sub>m3</sub>	f <sub>m4</sub>	.	.	.	f <sub>M(N-1)</sub>	f <sub>MN</sub>		

FIG. 5








FIG. 6

FIG. 7

100




FIG. 8




FIG. 9





FIG. 10



## ENCODING AND DECODING OF INFORMATION IN AUDIO SIGNALS

**Matter enclosed in heavy brackets [ ] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.**

### *CROSS-REFERENCE TO RELATED APPLICATIONS AND U.S. PATENT DOCUMENT*

*This is an application to reissue U.S. Pat. No. 6,871,180 issued Mar. 22, 2005 from application Ser. No. 09/318,045 filed May 25, 1999.*

### BACKGROUND OF THE INVENTION

The present invention relates to methods and apparatus for extracting an information signal from an encoded audio signal.

There are various motivations to permanently or indelibly incorporate information signals into audio signals, referred to as "watermarking." Such an audio watermark may provide, for example, an indication of authorship, content, lineage, existence of copyright, or the like for the audio signals so marked. Alternatively, other information may be incorporated into audio signals either concerning the signal itself or unrelated to it. The information may be incorporated in an audio signal for various purposes, such as identification or as an address or command, whether or not related to the signal itself.

There is considerable interest in encoding audio signals with information to produce encoded audio signals having substantially the same perceptible characteristics as the original unencoded audio signals. Recent successful techniques exploit the psychoacoustic masking effect of the human auditory system whereby certain sounds are humanly imperceptible when received along with other sounds.

One particularly successful utilization of the psychoacoustic masking effect is described in U.S. Pat. No. 5,450,490 and U.S. Pat. No. 5,764,763 (Jensen et al.) in which information is represented by a multiple-frequency code signal which is incorporated into an audio signal based upon the masking ability of the audio signal. The encoded audio signal is suitable for broadcast transmission and reception as well as for recording and reproduction. When received the audio signal is then processed to detect the presence of the multiple-frequency code signal. Sometimes, only a portion of the multiple-frequency code signal, e.g., a number of single frequency code components, inserted into the original audio signal are detected in the received audio signal. If a sufficient quantity of code components is detected, the information signal itself may be recovered.

Generally, an acoustic signal having low amplitude levels will have only minimal capacity, if any at all, to acoustically mask an information signal. For example, such low amplitude levels can occur during a pause in a conversation, during an interlude between segments of music, or even within certain types of music. During a lengthy period of low amplitude levels, it may be difficult to incorporate a code signal in an audio signal without causing the encoded audio signal to differ from the original in an acoustically perceptible manner.

A further problem is the occurrence of burst errors during the transmission or reproduction of encoded audio signals. Burst errors may appear as temporally contiguous segments of signal error. Such errors generally are unpredictable and

substantially affect the content of an encoded audio signal. Burst errors typically arise from failure in a transmission channel or reproduction device due to severe external interferences, such as an overlapping of signals from different transmission channels, an occurrence of system power spikes, an interruption in normal operations, an introduction of noise contamination (intentionally or otherwise), and the like. In a transmission system, such circumstances may cause a portion of the transmitted encoded audio signals to be entirely unreceivable or significantly altered. Absent retransmission of the encoded audio signal, the affected portion of the encoded audio may be wholly unrecoverable, while in other instances alterations to the encoded audio signal may render the embedded information signal undetectable. In many applications, such as radio and television broadcasting, real-time retransmission of encoded audio signals is simply unfeasible.

In systems for acoustically reproducing audio signals recorded on media, a variety of factors may cause burst errors in the reproduced acoustic signal. Commonly, an irregularity in the recording media, caused by damage, obstruction, or wear, results in certain portions of recorded audio signals being unreproducible or significantly altered upon reproduction. Also, misalignment of or interference with the recording or reproducing mechanism relative to the recording medium can cause burst-type errors during an acoustic reproduction of recorded audio signals. Further, the acoustic limitations of a speaker as well as the acoustic characteristics of the listening environment may result in spatial irregularities in the distribution of acoustic energy. Such irregularities may cause burst errors to occur in received acoustic signals, interfering with code recovery.

### OBJECTS AND SUMMARY OF THE INVENTION

Therefore, an object of the present invention is to provide systems and methods for detecting code symbols in audio signals which alleviate the problems caused by periods of low signal levels and burst errors.

It is another object of the invention to provide such systems and methods which afford reliable operation under adverse conditions.

It is a further object of the invention to provide such systems and methods which are robust.

In accordance with an aspect of the present invention, systems and methods are provided for decoding at least one message symbol represented by a plurality of code symbols in an audio signal. The systems and methods comprise the means for and the steps of, respectively, receiving first and second code symbols representing a common message symbol, the first and second code symbols being displaced in time in the audio signal, accumulating a first signal value representing the first code symbol and a second signal value representing the second code symbol, and examining the accumulated first and second signal values to detect the common message symbol.

In accordance with another aspect of the present invention, a system is provided for decoding at least one message symbol represented by a plurality of code symbols in an audio signal. The system comprises, an input device for receiving first and second code symbols representing a common message symbol, the first and second code symbols being displaced in time in the audio signal; and a digital processor in communication with the input device to receive data therefrom representing the first and second code symbols, the digital processor being programmed to accumulate a first

signal value representing the first code symbol and a second signal value representing the second code symbol, the digital processor being further programmed to examine the accumulated first and second signal values to detect the common message symbol.

In certain embodiments, the first and second signal values are accumulated by storing the values separately and the common message symbol is detected by examining both of the separately stored values. The first and second signal values may represent signal values derived from multiple other signal values, such as values of individual code frequency components, or a single signal value, such as a measure of the magnitude of a single code frequency component. Moreover, a derived value may be obtained as a linear combination of multiple signal values, such as a summation of weighted or unweighted values, or as a non-linear function thereof.

In further embodiments, the first and second signal values are accumulated by producing a third signal value derived from the first and second values. The third signal value in some embodiments is derived through a linear combination of the first and second signal values, such as a weighted or unweighted summation thereof, or as a nonlinear function thereof.

Other objects, features, and advantages according to the present invention will become apparent from the following detailed description of certain advantageous embodiments when read in conjunction with the accompanying drawings in which the same components are identified by the same reference numerals.

#### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a functional block diagram of an encoding apparatus;

FIG. 2 is a table to which reference will be made in explaining a methodology for encoding information in an audio signal;

FIGS. 3A, 3B, and 3C are schematic diagrams which illustrate an audio signal encoding methodology;

FIG. 4 is another table to which reference will be made in explaining a methodology for encoding information in an audio signal;

FIG. 5 is a block diagram illustrating a multiple-stage audio signal encoding system;

FIG. 6 is a functional block diagram of a personal portable meter;

FIG. 7 is a functional block diagram illustrating a decoding apparatus;

FIG. 8 is a flowchart illustrating a methodology for retrieving an information code from an encoded audio signal;

FIG. 9 is a schematic diagram of a circular SNR buffer used in carrying out the methodology of FIG. 8;

FIG. 10 is a flow chart illustrating another methodology for retrieving an information code from an encoded audio signal.

#### DETAILED DESCRIPTION OF CERTAIN ADVANTAGEOUS EMBODIMENTS

The present invention relates to the use of especially robust encoding which converts information into redundant sequences of code symbols. In certain embodiments, each code symbol is represented by a set of different, predetermined single-frequency code signals; however, in other embodiments different code symbols may optionally share certain single-frequency code signals or may be provided by a methodology which does not assign predetermined frequency components to a given symbol. The redundant

sequence of symbols is incorporated into the audio signals to produce encoded audio signals that are unnoticed by the listener but nevertheless recoverable.

The redundant code symbol sequence is especially suited for incorporation into audio signals having low masking capacity, such as audio signals having many low amplitude portions or the like. Additionally, when incorporated into audio signals, the redundant sequence of code symbols resists degradation by burst errors which affect temporally contiguous audio signals. As described hereinabove, such errors may be the result of imperfect audio signal recording, reproduction, and/or storage processes, transmission of the audio signals through a lossy and/or noisy channel, irregularities in an acoustic environment, or the like.

To recover the encoded information in certain advantageous embodiments, the encoded audio signals are examined in an attempt to detect the presence of predetermined single-frequency code components. During the encoding process, some single-frequency code components may not have been incorporated into the audio signals in certain signal intervals due to insufficient masking capacity in the audio signals in these intervals. Burst errors which have corrupted portions of the encoded audio signals can result in the deletion of certain code signals from the encoded audio signals or in the insertion of erroneous signals, such as noise, into the encoded audio signals. Thus, examination of the encoded audio signals is likely to reveal a much distorted version of the original sequence of sets of single-frequency code signals that represented the information.

The single-frequency code components that are recovered, along with the erroneous additional signals that are mistakenly detected as code signals, are processed to discern the original sequence of code symbols, if possible. The code signal detection and processing operations are specifically adapted to exploit the strengths of the encoding methodology. As a result, the detection and processing methodology of the present invention provides improved error tolerance.

FIG. 1 is a functional block diagram of an audio signal encoder 10. Encoder 10 implements an optional symbol generation function 12, a symbol sequence generation function 14, a symbol encoding function 16, an acoustic masking effect evaluation/adjustment function 18, and an audio signal inclusion function 20. Preferably encoder 10 comprises a software-controlled computer system. The computer may be provided with an analog processor for sampling an analog audio signal to be encoded, or may input the audio signal directly in digital form, with or without resampling. Alternatively, encoder 10 may comprise one or more discrete signal processing components.

The symbol generation function 12, when employed, translates an information signal into a set of code symbols. This function may be carried out with the use of a memory device, such as a semiconductor EPROM of the computer system, which is prestored with a table of code symbols suitable for indexing with respect to an information signal. An example of a table for translating an information signal into a code symbol for certain applications is shown in FIG. 2. The table may be stored on a hard drive or other suitable storage device of the computer system. The symbol generation function may also be carried out by one or more discrete components, such as an EPROM and associated control devices, by a logic array, by an application specific integrated circuit, or any other suitable device or combination of devices. The symbol generation function may also be implemented by one or more devices which also implement one or more of the remaining functions illustrated in FIG. 1.

5

The symbol sequence generating function **14** formats the symbols produced by the symbol generating function (or input directly to the encoder **10**) into a redundant sequence of code or information symbols. As part of the formatting process, in certain embodiments marker and/or synchronization symbols are added to the sequence of code symbols. The redundant sequence of code symbols is designed to be especially resistant to burst errors and audio signal encoding processes. Further explanation of redundant sequences of code symbols in accordance with certain embodiments will be provided in connection with the discussion of FIGS. **3A**, **3B**, and **3C** below. Preferably, the generating function **14** is implemented in a processing device, such as a microprocessor system, or by a dedicated formatting device, such as an application specific integrated circuit or a logic array, by a plurality of components or a combination of the foregoing. The symbol sequence generating function may also be implemented by one or more devices which also implement one or more of the remaining functions illustrated in FIG. **1**.

As noted above, the symbol sequence generating function **14** is optional. For example, the encoding process may be carried out such that the information signal is translated directly into a predetermined symbol sequence, without implementing separate symbol generating and symbol sequence generating functions.

Each symbol of the sequence of symbols thus produced is converted by the symbol encoding function **16** into a plurality of single-frequency code signals. In certain advantageous embodiments the symbol encoding function is performed by means of a memory device of the computer system, such as a semiconductor EPROM, which is prestored with sets of single-frequency code signals that correspond to each symbol. An example of a table of symbols and corresponding sets of single-frequency code signals is shown in FIG. **4**.

Alternatively, the sets of code signals may be stored on a hard drive or other suitable storage device of the computer system. The encoding function may also be implemented by one or more discrete components, such as an EPROM and associated control devices, by a logic array, by an application specific integrated circuit or any other suitable device or combination of devices. The encoding function may also be carried out by one or more devices which also implement one or more of the remaining functions illustrated in FIG. **1**.

In the alternative, the encoded sequence may be generated directly from the information signal, without implementing the separate functions **12**, **14**, and **16**.

The acoustic masking effect evaluation/adjustment function **18** determines the capacity of an input audio signal to mask single-frequency code signals produced by the symbol encoding function **16**. Based upon a determination of the masking ability of the audio signal, the function **18** generates adjustment parameters to adjust the relative magnitudes of the single-frequency code signals so that such code signals will be rendered inaudible by a human listener when incorporated into the audio signal. Where the audio signal is determined to have low masking capacity, due to low signal amplitude or other signal characteristics, the adjustment parameters may reduce the magnitudes of certain code signals to extremely-low levels or may nullify such signals entirely. Conversely, where the audio signal is determined to have a greater masking capacity, such capacity may be utilized through the generation of adjustment parameters that increase the magnitudes of particular code signals. Code signals having increased magnitudes are generally more likely to be distinguishable from noise and thus detectable by a decoding device. Further details of certain advantageous embodiments of such evaluation/adjustment function are set forth in U.S.

6

Pat. No. 5,764,763 and U.S. Pat. No. 5,450,490 to Jensen, et al., each entitled Apparatus and Methods for Including Codes in Audio Signals and Decoding, which are incorporated herein by reference in their entirety.

In certain embodiments, the function **18** applies the adjustment parameters to the single-frequency code signals to produce adjusted single-frequency code signals. The adjusted code signals are included in the audio signal by the function **20**. Alternatively, the function **18** supplies the adjustment parameters along with the single-frequency code signals for adjustment and inclusion in the audio signal by the function **20**. In still other embodiments, the function **18** is combined with one or more of the functions **12**, **14**, and **16** to produce magnitude-adjusted single-frequency code signals directly.

In certain embodiments, the acoustic masking effect evaluation/adjustment function **18** is implemented in a processing device, such as a microprocessor system which may also implement one or more of the additional functions illustrated in FIG. **1**. The function **18** may also be carried out by a dedicated device, such as an application specific integrated circuit or a logic array, or by a plurality of discrete components, or a combination of the foregoing.

The code inclusion function **20** combines the single-frequency code components with the audio signal to produce an encoded audio signal. In a straightforward implementation, the function **20** simply adds the single-frequency code signals directly to the audio signal. However, the function **20** may overlay the code signals upon the audio signal. Alternatively, modulator **20** may modify the amplitudes of frequencies within the audio signal according to an input from acoustic masking effect evaluation function **18** to produce an encoded audio signal that includes the adjusted code signals. Moreover, the code inclusion function may be carried out either in the time domain or in the frequency domain. The code inclusion function **20** may be implemented by means of an adding circuit, or by means of a processor. This function may also be implemented by one or more devices described above which also implement one or more of the remaining functions illustrated in FIG. **1**.

One or more of the functions **12** through **20** may be implemented by a single device. In certain advantageous embodiments, the functions **12**, **14**, **16** and **18** are implemented by a single processor, and in still others a single processor carries out all of the functions illustrated in FIG. **1**. Moreover, two or more of the functions **12**, **14**, **16** and **18** may be implemented by means of a single table maintained in an appropriate storage device.

FIG. **2** illustrates an exemplary translation table for converting an information signal into a code symbol. As shown, an information signal may comprise information regarding the content of, the characteristics of, or other considerations relating to a particular audio signal. For example, it is contemplated that an audio signal could be modified to include an inaudible indication that copyright is claimed in the audio program. Correspondingly, a symbol, such as  $S_1$ , may be utilized to indicate that copyright is claimed in the particular work. Similarly, an author may be identified with a unique symbol  $S_2$  or a broadcasting station identified with a unique symbol  $S_3$ . Further, a particular date could be represented by a symbol  $S_4$ . Of course many other types of information could be included in an information signal and translated into a symbol. For example, information such as addresses, commands, encryption keys, etc., may be encoded in such symbols. Alternatively, sets or sequences of symbols, in addition to or instead of individual symbols, may be utilized to represent particular types of information. As another alternative, an entire symbolic language may be implemented to represent



any type of information signal. Also, the encoded information need not be related to the audio signal.

FIG. 3A is a schematic diagram illustrating a stream of symbols which might be generated by the symbol generating function 12 of FIG. 1, while FIGS. 3B and 3C are schematic diagrams illustrating sequences of symbols which might be generated by the symbol sequence generating function 14 of FIG. 1 in response to the symbol stream of FIG. 3A. In FIGS. 3A through 3C,  $S_1$ ,  $S_2$ ,  $S_3$ , and  $S_4$  are used as examples of symbols to illustrate features of the present invention and are not meant to limit its applicability. For example, the information represented by any one or more of the symbols  $S_1$ ,  $S_2$ ,  $S_3$  or  $S_4$  may be selected arbitrarily without regard to that represented by any one or more of the other symbols.

FIG. 3B illustrates an example of a core unit of a redundant symbol sequence representative of an input set of four symbols,  $S_1$ ,  $S_2$ ,  $S_3$ , and  $S_4$ . The core unit begins with a first message segment having sequence or marker symbol,  $S_A$ , followed by the four input data symbols, followed by three repeating message segments each comprised of a sequence or marker symbol,  $S_B$ , and the four input symbols. For many applications, this core unit alone is sufficiently redundant to provide the required level of survivability. Alternatively, this core unit may itself be repeated to increase survivability. Moreover, the core unit may have more or less than four message segments, as well as segments having more or less than four or five symbols.

Generalizing from this example, an input set of N symbols,  $S_1, S_2, S_3, \dots, S_{N-1}, S_N$ , is represented by the redundant symbol sequence comprising  $S_A, S_1, S_2, S_3, \dots, S_{N-1}, S_N$ , followed by (P-1) repeating segments comprising  $S_B, S_1, S_2, S_3, \dots, S_{N-1}, S_N$ . As in the example, this core unit may itself be repeated to increase survivability. In addition, the sequence of symbols in the message segments may be varied from segment to segment so long as the decoder is arranged to recognize corresponding symbols in the various segments. Moreover, different sequence or marker symbols and combinations thereof may be employed, and the positions of the markers with respect to the data symbols may be arranged differently. For example, the sequence can take the form,  $S_1 \dots, S_2, \dots, S_A, \dots, S_N$  or the form,  $S_1, S_2, \dots, S_N, S_A$ .

FIG. 3C illustrates an example of an advantageous core unit of a redundant symbol sequence representative of an input set of four data symbols,  $S_1, S_2, S_3$ , and  $S_4$ . The core unit begins with a sequence or marker symbol,  $S_A$ , followed by the four input data symbols, followed by a sequence or marker symbol,  $S_B$ , followed by  $S_{(1+\beta)} \bmod M, S_{(2+\beta)} \bmod M, S_{(3+\beta)} \bmod M, S_{(4+\beta)} \bmod M$ , where M is the number of different symbols in the available symbol set and where  $\beta$  is an offset having a value between  $\emptyset$  and M. In an advantageous embodiment, the offset  $\beta$  is selected as a CRC checksum. In still other embodiments, the value of the offset  $\beta$  is varied from time to time to encode additional information in the message. For example, if the offset can vary from 0 to 9, nine different information states can be encoded in the offset.

Generalizing from this example, an input set of N symbols,  $S_1, S_2, S_3, \dots, S_{N-1}, S_N$ , is represented by the redundant symbol sequence comprising  $S_A, S_1, S_2, S_3, \dots, S_{N-1}, S_N, S_B, S_{(1+\beta)} \bmod M, S_{(2+\beta)} \bmod M, S_{(3+\beta)} \bmod M, \dots, S_{(N-1+\beta)} \bmod M, S_{(N+\beta)} \bmod M$ . That is, the same information is represented by two or more different symbols in the same core unit and recognized according to their order therein. In addition, these core units may themselves be repeated to increase survivability. Since the same information is represented by multiple different symbols, the coding is made substantially more robust. For example, the structure of an audio signal can mimic the frequency component of one of the data symbols

$S_N$ , but the likelihood that the audio signal will also mimic its corresponding offset  $S_{(N+\beta)} \bmod M$  at its predetermined occurrence is very much lower. Also, since the offset is the same for all symbols within a given segment, this information provides a further check on the validity of the detected symbols within that segment. Consequently, the encoding format of FIG. 3C substantially reduces the likelihood of false detections induced by the structure of the audio signal.

A particular strength of the redundant sequence exemplified in FIG. 3 is its utilization of the input symbols in their original order followed by (a) a different arrangement of the input symbols, (b) an arrangement of symbols that includes other symbols in place of one or more of the input symbols, with or without rearrangement of input symbol order, or (c) an arrangement of symbols different from the input symbols. Arrangements (b) and (c) are particularly robust since, upon symbol encoding, an increased diversity of single-frequency code signals is achieved. Assuming that the input symbols are encoded collectively from among a first group of code signals, symbols in arrangements (b) and (c) will be encoded with another group of code signals which to some extent does not overlap the first group. A greater diversity of code signals will generally increase the likelihood that some code signals are within the masking capacity of the audio signal.

The table of FIG. 4 illustrates an exemplary conversion for a sequence or marker symbol,  $S_A$ , a sequence or marker symbol,  $S_B$ , and N data symbols,  $S_1, S_2, S_3, \dots, S_{N-1}, S_N$ , into corresponding sets of M single-frequency code signals  $f_{1x}, f_{2x}, f_{3x}, \dots, f_{[M-1]x}, f_{Mx}$ , where x references the identifying subscript of the particular symbol. Although the single-frequency code signals may occur throughout the frequency range of the audio signal and, to some extent, outside such frequency range, the code signals of this embodiment are within the frequency range 500 Hz to 5500 Hz but may be selected as a different frequency range. In one embodiment, the sets of M single-frequency code signals may share certain single-frequency code signals; however, in a preferred embodiment, the single-frequency code signals are completely non-overlapping. Moreover, it is not necessary that all symbols be represented by the same number of frequency components.

FIG. 5 illustrates a multiple-stage audio signal encoding system 50. This system implements multiple audio signal encoders to successively encode an audio signal 52 as it travels along a typical audio signal distribution network. At each stage of distribution, the audio signal is successively encoded with an information signal pertinent to the particular stage. Preferably, the successive encodings of the respective information signals do not produce code signals that overlap in frequency. Nevertheless, due to the robust nature of the encoding methodology, partial overlap among the frequency components of the respective encoded information signals is tolerable. System 50 includes a recording facility 54; a broadcaster 66; a relay station 76; audio signal encoders 58, 70, and 80; an audio signal recorder 62; a listener facility 86; and an audio signal decoder 88.

Recording facility 54 includes apparatus for receiving and encoding audio signals and recording encoded audio signals upon a storage medium. Specifically, facility 54 includes audio signal encoder 58 and audio signal recorder 62. Audio signal encoder 58 receives an audio signal feed 52 and a recording information signal 56 and encodes audio signal 52 with information signal 56 to produce an encoded audio signal 60. Audio signal feed 52 may be produced by any conventional source of audio signals such as a microphone, an apparatus for reproducing recorded audio signals, or the like. Recording information signal 56 preferably comprises infor-

mation regarding audio signal feed **52**, such as its authorship, content, or lineage, or the existence of copyright, or the like. Alternatively, recording information signal **56** may comprise any type of data.

Recorder **62** is a conventional device for recording encoded audio signals **60** upon a storage medium which is suitable for distribution to one or more broadcasters **66**. Alternatively, audio signal recorder **62** may be omitted entirely. Encoded audio signals **60** may be distributed via distribution of the recorded storage media or via a communication link **64**. Communication link **64** extends between recording facility **54** and broadcaster **66** and may comprise a broadcast channel, a microwave link, a wire or fiber optic connection, or the like.

Broadcaster **66** is a broadcasting station that receives encoded audio signals **60**, further encodes such signals **60** with a broadcaster information signal **68** to produce a twice-encoded audio signal **72**, and broadcasts the twice-encoded audio signal **72** along a transmission path **74**. Broadcaster **66** includes an audio signal encoder **70** which receives encoded audio signal **60** from recording facility **54** and a broadcaster information signal **68**. Broadcaster information signal **68** may comprise information regarding broadcaster **66**, such as an identification code, or regarding the broadcasting process, such as the time, date or characteristics of the broadcast, the intended recipient(s) of the broadcast signal, or the like. Encoder **70** encodes encoded audio signal **60** with information signal **68** to produce twice-encoded audio signal **72**. Transmission path **74** extends between broadcaster **66** and relay station **76** may comprise a broadcast channel, a microwave link, a wire or fiber optic connection, or the like.

Relay station **76** receives a twice-encoded audio signal **72** from broadcaster **66**, further encodes that signal with a relay station information signal **78**, and transmits the thrice-encoded audio signal **82** to a listener facility **86** via a transmission path **84**. Relay station **76** includes an audio signal encoder **80** which receives twice-encoded audio signal **72** from broadcaster **66** and a relay station information signal **78**. Relay station information signal **78** preferably comprises information regarding relay station **76**, such as an identification code, or regarding the process of relaying the broadcast signal, such as the time, date or characteristics of the relay, the intended recipient(s) of the relayed signal, or the like. Encoder **80** encodes twice-encoded audio signal **72** with relay station information signal **78** to produce thrice-encoded audio signal **82**. Transmission path **84** extends between relay station **76** and listener facility **86** and may comprise a broadcast channel, a microwave link, a wire or fiber optic connection, or the like. Optionally, transmission path **84** may be an acoustic transmission path.

Listener facility **86** receives thrice-encoded audio signal **82** from relay station **76**. In audience estimate applications, listener facility **86** is located where a human listener may perceive an acoustic reproduction of audio signal **82**. If audio signal **82** is transmitted as an electromagnetic signal, listener facility **86** preferably includes a device for acoustically reproducing that signal for the human listener. However, if audio signal **82** is stored upon a storage medium, listener facility **86** preferably includes a device for reproducing signal **82** from the storage medium.

In other applications, such as music identification and commercial monitoring, a monitoring facility is employed rather than listener **86**. In such a monitoring facility, the audio signal **82** preferably is processed to receive the encoded message without acoustic reproduction.

Audio signal decoder **88** may receive thrice encoded audio signal **82** as an audio signal or, optionally, as an acoustic signal. Decoder **88** decodes audio signal **82** to recover one or

more of the information signals encoded therein. Preferably, the recovered information signal(s) are processed at listener facility **86** or recorded on a storage medium for later processing.

Alternatively, the recovered information signal(s) may be converted into images for visual display to the listener.

In an alternate embodiment, recording facility **54** is omitted from system **50**. Audio signal feed **52**, representing, for example, a live audio performance, is provided directly to broadcaster **66** for encoding and broadcast. Accordingly, broadcaster information signal **68** may further comprise information regarding audio signal feed **52**, such as its authorship, content, or lineage, or the existence of copyright, or the like.

In another alternate embodiment, relay station **76** is omitted from system **50**. Broadcaster **66** provides twice-encoded audio signal **72** directly to listener **86** via transmission path **74** which is modified to extend therebetween. As a further alternative, both recording facility **54** and relay station **76** may be omitted from system **50**.

In another alternate embodiment, broadcaster **66** and relay station **76** are omitted from system **50**. Optionally, communication link **64** is modified to extend between recording facility **54** and listener facility **86** and to carry encoded audio signal **60** therebetween. Preferably, audio signal recorder **62** records encoded audio signal **60** upon a storage medium which is thereafter conveyed to listener facility **86**. An optional reproduction device at listener facility **86** reproduces the encoded audio signal from the storage medium for decoding and/or acoustic reproduction.

FIG. **6** provides an example of a personal portable meter **40** for use in audience estimate applications. The meter **90** includes a housing **92**, illustrated in phantom lines, having a size and shape permitting it to be carried on the person of an audience member. For example, the housing may have the same size and shape as a pager unit.

A microphone **93** is within the housing **92** and serves as an acoustic transducer to transduce received acoustic energy, including encoded audio signals, to analog electrical signals. The analog signals are converted to digital by an analog to digital converter and the digital signals are then supplied to a digital signal processor (DSP) **95**. The DSP **95** implements a decoder in accordance with the present invention in order to detect the presence of predetermined codes in the audio energy received by the microphone **93** indicating that the person carrying the personal portable meter **90** has been exposed to a broadcast of a certain station or channel. If so, the DSP **95** stores a signal representing such detection in its internal memory along with an associated time signal.

The meter **90** also includes a data transmitter/receiver, such as an infrared transmitter/receiver **97** coupled with the DSP **95**. The transmitter/receiver **97** enables the DSP **95** to provide its data to a facility for processing such data from multiple meters **90** to produce audience estimates, as well as to receive instructions and data, for example, to set up the meter **90** for carrying out a new audience survey.

Decoders in accordance with certain advantageous embodiments of the present invention are illustrated by the functional block diagram of FIG. **7**. An audio signal which may be encoded as described hereinabove with a plurality of code symbols, is received at an input **102**. The received audio signal may be a broadcast, internet or otherwise communicated signal, or a reproduced signal. It may be a direct coupled or an acoustically coupled signal. From the following description in connection with the accompanying drawings, it

## 11

will be appreciated that the decoder **100** is capable of detecting codes in addition to those arranged in the formats disclosed hereinabove.

For received audio signals in the time domain, the decoder **100** transforms such signals to the frequency domain by means of a function **106**. The function **106** preferably is performed by a digital processor implementing a fast Fourier transform (FFT) although a direct cosine transform, a chirp transform or a Winograd transform algorithm (WFTA) may be employed in the alternative. Any other time-to-frequency-domain transformation function providing the necessary resolution may be employed in place of these. It will be appreciated that in certain implementations, the function **106** may also be carried out by analog or digital filters, by an application specific integrated circuit, or any other suitable device or combination of devices. The function **106** may also be implemented by one or more devices which also implement one or more of the remaining functions illustrated in FIG. 7.

The frequency domain-converted audio signals are processed in a symbol values derivation function **110**, to produce a stream of symbol values for each code symbol included in the received audio signal. The produced symbol values may represent, for example, signal energy, power, sound pressure level, amplitude, etc., measured instantaneously or over a period of time, on an absolute or relative scale, and may be expressed as a single value or as multiple values. Where the symbols are encoded as groups of single frequency components each having a predetermined frequency, the symbol values preferably represent either single frequency component values or one or more values based on single frequency component values.

The function **110** may be carried out by a digital processor, such as a digital signal processor (DSP) which advantageously carries out some or all of the other functions of decoder **100**. However, the function **110** may also be carried out by an application specific integrated circuit, or by any other suitable device or combination of devices, and may be implemented by apparatus apart from the means which implement the remaining functions of the decoder **100**.

The stream of symbol values produced by the function **110** are accumulated over time in an appropriate storage device on a symbol-by-symbol basis, as indicated by the function **116**. In particular, the function **116** is advantageous for use in decoding encoded symbols which repeat periodically, by periodically accumulating symbol values for the various possible symbols. For example, if a given symbol is expected to recur every X seconds, the function **116** may serve to store a stream of symbol values for a period of nX seconds (n>1), and add to the stored values of one or more symbol value streams of nX seconds duration, so that peak symbol values accumulate over time, improving the signal-to-noise ratio of the stored values.

The function **116** may be carried out by a digital processor, such as a DSP, which advantageously carries out some or all of the other functions of decoder **100**. However, the function **110** may also be carried out using a memory device separate from such a processor, or by an application specific integrated circuit, or by any other suitable device or combination of devices, and may be implemented by apparatus apart from the means which implements the remaining functions of the decoder **100**.

The accumulated symbol values stored by the function **116** are then examined by the function **120** to detect the presence of an encoded message and output the detected message at an output **126**. The function **120** can be carried out by matching the stored accumulated values or a processed version of such

## 12

values, against stored patterns, whether by correlation or by another pattern matching technique. However, the function **120** advantageously is carried out by examining peak accumulated symbol values and their relative timing, to reconstruct their encoded message. This function may be carried out after the first stream of symbol values has been stored by the function **116** and/or after each subsequent stream has been added thereto, so that the message is detected once the signal-to-noise ratios of the stored, accumulated streams of symbol values reveal a valid message pattern.

FIG. 8 is a flow chart for a decoder according to one advantageous embodiment of the invention implemented by means of a DSP. Step **130** is provided for those applications in which the encoded audio signal is received in analog form, for example, where it has been picked up by a microphone (as in FIG. 6 embodiment) or an RF receiver.

The decoder of FIG. 8 is particularly well adapted for detecting code symbols each of which includes a plurality of predetermined frequency components, e.g. ten components, as within a frequency range of 1000 Hz to 3000 Hz. It is designed specifically to detect a message having the sequence illustrated in FIG. 3C wherein each symbol occupies an interval of one half-second. In this exemplary embodiment, it is assumed that the symbol set consists of twelve symbols, each having ten predetermined frequency components, none of which is shared with any other symbol of the symbol set. It will be appreciated that the FIG. 8 decoder may readily be modified to detect different numbers of code symbols, different numbers of components, different symbol sequences and symbol durations, as well as components arranged in different frequency bands.

In order to separate the various components, the DSP repeatedly carries out FFTs on audio signal samples falling within successive, predetermined intervals. The intervals may overlap, although this is not required. In an exemplary embodiment, ten overlapping FFT's are carried out during each second of decoder operation. Accordingly, the energy of each symbol period falls within five FFT periods. The FFT's may be windowed, although this may be omitted in order to simplify the decoder. The samples are stored and, when a sufficient number are thus available, a new FFT is performed, as indicated by steps **134** and **138**.

In this embodiment, the frequency component values are produced on a relative basis. That is, each component value is represented as a signal-to-noise ratio (SNR), produced as follows. The energy within each frequency bin of the FFT in which a frequency component of any symbol can fall provides the numerator of each corresponding SNR. Its denominator is determined as an average of adjacent bin values. For example, the average of seven of the eight surrounding bin energy values may be used, the largest value of the eight being ignored in order to avoid the influence of a possible large bin energy value which could result, for example, from an audio signal component in the neighborhood of the code frequency component. Also, given that a large energy value could also appear in the code component bin, for example, due to noise or an audio signal component, the SNR is appropriately limited. In this embodiment, if  $SNR \geq 6.0$ , then SNR is limited to 6.0, although a different maximum value may be selected.

The ten SNR's of each FFT and corresponding to each symbol which may be present, are combined to form symbol SNR's which are stored in a circular symbol SNR buffer, as indicated in step **142** and illustrated schematically in FIG. 9. In certain embodiments, the ten SNR's for a symbol are simply added, although other ways of combining the SNR's may be employed.

As indicated by FIG. 9, the symbol SNR's for each of the twelve symbols A, B and 0-9, are stored in the symbol SNR buffer as separate sequences, one symbol SNR for each FFT for 50  $\mu$ l FFT's. After the values produced in the 50 FFT's have been stored in the symbol SNR buffer, new symbol SNR's are combined with the previously stored values, as described below.

When the symbol SNR buffer is filled, this is detected in a step 146. In certain advantageous embodiments, the stored SNR's are adjusted to reduce the influence of noise in a step 152, although this step is optional in many applications. In this optional step, a noise value is obtained for each symbol (row) in the buffer by obtaining the average of all stored symbol SNR's in the respective row each time the buffer is filled. Then, to compensate for the effects of noise, this average or "noise" value is subtracted from each of the stored symbol SNR values in the corresponding row. In this manner, a "symbol" appearing only briefly, and thus not a valid detection, is averaged out over time. Referring also to FIG. 3C, in order to avoid inflating the noise value at the decoder, preferably the encoding scheme is constrained so that the same symbol does not appear twice in the first half of the message (i.e., within symbol sequence  $S_A, S_1, S_2, S_3, S_4$ ).

After the symbol SNR's have been adjusted by subtracting the noise level, the decoder attempts to recover the message by examining the pattern of maximum SNR values in the buffer in a step 156. In certain embodiments, the maximum SNR values for each symbol are located in a process of successively combining groups of five adjacent SNR's, by weighting the values in the sequence in proportion to the sequential weighting (6 10 10 10 6) and then adding the weighted SNR's to produce a comparison SNR centered in the time period of the third SNR in the sequence. This process is carried out progressively throughout the fifty FFT periods of each symbol. For example, a first group of five SNR's for the "A" symbol in FFT periods 1 through 5 are weighted and added to produce a comparison SNR for FFT period 3. Then a further comparison SNR is produced using the SNR's from FFT periods 2-6, and so on until comparison values have been obtained centered on FFT periods 3 through 48. However, other means may be employed for recovering the message. For example, either more or less than five SNR's may be combined, they may be combined without weighing, or they may be combined in a non-linear fashion.

After the comparison SNR values have been obtained, the decoder examines the comparison SNR values for a message pattern. First, the marker code symbols  $S_A$  and  $S_B$  are located. Once this information is obtained, the decoder attempts to detect the peaks of the data symbols. The use of a predetermined offset between each data symbol in the first segment and the corresponding data symbol in the second segment provides a check on the validity of the detected message. That is, if both markers are detected and the same offset is observed between each data symbol in the first segment and its corresponding data symbol in the second segment, it is highly likely that a valid message has been received.

With reference both to FIGS. 3C and 9, assuming that the beginning of the buffer corresponds with the beginning of the message (which usually is not the case), a peak P of the comparison SNR's for the "A" symbol should appear in the third FFT period, as indicated. Then the decoder will expect the next peak to appear in the position corresponding to the first data symbol 0-9 in the eighth FFT period. In this example, it is assumed that the first data symbol is "3". If the last data symbol is "4" and the value of 6 is 2, the decoder will find a peak of the symbol "6" in FFT period 48, as indicated in FIG. 9. If the message is thus detected (i.e., markers

detected with data symbols appearing where expected and with the same offset throughout), as indicated in steps 162 and 166, the message is logged or output and the SNR buffer is cleared.

However, if the message is not thus found, a further fifty overlapping FFT's are carried out on the following portions of the audio signal and the symbol SNR's so produced are added to those already in the circular buffer. The noise adjustment process is carried out as before and the decoder attempts to detect the message pattern again. This process is repeated continuously until a message is detected. In the alternative, the process may be carried out a limited number of times.

It will be apparent from the foregoing to modify the operation of the decoder depending on the structure of the message, its timing, its signal path, the mode of its detection, etc., without departing from the scope of the present invention. For example, in place of storing SNR's, FFT results may be stored directly for detecting a message.

FIG. 10 is a flow chart for another decoder according to a further advantageous embodiment likewise implemented by means of a DSP. The decoder of FIG. 10 is especially adapted to detect a repeating sequence of five code symbols consisting of a marker symbol followed by four data symbols wherein each of the code symbols includes a plurality of predetermined frequency components and has a duration of one-half second in the message sequence. It is assumed that each symbol is represented by ten unique frequency components and that the symbol set includes twelve different symbols A, B and 0-9, as in the code of FIG. 3C. However, the FIG. 9 embodiment may readily be modified to detect any number of symbols, each represented by one or more frequency components.

Steps employed in the decoding process illustrated in FIG. 10 which correspond to those of FIG. 8 are indicated by the same reference numerals, and these steps consequently are not further described. The FIG. 10 embodiment uses a circular buffer which is twelve symbols wide by 150 FFT periods long. Once the buffer has been filled, new symbol SNRs each replace what are than the oldest symbol SNR values. In effect, the buffer stores a fifteen second window of symbol SNR values.

As indicated in step 174, once the circular buffer is full, its contents are examined in a step 178 to detect the presence of the message pattern. Once full, the buffer remains full continuously, so that the pattern search of step 178 may be carried out after every FFT.

Since each five symbol message repeats every 2½ seconds, each symbol repeats at intervals of 2½ seconds or every 25 FFT's. In order to compensate for the effects of burst errors and the like, the SNR's  $R_1$  through  $R_{150}$  are combined by adding corresponding values of the repeating messages to obtain 25 combined SNR values  $SNR_n, n=1, 2 \dots 25$ , as follows:

$$SNR_n = \sum_{i=0}^5 R_{n+25i}$$

Accordingly, if a burst error should result in the loss of a signal interval  $i$ , only one of the six message intervals will have been lost, and the essential characteristics of the combined SNR values are likely to be unaffected by this event.

Once the combined SNR values have been determined, the decoder detects the position of the marker symbol's peak as

## 15

indicated by the combined SNR values and derives the data symbol sequence based on the marker's position and the peak values of the data symbols.

Once the message has thus been formed, as indicated in steps 182 and 183, the message is logged. However, unlike the embodiment of FIG. 8 the buffer is not cleared. Instead, the decoder loads a further set of SNR's in the buffer and continues to search for a message.

As in the decoder of FIG. 8, it will be apparent from the foregoing to modify the decoder of FIG. 10 for different message structures, message timings, signal paths, detection modes, etc., without departing from the scope of the present invention. For example, the buffer of the FIG. 10 embodiment may be replaced by any other suitable storage device; the size of the buffer may be varied; the size of the SNR values windows may be varied; and/or the symbol repetition time may vary. Also, instead of calculating and storing signal SNR's to represent the respective symbol values, a measure of each symbol's value relative to the other possible symbols, for example, a ranking of each possible symbol's magnitude, is instead used in certain advantageous embodiments.

In a further variation which is especially useful in audience measurement applications, a relatively large number of message intervals are separately stored to permit a retrospective analysis of their contents to detect a channel change. In another embodiment, multiple buffers are employed, each accumulating data for a different number of intervals for use in the decoding method of FIG. 8. For example, one buffer could store a single message interval, another two accumulated intervals, a third four intervals and a fourth eight intervals. Separate detections based on the contents of each buffer are then used to detect a channel change.

Although illustrative embodiments of the present invention and modifications thereof have been described in detail herein, it is to be understood that this invention is not limited to these precise embodiments and modifications, and that other modifications and variations may be effected therein by one skilled in the art without departing from the scope and spirit of the invention as defined by the appended claims.

What is claimed is:

1. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol; and

means for examining the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

2. The system of claim 1, wherein the accumulating means is operative to produce a third signal value derived from the first and second signal values and the examining means is operative to detect the predetermined message symbol based on the third signal value.

## 16

3. The system of claim 2, wherein the accumulating means is operative to produce the third signal value by linearly combining the first and second signal values.

4. The system of claim 2, wherein the accumulating means is operative to produce the third signal value as a non-linear function of the first and second signal values.

5. The system of claim 1, wherein the accumulating means is operative to store the first and second signal values, and the examining means is operative to detect the predetermined message symbol by examining both of the first and second signal values.

6. The system of claim 1, wherein the receiving means comprises an acoustic transducer for transducing an acoustic audio signal to an electrical signal, the acoustic audio signal having a plurality of code symbols representing a plurality of message symbols comprising source data for the acoustic audio signal, and further comprising a memory for storing indications of detected message symbols.

7. The system of claim 5, further comprising a housing for the system adapted to be carried on the person of an audience member and means for transmitting the stored data for use in producing audience estimates.

8. A method for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol; and examining the accumulated first and second signal values to detect the predetermined message symbol.

9. The method of claim 8, further comprising receiving the first and second code symbols by transducing an acoustic audio signal to an electrical signal, the acoustic audio signal having a plurality of message symbols comprising source data for the acoustic audio signal, and storing data representing indications of detected message symbols.

10. The method of claim 9, further comprising transmitting the stored data for use in producing audience estimates.

11. A system for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

17

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate a first signal value representing the first code symbol and a second signal value representing the second code symbol, the digital processor being further programmed to examine the accumulated first and second signal values to detect the predetermined message symbol.

12. The system of claim 11, wherein the input device comprises an acoustic transducer for transducing an acoustic signal to an electrical signal, the acoustic audio signal having a plurality of code symbols representing a plurality of message symbols comprising source data for the acoustic audio signal, the digital processor having a memory for storing data representing indications of detected message symbols.

13. The system of claim 12, further comprising a housing for the system adapted to be carried on the person of an audience member and means for transmitting the stored data for use in producing audience estimates.

14. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols, the first and second code symbols each comprising a predetermined number of frequency components;

means for producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol based on the first set of component values and a second signal value of the second code symbol representing the predetermined message symbol based on the second set of component values; and

means for examining the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

15. A method for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and

18

second code symbols, the first and second code symbols each comprising a predetermined number of frequency components;

producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol;

accumulating a first signal value of the first code symbol representing the predetermined message symbol based on the first set of component values and a second signal value of the second code symbol representing the predetermined message symbol based on the second set of component values; and examining the accumulated first and second signal values to detect the predetermined message symbol.

16. A system for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols, the first and second code symbols each comprising a predetermined number of frequency components; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to produce first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol the digital processor being further programmed to produce a first signal value based on the first set of component values and a second signal value based on the second set of component values and to accumulate a first signal value representing the first code symbol and a second signal value representing the second code symbol, the digital processor being further programmed to examine the accumulated first and second signal values to detect the predetermined message symbol.

17. A system for decoding predetermined message symbols of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message

## 19

symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value representing the second code symbol thereof; and

means for examining the accumulated sets of first and second signal values to detect the presence of the at least one marker symbol based on its signal value set and to detect the at least one data symbol based on the detected presence of the at least one marker symbol and the corresponding signal value set of the at least one data symbol.

**18.** A method for decoding predetermined message symbols of a plurality of message symbols incorporated in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

accumulating sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value representing the second code symbol thereof; and

examining the accumulated sets of first and second signal values to detect the presence of the marker symbol based on its signal value set and to detect at least one data symbol based on the detected presence of the marker symbol and the corresponding signal value set of the at least one data symbol.

**19.** A system for decoding predetermined message symbols of a plurality of message symbols incorporated in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message

## 20

symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value representing the second code symbol thereof, the digital processor being further programmed to examine the accumulated sets of first and second signal values to detect the presence of the marker symbol based on its signal value set and to detect at least one data symbol based on the detected presence of the marker symbol and the corresponding signal value set of the at least one data symbol.

**20.** A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol, wherein the accumulating means is operative to produce the first and second signal values based on multiple other signal values; and

means for examining the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

**21.** A method for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol based on multiple other signal values; and

examining the accumulated first and second signal values to detect the predetermined message symbol.

21

22. A system for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate a first signal value representing the first code symbol and a second signal value representing the second code symbol based on multiple other signal values, the digital processor being further programmed to examine the accumulated first and second signal values to detect the predetermined message symbol.

23. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof; and

means for examining the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

24. A method for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

22

accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof; and

examining the accumulated first and second signal values to detect the predetermined message symbol.

25. A system for decoding a predetermined message symbol of a plurality of message symbols incorporated in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate a first signal value representing the first code symbol and a second signal value representing the second code symbol, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof, the digital processor being further programmed to examine the accumulated first and second signal values to detect the predetermined message symbol.

26. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols, the first and second code symbols each comprising a predetermined number of frequency components;

means for producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol based on the first set of component values and a second signal value of the second code symbol representing the predetermined message symbol based on the second set



## 23

of component values, and for producing a third signal value derived from the first and second signal values; and

means for detecting the predetermined message symbol represented by the first and second code symbols based on the third signal value.

27. A system for decoding a message represented by a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value representing the second code symbol thereof and for producing a third signal value derived from the first and second signal values; and

means for detecting a respective one of the plurality of message symbols represented by the first and second code symbols based on the third signal value and for detecting the message by detecting the presence of the marker symbol based on its signal value set and detecting at least one data symbol based on the detected presence of the marker symbol and the corresponding signal value set of the at least one data symbol.

28. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

means for receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

means for accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol, wherein the accumulating means is operative to produce the first and second signal values based on multiple other signal values and wherein the accumulating means is operative to store the first and second signal values; and

## 24

means for examining both of the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

29. The system of claim 28, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof.

30. The system of claim 28, wherein the first and second code symbols each comprise a predetermined number of frequency components, and further comprising means for producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol, and means for producing the first signal value based on the first set of component values and producing the second signal value based on the second set of component values.

31. A method for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols, the first and second code symbols each comprising a predetermined number of frequency components;

producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol;

accumulating a first signal value of the first code symbol representing the predetermined message symbol based on the first set of component values and a second signal value of the second code symbol representing the predetermined message symbol based on the second set of component values, and for producing a third signal value derived from the first and second signal values; and

detecting the predetermined message symbol represented by the first and second code symbols based on the third signal value.

32. A method for decoding a message represented by a plurality of message symbols embedded in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in

25

and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

accumulating sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value

producing a third signal value derived from the first and second signal values;

detecting a respective one of the plurality of message symbols represented by the first and second code symbols based on the third signal value; and

detecting the message by detecting the presence of the marker symbol based on its signal value set and detecting at least one data symbol based on the detected presence of the marker symbol and the corresponding signal value set of the at least one data symbol.

**33.** A method for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

receiving an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols;

accumulating a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol based on multiple other signal values;

storing the first and second signal values; and

examining both of the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

**34.** The method of claim **33**, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof.

**35.** The method of claim **33**, wherein the first and second code symbols each comprise a predetermined number of frequency components, and further comprising producing first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol, and producing the first signal value based on the first set of component values and producing the second signal value based on the second set of component values.

**36.** A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols

26

being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols, the first and second code symbols each comprising a predetermined number of frequency components;

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to produce first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol, the digital processor being further programmed to accumulate a first signal value of the first code symbol representing the predetermined message symbol based on the first set of component values and a second signal value of the second code symbol representing the predetermined message symbol based on the second set of component values, to produce a third signal value derived from the first and second signal values, and to detect the predetermined message symbol represented by the first and second code symbols based on the third signal value.

**37.** A system for decoding a message represented by a plurality of message symbols embedded in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being represented by plural sets of first and second code symbols, each set representing a respective one of the plurality of message symbols, the plural sets of first and second code symbols being arranged as a message having a predetermined sequence including at least one marker symbol and at least one data symbol, at least one of the marker symbol and the data symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate sets of first and second signal values, each signal value set corresponding to a respective one of the sets of first and second code symbols and including a first signal value representing the first code symbol of the respective code symbol set and a second signal value representing the second code symbol thereof, the digital processor being further programmed to produce a third signal value derived from the first and second signal values, to detect a respective one of the plurality of message symbols represented by the first and second code symbols based on the third signal value, and to detect the message by detecting the presence of the marker symbol based on its signal value set and detecting at least one data symbol based on the detected presence of the marker symbol and the corresponding signal value set of the at least one data symbol.

38. A system for decoding a predetermined message symbol of a plurality of message symbols embedded in an audio signal, comprising:

an input device for an audio signal in which a plurality of message symbols have been incorporated so that the message symbols are inaudible when the audio signal is reproduced audibly, the plurality of message symbols being contained within a predetermined message as a plurality of code symbols, the predetermined message symbol being represented by first and second code symbols incorporated in and displaced in time in the audio signal with at least one code symbol representing a different one of the message symbols being incorporated in the audio signal and positioned in time between the first and second code symbols; and

a digital processor in communication with the input device to receive the audio signal therefrom, the digital processor being programmed to accumulate a first signal value of the first code symbol representing the predetermined message symbol and a second signal value of the second code symbol representing the predetermined message symbol based on multiple other signal values, to store the first and second signal values, and to examine both of the accumulated first and second signal values to detect the predetermined message symbol represented by the first and second code symbols.

39. The system of claim 38, wherein the first and second signal values are produced from respective sets of time displaced signal values, each of the time displaced signal values representing a value of a respective one of the first and second code symbols during a corresponding time period thereof.

40. The system of claim 38, wherein the first and second code symbols each comprise a predetermined number of frequency components, and wherein the digital processor is programmed to produce first and second sets of component values, each set corresponding to a respective one of the first and second code symbols and each component value of each set representing a characteristic of a respective frequency component of the corresponding symbol, and the digital processor is further programmed to produce the first signal value based on the first set of component values and to produce the second signal value based on the second set of component values.

41. A method of encoding a predetermined message in an audio signal using a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message; and

encoding the audio signal using the processing device with a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols;

wherein each of the code symbols in the first encoded sequence of code symbols comprises a first plurality of single frequency components and each of the code symbols in the second encoded sequence of code symbols comprises a second plurality of single frequency components, and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

42. A method according to claim 41, wherein each code symbol in the first encoded sequence of code symbols corre-

sponds to a respective code symbol in the second encoded sequence of code symbols, and wherein each code symbol in the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the respective code symbol in the second encoded sequence of code symbols.

43. A method according to claim 41, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols and is selected based on the order of the respective code symbol of the first encoded sequence of code symbols.

44. A method according to claim 43, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

45. A method according to claim 44, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

46. A method according to claim 41, wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and wherein each code symbol in the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single frequency code components of the code symbols within the predetermined set of code symbols.

47. A method according to claim 41, wherein the processing device is a record device storing a recorded audio signal encoded with a predetermined message.

48. A method according to claim 47, wherein each code symbol in the first encoded sequence of code symbols corresponds to a respective code symbol in the second encoded sequence of code symbols.

49. A method according to claim 47, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols.

50. A method according to claim 49, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

51. A method according to claim 50, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

52. A method according to claim 47, wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and wherein each code symbol in the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single frequency code components of the code symbols within the predetermined set of code symbols.

53. A method for encoding information in an audio signal using a processing device, comprising the steps of:

translating an information signal using the processing device into a first set of code symbols representing the information signal and a second set of code symbols representing the information signal, such that each of the code symbols in the first and second sets of code symbols comprises a corresponding plurality of single-frequency code components, at least some of the single-frequency code components of the code symbols in the first set of code symbols differing from the single-frequency code components of the code symbols in the second set of code symbols;

and, using the processing device, combining the single-frequency code components of the first and second sets of code symbols with the audio signal to produce an encoded audio signal, such that the single-frequency code components of the code symbols in the first set of code symbols are time-displaced from the single-frequency code components of the code symbols in the second set of code symbols in the audio signal.

54. A method according to claim 53, wherein the processing device is a record device storing a recorded audio signal encoded with a predetermined message.

55. A method of encoding a predetermined message in an audio signal using a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message; and

encoding the audio signal with a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols;

wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

56. A method according to claim 55, wherein each code symbol in the first encoded sequence of code symbols corresponds to a respective code symbol in the second encoded sequence of code symbols, and wherein each code symbol in the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of its respective code symbol in the second encoded sequence of code symbols.

57. A method according to claim 55, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols and is selected based on the order of the respective code symbol of the first encoded sequence of code symbols.

58. A method according to claim 57, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

59. A method according to claim 58, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

60. A method according to claim 55, wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of sym-

bols and wherein each code symbol in the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single frequency code components of the code symbols within the predetermined set of code signals.

61. A method according to claim 55, wherein the processing device is a record device storing a recorded audio signal encoded with a predetermined message.

62. A method according to claim 61, wherein each code symbol in the first encoded sequence of code symbols corresponds to a respective code symbol in the second encoded sequence of code symbols, and wherein each code symbol in the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the respective code symbol in the second encoded sequence of code symbols.

63. A method according to claim 61, wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and wherein each code symbol in the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single frequency code components of the code symbols within the predetermined set of code symbols.

64. A method according to claim 61, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols and is selected based on the order of the respective code symbol of the first encoded sequence of code symbols.

65. A method according to claim 64, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

66. A method according to claim 65, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

67. A method of encoding a predetermined message in an audio signal using a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message; and

encoding the audio signal using the processing device with a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols;

wherein each code symbol in the second encoded sequence of code symbols corresponds to a respective code symbol in the first encoded sequence of code symbols, and wherein each code symbol in the second encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the corresponding code symbol in the first encoded sequence of code symbols.

68. A method according to claim 67, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predeter-

31

mined order, and wherein each code symbol of the second encoded sequence of code symbols is selected based on the predetermined order of the corresponding code symbol of the first encoded sequence of code symbols.

69. A method according to claim 68, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the corresponding code symbol of the first encoded sequence of code symbols.

70. A method according to claim 69, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

71. A method according to claim 67, wherein the processing device is a record device storing a recorded audio signal encoded with a predetermined message.

72. A method according to claim 71, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols is selected based on the predetermined order of the corresponding code symbol of the first encoded sequence of code symbols.

73. A method according to claim 72, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the corresponding code symbol of the first encoded sequence of code symbols.

74. A method according to claim 73, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

75. A method of encoding a predetermined message in an audio signal using a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message; and

encoding the audio signal using the processing device with a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols, wherein the first and second encoded sequences of code symbols are inaudible when the audio signal is reproduced audibly;

wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols and is selected based on the order of the respective code symbol of the first encoded sequence of code symbols,

and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

76. A method according to claim 75, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from its respective code symbol of the first encoded sequence of code symbols.

32

77. A method according to claim 76, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

78. A method according to claim 75, wherein the processing device comprises a record device storing a recorded audio signal encoded with a predetermined message.

79. A method according to claim 78, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

80. A method according to claim 79, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

81. A method of encoding a predetermined message in an audio signal using a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message;

encoding the audio signal using the processing device with a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols; and

wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and each code symbol of the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single-frequency code components of the code symbols within the predetermined set of code symbols,

and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

82. A method according to claim 81, wherein the processing device comprises a record device storing a recorded audio signal encoded with a predetermined message.

83. A method of encoding a predetermined message in an audio signal in a processing device, comprising:

encoding the audio signal using the processing device with a first encoded sequence of code symbols representing the predetermined message, each of the first encoded code symbols comprising a first plurality of single frequency components; and

encoding the audio signal using the processing device with a second encoded sequence of code symbols representing the predetermined message, each of the second encoded code symbols comprising a second plurality of single frequency components, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols,

and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

84. A method according to claim 83, further comprising:  
encoding the audio signal with a marker symbol positioned  
in time adjacent at least one of the first encoded  
sequence of code symbols and the second encoded  
sequence of code symbols.
85. A method according to claim 83, further comprising:  
encoding the audio signal with a first marker symbol adja-  
cent the first encoded sequence of code symbols and a  
second marker symbol adjacent the second encoded  
sequence of code symbols.
86. A method according to claim 83, wherein the process-  
ing device comprises a record device storing a recorded audio  
signal encoded with a predetermined message.
87. A method according to claim 86, further comprising:  
encoding the audio signal with a marker symbol positioned  
in time adjacent at least one of the first encoded  
sequence of code symbols and the second encoded  
sequence of code symbols.
88. A method according to claim 86, further comprising:  
encoding the audio signal with a marker symbol adjacent  
the first encoded sequence of code symbols and adjacent  
the second encoded sequence of code symbols.
89. An apparatus for encoding a predetermined message in  
an audio signal, comprising:  
a memory  
an encoder, operatively coupled to the memory, that  
encodes the audio signal with a first encoded sequence  
of code symbols representing the predetermined mes-  
sage and a second encoded sequence of code symbols  
representing the predetermined message, such that the  
second encoded sequence of code symbols differs from  
the first encoded sequence of code symbols and the sec-  
ond encoded sequence of code symbols is displaced in  
time in the audio signal with respect to the first encoded  
sequence of code symbols;  
wherein each of the code symbols in the first encoded  
sequence of code symbols comprises a first plurality of  
single frequency components and each of the code sym-  
bols in the second encoded sequence of code symbols  
comprises a second plurality of single frequency com-  
ponents,  
and wherein the first encoded sequence of code symbols  
has a frequency content which differs at least in part  
from a frequency content of the second encoded  
sequence of code symbols.
90. An apparatus according to claim 89, wherein each code  
symbol in the first encoded sequence of code symbols corre-  
sponds to a respective code symbol in the second encoded  
sequence of code symbols.
91. An apparatus according to claim 89, wherein the code  
symbols in the first and second encoded sequences of code  
symbols are selected from a predetermined set of code sym-  
bols in which the code symbols are arranged in a predeter-  
mined order, and wherein each code symbol of the second  
encoded sequence of code symbols corresponds to a respec-  
tive code symbol of the first encoded sequence of code sym-  
bols and is selected based on the order of the respective code  
symbol of the first encoded sequence of code symbols.
92. An apparatus according to claim 91, wherein each code  
symbol of the second encoded sequence of code symbols is  
selected from the predetermined set of code symbols based on  
a predetermined offset in the predetermined order from the  
respective code symbol of the first encoded sequence of code  
symbols.
93. An apparatus according to claim 92, wherein the pre-  
determined offset is the same for all code symbols of the  
second encoded sequence of code symbols.

94. An apparatus according to claim 89, wherein the code  
symbols of the first and second encoded sequences of code  
symbols are selected from a predetermined set of code sym-  
bols and wherein each code symbol in the predetermined set  
of code symbols comprises a combination of single-frequency  
code components unique among all combinations of single  
frequency code components of the code symbols within the  
predetermined set of code symbols.
95. An apparatus for encoding information in an audio  
signal, comprising:  
a translator that translates an information signal into a  
first set of code symbols representing the information  
signal and a second set of code symbols representing the  
information signal, each of the code symbols in the first  
and second sets of code symbols having a corresponding  
plurality of single-frequency code components, such  
that at least some of the single-frequency code compo-  
nents of the code symbols in the first set of code symbols  
differ from the single-frequency code components of  
code symbols in the second set of code symbols; and  
an encoder that combines the single-frequency code com-  
ponents of the first and second sets of code symbols with  
the audio signal to produce an encoded audio signal,  
such that the single-frequency code components of the  
code symbols in the first set of code symbols are time-  
displaced from the single-frequency code components of  
the code symbols in the second set of code symbols in the  
audio signal.
96. An apparatus for encoding a predetermined message in  
an audio signal, comprising:  
a memory;  
an encoder, operatively coupled to the memory, that  
encodes the audio signal with a first encoded sequence  
of code symbols representing the predetermined mes-  
sage and a second encoded sequence of code symbols  
representing the predetermined message, such that the  
second encoded sequence of code symbols differs from  
the first encoded sequence of code symbols and the sec-  
ond encoded sequence of code symbols is displaced in  
time in the audio signal with respect to the first encoded  
sequence of code symbols; and  
wherein the first encoded sequence of code symbols has a  
frequency content which differs at least in part from a  
frequency content of the second encoded sequence of  
code symbols.
97. An apparatus according to claim 96, wherein each code  
symbol in the first encoded sequence of code symbols corre-  
sponds to a respective code symbol in the second encoded  
sequence of code symbols, and wherein each code symbol in  
the first encoded sequence of code symbols has a frequency  
content which differs at least in part from a frequency content  
of the respective code symbol in the second encoded sequence  
of code symbols.
98. An apparatus according to claim 96, wherein the code  
symbols in the first and second encoded sequences of code  
symbols are selected from a predetermined set of code sym-  
bols in which the code symbols are arranged in a predeter-  
mined order, and wherein each code symbol of the second  
encoded sequence of code symbols corresponds to a respec-  
tive code symbol of the first encoded sequence of code sym-  
bols and is selected based on the order of the respective code  
symbol of the first encoded sequence of code symbols.

35

99. An apparatus according to claim 98, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

100. An apparatus according to claim 99, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

101. An apparatus according to claim 96, wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and wherein each code symbol in the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single frequency code components of the code symbols within the predetermined set of code symbols.

102. An apparatus for encoding a predetermined message in an audio signal, comprising:

a memory;

an encoder, operatively coupled to the memory, that encodes the audio signal with a first encoded sequence of code symbols representing the predetermined message and a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols; and

wherein each code symbol in the second encoded sequence of code symbols corresponds to a respective code symbol in the first encoded sequence of code symbols, and wherein each code symbol in the second encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the corresponding code symbol in the first encoded sequence of code symbols.

103. An apparatus according to claim 102, wherein the code symbols in the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols is selected based on the predetermined order of the corresponding code symbol of the first encoded sequence of code symbols.

104. An apparatus according to claim 103, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the corresponding code symbol of the first encoded sequence of code symbols.

105. An apparatus according to claim 104, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

106. An apparatus for encoding a predetermined message in an audio signal, comprising:

a memory; and

an encoder, operatively coupled to the memory, that encodes the audio signal with a first encoded sequence of code symbols representing the predetermined message and a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded

36

sequence of code symbols, wherein the first and second encoded sequences of code symbols are inaudible when the audio signal is reproduced audibly;

and wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols in which the code symbols are arranged in a predetermined order, and wherein each code symbol of the second encoded sequence of code symbols corresponds to a respective code symbol of the first encoded sequence of code symbols and is selected based on the order of the respective code symbol of the first encoded sequence of code symbols,

and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

107. An apparatus according to claim 106, wherein each code symbol of the second encoded sequence of code symbols is selected from the predetermined set of code symbols based on a predetermined offset in the predetermined order from the respective code symbol of the first encoded sequence of code symbols.

108. An apparatus according to claim 107, wherein the predetermined offset is the same for all code symbols of the second encoded sequence of code symbols.

109. An apparatus for encoding a predetermined message in an audio signal, comprising:

a memory;

an encoder that encodes the audio signal with a first encoded sequence of code symbols representing the predetermined message and a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols; and

wherein the code symbols of the first and second encoded sequences of code symbols are selected from a predetermined set of code symbols and each code symbol of the predetermined set of code symbols comprises a combination of single-frequency code components unique among all combinations of single-frequency code components of the code symbols within the predetermined set of code symbols,

and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.

110. An apparatus for encoding a predetermined message in an audio signal, comprising:

a memory; and

an encoder that encodes the audio signal with a first encoded sequence of code symbols representing the predetermined message and a second encoded sequence of code symbols representing the predetermined message, such that the second encoded sequence of code symbols differs from the first encoded sequence of code symbols and the second encoded sequence of code symbols is displaced in time in the audio signal with respect to the first encoded sequence of code symbols,

wherein each of the code symbols in the first encoded sequence of code symbols comprises a first set of single frequency components and each of the code symbols in the second encoded sequence of code symbols comprises

37

*a second set of single frequency components, and wherein the first encoded sequence of code symbols has a frequency content which differs at least in part from a frequency content of the second encoded sequence of code symbols.*

*111. An apparatus according to claim 110, wherein the audio signal is further encoded with a marker symbol positioned in time adjacent at least one of the first encoded*

38

*sequence of code symbols and the second encoded sequence of code symbols.*

*112. An apparatus according to claim 110, wherein the audio signal is further encoded with a first marker symbol adjacent the first encoded sequence of code symbols and a second marker symbol adjacent the second encoded sequence of code symbols.*

\* \* \* \* \*