

US00RE43949E

(19) **United States**
(12) **Reissued Patent**
Park et al.

(10) **Patent Number:** **US RE43,949 E**
(45) **Date of Reissued Patent:** **Jan. 29, 2013**

(54) **ALLOCATING RADIO RESOURCES IN MOBILE COMMUNICATIONS SYSTEM**

(75) Inventors: **Sung-Jun Park**, Anyang-si (KR);
Young-Dae Lee, Anyang-si (KR);
Sung-Duck Chun, Anyang-si (KR);
Myung-Cheul Jung, Anyang-si (KR);
Patrick Fischer, Bourg la Reine (FR)

(73) Assignee: **LG Electronics Inc.**, Seoul (KR)

(21) Appl. No.: **13/476,961**

(22) Filed: **May 21, 2012**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **7,881,724**
Issued: **Feb. 1, 2011**
Appl. No.: **12/160,100**
PCT Filed: **Jan. 4, 2007**
PCT No.: **PCT/KR2007/000067**
§ 371 (c)(1),
(2), (4) Date: **Jul. 3, 2008**
PCT Pub. No.: **WO2007/078165**
PCT Pub. Date: **Jul. 12, 2007**

U.S. Applications:

(60) Provisional application No. 60/771,791, filed on Feb. 8, 2006, provisional application No. 60/771,305, filed on Feb. 7, 2006, provisional application No. 60/757,063, filed on Jan. 5, 2006.

(30) **Foreign Application Priority Data**

Aug. 3, 2006 (KR) 10-2006-0073210

(51) **Int. Cl.**
H04W 72/00 (2009.01)
H04W 4/00 (2009.01)
H04B 7/212 (2006.01)

(52) **U.S. Cl.** **455/452.2; 370/329; 370/348**

(58) **Field of Classification Search** **455/450, 455/452.2, 515, 436, 451, 452.1, 453; 370/329, 370/348**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,659,756 A 8/1997 Hefferon et al.
5,828,677 A 10/1998 Sayeed et al.
6,088,342 A 7/2000 Cheng et al.
6,138,158 A 10/2000 Boyle et al.
6,317,430 B1 11/2001 Knisely et al.
6,330,448 B1 12/2001 Otsuka et al.
6,381,229 B1 4/2002 Narvinger et al.
6,480,525 B1 11/2002 Parsa et al.
6,571,102 B1 5/2003 Hogberg et al.
6,597,668 B1 7/2003 Schafer et al.
6,597,675 B1 7/2003 Esmailzadeh et al.
6,694,148 B1 2/2004 Frodigh et al.
6,717,925 B1 4/2004 Leppisaari et al.

(Continued)

FOREIGN PATENT DOCUMENTS

CN 1411668 4/2003
CN 1649285 8/2005

(Continued)

OTHER PUBLICATIONS

Ericsson, "User plane protocol enhancements," R2-052749, TSG-RAN WG2 Meeting #48bis, Oct. 2005.


(Continued)

Primary Examiner — Christopher M Brandt
(74) *Attorney, Agent, or Firm* — Lee, Hong, Degerman, Kang & Waimey

(57) **ABSTRACT**

Transmitting information using a preamble of a Random Access Channel (RACH) in an Evolved Universal mobile Telecommunications System (E-UMTS) is provided. A preamble transmission is used to inform a base station of specific information when a terminal uses a RACH and the base station efficiently allocates radio resources for data transmission to the terminal according to the specific information. Delay time before the terminal transmits data is reduced and unnecessary consumption of radio resources is minimized.

14 Claims, 3 Drawing Sheets



US RE43,949 E

Page 3

2006/0062196	A1	3/2006	Cai et al.	JP	2001522557	11/2001
2006/0072494	A1	4/2006	Matusz	JP	2002501695	1/2002
2006/0083183	A1	4/2006	Teague et al.	JP	2002064589	2/2002
2006/0088009	A1	4/2006	Gibbs et al.	JP	2002-135231	5/2002
2006/0120403	A1	6/2006	Murata et al.	JP	2002-374321	12/2002
2006/0143300	A1	6/2006	See et al.	JP	2003-008635	1/2003
2006/0146745	A1	7/2006	Cai et al.	JP	2003504942	2/2003
2006/0153232	A1	7/2006	Shvodian	JP	2003504968	2/2003
2006/0154680	A1	7/2006	Kroth et al.	JP	2003078480	3/2003
2006/0168343	A1	7/2006	Ma et al.	JP	2003116172	4/2003
2006/0193282	A1	8/2006	Ikawa et al.	JP	2003-174470	6/2003
2006/0256818	A1	11/2006	Shvodian et al.	JP	2003333661	11/2003
2006/0292982	A1	12/2006	Ye et al.	JP	2004-128967	4/2004
2007/0071025	A1	3/2007	Bergstrom et al.	JP	2004-312771	11/2004
2007/0081483	A1	4/2007	Jang et al.	JP	2004-320165	11/2004
2007/0081513	A1	4/2007	Torsner	JP	2004-349884	12/2004
2007/0098006	A1	5/2007	Parry et al.	JP	2005500761	1/2005
2007/0099619	A1	5/2007	Parekh et al.	JP	2005510950	4/2005
2007/0104151	A1	5/2007	Papasakellariou et al.	JP	2005517369	6/2005
2007/0117579	A1	5/2007	Cai et al.	JP	2005522923	7/2005
2007/0135080	A1	6/2007	Islam et al.	JP	2005-217743	8/2005
2007/0140115	A1	6/2007	Bienas et al.	JP	2005525066	8/2005
2007/0147326	A1	6/2007	Chen	JP	2005525720	8/2005
2007/0206531	A1	9/2007	Pajukoski et al.	JP	2005-236988	9/2005
2007/0218930	A1	9/2007	Kuo	JP	2005237013	9/2005
2007/0254662	A1	11/2007	Khan et al.	JP	2005244958	9/2005
2007/0274253	A1	11/2007	Zhang et al.	JP	2005278167	10/2005
2008/0031253	A1	2/2008	Kim et al.	JP	2005536168	11/2005
2008/0069031	A1	3/2008	Zhang et al.	JP	2005-539462	12/2005
2008/0095105	A1	4/2008	Sundberg et al.	JP	2006-025437	1/2006
2008/0130643	A1	6/2008	Jain et al.	JP	2006014372	1/2006
2008/0137564	A1	6/2008	Herrmann	JP	2006020044	1/2006
2008/0212541	A1	9/2008	Vayanos et al.	JP	2006505998	2/2006
2008/0232291	A1	9/2008	Hus et al.	JP	2006-352705	12/2006
2008/0267136	A1	10/2008	Baker et al.	JP	2007536790	12/2007
2009/0011769	A1	1/2009	Park et al.	JP	2009284532	12/2009
2009/0175241	A1	7/2009	Ohta et al.	KR	10-2001-0111634	12/2001
2009/0319850	A1	12/2009	Baek et al.	KR	10-2001-0111637	12/2001
2009/0323624	A1	12/2009	Kim	KR	10-2004-0048675	6/2004
2009/0323646	A1	12/2009	Ketchum et al.	KR	10-2004-0064867	7/2004
2010/0014430	A1	1/2010	Oka et al.	KR	10-2004-0089937	10/2004
2010/0034095	A1	2/2010	Ho et al.	RU	2168278	5/2001
2010/0103899	A1	4/2010	Kwak et al.	RU	2191479	10/2002
2010/0105334	A1	4/2010	Terry et al.	RU	2232469	7/2004
2010/0226263	A1	9/2010	Chun et al.	RU	2232477	7/2004
2011/0038376	A1	2/2011	Wiemann et al.	RU	2237380	9/2004
				RU	2263415	10/2005
				RU	2005115869	10/2005
				RU	2270526	2/2006
				TW	407407	10/2000
				TW	548916	8/2003
				TW	552815	9/2003
				TW	586283	5/2004
				TW	589818	6/2004
				TW	590340	6/2004
				TW	592412	6/2004
				TW	I228008	2/2005
				TW	I229268	3/2005
				TW	200522579	7/2005
				TW	I237478	8/2005
				TW	I242951	11/2005
				TW	I253824	4/2006
				TW	280755	5/2007
				WO	99/44383	9/1999
				WO	99-60729	11/1999
				WO	99/63713	12/1999
				WO	02/03720	1/2002
				WO	02/39697	5/2002
				WO	02/39760	5/2002
				WO	02/43403	5/2002
				WO	02/47417	6/2002
				WO	02075442	9/2002
				WO	02/02110	12/2002
				WO	02/102110	12/2002
				WO	03/007636	1/2003
				WO	03/017691	2/2003
				WO	03/043259	5/2003
				WO	03/047155	6/2003
				WO	03/056723	7/2003
FOREIGN PATENT DOCUMENTS						
CN	1658545	8/2005				
CN	1663158	8/2005				
CN	1692661	11/2005				
EP	0617875	12/1997				
EP	0978958	2/2000				
EP	1009184	6/2000				
EP	1041850	10/2000				
EP	1261222	11/2002				
EP	1361514	11/2003				
EP	1392074	2/2004				
EP	1441473	7/2004				
EP	1478203	11/2004				
EP	1496639	1/2005				
EP	1557968	7/2005				
EP	1599063	11/2005				
EP	1605724	12/2005				
EP	1684538	1/2006				
JP	1994013959	1/1994				
JP	06-121001	4/1994				
JP	09-055693	2/1997				
JP	1997055693	2/1997				
JP	09-186704	7/1997				
JP	1997327072	12/1997				
JP	11-331949	11/1999				
JP	1999308671	11/1999				
JP	2000-032088	1/2000				
JP	2000-151494	5/2000				
JP	2000175271	6/2000				
JP	2000184428	6/2000				
JP	2001095031	4/2001				
JP	2001-298770	10/2001				

WO	03/096571	11/2003
WO	2004/030393	4/2004
WO	2004/034656	4/2004
WO	2004/045234	5/2004
WO	2004/075442	9/2004
WO	2004/089030	10/2004
WO	2004/091130	10/2004
WO	2005006660	1/2005
WO	2005/018269	2/2005
WO	2005/034418	4/2005
WO	2005/036917	4/2005
WO	2005/055472	6/2005
WO	2005/071887	8/2005
WO	2005/074312	8/2005
WO	2005/088886	9/2005
WO	2005099125	10/2005
WO	2005/109695	11/2005
WO	2005109837	11/2005
WO	2005/125125	12/2005
WO	2005117317	12/2005
WO	2005119941	12/2005
WO	2005125125	12/2005
WO	2006/012946	2/2006
WO	2006011953	2/2006
WO	2006/033552	3/2006
WO	2007/078156	7/2007
WO	2007/095966	8/2007
WO	2007091831	8/2007

OTHER PUBLICATIONS

IPWireless, "Layer 2 functions for LTE," R2-052377, 3GPP TSG RAN WG2 #48bis, Oct. 2005.
 LG Electronics Inc., "MAC Architecture of LTE," R2-060105, 3GPP TSG-RAN WG2 #50, Jan. 2006.
 LG Electronics Inc., "Discussion on RLC PDU Structure," R2-070721, 3GPP TSG-RAN WG2 #57, Feb. 2007.
 LG Electronics Inc., "HARQ and ARQ Operation," R2-060563, 3GPP TSG-RAN WG2 #51, Feb. 2006.
 China Mobile Communications Co., "RRC States Analysis in LTE," R2-052140, 3GPP TSG RAN WG2 #48, Aug. 2005.
 Panasonic, "E-UTRA Transport and Logical Channels," R2-052860, 3GPP TSG RAN WG2#49, Nov. 2005.
 Siemens, "States in E-UTRAN," R2-052051, 3GPP TSG-RAN WG RAN2#48, Aug. 2005.
 Qualcomm Europe, "Signaling optimization for E-UTRAN," R2-052407, 3GPP TSG-RAN WG 2 meeting #48-bis, Oct. 2005.
 3rd Generation Partnership Project, "Technical Specification Group Radio Access Network; Introduction of the Multimedia Broadcast Multicast Service (MBMS) in the Radio Access Network (RAN); Stage 2 (Release 6)," 3GPP TS 25.346, V6.7.0, Dec. 2005.
 Ericsson, "Solution for sending NAS together with RRC connection request", R2-071817, 3GPP TSG-RAN WG2#58, May 2007.

LG Electronics Inc., "Default SRB for initial access", R2-061958, 3GPP TSG-RAN WG2 LTE Ad-hoc, Jun. 2006.
<http://www.3gpp.org>, 3GPP TS 36.321 V8.4.0 (Dec. 2008), pp. 12-15 (Sections 5.1-5.1.4).
 Qualcomm, "Need for MAC-hs segmentation mechanism," 3GPP TSG-RAN WG2 meeting #28, R2-020769, Apr. 2002.
 Motorola, et al, "MAC-e/es header and functional split," 3GPP TSG-RAN WG2 meeting #45, R2-042360, Nov. 2004.
 LG Electronics Inc, "MAC Enhancement," 3GPP TSG-RAN WG2 #51, R2-060561, Feb. 2006.
 Ericsson, "E-UTRA Random Access," 3GPP TSG-RAN WG1 #43, R1-051445, Nov. 2005.
 LG Electronics Inc., "UE State Transition in LTE_ACTIVE," R2-061002, 3GPP TSG-RAN WG2 #52, Mar. 2006.
 Haardt, M., et al., "The TD-CDMA Based UTRA TDD Mode," IEEE Journal on Selected Areas in Communications, vol. 18, No. 8, pp. 1375-1385, Aug. 2000.
 Sarkar, S., et al., "Common-Channel Soft Handoff in CDMA2000," IEEE Transactions on Microwave Theory and Techniques, Jun. 2000, pp. 938-950, vol. 48, Issue 6.
 NTT DoCoMo, et al., "Multiplexing Method of Shared Control Channel in Uplink Single-Carrier FDMA Radio Access," 3GPP TSG-RAN WG1, R1-051143, Oct. 10, 2005.
 Huawei, "Further Considerations on Multiplexing Method of Shared Control Channel in Uplink Single-Carrier FDMA," 3GPP TSG-RAN WG1, R1-051430, Nov. 7, 2005.
 Philips, "Evolved Paging Indicators for LTE," 3GPP TSG-RAN WG2, R2-052985, Nov. 7, 2005.
 NTT DoCoMo, et al., "Paging Channel Structure for E-Utra Downlink," 3GPP TSG-RAN WG1, R1-060034, Jan. 23, 2006.
 LG Electronics Inc., "HARQ and ARQ Operation," 3GPP TSG-RAN WG2, R2-060106, Jan. 9, 2006.
 LG Electronics Inc., "Framing in the MAC Entity," 3GPP TSG-RAN WG2, R2-061012, Mar. 27, 2006.
 Motorola, "Paging Channel Design for E-UTRA," 3GPP TSG-RAN WG1, R1-061712, Jun. 27, 2006.
 Ericsson, "E-UTRA Random Access", TSG-RAN WG1 #43, R1-051445, Nov. 2005.
 Xu, H., et al.; "Performance Analysis on the Radio Link Control Protocol of UMTS System"; 2002 IEEE 56th Vehicular Technology Conference Proceedings; pp. 2026-2030; Sep. 2002.
 NTT Docomo, et al., "Paging Channel Structure for E-UTRA Downlink," 3GPP TSG-RAN WG1, R1-060034, Jan. 23, 2006.
 LG Electronics Inc., "HARQ and ARQ Operation," 3GPPTSG-RAN WG2, R2-060106, Jan. 9, 2006.
 Ericsson, "E-UTRA Random Access"; TSG-RAN WG1 #43; Seoul, Korea; Nov. 2005; R1-051445.

* cited by examiner

Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5





Fig. 6

Establishment Cause(A,B)	CQI (0,1)	Available resources(A~G) and signatures(0~15)	Number of random ids/signatures
A	0	A0,..., A10, B0,..., B7, C0,...,C1	21
B	0	B8,...,B15, C2,...,C4	11
A	1	C5,...,C9, D0,...,D8	14
B	1	A11,...,A15, C10,...,C15, D9,...,D15	18

Fig. 7



ALLOCATING RADIO RESOURCES IN MOBILE COMMUNICATIONS SYSTEM

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a reissue of U.S. patent application Ser. No. 12/160,100, filed on Jul. 3, 2008, now U.S. Pat. No. 7,881,724, which is the National Stage filing under 35 U.S.C. 371 of International Application No. PCT/KR2007/000067, filed on Jan. 4, 2007, which claims the benefit of earlier filing date and right of priority to Korean Application No. 10-2006-0073210, filed on Aug. 3, 2006, and also claims the benefit of U.S. Provisional Application Ser. Nos. 60/757,063, filed on Jan. 5, 2006, 60/771,305, filed on Feb. 7, 2006, and 60/771,791, filed on Feb. 8, 2006.

DISCLOSURE OF INVENTION

Technical Solution

This disclosure relates to transmitting information in a mobile communications system.

FIG. 1 illustrates an exemplary network structure of an E-UMTS. The E-UMTS system is a system that has evolved from an existing UMTS system.

Basic standardization for the E-UMTS system is currently being developed by the Third Generation Partnership Project (3GPP). The E-UMTS system may be referred to as a Long Term Evolution (LTE) system.

As illustrated in FIG. 1, an E-UMTS network may consist of an E-UTRAN and a Core Network (CN). The E-UTRAN may include User Equipment (UE), a base station, referred to as eNode B or eNB, and an Access Gateway (AG) located at the end of the network and connected to an external network.

The AG may be divided into a portion for processing user traffic and a portion for processing control traffic. The AG portion for processing user traffic and the AG portion for processing control traffic may be connected to each other via a new interface for communication.

One or more cells may exist in an eNode B (eNB). The eNode Bs may be connected by an interface for the transmission of user traffic and/or control traffic.

The CN may also include the AG and a node adapted for user registration of a UE. An interface may also be provided in the E-UMTS in order to divide the E-UTRAN and the CN.

Radio interface protocol layers between a mobile terminal and network may be classified into a first layer (L1), a second layer (L2) and a third layer (L3) based upon the lower three layers of an Open System Interconnection (OSI) model which is well known in communications systems. A physical layer of the first layer provides an information transfer service using a physical channel. A Radio Resource Control (RRC) layer positioned in the third layer controls radio resources between the mobile terminal and the network.

The RRC layer allows an RRC message exchange between the mobile terminal and the network. The RRC layer may be positioned in each network node, such as the eNode B and the AG, or positioned in either the eNode B or the AG.

FIG. 2 illustrates an architecture of radio interface protocols between a terminal and a UMTS Terrestrial Radio Access

Network (UTRAN) based upon a 3GPP radio access network specification. The radio interface protocols of FIG. 2 are horizontally formed of a physical layer, a data link layer and a network layer and vertically formed of a user plane for transmitting data information and a control plane for transmitting control signals.

The protocol layers of FIG. 2 may be divided into a first layer (L1), a second layer (L2) and a third layer (L3) based upon the lower three layers of an Open System Interconnection (OSI) model which is well known in communications systems. Each radio protocol layer in the control plane illustrated in FIG. 2 and each radio protocol layer in the user plane illustrated in FIG. 3 will now be explained.

A physical layer, which is a first layer, provides an information transfer service to an upper layer using a physical channel. The physical layer is connected to a Medium Access Control (MAC) layer (located at a higher level) via a transport channel.

Data is transferred between the MAC layer and the physical layer via a transport channel. Data also is transferred between different physical layers, specifically, between a physical layer of a transmitting side and a physical layer of a receiving side.

A MAC layer of the second layer provides a service via a logical channel to a Radio Link Control (RLC) layer, which is its upper layer. The RLC layer of the second layer supports reliable data transmission.

The functions performed by the RLC layer may be implemented as a functional block within the MAC. However, the RLC layer may not exist.

A Packet Data Convergence Protocol (PDCP) layer of the second layer is used to effectively transmit data using an IP packet, such as IPv4 or IPv6, on a radio interface with a relatively small bandwidth. The PDCP layer reduces unnecessary control information using a function called a header compression for this purpose.

A Radio Resource Control (RRC) layer located at the lowest portion of the third layer is only defined in the control plane. The RRC layer handles the transport and physical channels for the configuration, re-configuration and release of radio bearers. A Radio Bearer (RB) denotes a service provided by the second layer for data transfer between the mobile terminal and the UTRAN.

Downlink transport channels for transmitting data from a network to a mobile terminal may include a Broadcast Channel (BCH) for transmitting system information and a downlink Shared Channel (SCH) for transmitting user traffic or a control message. A traffic or control message of a downlink multicast or broadcast service may be transmitted either via the downlink SCH or via a separate downlink Multicast Channel (MCH). Uplink transport channels for transmitting data from a mobile terminal to a network may include a Random Access Channel (RACH) for transmitting an initial control message and an uplink Shared Channel (SCH) for transmitting a user traffic or control message.

Hereinafter, a random access channel (RACH) will be explained in detail. In general, an RACH is used to obtain a radio resource if there is no uplink radio resource to transmit data when a terminal matches a time synchronization with a network or the terminal transmits the corresponding data over the uplink.

For example, a terminal generally matches a downlink synchronization to enable reception of system information from a cell it desires to access when the terminal is turned on. The terminal should transmit an access request message to the network or base station for an RRC connection after receiving the system information. However, the terminal uses the

RACH if it does not currently match the time synchronization with the network and does not acquire an uplink radio resource.

In other words, the terminal requests a radio resource for transmitting an access request message from the network using the RACH. The base station then allocates an appropriate radio resource to the terminal in order to allow the terminal to transmit an RRC connection message. The terminal can then transmit the RRC connection message to the network using the allocated radio resource.

In another example, the terminal acquires a radio resource from the network according to radio resource scheduling and transmits data to the network using the allocated radio resource when the terminal forms an RRC connection with the network. However, the network may not allocate the uplink radio resource if there is no data left in the terminal buffer because it is inefficient to allocate an uplink radio resource to a terminal that has no data to transmit. The state of the terminal buffer is reported to the network periodically or according to an event generation. If new data that does not require a radio resource is generated in the buffer, the terminal uses the RACH because it does not currently have the uplink radio resource allocated. In other words, the terminal requests a radio resource required for data transmission from the network using the RACH.

Hereinafter, a RACH in a Wideband Code Division Multiple Access (WCDMA) will be explained. The RACH channel is used to transmit data with a short length over an uplink.

A portion of RRC messages, such as an RRC connection request message, a cell update message or a URA update message, may be transmitted on the RACH. A logical channel CCCH (Common Control Channel), DCCH (Dedicated Control Channel) and DTCH (Dedicated Traffic Channel) are mapped to the RACH and the RACH is mapped to a physical channel PRACH (Physical Random Access Channel).

The physical layer of a terminal selects one access slot and one signature to transmit a PRACH preamble via an uplink when the terminal MAC indicates a PRACH transmission to a physical layer of the terminal. The preamble is transmitted for an access slot interval having a length of 1.33 ms. One of 16 signatures is selected and transmitted for a certain length of an initial portion of the access slot.

The base station transmits a response signal using a downlink physical channel AICH (Acquisition Indicator Channel) after the terminal transmits the preamble. The AICH transmitted in response to the preamble transmits the signature selected by the preamble for a certain length of the initial portion of the access slot corresponding to the transmitted access slot.

The base station transmits a positive response (ACK) or negative response (NACK) to the terminal using the signature transmitted from the AICH. The terminal transmits a message portion with a length of 10 ms or 20 ms using an OVSF code corresponding to the transmitted signature upon receiving the ACK. The terminal MAC indicates the PRACH transmission again to the physical layer of the terminal after an appropriate time period upon receiving the NACK. The terminal transmits a new preamble using power one level higher than that of the previous preamble after a designated access slot if the terminal has not received the AICH corresponding to a previously transmitted preamble.

Channel Quality Indicator (CQI) information is information that enables a terminal to measure a downlink channel state in a current cell and provide the measured state to the base station. The base station then performs radio resource scheduling using the provided CQI information. For example, if the value of CQI may be between 1 to 10, whereby 1

indicates that a channel is not in a good state and 10 indicates that the channel is in a good state.

The base station may determine that the current downlink channel is in a good state and transmit data to the terminal according to a higher bit rate when the terminal transmits CQI information of 10 to the base station. Conversely, the base station may determine that the downlink channel is not in a good state and transmit data to the terminal according to a lower bit rate when the terminal transmits CQI information of 1 to the base station. The base station previously informs the terminal that the terminal should perform reporting periodically or according to an event generation in order to transmit the CQI information.

The present inventors recognized at least the following problems in currently existing RACH procedures. As previously indicated, the terminal first selects one signature and one access slot and then transmits a preamble over an uplink when using the RACH. Thereafter, the terminal transmits a message portion to the base station upon receiving an ACK from the base station in response to the preamble. Therefore, the terminal must perform the preamble transmission, the ACK reception and the message portion transmission in order to inform the base station of specific information using the RACH in related art methods. As a result, delay time is increased and radio resources are wasted. Based upon such problem recognition, various features and aspects described herein have been conceived by the present inventors.

An aspect of this disclosure is to provide a method of transmitting information in a mobile communications system that prevents unnecessary consumption of radio resources and reduces delay time for information transfer.

In one aspect, a method for allocating radio resources in a mobile communication system is provided. The method includes receiving grouping information related to signatures and occasions for accessing a Random Access Channel (RACH), selecting one signature and one Random Access Channel (RACH) occasion according to the grouping information, transmitting a preamble according to the selected signature and RACH occasion, receiving a message including a radio resource allocated according to the selected signature and RACH occasion and transmitting data using the allocated radio resource.

It is contemplated that RACH signatures and occasions are grouped according to predetermined criteria. It is further contemplated that the predetermined criteria include at least one of a purpose for using RACH, CQI information, a requested amount of radio resources and an establishment cause.

It is contemplated that the purpose for using RACH includes one of an initial access, handover, maintaining synchronization, an access release and a radio resource request. It is further contemplated that the establishment cause includes one of an emergency call, transition from an idle state to an active state and transition from a disconnected state to an active state. The grouping information may be received in one of system information and a paging message.

In another aspect of this disclosure, a method for allocating radio resources in a mobile communication system is provided. The method includes transmitting grouping information related to signatures and occasions for accessing a Random Access Channel (RACH), receiving a preamble transmitted according to a signature and RACH occasion selected according to the grouping information, transmitting a message including a radio resource allocated according to the selected signature and RACH occasion and receiving data transmitted using the allocated radio resource.

It is contemplated that the method further includes grouping the RACH signatures and occasions according to prede-

terminated criteria. It is further contemplated that the predetermined criteria include at least one of a purpose for using RACH, CQI information, a requested amount of radio resources and an establishment cause.

It is contemplated that the purpose for using RACH includes one of an initial access, handover, maintaining synchronization, an access release and a radio resource request. It is further contemplated that the establishment cause includes one of an emergency call, transition from an idle state to an active state and transition from a disconnected state to an active state.

It is contemplated that the grouping information is transmitted in one of system information and a paging message. It is further contemplated that the grouping information is transmitted in one of system information and a paging message. The method may further include changing and retransmitting the grouping information.

In another aspect of this disclosure, a method for allocating radio resources in a mobile communication system is provided. The method includes a network transmitting grouping information related to signatures and occasions for accessing a Random Access Channel (RACH), a mobile communication terminal selecting one signature and one Random Access Channel (RACH) occasion according to the grouping information, the mobile communication terminal transmitting a preamble according to the selected signature and RACH occasion, the network transmitting a message including a radio resource allocated according to the selected signature and RACH occasion and the mobile communication terminal transmitting data using the allocated radio resource.

It is contemplated that RACH signatures and occasions are grouped according to predetermined criteria. It is further contemplated that the predetermined criteria include at least one of a purpose for using RACH, CQI information, a requested amount of radio resources and an establishment cause.

It is contemplated that the purpose for using RACH includes one of an initial access, handover, maintaining synchronization, an access release and a radio resource request. It is further contemplated that the establishment cause includes one of an emergency call, transition from an idle state to an active state and transition from a disconnected state to an active state.

It is contemplated that the network transmits the grouping information in one of system information and a paging message. It is further contemplated that the method further includes the network changing and retransmitting the grouping information.

The foregoing and other features and aspects of this disclosure will become more apparent from the following detailed description when taken in conjunction with the accompanying drawings.

Additional features and aspects will be set forth in the description that follows, and in part will be apparent from the description, or may be learned by practice of the features in this disclosure. It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory and are intended to provide further explanation of the claims.

These and other exemplary embodiments will also become readily apparent to those skilled in the art from the following detailed description of the embodiments having reference to the attached figures, the features herein not being limited to any particular embodiments disclosed.

The accompanying drawings, which are included to provide further understanding and are incorporated in and constitute a part of this specification, illustrate various exemplary embodiments and together with the description serve to

explain the principles of this disclosure. Features, elements, and aspects that are referenced by the same numerals in different figures represent the same, equivalent, or similar features, elements, or aspects in accordance with one or more embodiments.

FIG. 1 illustrates an exemplary network structure of an E-UMTS that is a mobile communications system.

FIG. 2 illustrates each layer on a control plane of radio protocols.

FIG. 3 illustrates each layer on a user plane of radio protocols.

FIG. 4 illustrates a grouping of all RACH occasions by a base station according to a particular purpose according to certain embodiment(s).

FIG. 5 illustrates how a base station combines signatures and RACH occasions for their grouping according to certain embodiment(s).

FIG. 6 illustrates a grouping according to the combination of an establishment cause and CQI information described in FIG. 5.

FIG. 7 illustrates signal flow of a method for transmitting information in a mobile communications system in accordance with certain embodiment(s).

Description will now be given in detail with reference to the accompanying drawings. The features herein may be implemented in a mobile communications system, such as a UMTS. However, such features may be applied to other communications systems that are operated according to other specifications.

This disclosure proposes a method by which a terminal informs a base station of certain information using a preamble signature and transmission timing, or transmission occasion, of a RACH in order to decrease delay time before transmitting data and make efficient use of uplink radio resources. In order to accomplish this, the features described herein classify signatures and transmission occasions according to specific information for use.

In one embodiment, the features are implemented such that a preamble can be transmitted by selecting one signature and one resource from signatures grouped according to first information and transmission occasions grouped according to second information in a signature group and a RACH resource group classified according to several specific information. The specific information may include usage purpose of RACH, CQI information, information related to a requested amount of radio resource and information on an establishment cause.

For example, the usage purpose of RACH may include an initial access of a terminal, handover, synchronization maintenance, an access release, and a radio resource request. The CQI information is a value indicating a downlink channel state. The requested amount of radio resource indicates a buffer state of the terminal, which may be indicated with 50 bits, 100 bits, or 200 bits. The establishment cause may denote an emergency call, change of the terminal from an idle state to an active state, or change of the terminal from a disconnected, or detached state, to an active state.

The RACH resource may indicate a RACH occasion. Specifically, the RACH resource indicates informing terminals within a cell of resource information related to use of the RACH by the base station.

The resource information is configured with a specific frequency and a specific time. The resource information may also include a duration of the RACH occasion.

In another embodiment, the features are implemented such that a preamble can be transmitted by selecting one signature from the combination of signatures and RACH occasions and

a group configured with the combination as well as by using signatures grouped according to first information and transmission occasions grouped according to second information. In one exemplary embodiment, one signature always has the same meaning, such as information. However, one signature may have another meaning according to a transmission occasion with which it is combined in this embodiment.

Explanation will now be given of a method for selecting one signature and one resource from signatures grouped according to first information and transmission occasions grouped according to second information in order to transmit a preamble.

Signature Selection

A base station groups all the signatures according to a specific purpose. Information related to the grouped signatures is transmitted to a terminal using system information or a paging message. Therefore, the terminal selects one signature group from signature groups classified according to specific information related to a state of the terminal when using RACH. The terminal randomly selects one signature from the corresponding signature group once the one signature group has been selected.

For example, if there are 64 signatures, numerals 0 to 63 are set to the signatures. The base station uses a usage purpose of RACH as specific information that is a criterion for the grouping. A group 1 may be configured for the purpose of an initial access, a group 2 may be configured for the purpose of handover, a group 3 may be configured for the purpose of a synchronization maintenance, a group 4 may be configured for the purpose of an access release, and a group 5 may be configured for the purpose of a radio resource request. The base station appropriately maps the whole signatures onto each group.

In other words, the group 1 has signatures from 0 to 11, group 2 has signatures from 12 to 23, group 3 has signatures from 24 to 35, group 4 has signatures from 36 to 47, and group 5 has signatures from 48 to 63. Information (or grouping information) regarding the signatures grouped according to the usage purpose of RACH is transmitted to the terminal using system information or a paging message. Therefore, the terminal selects group 2 according to the set grouping information and thereafter randomly selects one of the signatures having numerals from 12 to 23 mapped onto the group 2 if the purpose of RACH is for handover.

Furthermore, the base station can dynamically change the grouping information. In other words, the base station can map more signatures onto the corresponding group if terminals within a cell frequently use a certain group among the signature groups.

For example, if group 4 has 12 signatures and group 5 has 16 signatures, the base station may decrease the number of signatures in group 4 and increase the number of signatures in group 5 if a frequency of use of the terminal within the cell is low in the group 4 and high in the group 5. The changed information related to the signature grouping is transmitted from the base station to the terminal using system information or a paging message.

RACH Occasion Selection

As illustrated in FIG. 4, the base station groups entire RACH occasions according to a specific purpose. The specific purpose may be the same as the previously disclosed specific information used as the criterion for the grouping of signatures or may be different.

For example, signatures may be grouped according to the usage purpose of RACH and RACH occasions may be grouped according to CQI information or both signatures and RACH occasions may be grouped according to the usage

purpose of RACH. Grouping information related to the grouped RACH occasions is transmitted to the terminal using system information or a paging message.

Accordingly, one group is selected from the groups of the RACH occasions according to the state of the terminal when the terminal uses a RACH. If the selected group includes two or more RACH occasions, the terminal randomly selects one RACH occasion from the selected group.

The base station uses CQI information as specific information for grouping RACH occasions. For example, the base station groups a group A with a bad channel state, a group B with a good channel state, and a group C with a best channel state. The base station appropriately maps the RACH occasions onto each group.

Information related to the grouping according to the CQI information is transmitted to the terminal using system information or a paging message. The terminal selects group A according to the set grouping information if the terminal is in a bad channel state. The terminal randomly selects one RACH occasion if group A includes two or more RACH occasions.

The base station can also dynamically change the grouping information. The grouping information that is changed by the base station every period of the RACH occasion or every multiple of the period is transmitted to the terminal using system information or a paging message.

A method of selecting one of groups configured by the combination of signatures and RACH occasions in order to transmit a preamble will now be explained. In this method, a particular signature may not always have the same information. For example, the same signature can deliver different information depending on an RACH occasion with which it is combined.

FIG. 5 illustrates how a base station combines signatures and RACH occasions for their grouping. FIG. 6 illustrates an actual grouping according to the combination of an establishment cause and CQI information described in FIG. 5.

As illustrated in FIG. 5, within one period, four RACH occasions A, B, C and D exist. The four RACH occasions may exist at the same time as shown in FIG. 5 or exist separately at different times. For example, the four RACH occasions A, B, C and D may all exist at Time 2 or exist separately at times 4, 5 and 6. The total number of signatures is assumed to be 16.

Establishment cause and CQI information are used as criteria for a grouping. The establishment cause and CQI information are used, respectively, in two cases. Four groups are generated using the establishment cause and CQI information as illustrated in FIG. 6. The terminal randomly selects one value from a third group which includes C5~C9 and D0~D8 if the establishment cause of the terminal is A and CQI value is 1. C5 indicates a RACH occasion of C and a signature of 5.

As previously indicated, one signature and one RACH occasion may not always indicate the same information. For example, a signature 10 may deliver different information depending on the RACH occasion with which it is combined. A RACH occasion A may also deliver different information depending on the signature with which it is combined. The grouping information according to the combination of signatures and RACH occasions are also transmitted to the terminal using system information or a paging message.

FIG. 7 illustrates an exemplary signal flow of a method of transmitting information in a mobile communications system in accordance with a certain embodiment(s). As illustrated in FIG. 7, a base station 20 groups entire signatures and RACH occasions according to specific purposes and informs a terminal 10 of information related to the grouping using system information or a paging message (S10).

According to a setup of the base station **20**, the terminal **10** selects one signature and one RACH occasion from the groups of signatures and RACH occasions or selects one group from groups configured by the combination of signatures and RACH occasions (S11). Using the previous example, the terminal **10** selects one value from the third group including C5-C9 and D0-D8.

The terminal **10** then transmits a preamble to the base station **20** using the selected signature and RACH occasion (S12). The base station **20** then determines to which group the corresponding signature and RACH occasion belong and schedules a radio resource according to the determination in order to allocate an appropriate radio resource to the terminal **10** (S13).

For example, when the terminal **10** has used a signature group for an initial access and RACH occasions have been grouped according to a requested amount of radio resources of 100 bits, the base station **20** allocates an appropriate radio resource to the terminal based upon the information. The terminal uses the corresponding radio resource to transmit uplink data to the base station **20** after receiving the appropriate radio resource allocated from the base station (S14).

The features described herein may be implemented such that a preamble transmission is used to inform the base station of specific information when the terminal uses a RACH and the base station can efficiently allocate a radio resource for data transmission to the terminal according to the specific information. Delay time before the terminal transmits data is reduced and consumption of radio resources is prevented or at least minimized

As the features in this disclosure may be embodied in several forms without departing from the characteristics thereof, it should also be understood that the above-described embodiments are not limited by any of the details of the foregoing description, unless otherwise specified, but rather should be construed broadly within its scope as defined in the appended claims. Therefore, all changes and modifications that fall within the metes and bounds of the claims, or equivalents of such metes and bounds are intended to be embraced by the appended claims.

The foregoing embodiments and features are merely exemplary and are not to be construed as limiting. The present teachings can be readily applied to other types of apparatuses.

This description is intended to be illustrative, and not to limit the scope of the claims. Many alternatives, modifications, and variations will be apparent to those skilled in the art. In the claims, means-plus-function clauses are intended to cover the structure described herein as performing the recited function and not only structural equivalents but also equivalent structures.

The invention claimed is:

1. A method for allocating radio resources in a mobile communication system, the method comprising:

receiving, by a mobile terminal, grouping information related to one or more preambles for accessing a Random Access Channel (RACH), wherein the one or more preambles are grouped according to an amount of the radio resources requested by the mobile terminal and the received grouping information is used to select at least one preamble group among a plurality of preamble groups;

selecting, by the mobile terminal, the at least one preamble group according to a state of the mobile terminal;

selecting, by the mobile terminal, at least one preamble from the at least one selected preamble group;
transmitting, by the mobile terminal, the at least one selected preamble;

receiving, by the mobile terminal, a radio resource allocated according to the at least one selected preamble;
and

transmitting, by the mobile terminal, data using the allocated radio resource.

2. The method of claim **1**, wherein the grouping information is received in one of system information and a paging message.

3. The method of claim **1**, wherein each of the one or more preambles includes a RACH signature and a RACH occasion.

4. The method of claim **1**, wherein the one or more preambles are random access preambles.

5. The method of claim **3**, wherein the RACH occasion is a radio resource for transmitting the RACH signature.

6. The method of claim **1**, wherein the grouping information is received through system information or a RRC connection reconfiguration message.

7. The method of claim **6**, wherein the grouping information is included in the RRC connection reconfiguration message during a performance of handover.

8. A method for allocating radio resources in a mobile communication system, the method comprising:

grouping, by a base station, one or more preambles according to an amount of the radio resources requested by the mobile terminal;

transmitting, by the base station, grouping information related to the one or more preambles for accessing a Random Access Channel (RACH), wherein the transmitted grouping information is used by the mobile terminal to select at least one preamble group among a plurality of preamble groups;

receiving, by the base station, at least one preamble among the one or more preambles, wherein the at least one preamble group is selected by the mobile terminal according to a state of the mobile terminal and the at least one preamble is selected by the mobile terminal from the at least one selected preamble group;

transmitting, by the base station, a radio resource allocated according to the at least one selected preamble; and
receiving, by the base station, data using the allocated radio resource.

9. The method of claim **8**, wherein the grouping information is transmitted in one of system information and a paging message.

10. The method of claim **8**, further comprising:

changing and retransmitting, by the base station, the grouping information after receiving the data.

11. The method of claim **8**, wherein each of the one or more preambles includes a RACH signature and a RACH occasion, and the one or more preambles are random access preambles.

12. The method of claim **11**, wherein the RACH occasion is a radio resource for transmitting the RACH signature.

13. The method of claim **8**, wherein the grouping information is transmitted through system information or a RRC connection reconfiguration message.

14. The method of claim **13**, wherein the grouping information is included in the RRC connection reconfiguration message during a performance of handover.