

US00RE44524E

(19) **United States**
(12) **Reissued Patent**
Pendse

(10) **Patent Number:** **US RE44,524 E**
(45) **Date of Reissued Patent:** **Oct. 8, 2013**

(54) **BUMP-ON-LEAD FLIP CHIP
INTERCONNECTION**

(71) Applicant: **STATS ChipPAC, Ltd.**, Singapore (SG)

(72) Inventor: **Rajendra D. Pendse**, Fremont, CA (US)

(73) Assignee: **STATS ChipPAC, Ltd.**, Singapore (SG)

(21) Appl. No.: **13/756,779**

(22) Filed: **Feb. 1, 2013**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **8,188,598**
Issued: **May 29, 2012**
Appl. No.: **13/088,647**
Filed: **Apr. 18, 2011**

U.S. Applications:

(60) Continuation of application No. 12/716,455, filed on Mar. 3, 2010, now Pat. No. 7,973,406, which is a continuation of application No. 12/062,293, filed on Apr. 3, 2008, now Pat. No. 7,700,407, which is a division of application No. 10/985,654, filed on Nov. 10, 2004, now Pat. No. 7,368,817.

(60) Provisional application No. 60/533,918, filed on Dec. 31, 2003, provisional application No. 60/518,864, filed on Nov. 10, 2003.

(51) **Int. Cl.**
H01L 23/48 (2006.01)
H01L 23/28 (2006.01)
H01L 21/44 (2006.01)

(52) **U.S. Cl.**
USPC **257/734**; 257/737; 257/778; 257/E23.021;
438/107; 438/108; 438/612; 438/613; 438/615

(58) **Field of Classification Search**
USPC 438/107, 108, 612-615; 257/734, 737,
257/778, E23.021

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,186,383 A 2/1993 Melton et al.
5,378,859 A 1/1995 Shirasaki et al.

(Continued)

FOREIGN PATENT DOCUMENTS

JP 04-355933 9/1992
JP 2005-28037 4/1993

(Continued)

OTHER PUBLICATIONS

Yamada, Hiroshi et al., "Advanced copper column based solder bump for flip-chip interconnection", International Symposium on Microelectronics, 1997, pp. 417-422, The British Library—"The world's knowledge".

(Continued)



Primary Examiner — Hsien Ming Lee

(74) *Attorney, Agent, or Firm* — Robert D. Atkins; Patent Law Group: Atkins & Associates, P.C.

(57) **ABSTRACT**

A semiconductor device has a semiconductor die with a plurality of bumps formed over the die. A substrate has a plurality of conductive traces formed on the substrate. Each trace has an interconnect site for mating to the bumps. The interconnect sites have parallel edges along a length of the conductive traces under the bumps from a plan view for increasing escape routing density. The bumps have a noncollapsible portion for attaching to a contact pad on the die and fusible portion for attaching to the interconnect site. The fusible portion melts at a temperature which avoids damage to the substrate during reflow. The noncollapsible portion includes lead solder, and fusible portion includes eutectic solder. The interconnect sites have a width which is less than 1.2 times a width of the conductive trace. Alternatively, the interconnect sites have a width which is less than one-half a diameter of the bump.

36 Claims, 8 Drawing Sheets



(56)

References Cited**U.S. PATENT DOCUMENTS**

5,386,624 A 2/1995 George et al.
 5,434,410 A 7/1995 Kulwicki
 5,508,561 A 4/1996 Tago et al.
 5,519,580 A 5/1996 Natarajan
 5,650,595 A 7/1997 Bently et al.
 5,710,071 A 1/1998 Beddingfield et al.
 5,844,782 A 12/1998 Fukasawa
 5,854,514 A 12/1998 Roldan et al.
 5,869,886 A 2/1999 Tokuno
 5,872,399 A 2/1999 Lee
 5,889,326 A 3/1999 Tanaka
 5,915,169 A 6/1999 Heo
 5,985,456 A 11/1999 Zhou et al.
 6,109,507 A 8/2000 Yagi et al.
 6,201,305 B1 3/2001 Darveaux et al.
 6,218,630 B1 4/2001 Takigami
 6,228,466 B1 5/2001 Tsukada et al.
 6,229,220 B1 5/2001 Saitoh et al.
 6,259,163 B1 7/2001 Ohuchi et al.
 6,281,450 B1 8/2001 Urasaki et al.
 6,297,560 B1 10/2001 Capote et al.
 6,324,754 B1 12/2001 DiStefano et al.
 6,329,605 B1 12/2001 Beroz et al.
 6,335,568 B1 1/2002 Yuzawa et al.
 6,335,571 B1 1/2002 Capote et al.
 6,383,916 B1 5/2002 Lin
 6,396,707 B1 5/2002 Huang et al.
 6,409,073 B1 6/2002 Kaskoun et al.
 6,441,316 B1 8/2002 Kusui
 6,448,665 B1 9/2002 Nakazawa et al.
 6,458,622 B1 10/2002 Keser et al.
 6,573,610 B1 6/2003 Tsai
 6,600,234 B2 7/2003 Kuwabara et al.
 6,608,388 B2 8/2003 Lin et al.
 6,660,560 B2 12/2003 Chaudhuri et al.
 6,678,948 B1 1/2004 Benzler et al.
 6,710,458 B2 3/2004 Seko
 6,734,557 B2 5/2004 Taniguchi et al.
 6,774,497 B1 8/2004 Qi et al.
 6,780,673 B2 8/2004 Venkateswaran et al.
 6,780,682 B2 8/2004 Pendse
 6,787,918 B1 9/2004 Tsai et al.
 6,809,262 B1 10/2004 Hsu
 6,818,545 B2 11/2004 Lee et al.
 6,821,878 B2 11/2004 Danvir et al.
 6,849,944 B2 2/2005 Murtuza et al.
 6,870,276 B1 3/2005 Moxham et al.
 6,888,255 B2 5/2005 Murtuza et al.
 6,913,948 B2 7/2005 Caletka et al.
 7,005,585 B2 2/2006 Ishizaki
 7,005,750 B2 2/2006 Lui et al.
 7,049,705 B2 5/2006 Huang
 7,057,284 B2 6/2006 Chauhan et al.
 7,064,435 B2 6/2006 Chung et al.
 7,098,407 B2 8/2006 Kim et al.
 7,102,239 B2 9/2006 Pu et al.
 7,173,828 B2 2/2007 Lin et al.
 7,224,073 B2 5/2007 Kim
 7,242,099 B2 7/2007 Lin et al.
 7,271,484 B2 9/2007 Reiss et al.
 7,294,929 B2 11/2007 Miyazaki
 7,317,245 B1 1/2008 Lee et al.
 7,405,484 B2 7/2008 Usui et al.
 7,436,063 B2 10/2008 Miyata et al.
 7,521,284 B2 4/2009 Miranda et al.
 7,642,660 B2 1/2010 Tay et al.
 7,670,939 B2 3/2010 Topacio et al.
 7,671,454 B2 3/2010 Seko
 7,700,407 B2 4/2010 Pendse




7,732,913 B2 6/2010 Hsieh et al.
 7,750,457 B2 7/2010 Seko
 7,790,509 B2 9/2010 Gerber
 7,791,211 B2 9/2010 Chen et al.
 7,847,399 B2 12/2010 Masumoto
 7,847,417 B2 12/2010 Araki et al.
 7,851,928 B2 12/2010 Gallegos et al.
 7,898,083 B2 3/2011 Castro
 7,902,660 B1 3/2011 Lee et al.
 7,902,678 B2 3/2011 Ohuchi et al.
 7,902,679 B2 3/2011 Lin et al.
 7,932,170 B1 4/2011 Huemoeller et al.
 7,947,602 B2 5/2011 Ito et al.
 7,973,406 B2 7/2011 Pendse
 2001/0013423 A1 8/2001 Dalal et al.
 2002/0041036 A1 4/2002 Smith
 2003/0049411 A1 3/2003 Chaudhuri et al.
 2004/0035909 A1 2/2004 Yeh et al.
 2004/0056341 A1 3/2004 Endo et al.
 2004/0105223 A1 6/2004 Okada et al.
 2004/0232562 A1 11/2004 Hortaleza et al.
 2005/0103516 A1 5/2005 Kaneyuki
 2005/0248037 A1 11/2005 Hung et al.
 2006/0131758 A1 6/2006 Dao
 2007/0200234 A1 8/2007 Gerber et al.
 2008/0093749 A1 4/2008 Gerber et al.
 2008/0179740 A1 7/2008 Liao
 2008/0277802 A1 11/2008 Tsai et al.
 2009/0108445 A1 4/2009 Liang
 2009/0114436 A1 5/2009 Chen
 2009/0152716 A1 6/2009 Sohara
 2009/0191329 A1 7/2009 Wang
 2009/0288866 A1 11/2009 Tsai et al.
 2009/0308647 A1 12/2009 Liao
 2010/0139965 A1 6/2010 Wang et al.
 2011/0049703 A1 3/2011 Hsu et al.

FOREIGN PATENT DOCUMENTS

JP 6503687 4/1994
 JP 9097791 4/1997
 JP 09-097791 8/1997
 JP 10-256307 9/1998
 JP 11145176 5/1999
 JP 11233571 8/1999
 JP 2000-031204 1/2000
 JP 2000-349194 12/2000
 JP 2000349194 12/2000
 JP 2001156203 6/2001
 JP 2002270732 9/2002
 JP 2004-221205 5/2004
 JP 2004165283 6/2004
 JP 2005109187 4/2005
 WO 9306964 A1 4/1993
 WO 03071842 A1 8/2001

OTHER PUBLICATIONS

Yamada, Hiroshi et al., "A fine pitch and high aspect ratio bump array for flip-chip interconnection", Int'l Electronics Manufacturing Technology Symposium, 1992, pp. 288-292, IEEE/CHMT.
 Lu, H. et al., "Predicting Optimal Process Conditions for Flip-Chip Assembly Using Copper Column Bumped Dies", Electronics Packaging Technology Conference, 2002, pp. 338-343.
 Kawahara, Toshimi, "SuperCSP", IEEE Transactions on Advanced Packaging, May 2000, pp. 215-219, vol. 23, No. 2.
 Son, Ho-Young, "Studies on the Thermal Cycling Reliability of Fine Pitch Cu/SnAg Double-Bump Flip Chip Assemblies on Organic Substrates: Experimental Results and Numerical Analysis", IEEE Electronic Components and Technology Conference, 2008, pp. 2035-2043.






FIG. 4








FIG. 5








FIG. 10A




FIG. 10B




FIG. 10C




FIG. 11A




FIG. 11B




FIG. 11C




FIG. 11D




FIG. 12




FIG. 13

BUMP-ON-LEAD FLIP CHIP INTERCONNECTION

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

CLAIM OF DOMESTIC PRIORITY

The present application *is a reissue application of U.S. Pat. No. 8,188,598, which is a continuation of U.S. application Ser. No. 12/716,455, filed Mar. 3, 2010, [and claims priority to the foregoing parent application pursuant to 35 U.S.C. §120] now U.S. Pat. No. 7,973,406, which is a continuation of U.S. application Ser. No. 12/062,293, filed Apr. 3, 2008, now U.S. Pat. No. 7,700,407, which is a division of U.S. application Ser. No. 10/985,654, filed Nov. 10, 2004, now U.S. Pat. No. 7,368,817, which claims the benefit of U.S. Provisional Application No. 60/518,864, filed Nov. 10, 2003, and U.S. Provisional Application No. 60/533,918, filed Dec. 31, 2003.*

FIELD OF THE INVENTION

This invention relates to semiconductor packaging and, particularly, to flip chip interconnection.

BACKGROUND OF THE INVENTION

Flip chip packages include a semiconductor die mounted onto a package substrate with the active side of the die facing the substrate. Conventionally, interconnection of the circuitry in the die with circuitry in the substrate is made by way of bumps which are attached to an array of interconnect pads on the die, and bonded to a corresponding (complementary) array of interconnect pads (often referred to as "capture pads") on the substrate.

The areal density of electronic features on integrated circuits has increased enormously, and chips having a greater density of circuit features also may have a greater density of sites for interconnection with a package substrate.

The package is connected to underlying circuitry, such as a printed circuit board (e.g., a "motherboard") in the device in which it is employed, by way of second level interconnects (e.g., pins) between the package and the underlying circuit. The second level interconnects have a greater pitch than the flip chip interconnects, and so the routing on the substrate conventionally "fans out". Significant technological advances have enabled construction of fine lines and spaces; but in the conventional arrangement space between adjacent pads limits the number of traces than can escape from the more inward capture pads in the array, and the fan out routing between the capture pads beneath the die and the external pins of the package is conventionally formed on multiple metal layers within the package substrate. For a complex interconnect array, substrates having multiple layers may be required to achieve routing between the die pads and the second level interconnects on the package.

Multiple layer substrates are expensive, and in conventional flip chip constructs the substrate alone typically accounts for more than half the package cost (about 60% in some typical instances). The high cost of multilayer substrates has been a factor in limiting proliferation of flip chip technology in mainstream products.

In conventional flip chip constructs the escape routing pattern typically introduces additional electrical parasitics,

because the routing includes short runs of unshielded wiring and vias between wiring layers in the signal transmission path. Electrical parasitics can significantly limit package performance.

SUMMARY OF THE INVENTION

According to the invention flip chip interconnect is accomplished by connecting the interconnect bump directly onto a lead, rather than onto a pad. The invention provides more efficient routing of traces on the substrate. Particularly, the signal routing can be formed entirely in a single metal layer of the substrate. This reduces the number of layers in the substrate, and forming the signal traces in a single layer also permits relaxation of some of the via, line and space design rules that the substrate must meet. This simplification of the substrate greatly reduces the overall cost of the flip chip package. The bump-on-lead architecture also helps eliminate such features as vias and "stubs" from the substrate design, and enables a microstrip controlled impedance electrical environment for signal transmission, thereby greatly improving performance.

In one general aspect the invention features a flip chip interconnection having solder bumps attached to interconnect pads on a die and mated onto corresponding traces on a substrate.

In another general aspect the invention features a flip chip package including a die having solder bumps attached to interconnect pads in an active surface, and a substrate having electrically conductive traces in a die attach surface, in which the bumps are mated directly onto the traces.

In general the bump-on-lead interconnection is formed according to methods of the invention without use of a solder mask to confine the molten solder during a re-melt stage in the process. Avoiding the need for a solder mask allows for finer interconnection geometry.

In some embodiments the substrate is further provided with a solder mask having openings over the interconnect sites on the leads. In some embodiments the substrate is further provided with solder paste on the leads at the interconnect sites.

In another general aspect the invention features a method for forming flip chip interconnection, by providing a substrate having traces formed in a die attach surface and a die having bumps attached to interconnect pads in an active surface; supporting the substrate and the die; dispensing a quantity of a curable adhesive on the substrate (covering at least the connection sites on the traces) or on the active side of the die (covering at least the bumps); positioning the die with the active side of the die toward the die attach surface of the substrate, and aligning the die and substrate and moving one toward the other so that the bumps contact the corresponding traces (leads) on the substrate; applying a force to press the bumps onto the mating traces, sufficient to displace the adhesive from between the bump and the mating trace; at least partially curing the adhesive; melting and then re-solidifying the solder, forming a metallurgical interconnection between the bump and the trace.

In another general aspect the invention features a method for forming flip chip interconnection, by providing a substrate having traces formed in a die attach surface and having a solder mask having openings over interconnect sites on the leads, and a die having bumps attached to interconnect pads in an active surface; supporting the substrate and the die; positioning the die with the active side of the die toward the die attach surface of the substrate, and aligning the die and substrate and moving one toward the other so that the bumps

3

contact the corresponding traces (leads) on the substrate; melting and then re-solidifying to form the interconnection between the bump and the trace.

In some embodiments the solder bump includes a collapsible solder portion, and the melt and solidifying step melts the bump to form the interconnection on the lead. In some embodiments the substrate is further provided with a solder paste on the leads, and the step of moving the die and the substrate toward one another effects a contact between the bumps and the solder on the leads, and the melt and solidifying step melts the solder on the lead to form the interconnection.

In another general aspect the invention features a method for forming flip chip interconnection, by providing a substrate having traces formed in a die attach surface and having a solder mask having openings over interconnect sites on the leads and having solder paste on the leads at the interconnect sites, and a die having bumps attached to interconnect pads in an active surface; supporting the substrate and the die; positioning the die with the active side of the die toward the die attach surface of the substrate, and aligning the die and substrate and moving one toward the other so that the bumps contact the solder paste on the corresponding traces (leads) on the substrate; melting and then re-solidifying the solder paste, forming a metallurgical interconnection between the bump and the trace.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a diagrammatic sketch of a portion of a conventional bump-on-capture pad flip chip interconnection, in a sectional view parallel to the plane of the package substrate surface, as indicated by the arrows 1-1' in FIG. 2;

FIG. 2 is a diagrammatic sketch showing a portion of a conventional bump-on-capture pad flip chip interconnection, in a sectional view perpendicular to the plane of the package substrate surface, as indicated by the arrows 2-2' in FIG. 1;

FIG. 3 is a diagrammatic sketch showing a portion of another conventional bump-on-capture pad flip chip interconnection, in a sectional view perpendicular to the plane of the package substrate surface;

FIG. 4 is a diagrammatic sketch of a portion of an embodiment of a bump-on-lead flip chip interconnection according to the invention, in a sectional view parallel to the plane of the package substrate surface;

FIG. 5 is a diagrammatic sketch showing a portion of an embodiment of a bump-on-lead flip chip interconnection according to the invention as in FIG. 4, in a sectional view perpendicular to the plane of the package substrate surface, as indicated by the arrows 6-6' in FIG. 4;

FIG. 6 is a diagrammatic sketch of a portion of another embodiment of a bump-on-lead flip chip interconnection according to the invention, in a sectional view parallel to the plane of the package substrate surface;

FIG. 7 is a diagrammatic sketch showing a portion of an embodiment of a bump-on-lead flip chip interconnection according to the invention as in FIG. 6, in a sectional view perpendicular to the plane of the package substrate surface, as indicated by the arrows 7-7' in FIG. 6;

FIGS. 8 and 9 are diagrammatic sketches, each of a portion of another embodiment of a bump-on-lead flip chip interconnection according to the invention, in a sectional view parallel to the plane of the package substrate surface;

FIGS. 10A-10C are diagrammatic sketches in a sectional view illustrating steps in a process for making a flip chip interconnection according to the invention;

4

FIGS. 11A-11D are diagrammatic sketches in a sectional view illustrating steps in a process for making a flip chip interconnection according to the invention;

FIG. 12 is a diagrammatic sketch showing a force and temperature schedule for a process for making a flip chip interconnection according to the invention; and

FIG. 13 is a diagrammatic sketch in a sectional view showing a bump-on-lead flip chip interconnection according to the invention, having composite bumps.

DETAILED DESCRIPTION OF THE DRAWINGS

The invention will now be described in further detail by reference to the drawings, which illustrate alternative embodiments of the invention. The drawings are diagrammatic, showing features of the invention and their relation to other features and structures, and are not made to scale. For improved clarity of presentation, in the figures illustrating embodiments of the invention, elements corresponding to elements shown in other drawings are not all particularly renumbered, although they are all readily identifiable in all the figures.

The conventional flip chip interconnection is made by using a melting process to join the bumps (conventionally, solder bumps) onto the mating surfaces of the corresponding capture pads and, accordingly, this is known as a "bump-on-capture pad" ("BOC") interconnect. Two features are evident in the BOC design: first, a comparatively large capture pad is required to mate with the bump on the die; second, an insulating material, typically known as a "solder mask" is required to confine the flow of solder during the interconnection process. The solder mask opening may define the contour of the melted solder at the capture pad ("solder mask defined"), or the solder contour may not be defined by the mask opening ("non-solder mask defined"); in the latter case—as in the example of FIG. 1, described in more detail below the solder mask opening may be significantly larger than the capture pad. The techniques for defining solder mask openings have wide tolerance ranges. Consequently, for a solder mask defined bump configuration, the capture pad must be large (typically considerably larger than the design size for the mask opening), to ensure that the mask opening will be located on the mating surface of the pad; and for a non-solder mask defined bump configuration, the solder mask opening must be larger than the capture pad. The width of capture pads (or diameter, for circular pads) is typically about the same as the ball (or bump) diameter, and can be as much as two to four times wider than the trace width. This results in considerable loss of routing space on the top substrate layer. In particular, for example, the "escape routing pitch" is much bigger than the finest trace pitch that the substrate technology can offer. This means that a significant number of pads must be routed on lower substrate layers by means of short stubs and vias, often beneath the footprint of the die, emanating from the pads in question.

FIGS. 1 and 2 show portions 10, 20 of a conventional flip chip package, in diagrammatic sectional views; the partial sectional view in FIG. 1 is taken in a plane parallel to the package substrate surface, along the line 1-1' in FIG. 2; and the partial sectional view in FIG. 2 is taken in a plane perpendicular to the package substrate surface, along the line 2-2' in FIG. 1. Certain features are shown as if transparent, but many of the features in FIG. 1 are shown at least partly obscured by overlying features. Referring now to both FIG. 1 and FIG. 2, a die attach surface of the package substrate includes a metal or layer formed on a dielectric layer 12. The metal layer is patterned to form leads 13 and capture pads 14. A insulating

5

layer 16, typically termed a “solder mask”, covers the die attach surface of the substrate; the solder mask is usually constructed of a photodefinable material, and is patterned by conventional photoresist patterning techniques to leave the mating surfaces of the capture pads 14 exposed. Interconnect bumps 15 attached to pads on the active side of the die 18 are joined to the mating surfaces of corresponding capture pads 14 on the substrate to form appropriate electrical interconnection between the circuitry on the die and the leads on the substrate. After the reflowed solder is cooled to establish the electrical connection, an underfill material 17 is introduced into the space between the die 18 and the substrate 12, mechanically stabilizing the interconnects and protecting the features between the die and the substrate.

As FIG. 1 shows by way of example, signal escape traces in the upper metal layer of the substrate (leads 13), lead from their respective capture pads 14 across the die edge location, indicated by the broken line 11, and away from the die footprint. In a typical example the signal traces may have an escape pitch P_E about 112 μm . A 30 μm /30 μm design rule is typical for the traces themselves in a configuration as shown in FIG. 1; that is, the traces are nominally 30 μm wide, and they can be spaced as close together as 30 μm . The capture pads are typically three times greater than the trace width and, accordingly in this example the capture pads have a width (or diameter, as they are roughly circular in this example) nominally 90 μm . And, in this example, the openings in the solder mask are larger than the pads, having a nominal width (diameter) of 135 μm .

FIGS. 1 and 2 show a non-solder mask defined solder contour. As the fusible material of the bumps on the die melt, the molten solder tends to “wet” the metal of the leads and capture pads, and the solder tends to “run out” over any contiguous metal surfaces that are not masked. The solder tends to flow along the contiguous lead 13, and here the solder flow is limited by the solder mask, for example at 19 in FIG. 1. A non-solder mask defined solder contour at the pad is apparent in FIG. 2, in which the material of the bumps 15 is shown as having flowed, 29, over the sides of the capture pads 14 and down to the surface of the dielectric layer of the substrate 12. This is referred to as a non-solder mask defined contour because the solder mask does not limit the flow of solder over the surface and down over the sides of the capture pads, and—unless there is a substantial excess of solder at the pad the flow of solder is limited by the fact that the dielectric surface of the substrate is typically not wettable by the molten solder. A lower limit on the density of the capture pads in a conventional arrangement, as in FIG. 1, is determined by, among other factors, limits on the capacity of the mask forming technology to make reliable narrow mask structures, and the need to provide mask structures between adjacent mask openings. A lower limit on the escape density is additionally determined by, among other factors, the need for escape lines from more centrally located capture pads to be routed between more peripherally located capture pads.

FIG. 3 shows a conventional solder mask defined solder contour, in a sectional view similar to that in FIG. 2. A die 38 is shown affixed by way of bumps 35 onto the mating surfaces of capture pads 34 formed along with traces (leads 33) by patterning a metal layer on the die attach side of a dielectric layer of the substrate 32. After the reflowed solder is cooled to establish the electrical connection, an underfill material 37 is introduced into the space between the die 38 and the substrate 32, mechanically stabilizing the interconnects and protecting the features between the die and the substrate. Here the capture pads 34 are wider than in the example of FIGS. 1 and 2, and the solder mask openings are smaller than the capture

6

pads, so that the solder mask material covers the sides and part of the mating surface each capture pad, as shown at 39, as well as the leads 33. When the bumps 35 are brought into contact with the mating surfaces of the respective capture pads 34, and then melted, the solder mask material 36 restricts the flow of the molten solder, so that the shapes of the solder contours are defined by the shapes and dimensions of the mask openings over the capture pads 34.

FIGS. 4 and 6 each show a portion of a bump-on-lead (“BOL”) flip chip interconnection according to an embodiment of the invention, in a diagrammatic partial sectional view taken in a plane parallel to the substrate surface, along the lines 4-4' and 6-6' in FIGS. 5 and 7, respectively. Certain features are shown as if transparent. According to the invention the interconnection is achieved by mating the bumps directly onto respective narrow leads or traces on the substrate and, accordingly, this is referred to herein as a “bump-on-lead” (“BOL”) interconnect. Solder mask materials typically cannot be resolved at such fine geometries and, according to these embodiments of the invention, no solder mask is used. Instead the function of confining molten solder flow is accomplished without a solder mask in the course of the assembly process (as described below). FIG. 5 shows a partial sectional view of a package as in FIG. 4, taken in a plane perpendicular to the plane of the package substrate surface, along the line 5-5' in FIG. 4; and FIG. 7 shows a partial sectional view of a package as in FIG. 6, taken in a plane perpendicular to the plane of the package substrate surface, along the line 7-7' in FIG. 6.

Escape routing patterns for bump-on-lead (“BOL”) substrates according to the invention are shown by way of example in FIGS. 4 and 6: in FIG. 4, arranged for a die on which the die attach pads for the interconnect balls are in a row near the die perimeter, the bumps 45 are mated onto corresponding interconnect sites on the escape traces 43 in a row near the edge of the die footprint, indicated by the broken line 41; in FIG. 6, arranged for a die on which the die attach pads are in an array of parallel rows near the die perimeter, the bumps 65 are mated onto corresponding interconnect sites on the escape traces 63 in a complementary array near the edge of the die footprint, indicated by the broken line 61.

As FIGS. 4 and 6 illustrate, the routing density achievable using bump-on-lead interconnect according to the invention can equal the finest trace pitch offered by the substrate technology. In the specific case illustrated, this constitutes a routing density which is approximately 90% higher than is achieved in a conventional bump-on-capture pad arrangement. In the perimeter row embodiments of BOL (e.g., FIG. 4), the bumps are placed at a fine pitch, which can equal the finest trace pitch of the substrate. This arrangement poses a challenge for the assembly process, because the bumping and bonding pitch must be very fine. In the perimeter array version of BOL (e.g., FIG. 6), the bumps are arranged on an area array, providing greater space for a larger bumping and bonding pitch, and relieving the technological challenges for the assembly process. Even in the array embodiments, the routing traces on the substrate are at the same effective pitch as in the perimeter row arrangement, and an arrangement as in FIG. 6 relieves the burden of fine pitch bumping and bonding without sacrificing the fine escape routing pitch advantage.

Referring particularly now to FIGS. 4 and 5, leads 43 are formed by patterning a metal layer on a die attach surface of a substrate dielectric layer 42. According to the invention, electrical interconnection of the die 48 is made by joining the bumps 45 on the die directly onto the leads 43. No capture pads are required according to the invention and, in embodi-

ments as in FIGS. 4 and 5, no solder mask is required; the process is described in detail below.

Conventional capture pads typically are about the same width (diameter) as the bumps, and are typically two to four times as wide as the trace or lead width. As will be appreciated, some variation in the width of leads is expected. As used herein, a variation in trace width of as much as 120% of the nominal or trace design rule width does not constitute a capture pad, and bump-on-lead interconnection according to the invention includes bumps formed on such wider portions of leads.

Similarly, referring to FIGS. 6 and 7, leads 63 are formed by patterning a metal layer on a die attach surface of a substrate dielectric layer 62. The signal escape traces lead across the die edge location, indicated by the broken line 61, and away from the die footprint. According to the invention, electrical interconnection of the die 68 is made by joining the bumps 65 on the die directly onto the leads 63. Certain of the escape traces, e.g. 66, leading across the die edge location from interconnect sites in rows toward the interior of the die footprint, pass between the bumps 65 on more peripheral rows of interconnect sites. No capture pads are required according to the invention and, in embodiments as in FIGS. 6 and 7, no solder mask is required; the process is described in detail below.

As FIGS. 4 and 6 illustrate, bump-on-lead interconnect according to the invention can provide a significantly higher signal trace escape routing density. Also, as FIGS. 4 and 6 illustrate, the BOL interconnect according to this aspect of the invention does not require use of a solder mask to define the solder contour at the interconnect site.

The BOL interconnection structure of embodiments such as are shown by way of example in FIGS. 4, 5, 6 and 7 can be produced according to the invention by any of several methods, not requiring a solder mask. In general, interconnect bumps (typically solder bumps) are affixed onto interconnect pads on the active side of the die. A die attach surface of the substrate (termed the "upper" surface) has an upper metal layer patterned to provide the traces as appropriate for interconnection with the arrangement of bumps on the particular die. Because no capture pads are required, the patterned traces (leads) need only route through sites corresponding to a pattern complementary to the arrangement of bumps on the die. In a preferred method of the invention, an encapsulating resin adhesive is employed to confine the solder flow during a melt phase of the interconnection process.

FIGS. 8 and 9 show two examples of a portion of a bump-on-lead flip chip interconnection according to other embodiments of the invention, in a diagrammatic sectional view taken in a plane parallel to the substrate surface. Certain features are shown as if transparent. According to this aspect of the invention a solder mask is provided, which may have a nominal mask opening diameter in the range about 80 um to 90 um. Solder mask materials can be resolved at such pitches and, particularly, substrates can be made comparatively inexpensively with solder masks having 90 um openings and having alignment tolerances plus or minus 25 um. In some embodiments laminate substrates (such as 4 metal layer laminates), made according to standard design rules, are used. In the embodiments of FIGS. 8 and 9, for example, the traces may be at ~90 um pitch and the interconnection sites may be in a 270 um area array, providing an effective escape pitch ~90 um across the edge of the die footprint, indicated by the broken line 81.

In embodiments as in FIGS. 8 and 9 a no-flow underfill is not required; a conventional capillary underfill can be employed.

In embodiments as in FIG. 8 the interconnection is achieved by mating the bumps directly onto an interconnect site 84 on a narrow lead or trace 83 patterned on a dielectric layer on the die attach surface of the substrate 82; there is no pad, and the solder mask 86 serves to limit flow of solder within the bounds of the mask openings 88, preventing solder flow away from the interconnect site along the solder-wettable lead. The solder mask may additionally confine flow of molten solder between leads, or this may be accomplished in the course of the assembly process.

In embodiments as in FIG. 9, as in FIG. 8, there are, according to the invention, no interconnect pads. Narrow leads or traces 93 patterned on a dielectric layer on the die attach surface of the substrate 92. Solder paste is provided at the interconnect sites 94 on the leads 93, to provide a fusible medium for the interconnect. The openings 98 in the solder mask 96 serve to define the paste. The paste is dispensed, for example by a standard printing process, then is reflowed, and then may be coined if necessary to provide uniform surfaces to meet the balls. The solder paste can be applied in the course of assembly using a substrate as described above with reference to FIG. 8; or, a substrate may be provided with paste suitably patterned prior to assembly. Other approaches to applying solder selectively to the interconnect sites may be employed in the solder-on-lead embodiments of the invention, including electroless plating and electroplating techniques. The solder-on-lead configuration provides additional solder volume for the interconnect, and can accordingly provide higher product yield, and can also provide a higher die standoff.

Accordingly, in some embodiments the solder-on-lead configuration according to the invention is employed for interconnection of a die having high-melting temperature solder bumps (such as a high-lead solder, conventionally used for interconnection with ceramic substrates) onto an organic substrate. The solder paste can be selected to have a melting temperature low enough that the organic substrate is not damaged during reflow. To form the interconnect in such embodiments the high-melting interconnect bumps are contacted with the solder-on-lead sites, and the remelt fuses the solder-on-lead to the bumps. Where a noncollapsible bump is used, together with a solder-on-lead process, no preapplied adhesive is required, as the displacement or flow of the solder is limited by the fact that only a small quantity of solder is present at each interconnect, and the noncollapsible bump prevents collapse of the assembly.

In other embodiments the solder-on-lead configuration according to the invention is employed for interconnection of a die having eutectic solder bumps.

One embodiment of a preferred method for making a bump-on-lead interconnection is shown diagrammatically in FIGS. 10A-10C.

Referring to the figures, a substrate 112 is provided, having at least one dielectric layer and having a metal layer on a die attach surface 113, the metal layer being patterned to provide circuitry, particularly traces or leads 114 having sites for interconnection, on the die attach surface. The substrate 112 is supported, for example on a carrier or stage 116, with a substrate surface 111 opposite the die attach surface 113 facing the support. A quantity of an encapsulating resin 122 is dispensed over the die attach surface 113 of the substrate, covering at least the interconnect sites on the leads 114. A die 102 is provided, having bumps 104 attached to die pads (not shown in the figure) on the active side 103. The bumps include a fusible material which contacts the mating surfaces of the leads. A pick-and-place tool 108 including a chuck 106 picks up the die by contact of the chuck 106 with the backside 101

of the die. Using the pick-and-place tool, the die is positioned facing the substrate with the active side of the die toward the die attach surface of the substrate, as shown in FIG. 10A; and the die and substrate are aligned and moved one toward the other (arrow M) so that the bumps **104** contact the corresponding interconnect sites on the traces (leads) **114** on the substrate. Then a force is applied (arrow F) to press the bumps **105** onto the mating surfaces **134** at the interconnect sites on the leads **115**, as shown in FIG. 10B. The force must be sufficient at least to displace the adhesive **122** from between the bumps and the mating surfaces at the interconnect sites on the leads **154**. The bumps may be deformed by the force, breaking the oxide film on the contacting surface of the bumps and/or on the mating surface of leads. The deformation of the bumps may result in the fusible material of the bumps being pressed onto the top and over the edges of the lead. The adhesive is caused to cure at least partially, as shown at **132**, as for example by heating to a selected temperature. At this stage the adhesive need only be partially cured, that is, only to an extent sufficient subsequently to prevent flow of molten solder along an interface between the adhesive and the conductive traces. Then the fusible material of the bumps **105** is melted and then is re-solidified, forming a metallurgical interconnection between the bump **105** and lead **115**, and the adhesive curing is completed, to complete the die mount and to secure the electrical interconnection at the mating surface (now an interconnect interface) **144**, as shown generally at **140** in FIG. 10C. In the plane of the sectional view shown in FIG. 10C, interconnection is formed between certain of the bumps **145** and corresponding interconnect sites on certain of the leads **155**, as for example in a configuration as in FIG. 6.

Other leads **156** are interconnected at other localities, which would be visible in other sectional views. A comparatively high trace density is shown. The curing of the adhesive **142** may be completed prior to, or concurrently with, or following melting the solder. Typically, the adhesive is a thermally curable adhesive, and the extent of curing at any phase in the process is controlled by regulating the temperature. The components can be heated and cured by raising the temperature of the chuck on the pick and place tool, or by raising the temperature of the substrate support, for example.

The process is shown in further detail in FIGS. 11A-11D. In FIG. 11A, a substrate **212** is provided on a die attach surface with conductive (metal) traces **214**, and interconnect sites on the traces are covered with an adhesive **222**. The die **202** is positioned in relation to the substrate **212** such that the active side of the die faces the die attach side of the substrate, and is aligned (arrows A) such that bumps **204** on the die are aligned with corresponding mating surfaces on traces **214**. The die and the substrate are moved toward one another so that the bumps contact the respective mating surfaces on the traces. Then as shown in FIG. 11B a force is applied to move the bumps **205** and traces **215** against one another, displacing the adhesive as shown at **232** in FIG. 11B, and deforming the bumps onto the mating surfaces **234** and over the edges of the traces. Deformation of the bumps on the traces breaks the oxide film on the contact surfaces of the bumps and the mating surfaces of the traces, establishing a good electrical connection, and deformation of the bumps over the edges of the traces helps establish a good temporary mechanical connection. As in the example of FIG. 10A-10C, the interconnect sites of certain of the traces **216** are out of the plane of FIG. 11B. Heat is applied to partially cure the adhesive as shown at **236** in FIG. 11C. Then heat is applied to raise the temperature of the bumps sufficiently to cause the fusible material of the bumps to melt, as shown in FIG. 11D. This substantially (though not necessarily fully) completes the cure of the adhe-

sive **246** and completes the metallurgical interconnection of the bumps **245** onto the mating surfaces **244** at the interconnect sites on the leads **215**. The cured adhesive stabilizes the die mount.

In an alternative embodiment of a preferred method, the adhesive can be pre-applied to the die surface, or at least to the bumps on the die surface, rather than to the substrate. The adhesive can, for example, be pooled in a reservoir, and the active side of the die can be dipped in the pool and removed, so that a quantity of the adhesive is carried on the bumps; then, using a pick-and-place tool, the die is positioned facing a supported substrate with the active side of the die toward the die attach surface of the substrate, and the die and substrate are aligned and moved one toward the other so that the bumps contact the corresponding traces (leads) on the substrate. Such a method is described in U.S. Pat. No. 6,780,682, Aug. 24, 2004, which is hereby incorporated by reference. Then forcing, curing, and melting are carried out as described above.

A force and temperature schedule for a process according to the invention is shown diagrammatically by way of example in FIG. 12. In this chart, time runs from left to right on the horizontal axis; a force profile **310** is shown as a thick solid line, and a temperature profile **320** is shown as a dotted line. The temperature profile begins at a temperature in the range about 80° C.- about 90° C. The force profile begins at essentially zero force. Beginning at an initial time t_i , the force is rapidly (nearly instantaneously) raised **312** from F_i to a displacement/deformation force F_d and held **314** at that force for a time, as discussed below. F_d is a force sufficiently great to displace the adhesive away from between the bumps and the mating surfaces of the leads; and, preferably, sufficient to deform the fusible (lead-contacting) portion of the bumps onto the mating surface, breaking the oxide films and forming a good metal-to-metal (metallurgical) contact, and, in some embodiments, over the edges of the leads to establish a mechanical interlock of the bumps and the leads ("creep" deformation). The total amount of force required will depend upon the bump material and dimensions and upon the number of bumps, and can be determined without undue experimentation. As the force is raised, the temperature is also rapidly raised **322** from an initial temperature T_i to a gel temperature T_g . The gel temperature T_g is a temperature sufficient to partially cure the adhesive (to a "gel"). Preferably, the force and temperature ramps are set so that there is a short lag time t_{def} following the moment when F_d is reached and before T_g is reached, at least long enough to permit the elevated force to displace the adhesive and to deform the bumps before the partial cure of the adhesive commences. The assembly is held **314, 324** at the displacement/deformation pressure F_d and at the gel temperature T_g for a time t_{gel} sufficient to effect the partial cure of the adhesive. The adhesive should become sufficiently firm that it can subsequently maintain a good bump profile during the solder remelt phase—that is, sufficiently firm to prevent undesirable displacement of the molten fusible material of the bump, or flow of the molten fusible material along the leads. Once the adhesive has partially cured to a sufficient extent, the pressure may be ramped down rapidly **318** to substantially no force (weight of the components). The temperature is then rapidly raised further **323** to a temperature T_m sufficient to remelt the fusible portions (solder) of the bumps, and the assembly is held **325** at the remelt temperature T_m for a time $t_{melt/cure}$ at least sufficient to fully form the solder remelt on the traces, and preferably sufficient to substantially (though not necessarily fully) cure the adhesive. Then the temperature is ramped down **328** to the initial

11

temperature T_i , and eventually to ambient. The process outlined in FIG. 12 can run its course over a time period of 5-10 seconds.

The adhesive in embodiments as in FIG. 12 may be referred to as a “no-flow underfill”. In some approaches to flip chip interconnection, the metallurgical interconnection is formed first, and then an underfill material is flowed into the space between the die and the substrate. The “no-flow underfill” according to the invention is applied before the die and the substrate are brought together, and the no-flow underfill is displaced by the approach of the bumps onto the leads, and by the opposed surfaces of the die and the substrate. The adhesive for the no-flow underfill adhesive according to the invention is preferably a fast-gelling adhesive—that is, a material that gels sufficiently at the gel temperature in a time period in the order of 1-2 seconds. Preferred materials for the no-flow underfill adhesive include, for example, so-called non-conductive pastes, such as those marketed by Toshiba Chemicals and by Loktite-Henkel, for example.

Alternative bump structures may be employed in the bump-on-lead interconnects according to the invention. Particularly, for example, so-called composite solder bumps may be used. Composite solder bumps have at least two bump portions, made of different bump materials, including one which is collapsible under reflow conditions, and one which is substantially non-collapsible under reflow conditions. The non-collapsible portion is attached to the interconnect site on the die; typical conventional materials for the non-collapsible portion include various solders having a high lead (Pb) content, for example. The collapsible portion is joined to the non-collapsible portion, and it is the collapsible portion that makes the connection with the lead according to the invention. Typical conventional materials for the collapsible portion of the composite bump include eutectic solders, for example.

An example of a bump-on-lead interconnect employing a composite bump is shown in a diagrammatic sectional view in FIG. 13. Referring now to FIG. 13, die 302 is provided on die pads in the active side of the die with composite bumps 344 that include a noncollapsible portion 345 and a collapsible portion 347. The collapsible portion may be, for example, a eutectic solder or a relatively low temperature melt solder). The collapsible portion contacts the mating surface of the lead and, where deformation of the fusible portion of the bump over the lead 355 is desired, the collapsible portion of the bump is deformable under the conditions of force employed. The noncollapsible portion may be, for example, a solder having a high lead (Pb) content. The noncollapsible portion does not deform when the die is moved under pressure against the substrate 312 during processing, and does not melt during the reflow phase of the process. Accordingly the noncollapsible portion can be dimensioned to provide a standoff distance between the active surface of the die and the die attach surface of the substrate.

As may be appreciated, the bumps in embodiments as shown in, for example, FIGS. 4, 5, 6 and 7 need not necessarily be fully collapsible bumps. The structures shown in those FIGs. may alternatively be made using composite bumps, or using a solder-on-lead method, as described above.

Other embodiments are within the following claims.

What is claimed is:

1. A method of forming a semiconductor device, comprising:
 - providing a semiconductor die;
 - forming a plurality of bumps over the semiconductor die;
 - providing a substrate; and

12

forming a plurality of conductive traces on the substrate, each trace having an interconnect site for mating to the bumps, the interconnect sites having parallel edges with a width which is less than one-half a diameter of the bump, wherein one of the bumps has a noncollapsible portion for attaching to a contact pad on the semiconductor die and a fusible portion for attaching to the interconnect site.

2. The method of claim 1, wherein the noncollapsible portion includes lead solder and the fusible portion includes eutectic solder.

3. The method of claim 1, wherein the fusible portion melts at a temperature which avoids damage to the substrate during reflow.

4. The method of claim 1, wherein one of the bumps contacts a sidewall of one of the interconnect sites.

5. The method of claim 1, further including disposing an underfill material between the semiconductor die and substrate.

6. The method of claim 1, wherein the interconnect sites have a width which is less than 1.2 times a width of the conductive trace.

7. A method of making a semiconductor device, comprising:

- providing a semiconductor die;
- forming a bump over the semiconductor die; and
- providing a substrate having a conductive trace formed on a die attach surface of the substrate for mating to the bump, the conductive trace having an interconnect site with a width which is less than one-half a diameter of the bump, wherein the bump has a noncollapsible portion including lead solder for attaching to a contact pad on the semiconductor die and a fusible portion including eutectic solder for attaching to the interconnect site.

8. The method of claim 7, wherein the fusible portion melts at a temperature which avoids damage to the substrate during reflow.

9. The method of claim 7, further including disposing an underfill material between the semiconductor die and substrate.

10. A method of making a semiconductor device, comprising:

- providing a semiconductor die;
- forming a bump over the semiconductor die; and
- providing a substrate having a conductive trace formed on a die attach surface of the substrate, the conductive trace having an interconnect site for mating with the bump, the interconnect site having a width less than one-half a width of the bump, wherein the bump has a noncollapsible portion for attaching to a contact pad on the semiconductor die and a fusible portion for attaching to the interconnect site.

11. The method of claim 10, wherein the fusible portion melts at a temperature which avoids damage to the substrate during reflow.

12. The method of claim 10, wherein the noncollapsible portion includes lead solder and the fusible portion includes eutectic solder.

13. The method of claim 10, wherein the bump contacts a sidewall of the interconnect site.

14. A semiconductor device, comprising:

- a semiconductor die;
- a plurality of bumps formed over the semiconductor die;
- a substrate; and
- a plurality of conductive traces formed on the substrate, each trace having an interconnect site for mating to the bumps, the interconnect sites having parallel edges with

13

a width less than one-half a width of the bumps, wherein one of the bumps has a noncollapsible portion for attaching to a contact pad on the semiconductor die and a fusible portion for attaching to the interconnect site.

15. The semiconductor device of claim 14, wherein the noncollapsible portion includes lead solder.

16. The semiconductor device of claim 14, wherein the fusible portion includes eutectic solder.

17. The semiconductor device of claim 14, wherein the interconnect sites have a width which is less than 1.2 times a width of the conductive trace.

18. The semiconductor device of claim 14, wherein the bumps have a pitch as determined by a spacing between adjacent conductive traces that can be achieved on the substrate.

19. A method of making a semiconductor device, comprising:

providing a semiconductor die;

forming a plurality of bumps over a surface of the semiconductor die, each one of the bumps including a non-collapsible portion and a fusible portion;

providing a substrate;

forming a plurality of conductive traces including interconnect sites over a surface of the substrate, wherein a width of the interconnect sites is less than one-half a width of the bumps; and

bonding the fusible portion of the bumps to a surface of the interconnect sites by deforming the fusible portion against the interconnect sites while the non-collapsible portion of the bumps maintains vertical standoff between the semiconductor die and substrate.

20. The method of claim 19, wherein the non-collapsible portion of the bumps includes lead solder for attaching to a contact pad on the semiconductor die and the fusible portion of the bumps includes eutectic solder for attaching to the surface of the interconnect sites.

21. The method of claim 19, further including depositing an underfill material between the semiconductor die and substrate.

22. The method of claim 19, wherein the fusible portion of one of the bumps contacts a sidewall of one of the interconnect sites.

23. A method of making a semiconductor device, comprising:

providing a semiconductor die;

forming a bump over a surface of the semiconductor die, the bump including a non-collapsible portion and a fusible portion;

providing a substrate;

forming an interconnect site over a surface of the substrate, wherein a width of the interconnect site is less than one-half a width of the bump; and

bonding the fusible portion of the bump to a surface of the interconnect site, the non-collapsible portion of the bump maintaining vertical standoff between the semiconductor die and substrate.

14

24. The method of claim 23, wherein the non-collapsible portion of the bump includes lead solder for attaching to a contact pad on the semiconductor die.

25. The method of claim 23, wherein the fusible portion of the bump includes eutectic solder for attaching to the surface of the interconnect site.

26. The method of claim 23, further including depositing an underfill material between the semiconductor die and substrate.

27. The method of claim 23, wherein the fusible portion of the bump contacts a sidewall of the interconnect site.

28. A method of making a semiconductor device, comprising:

providing a semiconductor die;

providing a substrate having an interconnect site formed over a surface of the substrate;

providing a bump having a non-collapsible portion and a fusible portion, wherein a width of the interconnect site is less than one-half a width of the bump; and

bonding the bump between the surface of the substrate and a surface of the interconnect site, the non-collapsible portion of the bump maintaining vertical standoff between the semiconductor die and substrate.

29. The method of claim 28, wherein the non-collapsible portion of the bump includes lead solder for attaching to a contact pad on the semiconductor die.

30. The method of claim 28, wherein the fusible portion of the bump includes eutectic solder for attaching to the surface of the interconnect site.

31. The method of claim 28, further including depositing an underfill material between the semiconductor die and substrate.

32. The method of claim 28, wherein the fusible portion of the bump contacts a sidewall of the interconnect site.

33. A semiconductor device, comprising:

a semiconductor die;

a substrate having an interconnect site formed over a surface of the substrate; and

a bump having a non-collapsible portion and a fusible portion, wherein the bump is bonded between the interconnect site and the semiconductor die, the non-collapsible portion of the bump maintaining vertical standoff between the semiconductor die and substrate, wherein a width of the interconnect site is less than one-half a width of the bump.

34. The semiconductor device of claim 33, wherein the non-collapsible portion of the bump includes lead solder for attaching to a contact pad on the semiconductor die and the fusible portion of the bump includes eutectic solder for attaching to a surface of the interconnect site.

35. The semiconductor device of claim 33, further including an underfill material deposited between the semiconductor die and substrate.

36. The semiconductor device of claim 33, wherein the fusible portion of the bump contacts a sidewall of the interconnect site.

* * * * *