



US00RE45365E

(19) **United States**
(12) **Reissued Patent**
Loechelt et al.

(10) **Patent Number:** **US RE45,365 E**
(45) **Date of Reissued Patent:** ***Feb. 10, 2015**

(54) **SEMICONDUCTOR DEVICE HAVING A VERTICALLY-ORIENTED CONDUCTIVE REGION THAT ELECTRICALLY CONNECTS A TRANSISTOR STRUCTURE TO A SUBSTRATE**

(71) Applicant: **Semiconductor Components Industries, LLC, Phoenix, AZ (US)**

(72) Inventors: **Gary H. Loechelt, Tempe, AZ (US); John M. Parsey, Jr., Phoenix, AZ (US); Peter J. Zdebel, Gilbert, AZ (US); Gordon M. Grivna, Mesa, AZ (US)**

(73) Assignee: **Semiconductor Components Industries, Phoenix, AZ (US)**

(*) Notice: This patent is subject to a terminal disclaimer.

(21) Appl. No.: **14/019,375**

(22) Filed: **Sep. 5, 2013**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **7,902,601**
Issued: **Mar. 8, 2011**
Appl. No.: **12/335,730**
Filed: **Dec. 16, 2008**

U.S. Applications:

(60) Continuation of application No. 13/659,077, filed on Oct. 24, 2012, now Pat. No. Re. 44,547, which is an application for the reissue of Pat. No. 7,902,601, which is a division of application No. 11/582,889, filed on Oct. 19, 2006, now Pat. No. 7,482,220, which is a continuation-in-part of application No. 11/057,140, filed on Feb. 15, 2005, now Pat. No. 7,176,524.

(51) **Int. Cl.**
H01L 29/66 (2006.01)

(52) **U.S. Cl.**
USPC **257/339**; 257/133; 257/139; 257/140; 257/146; 257/147; 257/162; 257/342; 257/900; 257/E29.013; 257/E29.174; 257/E29.243; 257/E29.26

(58) **Field of Classification Search**
USPC 257/133, 139, 140, 146, 147, 162, 339, 257/342, 900, E29.013, E29.174, E29.243, 257/E29.26

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,216,275 A 6/1993 Chen
5,438,215 A 8/1995 Tihanyi
5,571,738 A * 11/1996 Krivokapic 438/291

(Continued)

OTHER PUBLICATIONS

Deboy, G. et al., "A New Generation of High Voltage MOSFETs Breaks the Limit Line of Silicon," IEDM '98, Dec. 6-9, 1998—pp. 683-685.

(Continued)



Primary Examiner — Long K Tran

(74) *Attorney, Agent, or Firm* — Abel Law Group, LLP; Kevin B. Jackson

(57) **ABSTRACT**

In one embodiment, a semiconductor device is formed in a body of semiconductor material. The semiconductor device includes a charge compensating trench formed in proximity to active portions of the device. The charge compensating trench includes a trench filled with various layers of semiconductor material including opposite conductivity type layers.

20 Claims, 14 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

5,872,421 A 2/1999 Potter
 5,998,288 A 12/1999 Gardner
 6,184,555 B1 2/2001 Tihanyi
 6,191,446 B1 2/2001 Gardner
 6,210,999 B1 4/2001 Gardner
 6,255,152 B1 7/2001 Chen
 6,274,904 B1 8/2001 Tihanyi
 6,278,165 B1 8/2001 Oowaki
 6,355,955 B1 3/2002 Gardner
 6,410,955 B1 6/2002 Baker
 6,465,869 B2 10/2002 Ahlers
 6,479,352 B2 11/2002 Blanchard
 6,498,382 B2 12/2002 Hirler et al.
 6,509,240 B2 1/2003 Ren
 6,512,267 B2 1/2003 Kinzer
 6,541,817 B1 4/2003 Hurkx
 6,576,516 B1* 6/2003 Blanchard 438/268

6,608,350 B2 8/2003 Kinzer
 6,693,338 B2 2/2004 Saitoh
 6,878,989 B2 4/2005 Izumisawa
 6,919,610 B2 7/2005 Saitoh
 7,019,360 B2* 3/2006 Blanchard et al. 257/329
 7,176,524 B2 2/2007 Loechelt
 7,253,477 B2 8/2007 Loechelt
 7,285,823 B2 10/2007 Loechelt
 7,902,601 B2 3/2011 Loechelt
 2001/0035561 A1 11/2001 Hirler et al.
 2004/0206989 A1* 10/2004 Aida et al. 257/263
 2005/0280085 A1 12/2005 Babcock et al.

OTHER PUBLICATIONS

Lorenz, L. et al., "COOLMOS™—a New Milestone in High Voltage Power MOS," ISPSD '99, May 26-28, 1999, pp. 3-10.
 Rub, M. et al., "A novel Trench concept for the Fabrication of Compensation Devices," ISPSD '03, Apr. 14-17, 2003, pp. 203-206.

* cited by examiner




FIG. 1




FIG. 2 10




FIG. 3

10




FIG. 4

10




FIG. 5




FIG. 6

10




FIG. 7




FIG. 8

ON-STATE OUTPUT RESISTANCE




FIG. 9





FIG. 10

FIG. 12






FIG. 11 10




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17

1

**SEMICONDUCTOR DEVICE HAVING A
VERTICALLY-ORIENTED CONDUCTIVE
REGION THAT ELECTRICALLY CONNECTS
A TRANSISTOR STRUCTURE TO A
SUBSTRATE**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue; a claim printed with strikethrough indicates that the claim was canceled, disclaimed, or held invalid by a prior post-patent action or proceeding.

RELATED U.S. APPLICATION DATA

[The present application is] *This application is a continuation reissue of and claims benefit under 35 U.S.C. §120 to U.S. application Ser. No. 13/659,077, now U.S. Pat. No. Re. 44,547, which is an application for reissue of U.S. Pat. No. 7,902,601 (U.S. application Ser. No. 12/335,730). More than one reissue application has been filed for U.S. Pat. No. 7,902,601. U.S. Pat. No. 7,902,601 issued from a divisional application based on prior U.S. application Ser. No. 11/582,889 now U.S. Pat. No. 7,482,220 filed on Oct. 19, 2006, which is a continuation-in-part application based on U.S. application Ser. No. 11/057,140 now U.S. Pat. No. 7,176,524 filed on Feb. 15, 2005. **[Both of these documents]** *U.S. application Ser. Nos. 13/659,077, 11/582,889, and 11/057,140* are hereby incorporated by reference, and priority thereto for common subject matter is hereby claimed.*

BACKGROUND OF THE INVENTION

This invention relates generally to semiconductor devices, and more specifically to power switching devices and methods of their manufacture.

Metal-oxide semiconductor field effect transistors (MOSFETs) are a common type of power switching device. A MOSFET device includes a source region, a drain region, a channel region extending between the source and drain regions, and a gate structure provided adjacent to the channel region. The gate structure includes a conductive gate electrode layer disposed adjacent to and separated from the channel region by a thin dielectric layer.

When a MOSFET device is in the on state, a voltage is applied to the gate structure to form a conduction channel region between the source and drain regions, which allows current to flow through the device. In the off state, any voltage applied to the gate structure is sufficiently low so that a conduction channel does not form, and thus current flow does not occur. During the off state, the device must support a high voltage between the source and drain regions.

Today's high voltage power switch market is driven by two major parameters: breakdown voltage (BV_{dss}) and on-state resistance (R_{dson}). For a specific application, a minimum breakdown voltage is required, and in practice, designers typically can meet a BV_{dss} specification. However, this is often at the expense of R_{dson}. This trade-off in performance is a major design challenge for manufacturers and users of high voltage power switching devices.

Recently, superjunction devices have gained in popularity to improve the trade-off between R_{dson} and BV_{dss}. In a conventional n-channel superjunction device, multiple heavily-doped diffused n-type and p-type regions replace one lightly doped n-type epitaxial region. In the on state, current flows through the heavily doped n-type regions, which lowers

2

R_{dson}. In the off or blocking state, the heavily doped n-type and p-type regions deplete into or compensate each other to provide a high BV_{dss}. Although superjunction devices look promising, significant challenges still exist in manufacturing them.

Another problem with present high voltage power switch products is that they typically require a large input (e.g., gate or control electrode) charge for switching from one state to another. This requirement places, among other things, an extra burden on peripheral control circuitry.

Accordingly, high voltage power switching device structures and methods of manufacture are needed that provide lower R_{dson}, high BV_{dss}, and that reduce input charge.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 illustrates an enlarged partial cross-sectional view of a switching device in accordance with the present invention;

FIGS. 2-7 illustrate enlarged partial cross-sectional views of the switching device of FIG. 1 at various stages of fabrication;

FIG. 8 is graph showing a breakdown voltage characteristic for the switching device of FIG. 1;

FIG. 9 is a graph showing on-state resistance characteristic for the switching device of FIG. 1;

FIG. 10 illustrates an enlarged partial top view of a cell structure suitable for a switching device in accordance with the present invention;

FIG. 11 illustrates an enlarged partial cross-sectional view of a switching device and edge termination structure in accordance with the present invention;

FIG. 12 illustrates an enlarged partial top view of an alternative trench isolation structure in accordance with the present invention;

FIG. 13 illustrates an enlarged partial cross-sectional view of the trench isolation structure of FIG. 12 taken along reference line 13-13 at an early stage of fabrication;

FIG. 14 illustrates an enlarged partial cross-sectional view of the structure of FIG. 13 after further processing;

FIG. 15 illustrates an enlarged partial cross-sectional view of a further trench isolation structure in accordance with the present invention;

FIG. 16 illustrates an enlarged partial cross-sectional view of an alternative embodiment of a charge compensation trench structure; and

FIG. 17 illustrates an enlarged partial cross-sectional view of a further embodiment of a charge compensation trench structure.

DETAILED DESCRIPTION OF A PREFERRED
EMBODIMENT

For ease of understanding, elements in the drawing figures are not necessarily drawn to scale, and like element numbers are used where appropriate throughout the various figures. While the discussion below describes an n-channel device, the invention also pertains to p-channel devices, which may be formed by reversing the conductivity type of the described layers and regions.

In addition, the device of the present invention may embody either a cellular design (where the body regions are a plurality of cellular regions) or a single body design (where the body region is comprised of a single region formed in an elongated pattern, typically in a serpentine pattern). However, the device of the present invention will be described as a cellular design throughout the description for ease of under-

standing. It should be understood that it is intended that the present invention encompass both a cellular design and a single base design.

FIG. 1 shows an enlarged partial cross-sectional view of an insulated gate field effect transistor (IGFET), MOSFET, superjunction device, or switching device or cell **10** in accordance with the present invention. By way of example, device **10** is among many such devices integrated with logic and/or other components into a semiconductor chip as part of a power integrated circuit. Alternatively, device **10** is among many such devices integrated together to form a discrete transistor device.

Device **10** includes a region of semiconductor material **11**, which comprises for example, an n-type silicon substrate **12** having a resistivity in a range of approximately 0.001 to about 0.005 ohm-cm, and may be doped with arsenic. In the embodiment shown, substrate **12** provides a drain contact. A semiconductor layer **14** is formed in or on substrate **12**, and in accordance with the present invention is lightly doped n-type or p-type, or contains negligible amounts of impurities (i.e., is intrinsic). In an exemplary embodiment, layer **14** is formed using conventional epitaxial growth techniques. In an exemplary embodiment suitable for a 750 volt device, layer **14** is p-type with a dopant concentration of about 1.0×10^{13} atoms/cm³ to about 5.0×10^{13} atoms/cm³, and has a thickness on the order of about 40 microns. The thickness of layer **14** is increased or decreased depending on the desired BV_{dss} rating of device **10**. It is understood that other materials may be used for body of semiconductor material **11** or portions thereof including silicon-germanium, silicon-germanium-carbon, carbon doped silicon, or the like.

Device **10** also includes an n-type region or blanket layer **17** formed in or adjacent to upper or major surface **18** of region of semiconductor material **11**. N-type region **17** provides a low resistance current path for device **10** as will be described in more detail below. In an exemplary embodiment, n-type region **17** has a maximum concentration on the order of about 6.0×10^{16} atoms/cm³, and a depth of about 0.4 microns. Optionally, a p-type region or blanket layer **19** is formed in or adjacent to major surface **18**, and is below or adjacent to n-type region **17**. P-type region **19** provides better control of the pn junction between n-type region **17** and semiconductor layer **14**, and provides charge compensation for n-type region **17** under full depletion conditions. In an exemplary embodiment, p-type region **19** has surface concentration of about 5.0×10^{15} atoms/cm³, and a depth of about 0.8 microns.

Device **10** further includes filled trenches, semiconductor material filled trenches, epitaxial filled regions or trenches, charge compensating trench regions, deep trench charge compensation regions, charge compensating filled trenches or charge compensation regions **22** in accordance with the present invention. Charge compensating filled trenches **22** include a plurality of layers or multiple layers of semiconductor material, including layers of opposite conductivity type, which are preferably separated by an intrinsic or buffer semiconductor layer or layers. The intrinsic layer functions, among other things, to prevent intermixing of the opposite conductivity type layers (i.e., the two charge layers), which would negatively impact the conduction efficiency of device **10** in the on state.

In an exemplary embodiment, filled trenches **22** include multiple layers or stacked layers of semiconductor material formed using epitaxial growth techniques. For example, filled trenches **22** include an n-type layer **23** formed on, over, or adjoining the trench walls or surfaces adjacent to body of semiconductor material **11**. An intrinsic semiconductor or

buffer layer **24** is formed on, over, or adjoining n-type layer **23**, a p-type layer **26** is formed on, over, or adjoining intrinsic semiconductor layer **24**, and an intrinsic semiconductor or buffer layer **27** is formed on, over, or adjoining p-type layer **26**. Intrinsic layer **24** functions, among other things, to prevent the mixing of layers **23** and **26**, which, as stated previously, improves the conduction efficiency of device **10**. Intrinsic layer **27** functions, among other things, to fill the remainder of the trench. For an n-channel device and in accordance with the present invention, n-type layers **23** provide a primary vertical low resistance current path from the channel to the drain when device **10** is in an on state. When device **10** is an off state, n-type layers **23** and p-type layers **26** compensate each other in accordance with the present invention to provide an increased BV_{dss} characteristic. It is understood that additional n-type and p-type layers may be used, and preferably separated by additional intrinsic or buffer layers.

By way of example, n-type layers **23** and p-type layers **26** each have a dopant concentration on the order of about 2.0×10^{16} to about 4.0×10^{16} atoms/cm³, and each have a thickness of about 0.1 microns to about 0.3 microns. In an exemplary embodiment, intrinsic semiconductor or buffer layers **24** and **27** are undoped or very lightly doped p-type with a dopant concentration of less than about 2.0×10^{14} atoms/cm³, and each has a thickness of about 0.5 microns to about 1.0 microns. The thickness of layer **27** is adjusted, for example, to fill the balance of the trench.

A body or doped region **31** is formed in semiconductor layer **14** between and in proximity or adjacent to filled trenches **22**, and extends from major surface **18**. In an exemplary embodiment, body region **31** comprises p-type conductivity, and has a dopant concentration suitable for forming an inversion layer that operates as conduction channels **45** of device **10** as described below. Body region **31** extends from major surface **18** to a depth of about 1.0 to about 5.0 microns. An n-type source region **33** is formed within or in body region **31** and extends from major surface **18** to a depth of about 0.2 microns to about 0.5 microns. A p-type body contact or contact region **36** is also formed in body region **31**, and provides a lower contact resistance to body region **31** at major surface **18**. In addition, contact region **36** lowers the sheet resistance of body region **31** under source region **33**, which suppresses parasitic bipolar effects.

A first dielectric layer **41** is formed over or adjoining portions of major surface **18**. In an exemplary embodiment, dielectric layer **41** comprises a thermal oxide layer having a thickness of about 0.1 microns to about 0.2 microns. A second dielectric layer **42** is formed over dielectric layer **41**. In an exemplary embodiment, second dielectric layer **42** comprises silicon nitride, and has a thickness of about 0.1 microns.

Gate dielectric layers **43** are formed over or adjoining other portions of major surface **18** adjacent to body region **31**. In an exemplary embodiment, gate dielectric layer **43** comprises silicon oxide, and has a thickness of about 0.05 microns to about 0.1 microns. In alternative embodiments, gate dielectric layer **43** comprises silicon nitride, tantalum pentoxide, titanium dioxide, barium strontium titanate, or combinations thereof including combinations with silicon oxide, or the like.

In accordance with an embodiment of the present invention, a doped polycrystalline semiconductor layer, conductive layer, or ground plane layer **46** is formed over dielectric layers **41** and **42**, and contacts p-type layers **26** through openings **47** formed in dielectric layers **41** and **42**. In an exemplary embodiment, conductive layer **46** comprises a polysilicon layer, has a thickness of about 0.1 microns, and has p-type conductivity for an n-channel device. When heat treated, p-type dopant from conductive layer **46** diffuses into filled

5

trenches **22** to form p-type doped regions **52**, which enhance ohmic contact to p-type layers **26**. In an alternative embodiment, conductive layer **46** comprises amorphous silicon, a metal, a silicide, or combinations thereof including combinations with polysilicon. If a metal is used for conductive layer **46**, p-type dopant is first implanted or deposited through openings **47** to form p-type doped regions **52** to enhance ohmic contact to p-type layers **26**. Conductive layer **46** preferably is tied or coupled directly or indirectly to a conductive contact or source contact layer **63** as shown in FIG. 1.

In accordance with the present invention, conductive layer **46** functions, among other things, as a ground plane to provide a path for minority carriers to be swept from or out of the device faster and more efficiently, which reduces the input charge required for switching device **10** from one state to another and enhances switching speed. Additionally, as will be explained in more detail below, conductive layer **46** is further used as part of an edge termination structure in accordance with the present invention.

A third dielectric layer **48** is formed over conductive layer **46**, and a fourth dielectric layer **51** is formed over third dielectric layer **48**. In an exemplary embodiment, dielectric layer **48** comprises silicon nitride (e.g., about 0.05 microns in thickness), and dielectric layer **51** comprises a deposited silicon oxide (e.g., about 0.7 microns in thickness). A conductive layer **53** is formed over dielectric layer **51**, and comprises for example, n-type polysilicon (e.g., about 0.3 microns in thickness).

Conductive spacer gate regions, vertical spacer gate regions, or spacer defined gate regions **57** are formed over gate dielectric layers **43**, and are isolated from conductive layer **46** by dielectric spacers **59**. Conductive spacer gate regions **57** together with gate dielectric layers **43** form a control electrode or gate structure **58**. Conductive spacer gate regions **57** comprise, for example, n-type polysilicon, and are about 0.8 microns in thickness. In an exemplary embodiment, dielectric spacers **59** comprise silicon nitride, and are about 0.1 microns in thickness. Spacer gate regions **57** are coupled to conductive layer **53** to provide a conductive gate structure, which controls the formation of channel **45** and the conduction of current in device **10**. In the embodiment shown, a conductive connective portion **77** couples spacer gate regions **57** to conductive layers **53**. Conductive connective portions **77** comprise for example, n-type polysilicon. A spacer gate region refers to a control electrode formed with gate material deposited on one surface to control a channel formed on another perpendicular surface. In the case of device **10**, channels **45** are formed at surface **18**, which is considered a horizontal surface. The control electrode film used to form spacer gate regions **57** is deposited along vertical surfaces **68**, which are perpendicular to surface **18**.

Conductive spacer gate regions **57** in accordance with the present invention provide a minimal gate to drain overlap compared to conventional devices, thereby significantly reducing gate charge. Additionally, in device **10** the electrical routing for the gate is provided by conductive layer **53**, which is elevated above major surface **18** thereby further reducing gate charge. Further, conductive layer **46** functions, among other things, as a ground plane interposed between the gate and drain regions to further reduce gate to drain capacitance. These features of the present invention provide enhanced switching speed and reduced input charge requirements.

A fifth dielectric layer **61** is formed over portions of device **10**, and comprises for example, silicon nitride having thickness of about 0.05 microns. An interlayer dielectric (ILD) layer **62** is formed over portions of device **10**, and comprises for example, a deposited silicon oxide having a thickness of

6

about 0.8 microns. An opening is formed in the dielectric layers to provide a contact to device **10** for source contact layer **63**. As shown, a portion of major surface **18** is etched so that source contact layer **63** makes contact to both source regions **33** and body region **36**. In an exemplary embodiment, source contact layer **63** comprises an aluminum silicon alloy or the like. A drain contact layer **66** is formed on an opposing surface of region of semiconductor material **11**, and comprises, for example, a solderable metal structure such a titanium-nickel-silver, chrome-nickel-gold, or the like.

The operation of device **10** proceeds as follows. Assume that source terminal **63** is operating at a potential V_S of zero volts, spacer gate regions **57** receive a control voltage $V_G=5.0$ volts, which is greater than the conduction threshold of device **10**, and drain terminal **66** operates at drain potential $V_D=5.0$ volts. The values of V_G and V_S cause body region **31** to invert under spacer gate regions **57** to form channels **45**, which electrically connect source regions **33** to layer **17**. A device current I_S flows from source terminal **63** and is routed through source regions **33**, channel **45**, layer **17**, n-type layers **23** to drain terminal **66**. Hence, current I_S flows vertically through n-type layers **23** to produce a low on resistance. In one embodiment, $I_S=1.0$ amperes. To switch device **10** to the off state, a control voltage V_G of less than the conduction threshold of device is applied to spacer gates **57** (e.g., $V_G<5.0$ volts). This removes channels **45**, I_S no longer flows through device **10**, and conductive layer **46** sweeps minority carriers out of the device. In the off state, n-type layers **23** and p-type layers **26** compensate each other as the depletion region from the primary blocking junction spreads, which enhances BV_{dss} . In one embodiment, the primary blocking junction is formed by body region **31** and semiconductor layer **14** when layer **14** is n-type. In another embodiment, the primary blocking junction is formed by semiconductor layer **14** and substrate **12** when layer **14** is p-type.

Turning now to FIGS. 2-7, a process for forming device **10** in accordance with the present invention is described. FIG. 2 shows an enlarged partial cross-sectional view of device **10** at an early stage of fabrication. In an early step, a dielectric layer **40** is formed over major surface **18**, and optional p-type region **19** is ion implanted into semiconductor layer **14** through dielectric layer **40**. In an exemplary embodiment, boron is implanted at a dose of about 5.0×10^{11} atoms/cm² and an implant energy of 600 KeV to form p-type layer **19**. Next n-type layer **17** is ion implanted into semiconductor layer **14** through dielectric layer **40**. In an exemplary embodiment, phosphorous is implanted at a dose of about 2.0×10^{12} atoms/cm² and an implant energy of 600 KeV to form n-type layer **17**.

Masking layer **71** is then formed over major surface **18** and patterned to form openings **72**. Dielectric layer **40** is then etched using conventional techniques to expose portions of body of semiconductor material **11** through openings **72**. By way of example, openings **72** have a width **74** on the order of about 3.0 microns to about 5.0 microns. Next, trenches **122** are etched through layers **17**, **19**, and **14**. In an exemplary embodiment, trenches **122** extend into at least a portion of substrate **12**. The depth of trenches **122** is determined by the thickness of semiconductor layer **14**, which is a function of BV_{dss} . In an exemplary embodiment, Deep Reactive Ion Etching (DRIE) etching with a fluorine or chlorine based chemistry is used to form trenches **122**. Several techniques are available for DRIE etching including cryogenic, high density plasma, or Bosch DRIE processing. In an exemplary embodiment, trenches **122** have substantially vertical sidewalls. In an alternative embodiment, trenches **122** have a tapered profile where the width of the trench at the trench

lower surface is less than width 74. Masking layer 71 is removed after trenches 122 are formed using conventional etch techniques. Although trenches 122 are stated as plural, it is understood that trenches 122 may be a single continuous trench or connected trench matrix (e.g., such as that shown in FIG. 10 and described below). Alternatively, trenches 122 may be a plurality of individual trenches with closed ends and separated by portions of body of semiconductor material 11.

FIG. 3 shows an enlarged partial cross-sectional view of device 10 at a further stage of processing. At this point, layers of semiconductor material are formed, grown, or deposited in trenches 122 as a first stage in forming filled trenches 22. In an exemplary embodiment, semiconductor epitaxial growth techniques are used to fill trenches 122.

In a first step, a thin thermal oxide is formed on the side-walls of trenches 122 to remove any surface damage caused by the DRIE step. The thin thermal oxide is then removed using conventional isotropic etching techniques. Next, body of semiconductor material 11 is placed into an epitaxial growth reactor and pre-cleaned as a first step of the epitaxial growth process. When silicon is the selected semiconductor material for the fill layers (e.g., layers 23, 24, 26, and 27), silicon source gases such as SiHCl_3 , SiH_2Cl_2 , SiH_4 or Si_2H_6 are suitable for forming these layers. In the embodiment shown, blanket layers are grown (i.e., the layers are grown over major surface 18 in addition to trenches 122). In an alternative embodiment, selective epitaxial growth techniques are used to form layers 23, 24, 26, and 27 so that these layers are not formed over dielectric layer 40.

N-type layer 23 is grown first along the surfaces of trenches 122, with arsenic being a suitable dopant source. In an exemplary embodiment, n-type layer 23 has a dopant concentration on the order of about 2.0×10^{16} to about 4.0×10^{16} atoms/cm³, and a thickness of about 0.1 microns to about 0.3 microns.

Next, intrinsic or buffer layer 24 is grown over n-type layer 23, and is either undoped (except for those trace impurities typically present in the silicon source material and/or residual dopant gases remaining in the reactor chamber after the previous growth step), or is very lightly doped p-type with a dopant concentration of less than about 2.0×10^{14} atoms/cm³. Layer 24 has a thickness of about 0.5 microns to about 1.0 microns. P-type layer 26 is then grown over layer 24, with a boron dopant source being suitable. In an exemplary embodiment, p-type layer 26 has a dopant concentration on the order of about 2.0×10^{16} to about 4.0×10^{16} atoms/cm³, and a thickness of about 0.1 microns to about 0.3 microns. Intrinsic or buffer layer 27 is then grown over p-type layer 26, and is either undoped (except for those trace impurities typically present in the silicon source material and/or residual dopant gases remaining in the reactor chamber after the previous growth step), or is very lightly doped p-type with a dopant concentration of less than about 2.0×10^{14} atoms/cm³. Layer 27 has a thickness of about 0.5 microns to about 1.0 microns. It should be understood that the thicknesses of layers 23, 24, 26, and 27 are adjusted depending on the width of trenches 122. In an exemplary embodiment, the thicknesses of these layers are such that the resultant epitaxial layers overfill trenches 122. When a blanket epitaxial growth process is used, layers 27, 26, 24, and 23 are subsequently planarized with chemical mechanical polishing techniques, etch-back techniques, combinations thereof, or the like. During the planarization process, epi layers 27, 26, 24, and 23 are planarized down or back to major surface 18 to form filled trenches 22. In an exemplary embodiment, the planarization process removes dielectric layer 40 as well. An additional etching step may be used to further remove any residual dielectric material from layer 40. If selective epitaxial growth or selective etch

back techniques are used, dielectric layer 40 may remain, and would replace layer 41 as described hereinafter.

FIG. 4 shows an enlarged partial cross-sectional view of device 10 after further processing. First dielectric layer 41 is formed over major surface 18, and comprises for example, a silicon oxide about 0.1 microns to about 0.2 microns thick. A thermal oxide grown at about 750 degrees Celsius is suitable. In an optional step, a sputter etch step is used to smooth the upper or exposed surface of first dielectric layer 41. Next, second dielectric layer 42 is formed over dielectric 41, and comprises, for example, about 0.1 microns of silicon nitride. A contact photolithography and etch step is then used to form openings 47 through second dielectric layer 42 and first dielectric layer 41. This exposes a portion of major surface 18 above filled trenches 22 as shown in FIG. 4. In an exemplary embodiment, opening 47 has a width 49 on the order of about 0.5 microns to about 1.0 microns.

Conductive layer 46 is then formed over second dielectric layer 42 and contacts or couples to filled trenches 22 through openings 47. In an exemplary embodiment, conductive layer 46 comprises about 0.1 microns of polysilicon, and is either deposited doped or undoped. If conductive layer 46 is deposited initially undoped, conductive layer 46 is subsequently doped using, for example, ion implantation techniques. In this exemplary embodiment, conductive layer 46 is doped with boron to provide a contact to p-type layer 26. A boron ion implant dose of about 5.0×10^{15} to about 1.0×10^{16} atoms/cm² with an implant energy of about 60 KeV is sufficient for doping conductive layer 26. During a subsequent heat treatment step, dopant from conductive layer 46 diffuses into filled trenches 22 to form p-type regions 52.

Next, third dielectric layer 48 is formed over conductive layer 46, and fourth dielectric layer 51 is formed over third dielectric layer 48. Third dielectric layer 48 comprises, for example, silicon nitride (e.g., about 0.05 microns in thickness), and dielectric layer 51 comprises a deposited oxide (e.g., about 0.7 microns in thickness). Conductive layer 53 is then formed over fourth dielectric layer 51, and comprises for example, n-type polysilicon (e.g., about 0.3 microns in thickness). A protective layer 54 is formed over conductive layer 53, and comprises for example, about 0.15 microns of silicon nitride.

A photolithographic and etch step is done to etch through portions of layers 54, 53, 51, 48, 46 and 42 to provide opening 70. This also forms pedestal stack structures 56, which are comprised of portions of layers 42, 46, 48, 51, 53 and 54. In an exemplary embodiment, opening 70 has a width 73 on the order of about 5.0 microns to about 8.0 microns.

FIG. 5 shows an enlarged partial cross-sectional view of device 10 after additional processing steps that form dielectric spacers 59. In an exemplary embodiment, a silicon nitride film is deposited over pedestal stack structures 56 and first dielectric layer 41. By way of example, a silicon nitride film about 0.1 microns thick is deposited using chemical vapor deposition techniques. Next, a conventional anisotropic etch back step is used to remove portions of the silicon nitride layer over pedestal stack structures 56 and first dielectric layer 41 while leaving portions of the silicon nitride layer on sidewalls or vertical surfaces 68 of pedestal stack structures 56 to form dielectric spacers 59.

A silicon oxide wet etch is then used to remove portions of dielectric layer 41 within opening 70. By way of example, a diluted hydrofluoric acid (e.g., 50:1) is used to etch dielectric layer 41. In an exemplary embodiment, the etch time is prolonged (e.g., 8 to 15 minutes) in order to undercut or remove material from dielectric layer 41 from beneath dielectric spacers 59 to form recessed portions 74. Recessing dielectric

layer **41** in this manner ensures that channels **45** (shown in FIG. **1**) formed in body region **31** extend into layer **17** to allow channel current to flow more efficiently. In an exemplary embodiment, portions **74** are recessed under dielectric spacers **59** a distance of about 0.1 microns. A thermal silicon oxide is then grown on major surface **18** within opening **70** to thickness of about 0.08 microns to form gate dielectric layer **43**.

FIG. **6** shows an enlarged partial cross-sectional view of device **10** after further processing. A conformal layer of semiconductor material is deposited over device **10** to a thickness of about 0.1 microns to about 0.15 microns. Boron dopant is then introduced through opening **70** and the conformal layer of semiconductor material into major surface **18** to provide p-type dopant for body region **31**. In an exemplary embodiment, the conformal layer of semiconductor material comprises undoped polysilicon, and the boron is implanted through the undoped polysilicon into layer **17**. An ion implant dose of about 1.0×10^{13} atoms/cm² and an implant energy of about 160 KeV is suitable for a 650 volt device. After the implant step, a clean or etch process is used to clean the surface of the conformal layer of semiconductor material.

A second conformal layer of semiconductor material is then deposited over the first conformal layer and both layers are etched to provide spacer gates **57**. In an exemplary embodiment, the second conformal layer of semiconductor material comprises about 0.8 microns of n-type polysilicon, which may be doped during the deposition process or doped subsequently using ion implantation or other doping techniques. After spacer gates **57** are formed, an additional 0.015 microns of gate dielectric (e.g., silicon oxide) is added to the surface of spacer gates **57** and exposed portions of gate oxide **43**.

In an exemplary embodiment, the etch step exposes dielectric layer **54** and the upper portions of dielectric spacers **59**. Protective layer **54** and the upper portions of dielectric spacers **59** are then etched so that protective layer **54** is removed, and upper portions of dielectric spacers **59** are removed between spacer gates **57** and conductive layers **53**.

In a further step, conductive material such as polysilicon is deposited to provide connective conductive portions **77**. Connective conductive portions **77** couple or electrically connect spacer gates **57** to conductive layers **53**. An n-type doping step is then done to dope connective conductive portions **77**, and to provide dopant for source regions **33**. In an exemplary embodiment, an arsenic implant dose of 3.0×10^{15} atoms/cm² with an implant energy of 80 KeV is used for this doping step.

FIG. **7** shows an enlarged partial cross-sectional view of device **10** after further steps in fabrication. Fifth dielectric layer **61** is deposited, and comprises for example, about 0.05 microns of silicon nitride. ILD layer **62** is then deposited over fifth dielectric layer **61**. In an exemplary embodiment, ILD layer **62** comprises a deposited silicon oxide about 0.8 microns in thickness. An optional ILD taper etch is used to taper portions **62a** of ILD layer **62**, which helps with step coverage for subsequently formed layers.

Next, a conventional photolithographic and etch step is used to form contact opening **81**, which exposes a portion of major surface **18**. Contact region **36** is then formed through opening **81** using a p-type ion implantation step. By way of example, a boron ion implant dose of 3.0×10^{14} atoms/cm² and an implant energy of 80 KeV is used. A conformal spacer layer is then deposited and etched to form spacers **82**. In an exemplary embodiment, a 0.3 micron layer of silicon nitride is deposited and etched to form spacers **82**. A rapid anneal step is used at this point to activate and diffuse the various ion

implants. For example, device **10** is exposed to a temperature of about 1030 degrees Celsius for about 45 seconds.

An etch step is then used to remove a portion of major surface **18** to form recessed portion **84**. This allows source contact layer **63** to contact both source regions **33** and contact region **36**, which shorts these regions together. Spacers **82** are then removed. In subsequent processing, source contact layer **63** is deposited and patterned. Substrate **12** is then optionally thinned, and drain contact layer **66** is deposited to provide the structure shown in FIG. **1**. Although not shown in FIGS. **2-7**, a photolithographic and etch step is used during the fabrication stages described for example, in FIGS. **4-6** to expose portions of conductive layer **46** to provide openings where source contact region **63** couples to conductive layer **46** as shown in FIG. **1**. It is further understood that other conductive layers such as silicide layers may be formed before depositing source contact layer **63**.

FIG. **8** is a graph depicting breakdown voltage (BV_{dss}) characteristics for device **10** in accordance with the present invention, and in accordance with the processing parameters described herein. As shown in FIG. **8**, device **10** exhibited a nominal breakdown voltage from drain to source of about 750 volts. Additionally and as shown in FIG. **8**, device further exhibited low leakage below breakdown.

FIG. **9** is a graph depicting on-state resistance (R_{dson}) characteristics for device **10** in accordance with the present invention, and in accordance with the processing parameters described herein. Device **10** exhibits excellent R_{dson} characteristics compared to conventional superjunction devices with similar BV_{dss}, which have typical R_{dson} values on the order of 36 milli-ohm cm².

FIG. **10** shows an enlarged partial cross-sectional view of a cell structure **300** suitable for device **10** in accordance with the present invention. Cell structure **300** is shown with a filled trench **322** in accordance with one embodiment of the present invention that surrounds a plurality **314** of polygonal shaped regions of semiconductor layer **14** where the active devices or cells are formed. It is understood that the polygonal shaped regions may have rounded corners, and that other shapes including round, square, rectangular, or the like are suitable. One feature of cell structure **300** is that it provides for a high packing density, which improves R_{dson} and current carrying capability. In accordance with present invention filled trenches **322** include n-type layers **23**, intrinsic layers **24** and **27**, and p-type layers **26**.

FIG. **11** is an enlarged partial cross-sectional view of another portion of device **10**, which shows an optional edge termination structure **100** in accordance with the present invention. One of the features of termination structure **100** is that it incorporates the basic components of device **10**, which saves on processing costs. Termination structure **100** includes a conductive contact layer or conductive layer **146**, which is formed over and adjacent to major surface **18**. In an exemplary embodiment, conductive contact layer **146** comprises the same material as conductive layer **46**, and is formed at the same time. For example, conductive contact layer **146** comprises p-type polysilicon. After a heat treatment, p-type dopant diffuses from conductive contact layer **146** to form p-type doped layer **152**, which counter-dopes n-type layer **17** and couples to optional p-type layer **19**. FIG. **11** further shows conductive contact layer **146** coupled to source contact layer **63** through opening **91**.

An isolation trench **103** is formed at the periphery of device **10**, and comprises, for example, an etched trench **106** that is filled with a dielectric material **108**. Optionally, a thermal oxide layer **110** is formed first to line the sidewalls and/or the lower surface of isolation trench **103**.

11

In an alternative embodiment and as shown in FIG. 11, isolation trench 103 further includes layers of semiconductor material, which are formed at the same time as filled trenches 22. By way of example, the layers of semiconductor material include n-type layer 23, intrinsic or buffer layer 24, p-type layer 26, and intrinsic or buffer layer 27 as described in conjunction with FIG. 1. If the layers of semiconductor material are excluded, then trench 106 is formed separately from filled trenches 22 during fabrication.

In an exemplary embodiment, dielectric material 108 comprises a silicon oxide formed using spin-on glass (SOG), BPSG, PSG, and/or TEOS deposition techniques. After the oxide is formed, the upper surface of the dielectric region is planarized using etch back or chemical mechanical planarization techniques, combinations thereof, or the like. In an exemplary embodiment, trench 106 has width of about 30 microns to about 100 microns, and is formed using techniques similar to those used to form trenches 122 described in conjunction with FIG. 2. The sidewalls of trench 106 may be substantially vertical, or tapered such that the width at the bottom of trench 106 is less than the width at the top of trench 106. By way of example, dielectric material 108 and/or dielectric layer 110 extends to a depth or distance below semiconductor layer 14 as shown in FIG. 11.

In an alternative embodiment when layers 23, 24, 26, 27 are included with isolation trench 103, an n-type region 109 is incorporated into substrate 12 below trench 106 to reduce any current leakage problems associated with die separation.

In accordance with the present invention, when semiconductor layer 14 comprises p-type conductivity, the primary junction for BV_{dss} is pn junction 114 formed by semiconductor layer 14 and n-type substrate 12. This feature simplifies edge termination structure 100, and saves on space. For example, conventional devices require a distance of about 1 to 3 times the thickness of the epitaxial layer for the termination structure. In the present invention, this distance is reduced to about one half the thickness.

In this embodiment, junction 114 is more planar than in conventional devices because the junction depletes up from substrate 12 instead of down and across from body region 31. Furthermore, since conductive contact layer 146 is coupled to semiconductor layer 14 through doped regions 152 and 19, junction 114 laterally extends to the edge of device 10. In this way, an optimized planar junction with optimized BV_{dss} is realized. Isolation trench 103 functions, among other things, to passivate junction 114.

FIG. 12 shows an enlarged partial top view of an alternative isolation trench 203 in accordance with the present invention. Region 131 designates that portion of device 10 used for the termination structure as described in conjunction with FIG. 11, and region 132 designates that portion of device 10 used for the active structure as described in FIG. 1. Isolation trench 203 includes a plurality or matrix of pillars or shapes 117 that are formed when the isolation trench is etched. In an exemplary embodiment, adjacent rows of shapes 117 are offset with respect to each other as shown in FIG. 12 so that shapes 117 are substantially equidistant from each other. In an exemplary embodiment, pillars 117 are spaced apart about 5 microns to about 15 microns.

By way of example, shapes 117 are pillars or regions of portions of body of semiconductor material 11. In an exemplary embodiment, shapes 117 are comprised of substrate 12, semiconductor layer 14, p-type layer 19, n-type layer 17, and dielectric layer 41, and have a width or diameter of about 0.8 microns to about 1.0 microns. This is more clearly shown in FIG. 13, which is an enlarged cross-sectional view of a portion of isolation trench 203 taken along reference line 13-13

12

of FIG. 12. FIG. 13 shows isolation trench 203 prior to the formation of dielectric material 208. Conventional photolithographic and etch techniques are used to form trenches 206 and shapes 117. For example, DRIE is used with a fluorine or chlorine based chemistry.

After trench 206 and shapes 117 are formed, dielectric layer 210 is formed as shown in FIG. 14. By way of example, dielectric layer 210 comprises a thermally grown silicon oxide. Next, dielectric layer 208 is deposited and planarized. In an exemplary embodiment, dielectric layer 208 comprises a spin-on glass. In accordance with the present invention, shapes 117 reduce dishing effects when dielectric layer 208 is deposited, which provides a more planar surface, better passivation, and a more reliable device. Shapes 117 may be round, square, rectangular, polygonal, trapezoidal, elliptical, triangular, combinations thereof, or the like. The shapes may further include rounded corners.

FIG. 15 shows an enlarged partial cross-sectional view of adjacent or a plurality of isolation trenches 203a and 203b depicted as portions of two devices separated by a scribe grid or region 461. In this embodiment, adjacent devices 10 on a semiconductor wafer include scribe grid 461 that comprises body of semiconductor material 11 instead of dielectric materials 208 and 210 being continuous between adjacent die. This allows a die separation device such as a dicing saw to separate the die along centerline 463, which provides for more robust die separation.

FIG. 16 shows an enlarged partial cross-sectional view of an alternative embodiment of a charge compensating trench region, deep trench charge compensation region, charge compensating filled trench or charge compensation region 122. Charge compensation trench 122 is similar to trench 22 except that a dielectric layer or passivation layer or liner 171 is formed as an innermost layer or region or core of the structure. That is, passivation liner 171 is formed overlying the outermost epitaxial layer (e.g., layer 27) within the trench region.

In one embodiment, liner 171 is configured to compensate for, protect against, or overcome lattice imperfections that may occur in the outermost epitaxially grown layer (e.g., layer 27) as it is formed. Of particular concern is the growth interface that is left when outermost layer 27 fills the trench. The growth interface may have a large concentration of imperfections. Such imperfections lead to undesired stresses, or trap unwanted impurities in certain applications, which lead to undesired conduction channels or short circuit paths in a charge compensated structure (e.g., structure 10). Liner 171 is configured to increase electrical resistance at the core of the charge compensation structure, which prevents unwanted current flow at high electric fields or at high temperatures.

Liner 171 comprises for example, an oxide, a nitride, or a combination of oxide(s) and nitride(s). In one embodiment, liner 171 comprises a dry oxide. In one embodiment, a conventional pre-diffusion clean step is used prior to forming liner 171.

FIG. 17 shows an enlarged partial cross-sectional view of an alternative embodiment of a charge compensating trench region, deep trench charge compensation region, charge compensating filled trench or charge compensation region 222. Charge compensation trench 222 is similar to trench 122 except that a dielectric layer or passivation layer or liner 271 is formed leaving a gap, void, or air gap 272 as the innermost region or core of the structure. In one embodiment, gap 272 extends from major surface 18 into semiconductor layer 14 as shown in FIG. 17. In an alternative embodiment, gap 272 only occupies a portion of the core.

13

In summary, a new switching device structure having deep trench charge compensation has been described including a method of manufacture. Also, a ground plane structure has been described that is suitable for the device of the present invention as well as other semiconductor devices. In addition, 5 edge termination structures have been described that are suitable for the device of the present invention as well as other semiconductor devices.

Although the invention has been described and illustrated with reference to specific embodiments thereof, it is not intended that the invention be limited to these illustrative 10 embodiments. Those skilled in the art will recognize that modifications and variations can be made without departing from the spirit of the invention. Therefore, it is intended that this invention encompass all such variations and modifications 15 as fall within the scope of the appended claims.

We claim:

- [1.** A semiconductor device comprising:
a body of semiconductor material; and
a charge compensation region including a trench formed in the body of semiconductor material, wherein the trench comprises a pair of opposite conductivity type single crystal semiconductor layers overlying surfaces of the trench, and wherein a first intrinsic layer separates the pair, and wherein a passivation liner is formed overlying an outermost one of the pair.]
- [2.** The device of claim 1, wherein the passivation liner comprises an oxide.]
- [3.** The device of claim 1 further comprising a conductive layer coupled to the charge compensation region.]
- [4.** The device of claim 1, wherein the passivation liner comprises a dielectric material.]
- [5.** The device of claim 1, wherein the passivation liner comprises a nitride.]
- [6.** The device of claim 1, wherein the passivation liner comprises an oxide and a nitride.]
- [7.** The device of claim 1, wherein the charge compensation region further includes a void.]
- [8.** The device of claim 7, wherein the void is formed at a centralized portion of the charge compensation region.]
- [9.** A semiconductor device comprising:
a body of semiconductor material; and
a trench formed in the body of semiconductor material;
a first layer comprising a single crystal semiconductor material formed overlying surfaces of the trench, wherein the first layer comprises a first conductivity type;
a first intrinsic layer formed overlying the first layer;
a second layer comprising a single crystal semiconductor material formed overlying the first intrinsic layer, wherein the second layer comprises a second conductivity type, and wherein the first intrinsic layer is configured to reduce intermixing of dopants between the first and second layers; and
a passivation layer formed overlying the second layer to form a charge compensation region.]
- [10.** The device of claim 9 further comprising a conductive layer coupled to the charge compensation region.]
- [11.** The device of claim 9, wherein the trench includes a void.]
- [12.** The device of claim 9, wherein the passivation layer comprises a dry oxide layer.]
- [13.** A semiconductor device comprising:
a body of semiconductor material having first and second opposing major surfaces;
a trench formed in the body of semiconductor material;

14

- a first semiconductor layer of a first conductivity type formed adjoining surfaces of the trench;
a first intrinsic layer formed adjoining the first semiconductor layer;
a second semiconductor layer of a second conductivity type formed adjacent to the first intrinsic to form a charge compensated region;
a passivation layer formed overlying the second semiconductor layer;
a first doped region in the body of semiconductor material formed adjacent the charge compensated region, wherein the first doped region comprises the second conductivity type;
a second doped region formed in the first doped region and comprising the first conductivity type; and
a control electrode formed adjacent the first and second doped regions.]
- [14.** The device of claim 13 further comprising a conductive layer coupled to the charge compensated region.]
- [15.** The device of claim 13, wherein the control electrode comprises a spacer gate structure.]
- [16.** The device of claim 13, wherein the passivation layer comprises an oxide layer.]
- [17.** The device of claim 13, wherein the passivation layer comprises a nitride layer.]
- [18.** The device of claim 13, wherein the passivation layer comprises an oxide layer and a nitride layer.]
- [19.** The device of claim 13, wherein the charge compensated region has a void.]
- 20.** *A semiconductor device comprising:*
a substrate;
a semiconductor layer overlying the substrate, wherein the semiconductor layer has a major surface spaced apart from the substrate;
a vertically-oriented conductive region adjacent to the major surface and extending towards the substrate;
a horizontally-oriented doped region of a first conductivity type adjacent to the major surface;
a body region of a second conductivity type adjacent to another portion of the major surface, wherein the horizontally-oriented doped region adjoins the body region;
a first conductive layer configured to reduce gate to drain capacitance; and
a gate electrode spaced apart from and electrically insulated from the body region and the horizontally-oriented doped region,
wherein:
a transistor structure of the semiconductor device comprises the horizontally-oriented doped region, the body region, and the gate electrode;
the first conductive layer is electrically connected to the transistor structure; and
the vertically-oriented conductive region electrically connects the transistor structure and the substrate to each other.
- 21.** *The device of claim 20, wherein the vertically-oriented conductive region comprises a second conductive layer.*
- 22.** *The device of claim 20, wherein the horizontally-oriented doped region is at least part of a drain region of the transistor structure.*
- 23.** *The device of claim 22, wherein the transistor structure further comprises a source region of the first conductivity type adjoining the body region, wherein the source region is electrically connected to the first conductive layer.*
- 24.** *The device of claim 20, further comprising a doped region of the second conductivity type below the horizontally-oriented doped region and within the semiconductor layer,*

wherein the doped region has a higher dopant concentration as compared to the semiconductor layer.

25. A semiconductor device comprising:
 a substrate;
 a semiconductor layer overlying the substrate, having a major surface spaced apart from the substrate, and defining a trench adjacent to the major surface and extending towards the substrate;
 a transistor structure comprising:
 a first current-carrying electrode of a first conductivity type adjacent to the major surface;
 at least a portion of a body region of a second conductivity type adjacent to the major surface; and
 a control electrode overlying the major surface;
 a doped region of the second conductivity type having a higher dopant concentration as compared to the semiconductor layer, wherein the doped region underlies and adjoins the first current-carrying electrode of the transistor structure; and
 a first conductive layer adjacent to the major surface and extending into the trench, wherein the first conductive layer is configured to provide a vertical current path between the transistor structure and the substrate.
26. The device of claim 25, further comprising a body contact region, wherein another portion of the body region underlies the body contact region.
27. The device of claim 25, wherein the doped region adjoins the first conductive layer.
28. The device of claim 25, wherein the doped region adjoins the body region.
29. The device of claim 25, wherein the first current-carrying electrode comprises a drain region of the transistor structure.
30. The device of claim 25, wherein the doped region is spaced apart from the semiconductor substrate.
31. The device of claim 25, wherein the at least a portion of the body region comprises a channel region of the transistor structure.
32. The device of claim 31, wherein the transistor structure is a lateral transistor.
33. The device of claim 31, wherein the transistor structure further comprises a source region, wherein:
 the source region has the first conductivity type and is adjacent to the major surface; and
 a drain region of the transistor structure comprises the first current-carrying electrode.
34. The device of claim 25, further comprising a conductive electrode, wherein the control electrode is a gate electrode of the transistor structure, and the conductive electrode is configured to reduce gate to drain capacitance.
35. The device of claim 34, wherein the conductive electrode includes a first portion extending into the trench and a second portion overlying the major surface.

36. The device of claim 34, wherein the transistor structure further comprises a source region in the body region, wherein the source region is electrically coupled to the conductive electrode.

37. A semiconductor device comprising:
 a substrate;
 a semiconductor layer overlying the substrate, having a major surface spaced apart from the substrate, and having an as-formed dopant concentration, wherein a portion of the semiconductor layer lies at a sidewall that defines at least part of a trench, and the portion has the as-formed dopant concentration;
 a transistor structure comprising:
 a first current-carrying electrode of a first conductivity type adjacent to the major surface;
 at least a portion of a body region of a second conductivity type adjacent to the major surface; and
 a control electrode overlying the major surface; and
 a first conductive layer adjacent to the major surface and extending into the trench, wherein the first conductive layer is configured to provide a vertical current path between the transistor and the substrate.
38. A semiconductor device comprising:
 a substrate;
 a semiconductor layer overlying the substrate and having a major surface spaced apart from the substrate;
 a transistor structure comprising:
 a first current-carrying electrode of a first conductivity type adjacent to the major surface;
 at least a portion of a body region of a second conductivity type adjacent to the major surface; and
 a control electrode overlying the major surface;
 a first conductive layer adjacent to the major surface and extending vertically towards the substrate, wherein the first conductive layer is configured to provide a vertical current path between the transistor structure and the substrate; and
 a second conductive layer overlies the major surface, wherein the second conductive layer is configured to reduce gate to drain capacitance and to be at substantially a same voltage as the first current-carrying electrode of the transistor structure.
39. The device of claim 38, wherein:
 the semiconductor layer has an as-formed dopant concentration;
 a portion of the semiconductor layer lies at a sidewall that defines at least a portion of a trench adjacent to the major surface and extending towards the substrate; and
 the portion has the as-formed dopant concentration.

* * * * *