



US00RE47975E

(19) **United States**
 (12) **Reissued Patent**
Zhang et al.

(10) **Patent Number:** **US RE47,975 E**
 (45) **Date of Reissued Patent:** ***May 5, 2020**

(54) **PERPENDICULAR MAGNETIC TUNNEL JUNCTION (PMTJ) WITH IN-PLANE MAGNETO-STATIC SWITCHING-ENHANCING LAYER**

(71) Applicant: **Avalanche Technology, Inc.**, Fremont, CA (US)

(72) Inventors: **Jing Zhang**, Los Altos, CA (US);
Yiming Huai, Pleasanton, CA (US);
Rajiv Yadav Ranjan, San Jose, CA (US);
Yuchen Zhou, San Jose, CA (US);
Zihui Wang, San Jose, CA (US);
Xiaojie Hao, Fremont, CA (US)

(73) Assignee: **Avalanche Technology, Inc.**, Fremont, CA (US)

(*) Notice: This patent is subject to a terminal disclaimer.

(21) Appl. No.: **16/100,649**

(22) Filed: **Aug. 10, 2018**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **9,679,625**
 Issued: **Jun. 13, 2017**
 Appl. No.: **14/930,523**
 Filed: **Nov. 2, 2015**

U.S. Applications:

(63) Continuation of application No. 13/161,412, filed on Jun. 15, 2011, now Pat. No. 9,196,332, which is a (Continued)

(51) **Int. Cl.**
H01L 29/82 (2006.01)
G11C 11/16 (2006.01)
 (Continued)

(52) **U.S. Cl.**
 CPC **G11C 11/161** (2013.01); **G11C 11/1675** (2013.01); **H01L 43/08** (2013.01)

(58) **Field of Classification Search**
 CPC **G11C 11/161**; **G11C 11/15**; **G11C 11/16**;
G11C 11/1675; **H01L 43/02**; **H01L 43/08**;
H01L 43/10
 See application file for complete search history.

(56) References Cited

U.S. PATENT DOCUMENTS

5,966,323 A 10/1999 Chen et al.
 6,803,615 B1 10/2004 Sin et al.
 (Continued)


Primary Examiner — Tuan H Nguyen

(74) *Attorney, Agent, or Firm* — Bing K. Yen

(57) ABSTRACT

An STTMRAM element includes a magnetic tunnel junction (MTJ) having a perpendicular magnetic orientation. The MTJ includes a barrier layer, a free layer formed on top of the barrier layer and having a magnetic orientation that is perpendicular and switchable relative to the magnetic orientation of the fixed layer. The magnetic orientation of the free layer switches when electrical current flows through the STTMRAM element. A switching-enhancing layer (SEL), separated from the free layer by a spacer layer, is formed on top of the free layer and has an in-plane magnetic orientation and generates magneto-static fields onto the free layer, causing the magnetic moments of the outer edges of the free layer to tilt with an in-plane component while minimally disturbing the magnetic moment at the center of the free layer to ease the switching of the free layer and to reduce the threshold voltage/current.

29 Claims, 8 Drawing Sheets






FIG. 2




FIG. 1




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7

FIG. 8




FIG. 9




FIG. 10




FIG. 11

**PERPENDICULAR MAGNETIC TUNNEL
JUNCTION (PMTJ) WITH IN-PLANE
MAGNETO-STATIC
SWITCHING-ENHANCING LAYER**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue; a claim printed with strikethrough indicates that the claim was canceled, disclaimed, or held invalid by a prior post-patent action or proceeding.

CROSS REFERENCE TO RELATED
APPLICATIONS

The present application *is a reissue application of U.S. Pat. No. 9,679,625, issued from U.S. patent application Ser. No. 14/930,523, which is a continuation of the commonly assigned application bearing Ser. No. 13/161,412 filed on Jun. 15, 2011, entitled "PERPENDICULAR MAGNETIC TUNNEL JUNCTION (pMTJ) WITH IN-PLANE MAGNETO-STATIC SWITCHING-ENHANCING LAYER,"* which is a continuation-in-part of a previously-filed continuation-in-part (CIP) U.S. patent application Ser. No. 13/099,321, filed on May 2, 2011, by Zhou et al. and entitled "Magnetic Random Access Memory With Field Compensation Layer and Multi-Level Cell", which is a CIP of U.S. patent application Ser. No. 13/029,054, filed on Feb. 16, 2011, by Zhou et al. and entitled "Magnetic Random Access Memory With Field Compensation Layer and Multi-Level Cell".

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates generally to a magnetic memory element having a magnetic tunnel junctions (MTJ) and particularly to a magnetic memory element having an MTJ with perpendicular anisotropy.

Background

Magnetic random access memory (MRAM) is rapidly gaining popularity as its use in replacing conventional memory is showing promise. Magnetic tunnel junctions (MTJs), an essential part of the MRAM, used to store information, are made of various layers, at least some of which determine the magnetic characteristic of the MRAM. An exemplary MTJ uses spin transfer torque to effectuate a change in the direction of magnetization of one or more free layers in the MTJ. That is, writing a bit ("1" or "0" in digital logic) of information is achieved by using a spin polarized current flowing through the MTJ, instead of using a magnetic field, to change states or program/write/erase the MRAM.

In spin transfer torque (STT) MTJ designs, when electrons flow across the MTJ stack, which is commonly referred to as "MTJ", in a direction that is perpendicular to the film plane or from the pinned (sometimes referred to as "reference" or "fixed") layer to the free (sometimes referred to as "switching" or "storage") layer, spin torque from electrons transmitted from the pinned layer to the free layer orientates the free layer magnetization in a direction that is parallel to that of the reference (or pinned) layer. When electrons flow from the free layer to the pinned layer, spin torque from electrons that are reflected from the pinned layer back into the free layer orientates the free layer magnetization to be anti-parallel relative to the magnetization of the

pinned layer. Thus, controlling the electron (current) flow direction causes switching of the direction of magnetization of the free layer. Resistance across the MTJ stack changes between low and high states based on the magnetization of the free layer, i.e. parallel versus anti-parallel, relative to that of the pinned layer.

However, a problem consistently experienced and preventing advancement of the use of MTJs in STTMRAM designs is reducing the threshold voltage or current used to switch the free layer magnetization during write operations. Such current and threshold voltage requirements limit the use of spin transfer torque-based MTJ devices in practical applications.

MTJs with perpendicular anisotropy, such that the magnetic moments of the free layer and the fixed layer thereof are in perpendicular directions relative to the plane of the film, are more appealing than their in-plane anisotropy counterparts largely due to the density and thermal stability improvements realized by the former.

While attempts are made to reduce the switching current and voltage of the MTJ, such attempts have largely addressed in-plane MTJ designs and not perpendicular MTJs. One way to reduce the switching current and voltage is to ease the switching of the free layer of an MTJ. Existing perpendicular MTJ designs include a free layer whose magnetic orientation (also referred to as anisotropy) relative to a reference ("fixed") layer, while perpendicular in direction, has high effective coercivity field (H_c). Effective H_c throughout the free layer is non-uniform. That is, effective perpendicular coercivity field (H_c) of the free layer changes relative to the position within the free layer such that the center of the free layer generally has a lower effective H_c than the outer edges of the free layer with effective H_c essentially increasing from the center of the free layer to its outer edges.

Lower effective H_c of the free layer would allow easier switching of the free layer and would lower the threshold voltage and current required to switch the magnetization of the free layer.

Thus, the need arises for decreasing the overall effective perpendicular anisotropic field of the free layer of magnetic memory element and thereby reducing the threshold voltage and current required to operate the same, with minimal impact on thermal stability of the free layer.

SUMMARY OF THE INVENTION

Briefly, a spin transfer torque magnetic random access memory (STTMRAM) element has a perpendicular magnetic orientation and is configured to store a state when electrical current is applied thereto. The STTMRAM element includes a seed layer, a magnetic tunnel junction (MTJ) with a perpendicular magnetic orientation including, a pinned layer with anti-ferromagnetic (AFM) layer formed on top of the seed layer and having a fixed perpendicular magnetic orientation, a barrier layer formed on top of the pinned layer, and a free layer formed on top of the barrier layer. The free layer has a magnetic orientation that is perpendicular and switchable relative to the magnetic orientation of the fixed layer. The magnetic orientation of the free layer switches when electrical current flows through the STTMRAM element. A switching-enhancing layer (SEL) is formed on top of the MTJ. The SEL has an in-plane magnetic orientation and generates magneto-static fields onto the free layer, causing the magnetic moments of the outer edges of the free layer to tilt with an in-plane component while minimally disturbing the magnetic moment at

the center of the free layer to ease the switching of the free layer and to reduce the threshold voltage/current.

These and other objects and advantages of the present invention will no doubt become apparent to those skilled in the art after having read the following detailed description of the various embodiments illustrated in the several figures of the drawing.

IN THE DRAWINGS

FIG. 1 shows the relevant portion of a spin transfer torque magnetic random access memory (STTMRAM) element 10, in accordance with an embodiment of the present invention.

FIG. 2 shows the relevant portion of an STTMRAM element 30, in accordance with another embodiment of the present invention.

FIG. 3 shows the STTMRAM element 10 when current is applied with electrons flowing from the BL 12 to the cap layer 28 and the element 10 is switching states from anti-parallel to parallel.

FIG. 4 shows the element 10 experiencing the application of electron flow, shown in a direction by the arrows 31, to be applied at the cap layer 28, flowing through the rest of the element 10, to the BL 12.

FIG. 5 shows a graph 50 of the characteristics of the elements 10 and 30 having different thicknesses vs. prior art magnetic elements.

FIG. 6 shows a graph 60 of the characteristics of the elements 10 and 30 having different Hk vs. prior art magnetic elements.

FIG. 7 shows the element 10 to include various embodiments of the SEL 26.

FIG. 8 shows the element 10 to include still further embodiments of the SEL 26.

FIG. 9 shows the element 10 to include various embodiments of the layer 24.

FIG. 10 shows the relevant portion of an STTMRAM element 120 in accordance with another embodiment of the present invention.

FIG. 11 shows a graph 170 of the behavior of the element 120 vs. that of a prior art magnetic memory.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

In the following description of the embodiments, reference is made to the accompanying drawings that form a part hereof, and in which is shown by way of illustration of the specific embodiments in which the invention may be practiced. It is to be understood that other embodiments may be utilized because structural changes may be made without departing from the scope of the present invention. It should be noted that the figures discussed herein are not drawn to scale and thicknesses of lines are not indicative of actual sizes.

In an embodiment of the present invention, a spin transfer torque magnetic random access memory (STTMRAM) element and a method of manufacturing the same is disclosed. The STTMRAM element has a substantially perpendicular magnetic orientation and is configured to program (or write) a state. Relevant layers of the STTMRAM element include a seed layer and a magnetic (also referred to as "magneto") tunnel junction (MTJ) having a perpendicular magnetic anisotropy. The MTJ includes a pinned layer with anti-ferromagnetic (AFM) layer, which is formed on top of the seed layer, with a perpendicular fixed magnetic orientation. The MTJ further includes a barrier layer formed on top of

the pinned layer and a free layer formed on top of the barrier layer with the free layer having a magnetic orientation that is substantially perpendicular relative to the film plane and switchable relative to the magnetic orientation of the fixed layer. The magnetic orientation of the free layer switches when electrical current flows through the STTMRAM element. The free layer, by itself, has a magnetic moment in a direction substantially perpendicular relative to the substrate at its center, and further has magnetic moments at its outer edges that are also substantially perpendicular relative to the substrate in their magnetic directions. A switching-enhancing layer (SEL), along with a spacer layer, is formed on top of the free layer and has an in-plane magnetic orientation. The SEL generates magneto-static fields affecting the outer edges of the free layer, causing the magnetization (or "magnetic orientation") of the free layer at its outer edges to have an in-plane component but minimally disturbing the magnetization at the center of the free layer. That is, magnetization at the outer edges of the free layer tilts with an in-plane component, caused by the magneto-static field from the SEL, thereby resulting in stronger spin torque at the outer edges to initiate the magnetization switching at the outer edges of the free layer. Moreover, through intra-layer exchange coupling, magnetization switching at the outer edges propagates to the center of the free layer and starts the switching of the magnetization at the center of the free layer. The latter is in addition to the switching of magnetization at the center of the free layer owing to the spin torque associated therewith. This advantageously results in easier switching of the free layer with a free layer edge magnetic moment that is tilted with in-plane component rather than a magnetic moment that is completely perpendicular.

FIG. 1 shows the relevant portion of a spin transfer torque magnetic random access memory (STTMRAM) element 10, in accordance with an embodiment of the present invention. The STTMRAM element 10 is shown to include a bottom electrode (BE) 12 on top of which is shown formed a seed layer 14, on top of which is shown formed an anti-ferromagnetic layer 16, on top of which is shown formed a pinned layer (PL) 18, on top of which is shown formed a barrier layer 20, on top of which is shown formed a free layer (FL) 22, on top of which is shown formed a spacer layer 24, on top of which is shown formed a switching-enhancing layer 26, on top of which is shown formed a cap layer 28. It is noted that the layer 28 also serves as the top electrode, readily known to those in the field.

It is noted that the pinned layer 18 is sometimes referred to as a "fixed layer" and the barrier layer 20 is sometimes referred to as a "tunnel layer" or a "barrier tunnel layer" or a "tunnel barrier layer" and the free layer 22 is sometimes referred to as a "switching layer" or "memory layer" or "storage layer" and the spacer layer 24 is sometimes referred to as a "separator layer" and the cap layer 28 is sometimes referred to as a "capping layer". It is understood that other layers, not shown in FIG. 1, may be and are typically formed on top of the layer 28, below the layer 12 and/or in between any of the layers shown in FIG. 1. It is also understood that the same applies to alternative embodiments shown and discussed herein relative to subsequent figures. It is further understood that the BE 12 is formed on top of a substrate and semiconductor device layers not shown in FIG. 1 but well known to those in the art.

The layer 18 is shown to have a magnetic moment (also known as "magnetization") in a direction shown by the arrow 19, the layer 22 is shown to have a magnetic moment in a direction shown by the arrow 21 and the layer 26 is shown to have a magnetic moment in a direction shown by

the arrow **23**. Electrons flow into the element **10**, either at **31** or at **33**, during read and write operations. It is noted that electrical current is applied to the element **10**, during a write operation, at **31** and **33** but in a direction that is opposite to the direction of electron flow. The element **10** is generally used to store digital information (or data) during write or program operations and this information is read during read operations. For these operations, various devices are coupled to the element **10** that are not shown in FIG. **1**, such as an access transistor, known to those in the art. For a description of these devices and methods of reading from and writing to the element **10**, the reader is directed to U.S. patent application Ser. No. 11/674,124, filed on Feb. 12, 2007, by Rajiv Yadav Ranjan, and entitled "Non-Uniform Switching Based Non-Volatile Magnetic Based Memory", the disclosures of which are incorporated herein by reference.

The element **10** has a perpendicular anisotropy in that the layer **22** has a magnetic moment that is perpendicular relative to the film plane. Similarly, the layer **18** has such a perpendicular anisotropy. The element **10** switches states to store a digital value in correspondence with the magnetic orientation of the layer **22** in that when this orientation is parallel to the magnetic orientation of the layer **18**, the element **10** is in one state ("0" or "1"), generally referred to as "parallel", and when the orientation of the layer **22** is anti-parallel, relative to the orientation of the layer **18**, the element **10** is in an opposite state. These different states result in unique resistances across the element **10**. In this manner, the digital value of "1" or "0" is distinguished during read operations.

In some embodiments, the BE **12** is made of tantalum (Ta), tantalum nitride (TaN), titanium nitride (TiN), ruthenium (Ru) or copper (Cu), the layer **14** is made of one or more elements from tantalum (Ta), titanium (Ti), niobium (Nb), nickel (Ni), molybdenum (Mo), vanadium (V), tungsten (W), silicon (Si), copper (Cu), aluminum (Al) chromium (Cr), Ru, or multilayers made of any combination of these materials. The layer **16** is made of platinum manganese (PtMn), iron manganese (FeMn), or iridium manganese (IrMn), and the layer **18** is made of Co, iron or Ni or an alloy made from a combination thereof or from Co, Fe, Ni or X or any combination thereof and where X is one or a combination of non-magnetic elements such as chromium (Cr), platinum (Pt), tantalum (Ta), titanium (Ti), tungsten (W), boron (B), vanadium (V), niobium (Nb), nickel (Ni), molybdenum (Mo), tungsten (W), silicon (Si), copper (Cu), aluminum (Al), gallium (Ga), platinum (Pt), palladium (Pd), samarium (Sm), oxygen (O), and nitrogen (N). Similarly, the layer **22** is made of a material typically used by the industry for making a free layer, as is the layer **20** made of a material known for making a tunnel layer.

It should be noted that while the embodiments of FIGS. **1** and **2** each show an AFM layer adjacent to the pinned layer, in certain embodiments this layer may not be present. In such case, one or more seed layers may be introduced in place of the AFM layer **16** to facilitate better crystal growth of the pinned layer, leading to a higher anisotropy.

While the layers **22** and **18** are each shown to be made of a single layer, in alternate embodiments, each of these layers may be made of multiple layers or one layer can be made of a single layer and the other can be made of multiple layers. Additionally and still alternatively, each of the layers **22** and **18** may be made of synthetic anti-ferromagnetic materials. Additionally, it should be noted that a thin layer of CoFeB, typically less than 2 nm thick, is introduced on either side of the barrier layer **20**, and between layers **20** and **22**, and layers **20** and **18** to enhance the spin polarization, leading to

a higher TMR. In one embodiment, about 1 nm thick $\text{Co}_{20}\text{Fe}_{60}\text{B}_{20}$ was introduced on either side of the barrier layer **20**.

The layer **24** is a non-magnetic layer and is advantageously non-spin-depolarizing, which causes the element **10** to be set apart from prior art MRAM structures because in the latter case, even when using a spacer layer, this layer has to be non-spin-depolarizing. Non-spin-depolarizing refers to electron spin not being disturbed or flipped when passing through the layer. Additionally, the element **10** is set apart from prior art in-plane MRAM structures with spin polarizer due to its perpendicular anisotropy.

The layers **16**, **18**, **20** and **22** define the MTJ of the element **10** and due to the magnetization orientation of the FL **22** and the PL **18**, the MTJ of the element **10** is considered to be a perpendicular MTJ (pMTJ).

As will be shown in greater detail shortly and discussed further, the SEL **26** advantageously causes the switching (also referred to herein as the "threshold") current/voltage required to program the element **10** to also be reduced. In some cases, such a decrease is 20-25% or more over prior art structures that do not use the SEL **26**. As shown by the arrow **23**, the direction of magnetization of the SEL **26** is in-plane and not perpendicular, this is important in the influence the SEL **26** has on the FL **22** relative to reducing the overall effective H_c of the FL **22**, which contributes to the reduction of the current and voltage required to switch the element **10**.

The structure of the element **10** is considered to be a "bottom structure" because the FL **22** is shown formed on top of the PL **18**. In the case where an STTMRAM element has a top structure, the free layer thereof is formed below its pinned layer, as shown in FIG. **2**.

FIG. **2** shows the relevant portion of an STTMRAM element **30**, in accordance with another embodiment of the present invention. The element **30** is analogous to the element **10** except that it has a "top structure" with the pinned layer **18** formed on top of the free layer **22**. Similarly, some of the other layers are positioned differently in that the seed layer **14** is shown formed on top of the BE **12**, the SEL **26** is shown formed on top of the seed layer **14**, the spacer layer **24** is shown formed on top of the SEL **26**, the FL **22** is shown formed on top of the spacer layer **24**, the barrier layer **20** is shown formed on top of the FL **22**, the PL **18** is shown formed on top of the barrier layer **20**, the AFM layer **16** is shown formed on top of the PL **18** and the cap layer **28** is shown formed on top of the AFM layer **16**.

FIG. **3** shows the STTMRAM element **10** when current is applied with electrons flowing from the BE **12** to the cap layer **28** and the element **10** is switching states from anti-parallel to parallel. The SEL **26** is shown to generate magneto-static field, shown by the arrows **40** and **42**, on mostly the edges of the FL **22** causing tilting of the magnetization with an in-plane component at the outer edges of the FL **22** yet resulting in minimal disturbance of the magnetization at the center of the FL **22**. The magnetization at the edges of the FL **22** are shown by the arrows **44** and are substantially in a direction that is out-of-plane with small in-plane component while the magnetization at substantially the center of the free layer, shown by the arrow **46**, is perpendicular relative to the plane of the film. It is noted that the longitudinal demagnetization field from the SEL **26** is stronger at the edges of the FL **22** and decays at the center of the FL **22** as shown by the dashed line **48** in FIG. **3**. In this respect, while the magnetization at the outer edges of the FL **22** is tilted in the presence of the SEL **26**, the magnetization at the center of the FL **22** is less affected and remains substantially perpendicular. In FIG. **3**, the SEL **26** is shown

to have a positive magnetic charge **36** on its left side, indicated by the symbol “+”, and a negative magnetic charge **38** on its right side, indicate by the symbol “-”.

In some embodiments, the SEL **26** has a thickness of 1 nm to 10 nm.

With the electron flow shown by the arrow **33**, the majority of the electrons with spin polarized by the pinned layer are transmitted through the barrier to the free layer. Spin momentum exerts larger spin torque at the outer edges of the FL **22** to assist switching. Advantageously, in operation, the magnetic moment, shown by the arrow **44** is tilted with an in-plane component having a large torque contributing to switching and the magnetization **46**, at the center of the FL **22**, switches following edge switching through the intra-layer exchange coupling thereof. The SEL **26** causes easing of the switching of the FL **22** by providing an in-plane biasing field at the outer edges of the FL **22**, which effectively reduces the required switching current.

FIG. **4** shows the element **10** experiencing the application of switching or electrical current with electron flow, shown in a direction by the arrows **31**, to be applied at the cap layer **28**, flowing through the rest of the element **10**, to the BE **12**. In the embodiment of FIG. **4**, the element **10** switches from a parallel state to an anti-parallel state. The electrons with a spin not aligned with the pinned layer are back-scattered to reverse the free layer magnetic orientation.

FIG. **5** shows a graph **50** including a y-axis representing the resistance, in kilo ohms, of the MTJ of various STTMRAM elements and an x-axis representing the voltage, in milli volts, applied to the STTMRAM elements. The voltage in the x-axis is the voltage referred to herein as the “threshold voltage” and it is the voltage at which the STTMRAM element changes resistance. The curve **52** shows the simulated performance of a conventional pMTJ element with no SEL while the curve **54** shows the simulated performance of the element **10** and the element **30** where the SEL **26** is 3 nano meters in thickness and the magnetic anisotropy, Hk, thereof is 5 kOe. As shown in FIG. **5**, there is somewhere between a 20-25% reduction in the voltage (and current) required to switch each of the elements **10** and **30** than that of a counterpart prior art element.

The curve **56** shows the performance of the elements **10** and **30** where the SEL **26** is 5 nano meters in thickness and as shown, the thicker SEL yields more voltage reduction. For example, a 20 milli volt reduction is shown by the curve **56**. It is noted that generally, the thicker the SEL **26**, the more effective the current reduction realized but the more challenge in forming the MTJ due to the etching process involved.

FIG. **6** shows a graph **60** of the characteristics of the elements **10** and **30** vs. prior art magnetic elements. In FIG. **6**, the x-axis represents the threshold voltage, in milli volts, applied to the magnetic elements and the y-axis represents the MTJ resistance, in kilo Ohms, of the magnetic elements.

The curve **62** shows the behavior of a prior art magnetic element, whereas the curve **64** shows the behavior of the element **10** where the thickness of the SEL **26** is 5 nano meters and the Hk is 1 kOe. The curve **66** shows the behavior of the element **10** with the SEL **26** having a thickness of 5 nano meters and an Hk of 5 kOe. Again, there is a substantial reduction of threshold voltage/current experienced when the SEL **26** is employed over prior art magnetic memory. Additionally, the threshold voltage increases by 20 milli volts when the Hk is reduced from 5 kOe to 1 kOe. That is because a weakly-pinned SEL is another damping source for the FL **22** when it is switching. It is

recommended that an Hk of 1 kOe or larger is an effective magnetic anisotropy required for the SEL **26**.

FIG. **7** shows the elements **10** and **30** to include various embodiments of the SEL **26**. In one embodiment, the SEL **26** is made of single layer **72** ferromagnetic (FM) material and has an in-plane anisotropy, as shown by the arrow **84**. In this respect, in some embodiments, the SEL **26** is made of cobalt (Co), iron or nickel (Ni) or an alloy made from a combination thereof or from Co, Fe, Ni or X or any combination thereof and where X is one or a combination of non-magnetic elements such as chromium (Cr), platinum (Pt), tantalum (Ta), titanium (Ti), tungsten (W), boron (B), vanadium (V), niobium (Nb), nickel (Ni), molybdenum (Mo), tungsten (W), silicon (Si), copper (Cu), aluminum (Al), gallium (Ga), platinum (Pt), palladium (Pd), samarium (Sm), oxygen (O), and nitrogen (N). The direction of magnetization is set by a large external in-plane field without annealing.

In other embodiments, the SEL **26** is made of multiple layers **74** formed from a ferromagnetic layer **80** on top of which is formed a spacer layer **78**, on top of which is formed a ferromagnetic layer **76**. In this respect, the layers **76** and **80** are anti-ferromagnetically coupled (AFC). The layer **80** has an in-plane anisotropy, as shown by the arrow **88** and the layer **76** has an in-plane anisotropy, as shown by the arrow **86**. In some embodiments, the layers **76** and **80** are each made of the same material as that disclosed above for the layer **72**. In some embodiments, the spacer layer **78** is made of the same material as that disclosed for the spacer layer **24** herein. In this embodiment, the layers **74** comprise a synthetic anti-ferromagnetic (SAF) structure having an in-plane anisotropy (or magnetic orientation).

In some embodiments, the layer **80** is formed on top of the layer **14** and in other embodiments, the layer **74** is flipped with the layer **76** formed on top of the layer **14**.

In still other embodiments, the SEL **26** is made of a FM layer **82** that is a single layer but has an out-of-plane magnetic anisotropy, as shown by the arrow **90** and in this respect is made of material that is different than the layer **72**.

In some embodiments, the layer **82** is made of CoPtX where X is selected from one of the following materials: Cr, Ta, Mo, Zr, Nb, B, C, N, P, Ti, SiO₂, and TiO₂, and the magnetization of the layer **82** is tilted away from an in-plane direction to be greater than 10 degrees.

In this embodiment, the magnetization component of the layer **82** is controlled and tilted toward a perpendicular direction, as shown by the arrow **90**. This helps to balance the anti-parallel to parallel vs. the parallel to anti-parallel switching current offset with controlled perpendicular field on the FL **22** from perpendicular magnetization component of the layer **82**.

FIG. **8** shows the element **30** to include still further embodiments of the SEL **26**. Accordingly, in one embodiment, the SEL **26** is made of bilayer **92**, which is formed of a FM layer **100** on top of which is formed a FM layer **98**. Each of the layers **98** and **100** is made of ferromagnetic material and have either a different magnetic isotropy (Hk) or a different saturation magnetization (Ms) or a different Hk and Ms relative to one another. The direction of magnetization of the layer **100** is in-plane and shown by the arrow **116** and the direction of magnetization of the layer **98**, which is also in-plane, is shown by the arrow **114**.

In yet another embodiment, the SEL **26** is made of the multi-layer **94**, which is shown formed of an anti-ferromagnetic (AFM) layer **108** on top of which is shown formed a FM layer **106** on top of which is shown formed a spacer layer **104**, on top of which is shown formed a FM layer **102**.

In this embodiment, the AFM layer **108** is formed on top of the layer **14**. Alternatively, in a bottom MTJ structure configuration **10**, the multi-layer **94** is flipped such that the FM layer **102** is formed on top of the layer **24** and the layer **104** is formed upon it and the layer **106** is formed on top of the layer **104** and the AFM layer **108** is formed on top of the layer **106**. In both embodiments, the layers **106** and **102** are anti-ferromagnetically coupled.

In still another embodiment, the SEL **26** is made of the bilayer **96**, which is shown made of an AFM layer **112** formed below a FM layer **110**. The AFM layer **112** is made of the same material as the layers **108** and **16**, and the FM layer **110** is made of the same material as the layer **72**. The layer **112** helps the magnetic orientation (which is commonly referred to as "magnetization") of the layer **110** remain in the same direction. The direction of the magnetic orientation of the layer **110**, which is in-plane, is shown by the arrow **121**.

FIG. **9** shows the element **30** to include various embodiments of the layer **24**. In one embodiment, the layer **24** is made of a bilayer **200**, which is shown to be made of an insulator layer **210** below a metal layer **208**. In the embodiment of FIG. **9**, the layer **210** is formed on top of the SEL **26**.

The layer **210** is made of any suitable insulating material, some examples of which are magnesium oxide (MgO), silicon dioxide (SiO₂), silicon nitride (SiN), and aluminum oxide (Al₂O₃). The layer **208** is made of any suitable metallic material, some examples of which are Ta, Ti, Ru, Pt, Cr, Cu, and Hf.

In other embodiments, the layers of the bilayer **200** are flipped, as shown by the bilayer **202** where the metal layer **214** is formed on top of the SEL **26** and the layer **212** is formed on top of the layer **214**.

Still alternatively, the layer **24** is made of a single layer, which is made of the same material as the layer **210**. To this end, the insulating layer **216** is shown as another embodiment.

Yet another embodiment of the element **10** is where the layer **24** is made of the metal layer **218**, which is a single layer and made of the same material as the layer **208**.

FIG. **10** shows the relevant portion of an STTMRAM element **120**, in accordance with another embodiment of the present invention. The element **120** is shown to include the BE **12**, the layer **14**, the free layer **122**, the layer **20**, the layer **18**, the layer **16**, the layer **28**, a spacer layer **124**, an SEL layer **126**, a spacer layer **128** and an SEL **130**. The layers **12**, **14**, **122**, **20**, **18**, **16** and **28** are shown separated from the layers **124**, **126**, **128** and **130** by an insulating layer **132** on either side thereof. The layer **122**, the layer **20** and the layer **18** and the AFM layer **16** collectively comprise the MTJ of the element **120**.

In the embodiment of FIG. **10**, the layer **14** is shown formed on top of the BE **12** and the FL **122** is shown formed on top of the layer **14**, the layer **20** is shown formed on top of the layer **122**, the layer **18** is shown formed on top of the layer **20**, the layer **16** is shown formed on top of the layer **18** and the layer **28** is shown formed on top of the layer **16**. The SEL **126** is shown formed on top of the layer **124**, which is shown formed on top of the layer **132**. Similarly, the SEL **130** is shown formed on top of the layer **128**, which is shown formed on top of the layer **132**. The SEL **126** is shown to have a negative magnetic charge adjacent to the MTJ and an in-plane anisotropy in a direction consistent with the direction of the arrow **140**. On the other hand, the SEL **130** has

positive magnetic charge adjacent to the MTJ and an in-plane anisotropy in a direction consistent with the direction of the arrow **142**.

As in each of the elements **10** and **30**, the FL **122** has a perpendicular anisotropy, as does the layer **18**. Also, the FL **122** has magnetic moments, shown by the arrows **144** that are tilted with in-plane components at the free layer's edges, as previously discussed. This is effectively done by the SELs **126** and **130**, which in the element **120** are shown on the sides of the MTJ of the element **120** instead of being in or a part of the MTJ, as in each of the elements **10** and **30**. Regardless, the element **120** operates in a manner analogous to the element **10**, as described above.

In some embodiments, the thickness of the layer **132** is 5-20 nano meters. There is a tradeoff for making the layer **132** too large or too small in thickness and therefore a balance to be struck. It is contemplated that if the thickness of the layer **132** is made to be too large, the magneto-static field on the FL **122** from the SEL will undesirably decay, resulting in less switching current reduction. If the thickness is made too small, the process of manufacturing the element **120** will become cumbersome or even unattainable because to make a narrow layer **132** with suitable step coverage is extremely difficult without potential shorting of the MTJ and the SELs **126/130**. For this reason, currently, the manufacturing of each of the elements **10** and **30** is contemplated to be easier than that of the element **120**.

Similar to the element **10**, while the element **120** is shown to be a "top structure", in other embodiments, it may be a "bottom structure" with the FL **122** formed on top of layer **18**.

FIG. **11** shows a graph **170** of the behavior of the element **120** vs. that of a prior art magnetic memory. The graph **170** has an x-axis representing the threshold voltage, in milli Volts, and a y-axis representing the resistance, in kilo Ohms, of the MTJ of the magnetic memory whose behavior the graph **170** captures.

In the graph **170**, four curves are shown: Curve **172** shows the behavior of a prior art magnetic memory with no SEL; Curve **174** shows the behavior of the curve **54** in FIG. **5** with the thickness of the SEL **26** being 3 nano meters and the Hk thereof being 5 kOe; Curve **176** shows the behavior of the curve **56** in FIG. **5** with the thickness of the SEL **26** being 5 nano meters and the Hk thereof being 5 kOe; and the curve **178** shows the behavior of the element **120** with the presence of the SEL **126**, which exhibits a greater improvement over the already-improved Curves **174** and **176**.

Although the present invention has been described in terms of specific embodiments, it is anticipated that alterations and modifications thereof will no doubt become apparent to those skilled in the art. It is therefore intended that the following claims be interpreted as covering all such alterations and modification as fall within the true spirit and scope of the invention.

What is claimed is:

1. A spin transfer torque magnetic random access memory (STTMRAM) element comprising:

- a magnetic free layer and a magnetic pinned layer in contact with a tunnel barrier layer interposed therebetween, said magnetic free layer having a variable perpendicular magnetic orientation, said magnetic pinned layer having an invariable perpendicular magnetic orientation; and
- a switching-enhancing layer (SEL) separated from said magnetic free layer by a first non-magnetic spacer layer, said SEL having an invariable in-plane magnetic orientation.

11

2. The STTMRAM element of claim 1, wherein said magnetic free layer includes multiple ferromagnetic layers.

3. The STTMRAM element of claim 1, wherein said magnetic free layer comprises cobalt and iron.

4. The STTMRAM element of claim 1, wherein said magnetic pinned layer includes multiple ferromagnetic layers.

5. The STTMRAM element of claim 1, wherein said magnetic pinned layer comprises cobalt and iron.

6. The STTMRAM element of claim 1, wherein said magnetic pinned layer includes two ferromagnetic layers separated by a second non-magnetic spacer layer, said two ferromagnetic layers having opposite perpendicular magnetization directions.

7. The STTMRAM element of claim 1, wherein said SEL includes multiple ferromagnetic layers.

8. The STTMRAM element of claim 1, wherein said SEL includes a ferromagnetic layer and an antiferromagnetic layer formed adjacent thereto.

9. The STTMRAM element of claim 1, wherein said SEL comprises cobalt and iron.

10. The STTMRAM element of claim 1, wherein said SEL includes a first switching-enhancing sublayer (SES) and a second SES separated by a third non-magnetic spacer layer with said first SES formed adjacent to said first non-magnetic spacer layer, said first and second switching-enhancing sublayers having opposite in-plane magnetization directions.

11. The STTMRAM element of claim 10, wherein each of said first and second switching-enhancing sublayers further includes a ferromagnetic layer.

12. The STTMRAM element of claim 10, wherein said second SES further includes a ferromagnetic layer and an antiferromagnetic layer formed adjacent thereto.

13. The STTMRAM element of claim 1, wherein said first non-magnetic spacer layer comprises a metal layer and an insulator layer.

14. The STTMRAM element of claim 1, wherein said first non-magnetic spacer layer is made of an insulator material.

15. The STTMRAM element of claim 1, wherein said first non-magnetic spacer layer is made of a conductor material.

16. The STTMRAM element of claim 1, wherein said first non-magnetic spacer layer is made of Ta, Ti, Ru, Pt, Cr, Cu, or Hf.

17. The STTMRAM element of claim 1 further comprising a cap layer formed adjacent to said SEL opposite said first non-magnetic spacer layer.

18. The STTMRAM element of claim 1 further comprising a seed layer formed adjacent to said SEL opposite said first non-magnetic spacer layer.

19. A spin transfer torque magnetic random access memory (STTMRAM) element comprising:

a magnetic free layer and a magnetic pinned layer in contact with a tunnel barrier layer interposed therebetween, said magnetic free layer having a variable perpendicular magnetic orientation, said magnetic pinned layer having an invariable perpendicular magnetic orientation; and

12

a switching-enhancing layer (SEL) separated from said magnetic free layer by a first non-magnetic spacer layer, said SEL having an in-plane magnetic orientation,

wherein said first non-magnetic spacer layer includes an insulator layer.

20. The STTMRAM element of claim 19, wherein said magnetic free layer includes multiple ferromagnetic layers.

21. The STTMRAM element of claim 19, wherein said magnetic pinned layer includes multiple ferromagnetic layers.

22. The STTMRAM element of claim 19, wherein said magnetic pinned layer comprises cobalt and iron.

23. A spin transfer torque magnetic random access memory (STTMRAM) element comprising:

a magnetic free layer and a magnetic pinned layer in contact with a tunnel barrier layer interposed therebetween, said magnetic free layer having a variable perpendicular magnetic orientation, said magnetic pinned layer having an invariable perpendicular magnetic orientation; and

a switching-enhancing layer (SEL) separated from said magnetic free layer by a first non-magnetic spacer layer, said SEL having an in-plane magnetic orientation,

wherein said magnetic pinned layer includes two ferromagnetic layers separated by a second non-magnetic spacer layer, said two ferromagnetic layers having opposite perpendicular magnetization directions.

24. The STTMRAM element of claim 19, wherein said SEL includes multiple ferromagnetic layers.

25. The STTMRAM element of claim 19, wherein said SEL comprises cobalt and iron.

26. The STTMRAM element of claim 19, wherein said first non-magnetic spacer layer is made of a conductor material.

27. The STTMRAM element of claim 19, wherein said first non-magnetic spacer layer is made of Ta, Ti, Ru, Pt, Cr, Cu, or Hf.

28. A spin transfer torque magnetic random access memory (STTMRAM) element comprising:

a magnetic free layer and a magnetic pinned layer in contact with a tunnel barrier layer interposed therebetween, said magnetic free layer having a variable perpendicular magnetic orientation, said magnetic pinned layer having an invariable perpendicular magnetic orientation; and

a switching-enhancing layer (SEL) separated from said magnetic free layer by a first non-magnetic spacer layer, said SEL having an in-plane magnetic orientation,

wherein said SEL includes a first switching-enhancing sublayer (SES) and a second SES separated by a third non-magnetic spacer layer with said first SES formed adjacent to said first non-magnetic spacer layer, said first and second switching-enhancing sublayers having opposite in-plane magnetization directions.

29. The STTMRAM element of claim 28, wherein each of said first and second switching-enhancing sublayers further includes a ferromagnetic layer.