



US00RE48444E

(19) **United States**
(12) **Reissued Patent**
Shabtay et al.

(10) **Patent Number: US RE48,444 E**
(45) **Date of Reissued Patent: *Feb. 16, 2021**

(54) **HIGH RESOLUTION THIN MULTI-APERTURE IMAGING SYSTEMS**

(71) Applicant: **Corephotonics Ltd.**, Tel-Aviv (IL)

(72) Inventors: **Gal Shabtay**, Tel-Aviv (IL); **Noy Cohen**, Tel-Aviv (IL); **Oded Gigushinski**, Herzlia (IL); **Ephraim Goldenberg**, Ashdod (IL)

(73) Assignee: **Corephotonics Ltd.**, Tel Aviv (IL)

(*) Notice: This patent is subject to a terminal disclaimer.

(21) Appl. No.: **16/383,618**

(22) Filed: **Apr. 14, 2019**

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **9,876,952**
Issued: **Jan. 23, 2018**
Appl. No.: **15/375,090**
Filed: **Dec. 11, 2016**

U.S. Applications:

(63) Continuation of application No. 14/386,823, filed as application No. PCT/IB2013/060356 on Nov. 23, 2013, now Pat. No. 9,538,152.

(Continued)

(51) **Int. Cl.**
H04N 5/232 (2006.01)
G06T 7/00 (2017.01)

(Continued)

(52) **U.S. Cl.**
CPC **H04N 5/232** (2013.01); **G06T 5/20** (2013.01); **G06T 7/00** (2013.01); **G06T 11/60** (2013.01);

(Continued)

(58) **Field of Classification Search**
CPC H04N 5/232; H04N 9/09; H04N 5/225; H04N 9/04; G06T 11/60; G06T 7/00; G06T 5/20

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,199,785 A 4/1980 McCullough et al.
5,005,083 A 4/1991 Grage et al.
(Continued)

FOREIGN PATENT DOCUMENTS

CN 101276415 A 10/2008
CN 102739949 A 10/2012
(Continued)

OTHER PUBLICATIONS

Statistical Modeling and Performance Characterization of a Real-Time Dual Camera Surveillance System, Greienhagen et al., Publisher: IEEE, 2000, 8 pages.

(Continued)



Primary Examiner — Mark Sager

(74) *Attorney, Agent, or Firm* — Nathan & Associates; Menachem Nathan

(57) **ABSTRACT**

A multi-aperture imaging system comprising a first camera with a first sensor that captures a first image and a second camera with a second sensor that captures a second image, the two cameras having either identical or different FOVs. The first sensor may have a standard color filter array (CFA) covering one sensor section and a non-standard color CFA covering another. The second sensor may have either Clear or standard CFA covered sections. Either image may be chosen to be a primary or an auxiliary image, based on a zoom factor. An output image with a point of view determined by the primary image is obtained by registering the auxiliary image to the primary image.

24 Claims, 7 Drawing Sheets



Related U.S. Application Data						
			8,094,208	B2 *	1/2012	Myhrvold H04N 5/2254 348/222.1
(60)	Provisional application No. 61/730,570, filed on Nov. 28, 2012.		8,115,825	B2	2/2012	Culbert et al.
			8,134,115	B2	3/2012	Koskinen et al.
			8,149,327	B2	4/2012	Lin et al.
			8,154,610	B2	4/2012	Jo et al.
(51)	Int. Cl.		8,179,457	B2	5/2012	Koskinen et al.
	<i>H04N 5/225</i> (2006.01)		8,238,695	B1	8/2012	Davey et al.
	<i>H04N 9/04</i> (2006.01)		8,274,552	B2	9/2012	Dahi et al.
	<i>G06T 11/60</i> (2006.01)		8,390,729	B2	3/2013	Long et al.
	<i>G06T 5/20</i> (2006.01)		8,391,697	B2	3/2013	Cho et al.
	<i>H04N 9/09</i> (2006.01)		8,400,555	B1	3/2013	Georgiev et al.
			8,439,265	B2	5/2013	Ferren et al.
(52)	U.S. Cl.		8,446,484	B2	5/2013	Muukki et al.
	CPC <i>H04N 5/225</i> (2013.01); <i>H04N 9/04</i> (2013.01); <i>H04N 9/09</i> (2013.01)		8,483,452	B2	7/2013	Ueda et al.
			8,514,491	B2	8/2013	Duparre
			8,553,106	B2	8/2013	Scarff
			8,542,287	B2	9/2013	Griffith et al.
(56)	References Cited		8,547,389	B2	10/2013	Hoppe et al.
	U.S. PATENT DOCUMENTS		8,587,691	B2	11/2013	Takane
			8,619,148	B1	12/2013	Watts et al.
			8,660,420	B2	2/2014	Chang
			8,803,990	B2	8/2014	Smith
	5,032,917 A 7/1991 Aschwanden		8,896,655	B2	11/2014	Mauchly et al.
	5,041,852 A 8/1991 Misawa et al.		8,976,255	B2	3/2015	Matsuoto et al.
	5,051,830 A 9/1991 von Hoessle		9,019,387	B2	4/2015	Nakano
	5,099,263 A 3/1992 Matsumoto et al.		9,025,073	B2	5/2015	Attar et al.
	5,248,971 A 9/1993 Mandl		9,025,077	B2	5/2015	Attar et al.
	5,287,093 A 2/1994 Amano et al.		9,041,835	B2	5/2015	Honda
	5,394,520 A 2/1995 Hall		9,137,447	B2	9/2015	Shibuno
	5,436,660 A 7/1995 Sakamoto		9,185,291	B1	11/2015	Shabtay et al.
	5,444,478 A 8/1995 Lelong et al.		9,215,377	B2	12/2015	Sokeila et al.
	5,459,520 A 10/1995 Sasaki		9,215,385	B2	12/2015	Luo
	5,657,402 A 8/1997 Bender et al.		9,270,875	B2	2/2016	Brisedoux et al.
	5,682,198 A 10/1997 Katayama et al.		9,286,680	B1	3/2016	Jiang et al.
	5,768,443 A 6/1998 Michael et al.		9,344,626	B2	5/2016	Silverstein et al.
	5,926,190 A 7/1999 Turkowski et al.		9,360,671	B1	6/2016	Zhou
	5,940,641 A 8/1999 McIntyre et al.		9,369,621	B2	6/2016	Malone et al.
	5,982,951 A 11/1999 Katayama et al.		9,413,930	B2	8/2016	Geerds
	6,101,334 A 8/2000 Fantone		9,413,984	B2	8/2016	Attar et al.
	6,128,416 A 10/2000 Oura		9,420,180	B2	8/2016	Jin
	6,148,120 A 11/2000 Sussman		9,438,792	B2	9/2016	Nakada et al.
	6,208,765 B1 3/2001 Bergen		9,485,432	B1	11/2016	Medasani et al.
	6,268,611 B1 7/2001 Pettersson et al.		9,578,257	B2	2/2017	Attar et al.
	6,549,215 B2 4/2003 Jouppi		9,618,748	B2	4/2017	Munger et al.
	6,611,289 B1 8/2003 Yu et al.		9,681,057	B2	6/2017	Attar et al.
	6,643,416 B1 11/2003 Daniels et al.		9,723,220	B2	8/2017	Sugie
	6,650,368 B1 11/2003 Doron		9,736,365	B2	8/2017	Laroia
	6,680,748 B1 1/2004 Monti		9,736,391	B2	8/2017	Du et al.
	6,714,665 B1 3/2004 Hanna et al.		9,768,310	B2	9/2017	Ahn et al.
	6,724,421 B1 4/2004 Glatt		9,800,798	B2	10/2017	Ravirala et al.
	6,738,073 B2 5/2004 Park et al.		9,851,803	B2	12/2017	Fisher et al.
	6,741,250 B1 5/2004 Furlan et al.		9,894,287	B2	2/2018	Qian et al.
	6,750,903 B1 6/2004 Miyatake et al.		9,900,522	B2	2/2018	Lu
	6,778,207 B1 8/2004 Lee et al.		9,927,600	B2	3/2018	Goldenberg et al.
	7,002,583 B2 2/2006 Rabb, III		2002/0005902	A1	1/2002	Yuen
	7,015,954 B1 3/2006 Foote et al.		2002/0030163	A1	3/2002	Zhang
	7,038,716 B2 5/2006 Klein et al.		2002/0063711	A1	5/2002	Park et al.
	7,199,348 B2 4/2007 Olsen et al.		2002/0075258	A1	6/2002	Park et al.
	7,206,136 B2 4/2007 Labaziewicz et al.		2002/0122113	A1	9/2002	Foote
	7,248,294 B2 7/2007 Slatter		2002/0167741	A1	11/2002	Koiwai et al.
	7,256,944 B2 8/2007 Labaziewicz et al.		2003/0030729	A1	2/2003	Prentice et al.
	7,305,180 B2 12/2007 Labaziewicz et al.		2003/0093805	A1	5/2003	Gin
	7,339,621 B2 3/2008 Fortier		2003/0160886	A1	8/2003	Misawa et al.
	7,346,217 B1 3/2008 Gold, Jr.		2003/0202113	A1	10/2003	Yoshikawa
	7,365,793 B2 4/2008 Cheatle et al.		2004/0008773	A1	1/2004	Itokawa
	7,411,610 B2 8/2008 Doyle		2004/0012683	A1	1/2004	Yamasaki et al.
	7,424,218 B2 9/2008 Baudisch et al.		2004/0017386	A1	1/2004	Liu et al.
	7,509,041 B2 3/2009 Hosono		2004/0027367	A1	2/2004	Pilu
	7,533,819 B2 5/2009 Barkan et al.		2004/0061788	A1	4/2004	Bateman
	7,561,191 B2 7/2009 May et al.		2004/0141086	A1	7/2004	Mihara
	7,619,683 B2 11/2009 Davis		2004/0240052	A1	12/2004	Minefuji et al.
	7,676,146 B2 3/2010 Border et al.		2005/0013509	A1	1/2005	Samadani
	7,738,016 B2 6/2010 Toyofuku		2005/0046740	A1	3/2005	Davis
	7,773,121 B1 8/2010 Huntsberger et al.		2005/0157184	A1	7/2005	Nakanishi et al.
	7,809,256 B2 10/2010 Kuroda et al.		2005/0168834	A1	8/2005	Matsumoto et al.
	7,880,776 B2 2/2011 LeGall et al.		2005/0200718	A1	9/2005	Lee
	7,918,398 B2 4/2011 Li et al.		2006/0054782	A1	3/2006	Olsen et al.
	7,964,835 B2 6/2011 Olsen et al.		2006/0056056	A1	3/2006	Ahiska et al.
	7,978,239 B2 7/2011 Deever et al.					

(56)

References Cited

U.S. PATENT DOCUMENTS

2006/0102907 A1 5/2006 Lee et al.
 2006/0125937 A1 6/2006 LeGall et al.
 2006/0170793 A1 8/2006 Pasquarette et al.
 2006/0175549 A1 8/2006 Miller et al.
 2006/0187310 A1 8/2006 Janson et al.
 2006/0187322 A1 8/2006 Janson et al.
 2006/0187338 A1 8/2006 May et al.
 2007/0024737 A1 2/2007 Nakamura et al.
 2007/0126911 A1 6/2007 Nanjo
 2007/0177025 A1 8/2007 Kopet et al.
 2007/0188653 A1 8/2007 Pollock et al.
 2007/0189386 A1 8/2007 Imagawa et al.
 2007/0257184 A1 11/2007 Olsen et al.
 2007/0285550 A1 12/2007 Son
 2008/0017557 A1 1/2008 Witdouck
 2008/0024614 A1 1/2008 Li et al.
 2008/0025634 A1 1/2008 Border et al.
 2008/0030592 A1 2/2008 Border et al.
 2008/0030611 A1 2/2008 Jenkins
 2008/0084484 A1 4/2008 Ochi et al.
 2008/0117316 A1 5/2008 Orimoto
 2008/0218611 A1 9/2008 Parulski et al.
 2008/0218612 A1 9/2008 Border et al.
 2008/0218613 A1 9/2008 Janson et al.
 2008/0219654 A1 9/2008 Border et al.
 2009/0086074 A1 4/2009 Li et al.
 2009/0109556 A1 4/2009 Shimizu et al.
 2009/0122195 A1 5/2009 Van Baar et al.
 2009/0122406 A1 5/2009 Rouvinen et al.
 2009/0128644 A1 5/2009 Camp et al.
 2009/0219547 A1 9/2009 Kauhanen et al.
 2009/0252484 A1 10/2009 Hasuda et al.
 2009/0295949 A1 12/2009 Ojala
 2009/0324135 A1 12/2009 Kondo et al.
 2010/0013906 A1 1/2010 Border et al.
 2010/0020221 A1 1/2010 Tupman et al.
 2010/0060746 A9 3/2010 Olsen et al.
 2010/0097444 A1 4/2010 Lablans
 2010/0103194 A1 4/2010 Chen et al.
 2010/0277619 A1 4/2010 Scarff
 2010/0165131 A1 7/2010 Makimoto et al.
 2010/0238327 A1 9/2010 Griffith et al.
 2010/0283842 A1 11/2010 Guissin et al.
 2010/0321494 A1 12/2010 Peterson et al.
 2011/0058320 A1 3/2011 Kim et al.
 2011/0064327 A1* 3/2011 Dagher G06T 5/004
 382/263
 2011/0080487 A1 4/2011 Venkataraman et al.
 2011/0121421 A1 5/2011 Charbon et al.
 2011/0128288 A1 6/2011 Petrou et al.
 2011/0164172 A1 7/2011 Shintani et al.
 2011/0216228 A1* 9/2011 Kawamura H04N 5/335
 348/273
 2011/0229054 A1 9/2011 Weston et al.
 2011/0234853 A1 9/2011 Hayashi et al.
 2011/0234881 A1 9/2011 Wakabayashi et al.
 2011/0242286 A1 10/2011 Pace et al.
 2011/0242355 A1 10/2011 Goma et al.
 2011/0285730 A1 11/2011 Lai et al.
 2011/0292258 A1 12/2011 Adler et al.
 2011/0298966 A1 12/2011 Kirschstein et al.
 2012/0026366 A1 2/2012 Golan et al.
 2012/0062780 A1 3/2012 Morihisa
 2012/0069235 A1 3/2012 Imai
 2012/0075489 A1 3/2012 Nishihara
 2012/0081566 A1* 4/2012 Cote H04N 5/2256
 348/222.1
 2012/0105579 A1 5/2012 Jeon et al.
 2012/0154614 A1 6/2012 Moriya et al.
 2012/0196648 A1 8/2012 Havens et al.
 2012/0229663 A1 9/2012 Nelson et al.
 2012/0249815 A1 10/2012 Bohn et al.
 2012/0287315 A1 11/2012 Huang et al.
 2012/0320467 A1 12/2012 Baik et al.
 2013/0002928 A1 1/2013 Imai

2013/0016427 A1 1/2013 Sugawara
 2013/0076922 A1 3/2013 Shihoh et al.
 2013/0093842 A1 4/2013 Yahata
 2013/0113894 A1 5/2013 Mirlay
 2013/0135445 A1 5/2013 Dahl et al.
 2013/0136355 A1* 5/2013 Demandolx H04N 5/3572
 382/167
 2013/0182150 A1 7/2013 Asakura
 2013/0201360 A1 8/2013 Song
 2013/0202273 A1 8/2013 Ouedraogo et al.
 2013/0235224 A1 9/2013 Park et al.
 2013/0250150 A1 9/2013 Malone et al.
 2013/0258044 A1 10/2013 Betts-LaCroix
 2013/0270419 A1 10/2013 Singh et al.
 2013/0278785 A1 10/2013 Nomura et al.
 2013/0321668 A1 12/2013 Kamath
 2014/0009631 A1 1/2014 Topliss
 2014/0049615 A1 2/2014 Uwagawa
 2014/0118584 A1 5/2014 Lee et al.
 2014/0192238 A1 7/2014 Attar et al.
 2014/0192253 A1 7/2014 Laroia
 2014/0218587 A1 8/2014 Shah
 2014/0313316 A1 10/2014 Olsson et al.
 2014/0362242 A1 12/2014 Takizawa
 2015/0002683 A1 1/2015 Hu et al.
 2015/0042870 A1 2/2015 Chan et al.
 2015/0070781 A1 3/2015 Cheng et al.
 2015/0092066 A1 4/2015 Geiss et al.
 2015/0138381 A1 5/2015 Ahn
 2015/0154776 A1 6/2015 Zhang et al.
 2015/0162048 A1 6/2015 Hirata et al.
 2015/0195458 A1 7/2015 Nakayama et al.
 2015/0215516 A1 7/2015 Dolgin
 2015/0237280 A1 8/2015 Choi et al.
 2015/0242994 A1 8/2015 Shen
 2015/0253543 A1 9/2015 Mercado
 2015/0253647 A1 9/2015 Mercado
 2015/0271471 A1 9/2015 Hsieh et al.
 2015/0286033 A1 10/2015 Osborne
 2015/0316744 A1 11/2015 Chen
 2015/0334309 A1 11/2015 Peng et al.
 2016/0044250 A1 2/2016 Shabtay et al.
 2016/0070088 A1 3/2016 Koguchi
 2016/0154202 A1 6/2016 Wippermann et al.
 2016/0154204 A1 6/2016 Lim et al.
 2016/0212358 A1 7/2016 Shikata
 2016/0241751 A1 8/2016 Park
 2016/0291295 A1 10/2016 Shabtay et al.
 2016/0295112 A1 10/2016 Georgiev et al.
 2016/0301840 A1 10/2016 Du et al.
 2016/0353008 A1 12/2016 Osborne
 2016/0353012 A1 12/2016 Kao et al.
 2017/0019616 A1 1/2017 Zhu et al.
 2017/0187962 A1 6/2017 Lee et al.
 2017/0214846 A1 7/2017 Du et al.
 2017/0214866 A1 7/2017 Zhu et al.
 2017/0242225 A1 8/2017 Fiske
 2017/0289458 A1 10/2017 Song et al.
 2018/0017844 A1 1/2018 Yu et al.
 2018/0024329 A1 1/2018 Goldenberg et al.
 2018/0059379 A1 3/2018 Chou
 2018/0120674 A1 5/2018 Avivi et al.
 2018/0150973 A1 5/2018 Tang et al.
 2018/0241922 A1 8/2018 Baldwin et al.
 2018/0295292 A1 10/2018 Lee et al.

FOREIGN PATENT DOCUMENTS

CN 103024272 A 4/2013
 CN 103841404 A 6/2014
 EP 1536633 A1 6/2005
 EP 1780567 A1 5/2007
 EP 2523450 A1 11/2012
 JP S59191146 A 10/1984
 JP 04211230 A 8/1992
 JP H07318864 A 12/1995
 JP 08271976 A 10/1996
 JP 2003298920 A 10/2003
 JP 2004133054 A 4/2004

(56)

References Cited

FOREIGN PATENT DOCUMENTS

JP	2004245982	A	9/2004
JP	2005099265	A	4/2005
JP	2006238325	A	9/2006
JP	2007228006	A	9/2007
JP	2007306282	A	11/2007
JP	2008076485	A	4/2008
JP	2011085666	A	4/2011
JP	2013106289	A	5/2013
KR	20090058229	A	6/2009
KR	20100008936	A	1/2010
KR	20140014787	A	2/2014
KR	101477178	B1	12/2014
KR	20150118012	A	10/2015
WO	2009097552		8/2009
WO	2010122841	A1	10/2010
WO	2014072818	A2	5/2014
WO	2017025822	A1	2/2017
WO	2017037688	A1	3/2017
WO	2018130898	A1	7/2018

OTHER PUBLICATIONS

A 3MPixel Multi-Aperture Image Sensor with 0.7 μm Pixels in 0.11 μm CMOS, Fife et al., Stanford University, 2008, 3 pages.
 Dual camera intelligent sensor for high definition 360 degrees surveillance, Scotti et al., Publisher: IET, May 9, 2000, 8 pages.
 Dual-sensor foveated imaging system, Hua et al., Publisher: Optical Society of America, Jan. 14, 2008, 11 pages.

Defocus Video Matting, McGuire et al., Publisher: ACM SIGGRAPH, Jul. 31, 2005, 11 pages.
 Compact multi-aperture imaging with high angular resolution, Santacana et al., Publisher: Optical Society of America, 2015, 10 pages.
 Multi-Aperture Photography, Green et al., Publisher: Mitsubishi Electric Research Laboratories, Inc., Jul. 2007, 10 pages.
 Multispectral Bilateral Video Fusion, Bennett et al., Publisher: IEEE, May 2007, 10 pages.
 Super-resolution imaging using a camera array, Santacana et al., Publisher: Optical Society of America, 2014, 6 pages.
 Optical Splitting Trees for High-Precision Monocular Imaging, McGuire et al., Publisher: IEEE, 2007, 11 pages.
 High Performance Imaging Using Large Camera Arrays, Wilburn et al., Publisher: Association for Computing Machinery, Inc., 2005, 12 pages.
 Real-time Edge-Aware Image Processing with the Bilateral Grid, Chen et al., Publisher: ACM SIGGRAPH, 2007, 9 pages.
 Superimposed multi-resolution imaging, Caries et al., Publisher: Optical Society of America, 2017, 13 pages.
 Viewfinder Alignment, Adams et al., Publisher: EUROGRAPHICS, 2008, 10 pages.
 Dual-Camera System for Multi-Level Activity Recognition, Bodor et al., Publisher: IEEE, Oct. 2014, 6 pages.
 Engineered to the task: Why camera-phone cameras are different, Giles Humpston, Publisher: Solid State Technology Jun. 2009, 3 pages.
 International Search Report and Written Opinion issued in related PCT patent application PCT/IB2013/060356, dated Apr. 17, 2014, 15 pages.

* cited by examiner




FIG. 1A




FIG. 1B

200




FIG. 2

300




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10

1100







FIG. 11A

Wide sensor (X1)

Wide-Tele sensor (X1.5)

Tele sensor (X2)



1102

1104

1106

FIG. 11B

HIGH RESOLUTION THIN MULTI-APERTURE IMAGING SYSTEMS

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue; a claim printed with strikethrough indicates that the claim was canceled, disclaimed, or held invalid by a prior post-patent action or proceeding.

CROSS REFERENCE TO RELATED APPLICATIONS

[This application is a Continuation application of U.S. patent application Ser. No. 14/386,823 (now allowed), which was a National Phase application from PCT patent application PCT/IB2013/060356 which claimed priority from U.S. Provisional Patent Application No. 61/730,570 having the same title and filed Nov. 28, 2012, the latter incorporated herein by reference in its entirety.] *This patent application is a reissue application of Ser. No. 15/375,090, filed Dec. 11, 2016, now U.S. Pat. No. 9,876,952, which is a continuation of U.S. patent application Ser. No. 14/386,823, filed Apr. 22, 2014, now U.S. Pat. No. 9,538,152, which was a National Phase application from PCT application PCT/IB2013/060356 which claimed priority from U.S. Provisional Patent Application No. 61/730,570 having the same title and filed Nov. 28, 2012, the latter incorporated herein by reference in its entirety. This broadening reissue application is a parent to each of the following four co-pending continuation reissue applications: U.S. patent application Ser. No. 16/384,140 (filed Apr. 15, 2019), U.S. patent application Ser. No. 16/384,197 (filed Apr. 15, 2019), U.S. patent application Ser. No. 16/384,244 (filed Apr. 15, 2019) and U.S. patent application Ser. No. 16/419,604 (filed May 22, 2019).*

FIELD

Embodiments disclosed herein relate in general to multi-aperture imaging (“MAI”) systems (where “multi” refers to two or more apertures) and more specifically to thin MAI systems with high color resolution and/or optical zoom.

BACKGROUND

Small digital cameras integrated into mobile (cell) phones, personal digital assistants and music players are becoming ubiquitous. Each year, mobile phone manufacturers add more imaging features to their handsets, causing these mobile imaging devices to converge towards feature sets and image quality that customers expect from stand-alone digital still cameras. Concurrently, the size of these handsets is shrinking, making it necessary to reduce the total size of the camera accordingly while adding more imaging features. Optical Zoom is a primary feature of many digital still cameras but one that mobile phone cameras usually lack, mainly due to camera height constraints in mobile imaging devices, cost and mechanical reliability.

Mechanical zoom solutions are common in digital still cameras but are typically too thick for most camera phones. Furthermore, the F/# (“F number”) in such systems typically increases with the zoom factor (ZF) resulting in poor light sensitivity and higher noise (especially in low-light scenarios). In mobile cameras, this also results in resolution

compromise, due to the small pixel size of their image sensors and the diffraction limit optics associated with the F/#.

One way of implementing zoom in mobile cameras is by over-sampling the image and cropping and interpolating it in accordance with the desired ZF. While this method is mechanically reliable, it results in thick optics and in an expensive image sensor due to the large number of pixels so associated therewith. As an example, if one is interested in implementing a 12 Megapixel camera with X3 ZF, one needs a sensor of 108 Megapixels.

Another way of implementing zoom, as well as increasing the output resolution, is by using a dual-aperture imaging (“DAI”) system. In its basic form, a DAI system includes two optical apertures which may be formed by one or two optical modules, and one or two image sensors (e.g., CMOS or CCD) that grab the optical image or images and convert the data into the electronic domain, where the image can be processed and stored.

The design of a thin MAI system with improved resolution requires a careful choice of parameters coupled with advanced signal processing algorithms to support the output of a high quality image. Known MAI systems, in particular ones with short optical paths, often trade-off functionalities and properties, for example zoom and color resolution, or image resolution and quality for camera module height. Therefore, there is a need for, and it would be advantageous to have thin MAI systems that produce an image with high resolution (and specifically high color resolution) together with zoom functionality.

Moreover, known signal processing algorithms used together with existing MAI systems often further degrade the output image quality by introducing artifacts when combining information from different apertures. A primary source of these artifacts is the image registration process, which has to find correspondences between the different images that are often captured by different sensors with different color filter arrays (CFAs). There is therefore a need for, and it would be advantageous to have an image registration algorithm that is more robust to the type of CFA used by the cameras and which can produce better correspondence between images captured by a multi-aperture system.

SUMMARY

Embodiments disclosed herein teach the use of multi-aperture imaging systems to implement thin cameras (with short optical paths of less than about 9 mm) and/or to realize optical zoom systems in such thin cameras. Embodiments disclosed herein further teach new color filter arrays that optimize the color information which may be achieved in a multi-aperture imaging system with or without zoom. In various embodiments, a MAI system disclosed herein includes at least two sensors or a single sensor divided into at least two areas. Hereinafter, the description refers to “two sensors”, with the understanding that they may represent sections of a single physical sensor (imager chip). Exemplarily, in a dual-aperture imaging system, a left sensor (or left side of a single sensor) captures an image coming from a first aperture while a right sensor (or right side of a single sensor) captures an image coming from a second aperture. In various embodiments disclosed herein, one sensor is a “Wide” sensor while another sensor is a “Tele” sensor, see e.g. FIG. 1A. The Wide sensor includes either a single standard CFA or two different CFAs: a non-standard CFA with higher color sampling rate positioned in an “overlap area” of the sensor (see below description of FIG. 1B) and

a standard CFA with a lower color sampling rate surrounding the overlap area. When including a single standard CFA, the CFA may cover the entire Wide sensor area. A "standard CFA" may include a RGB (Bayer) pattern or a non-Bayer pattern such as RGBE, CYYM, CYGM, RGBW#1, RGBW#2 or RGBW#3. Thus, reference may be made to "standard Bayer" or "standard non-Bayer" patterns or filters. As used herein, "non-standard CFA" refers to a CFA that is different in its pattern that CFAs listed above as "standard". Exemplary non-standard CFA patterns may include repetitions of a 2x2 micro-cell in which the color filter order is RR-BB, RB-BR or YC-CY where Y=Yellow=Green+Red, C=Cyan=Green+Blue; repetitions of a 3x3 micro-cell in which the color filter order is GBR-RGB-BRG; and repetitions of a 6x6 micro-cell in which the color filter order is RBBRRB-RWRBWB-BBRBRR-RRBRBB-BWBRWR-BRRBBR, or BBGRRG-RGRBGB-GBRGRB-RRGBBG-BGBRGR-GRBGBR, or RBBRRB-RGRBGB-BBRBRR-RRBRBB-BGBRGR-BRRBBR, or RBRBRB-BGBRGR-RBRBRB-BRBRBR-RGRBGB-BRBRBR.

The Tele sensor may be a Clear sensor (i.e. a sensor without color filters) or a standard CFA sensor. This arrangement of the two (or more than two) sensors and of two (or more than two) Wide and Tele "subset cameras" (or simply "subsets") related to the two Wide and Tele subsets. Each sensor provides a separate image (referred to respectively as a Wide image and a Tele image), except for the case of a single sensor, where two images are captured (grabbed) by the single sensor (example above). In some embodiments, zoom is achieved by fusing the two images, resulting in higher color resolution that approaches that of a high quality dual-aperture zoom camera. Some thin MAI systems disclosed herein therefore provide zoom, super-resolution, high dynamic range and enhanced user experience.

In some embodiments, in order to reach optical zoom capabilities, a different magnification image of the same scene is grabbed by each subset, resulting in field of view (FOV) overlap between the two subsets. In some embodiments, the two subsets have the same zoom (i.e. same FOV). In some embodiments, the Tele subset is the higher zoom subset and the Wide subset is the lower zoom subset. Post processing is applied on the two images grabbed by the MAI system to fuse and output one fused (combined) output zoom image processed according to a user ZF input request. In some embodiments, the resolution of the fused image may be higher than the resolution of the Wide/Tele sensors. As part of the fusion procedure, up-sampling may be applied on the Wide image to scale it to the Tele image.

In an embodiment there is provided a multi-aperture imaging system comprising a first camera subset that provides a first image, the first camera subset having a first sensor with a first plurality of sensor pixels covered at least in part with a non-standard CFA, the non-standard CFA used to increase a specific color sampling rate relative to a same color sampling rate in a standard CFA; a second camera subset that provides a second image, the second camera subset having a second sensor with a second plurality of sensor pixels either Clear or covered with a standard CFA; and a processor configured to process the first and second images into a combined output image.

In some embodiments, the first and the second camera subsets have identical FOVs and the non-standard CFA may cover an overlap area that includes all the pixels of first sensor, thereby providing increased color resolution. In some such embodiments, the processor is further configured to, during the processing of the first and second images into a combined output image, register respective first and sec-

ond Luma images obtained from the first and second images, the registered first and second Luma images used together with color information to form the combined output image. In an embodiment, the registration includes finding a corresponding pixel in the second Luma image for each pixel in the first Luma image, whereby the output image is formed by transferring information from the second image to the first image. In another embodiment, the registration includes finding a corresponding pixel in the first Luma image for each pixel in the second Luma image, whereby the output image is formed by transferring information from the first image to the second image.

In some embodiments, the first camera subset has a first FOV, the second camera subset has a second, smaller FOV than the first FOV, and the non-standard CFA covers an overlap area on the first sensor that captures the second FOV, thereby providing both optical zoom and increased color resolution. In some such embodiments, the processor is further configured to, during the processing of the first and second images into a combined output image and based on a ZF input, register respective first and second Luma images obtained from the first and second images, the registered first and second Luma images used together with color information to form the combined output image. For a ZF input that defines an FOV greater than the second FOV, the registration includes finding a corresponding pixel in the second Luma image for each pixel in the first Luma image and the processing includes forming the output image by transferring information from the second image to the first image. For a ZF input that defines an FOV smaller than or equal to the second FOV, the registration includes finding a corresponding pixel in the first Luma image for each pixel in the second Luma image, and the processing includes forming the output image by transferring information from the first image to the second image.

In an embodiment there is provided a multi-aperture imaging system comprising a first camera subset that provides a first image, the first camera subset having a first sensor with a first plurality of sensor pixels covered at least in part with a standard CFA; a second camera subset that provides a second image, the second camera subset having a second sensor with a second plurality of sensor pixels either Clear or covered with a standard CFA; and a processor configured to register first and second Luma images obtained respectively from the first and second images and to process the registered first and second Luma images together with color information into a combined output image.

In some embodiments, the first and the second camera subsets have identical first and second FOVs. In some such embodiments, the registration includes finding a corresponding pixel in the second Luma image for each pixel in the first Luma image and the processing includes forming the output image by transferring information from the second image to the first image. In other such embodiments, the registration includes finding a corresponding pixel in the first Luma image for each pixel in the second Luma image and the processing includes forming the output image by transferring information from the first image to the second image.

In some embodiments, the first camera subset has a first FOV, the second camera subset has a second, smaller FOV than the first FOV, and the processor is further configured to register the first and second Luma images based on a ZF input. For a ZF input that defines an FOV greater than the second FOV, the registration includes finding a corresponding pixel in the second Luma image for each pixel in the first Luma image and the processing includes forming the output

image by transferring information from the second image to the first image. For a ZF input that defines an FOV smaller than or equal to the second FOV, the registration includes finding a corresponding pixel in the first Luma image for each pixel in the second Luma image, and the processing includes forming the output image by transferring information from the first image to the second image.

BRIEF DESCRIPTION OF THE DRAWINGS

Non-limiting examples of embodiments disclosed herein are described below with reference to figures attached hereto that are listed following this paragraph. The drawings and descriptions are meant to illuminate and clarify embodiments disclosed herein, and should not be considered limiting in any way.

FIG. 1A shows schematically a block diagram illustrating a dual-aperture zoom imaging system disclosed herein;

FIG. 1B shows an example of an image captured by the Wide sensor and the Tele sensor while illustrating the overlap area on the Wide sensor;

FIG. 2 shows schematically an embodiment of a Wide sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 3 shows schematically another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 4 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 5 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 6 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 7 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 8 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 9 shows schematically yet another embodiment of a Wide camera sensor that may be implemented in a dual-aperture zoom imaging system disclosed herein;

FIG. 10 shows a schematically in a flow chart an embodiment of a method disclosed herein for acquiring and outputting a zoom image;

FIG. 11A shows exemplary images captured by a triple aperture zoom imaging system disclosed herein;

FIG. 11B illustrates schematically the three sensors of the triple aperture imaging system of FIG. 11A.

DETAILED DESCRIPTION

Embodiments disclosed herein relate to multi-aperture imaging systems that include at least one Wide sensor with a single CFA or with two different CFAs and at least one Tele sensor. The description continues with particular reference to dual-aperture imaging systems that include two (Wide and Tele) subsets with respective sensors. A three-aperture imaging system is described later with reference to FIGS. 11A-11B.

The Wide sensor includes an overlap area (see description of FIG. 1B) that captures the Tele FOV. The overlap area may cover the entire Wide sensor or only part of the sensor. The overlap area may include a standard CFA or a non-

standard CFA. Since the Tele image is optically magnified compared to the Wide image, the effective sampling rate of the Tele image is higher than that of the Wide image. Thus, the effective color sampling rate in the Wide sensor is much lower than the Clear sampling rate in the Tele sensor. In addition, the Tele and Wide images fusion procedure (see below) requires up-scaling of the color data from the Wide sensor. Up-scaling will not improve color resolution. In some applications, it is therefore advantageous to use a non-standard CFA in the Wide overlap area that increases color resolution for cases in which the Tele sensor includes only Clear pixels. In some embodiments in which the Tele sensor includes a Bayer CFA, the Wide sensor may have a Bayer CFA in the overlap area. In such embodiments, color resolution improvement depends on using color information from the Tele sensor in the fused output image.

FIG. 1A shows schematically a block diagram illustrating a dual-aperture zoom imaging (“DAZI”) system 100 disclosed herein. System 100 includes a dual-aperture camera 102 with a Wide subset 104 and a Tele subset 106 (each subset having a respective sensor), and a processor 108 that fuses two images, a Wide image obtained with the Wide subset and a Tele image obtained with the Tele subset, into a single fused output image according to a user-defined “applied” ZF input or request. The ZF is input to processor 108. The Wide sensor may include a non-standard CFA in an overlap area illustrated by 110 in FIG. 1B. Overlap area 110 is surrounded by a non-overlap area 112 with a standard CFA (for example a Bayer pattern). FIG. 1B also shows an example of an image captured by both Wide and Tele sensors. Note that “overlap” and “non-overlap” areas refer to parts of the Wide image as well as to the CFA arrangements of the Wide sensor. The overlap area may cover different portions of a Wide sensor, for example half the sensor area, a third of the sensor area, a quarter of the sensor area, etc. A number of such Wide sensor CFA arrangements are described in more detail with reference to FIGS. 2-9. The non-standard CFA pattern increases the color resolution of the DAZI system.

The Tele sensor may be Clear (providing a Tele Clear image scaled relative to the Wide image) or may include a standard (Bayer or non-Bayer) CFA. It in the latter case, it is desirable to define primary and auxiliary sensors based on the applied ZF. If the ZF is such that the output FOV is larger than the Tele FOV, the primary sensor is the Wide sensor and the auxiliary sensor is the Tele sensor. If the ZF is such that the output FOV is equal to, or smaller than the Tele FOV, the primary sensor is the Tele sensor and the auxiliary sensor is the Wide sensor. The point of view defined by the output image is that of the primary sensor.

FIG. 2 shows schematically an embodiment of a Wide sensor 200 that may be implemented in a DAZI system such as system 100. Sensor 200 has a non-overlap area 202 with a Bayer CFA and an overlap area 204 covered by a non-standard CFA with a repetition of a 4×4 micro-cell in which the color filter order is BBRR-RBBR-RRBB-BRRB. In this figure, as well as in FIGS. 3-9, “Width 1” and “Height 1” refer to the full Wide sensor dimension. “Width 2” and “Height 2” refer to the dimensions of the Wide sensor overlap area. Note that in FIG. 2 (as in following FIGS. 3-5 and 7, 8) the empty row and column to the left and top of the overlap area are for clarity purposes only, and that the sensor pixels follow there the pattern of the non-overlap area (as shown in FIG. 6). In overlap area 204, R and B are sampled at $\frac{1}{2}^{0.5}$ Nyquist frequency in the diagonal (left to right) direction with 2 pixel intervals instead of at $\frac{1}{2}$ Nyquist frequency in a standard Bayer pattern.

7

FIG. 3 shows schematically an embodiment of a Wide sensor 300 that may be implemented in a DAZI system such as system 100. Sensor 300 has a non-overlap area 302 with a Bayer CFA and an overlap area 304 covered by a non-standard CFA with a repetition of a 2x2 micro-cell in which the color filter order is BR-RB. In the overlap area, R and B are sampled at $\frac{1}{2}^{0.5}$ Nyquist frequency in both diagonal directions.

FIG. 4 shows schematically an embodiment of a Wide sensor 400 that may be implemented in a DAZI system such as system 100. Sensor 400 has a non-overlap area 402 with a Bayer CFA and an overlap area 404 covered by a non-standard CFA with a repetition of a 2x2 micro-cell in which the color filter order is YC-CY, where Y=Yellow=Green+Red, C=Cyan=Green+Blue. As a result, in the overlap area, R and B are sampled at $\frac{1}{2}^{0.5}$ Nyquist frequency in a diagonal direction. The non-standard CFA includes green information for registration purposes. This allows for example registration between the two images where the object is green, since there is green information in both sensor images.

FIG. 5 shows schematically an embodiment of a Wide sensor 500 that may be implemented in a DAZI system such as system 100. Sensor 500 has a non-overlap area 502 with a Bayer CFA and an overlap area 504 covered by a non-standard CFA with a repetition of a 6x6 micro-cell in which the color filter order is RBBRRB-RWRBWB-BBRBRR-RRBRBB-BWBRWR-BRRBBR, where "W" represents White or Clear pixels. In the overlap area, R and B are sampled at a higher frequency than in a standard CFA. For example, in a Bayer pixel order, the Red average sampling rate ("R_s") is 0.25 (sampled once for every 4 pixels). In the overlap area pattern, R_s is 0.44.

FIG. 6 shows schematically an embodiment of a Wide sensor 600 that may be implemented in a DAZI system such as system 100. Sensor 600 has a non-overlap area 602 with a Bayer CFA and an overlap area 604 covered by a non-standard CFA with a repetition of a 6x6 micro-cell in which the color filter order is BBGRRG-RGRBGB-GBRGRB-RRBBG-BGBRGR-GRBGBR. In the overlap area, R and B are sampled at a higher frequency than in a standard CFA. For example, in the overlap area pattern, R_s is 0.33 vs. 0.25 in a Bayer pixel order.

FIG. 7 shows schematically an embodiment of a Wide sensor 700 that may be implemented in a DAZI system such as system 100. Sensor 700 has a non-overlap area 702 with a Bayer CFA and an overlap area 704 covered by a non-standard CFA with a repetition of a 3x3 micro-cell in which the color filter order is GBR-RGB-BRG. In the overlap area, R and B are sampled at a higher frequency than in a standard CFA. For example, in the overlap area pattern, R_s is 0.33 vs. 0.25 in a Bayer pixel order.

FIG. 8 shows schematically an embodiment of a Wide sensor 800 that may be implemented in a DAZI system such as system 100. Sensor 800 has a non-overlap area 802 with a Bayer CFA and an overlap area 804 covered by a non-standard CFA with a repetition of a 6x6 micro-cell in which the color filter order is RBBRRB-RGRBGB-BBRBRR-RRBRBB-BGBRGR-BRRBBR. In the overlap area, R and B are sampled at a higher frequency than in a standard CFA. For example, in the overlap area pattern, R_s is 0.44 vs. 0.25 in a Bayer pixel order.

FIG. 9 shows schematically an embodiment of a Wide sensor 900 that may be implemented in a DAZI system such as system 100. Sensor 900 has a non-overlap area 902 with a Bayer CFA and an overlap area 904 covered by a non-standard CFA with a repetition of a 6x6 micro-cell in which the color filter order is RBRBRB-BGBRGR-RBRBRB-

8

BRBRBR-RGRBGB-BRBRBR. In the overlap area, R and B are sampled at a higher frequency than in a standard CFA. For example, in the overlap area pattern, R_s is 0.44 vs. 0.25 in a Bayer pixel order.

5 Processing Flow

In use, an image is acquired with imaging system 100 and is processed according to steps illustrated in a flowchart shown in FIG. 10. In step 1000, demosaicing is performed on the Wide overlap area pixels (which refer to the Tele image FOV) according to the specific CFA pattern. If the CFA in the Wide overlap area is a standard CFA, a standard demosaicing process may be applied to it. If the CFA in the Wide overlap area is non-standard CFA, the overlap and non-overlap subsets of pixels may need different demosaicing processes. That is, the Wide overlap area may need a non-standard demosaicing process and the Wide non-overlap area may need a standard demosaicing process. Exemplary and non-limiting non-standard demosaicing interpolations for the overlap area of each of the Wide sensors shown in FIGS. 2-9 are given in detail below. The aim of the demosaicing is to reconstruct missing colors in each pixel. Demosaicing is applied also to the Tele sensor pixels if the Tele sensor is not a Clear only sensor. This will result in a Wide subset color image where the colors (in the overlap area) hold higher resolution than those of a standard CFA pattern. In step 1002, the Tele image is registered (mapped) into the Wide image. The mapping includes finding correspondences between pixels in the two images. In step 1002, actual registration is performed on luminance Tele and Wide images (respectively Luma_{Tele} and Luma_{Wide}) calculated from the pixel information of the Tele and Wide cameras. These luminance images are estimates for the scene luminance as captured by each camera and do not include any color information. If the Wide or Tele sensors have CFAs, the calculation of the luminance images is performed on the respective demosaiced images. The calculation of the Wide luminance image varies according to the type of non-standard CFA used in the Wide overlap area. If the CFA permits calculation of a full RGB demosaiced image, the luminance image calculation is straightforward. If the CFA is such that it does not permit calculation of a full RGB demosaiced image, the luminance image is estimated from the available color channels. If the Tele sensor is a Clear sensor, the Tele luminance image is just the pixel information. Performing the registration on luminance images has the advantage of enabling registration between images captured by sensors with different CFAs or between images captured by a standard CFA or non-standard CFA sensor and a standard CFA or Clear sensor and avoiding color artifacts that may arise from erroneous registration.

In step 1004, the data from the Wide and Tele images is processed together with the registration information from step 1002 to form a high quality output zoom image. In cases where the Tele sensor is a Clear only sensor, the high resolution luminance component is taken from the Tele sensor and color resolution is taken from the Wide sensor. In cases where the Tele sensor includes a CFA, both color and luminance data are taken from the Tele subset to form the high quality zoom image. In addition, color and luminance data is taken from the Wide subset.

Exemplary Process for Fusing a Zoom Image

1. Special Demosaicing

In this step, the Wide image is interpolated to reconstruct the missing pixel values. Standard demosaicing is applied in the non-overlap area. If the overlap area includes a standard CFA, standard demosaicing is applied there as well. If the overlap area includes a non-standard CFA, a special demo-

saicing algorithm is applied, depending on the CFA pattern used. In addition, in case the Tele sensor has a CFA, standard demosaicing is applied to reconstruct the missing pixel values in each pixel location and to generate a full RGB color image.

2. Registration Preparation

Tele image: a luminance image $Luma_{Tele}$ is calculated from the Tele sensor pixels. If the Tele subset has a Clear sensor, $Luma_{Tele}$ is simply the sensor pixels data. If the Tele subset has a standard CFA, $Luma_{Tele}$ is calculated from the demosaiced Tele image.

Wide image: as a first step, in case the Wide overlap CFA permits estimating the luminance component of the image, the luminance component is calculated from the demosaiced Wide image, $Luma_{Wide}$. If the CFA is one of those depicted in FIGS. 4-9, a luminance image is calculated first. If the CFA is one of the CFAs depicted in FIG. 2 or FIG. 3, a luminance image is not calculated. Instead, the following registration step is performed between a weighted average of the demosaiced channels of the Wide image and $Luma_{Tele}$. For convenience, this weighted average image is also denoted $Luma_{Wide}$. For example, if the Wide sensor CFA in the overlap region is as shown in FIG. 2, the demosaiced channels R_{Wide} and B_{Wide} are averaged to create $Luma_{Wide}$ according to $Luma_{Wide} = (f1 * R_{Wide} + f2 * B_{Wide}) / (f1 + f2)$, where $f1$ may be $f1=1$ and $f2$ may be $f2=1$.

Low-pass filtering is applied on the Tele luminance image in order to match its spatial frequency content to that of the $Luma_{Wide}$ image. This improves the registration performance, as after low-pass filtering the luminance images become more similar. The calculation is $Luma_{Tele} \rightarrow \text{Low pass filter} \rightarrow Luma_{Tele}^{LP}$, where "LP" denotes an image after low pass filtering.

3. Registration of $Luma_{Wide}$ and $Luma_{Tele}^{LP}$

This step of the algorithm calculates the mapping between the overlap areas in the two luminance images. The registration step does not depend on the type of CFA used (or the lack thereof), as it is applied on luminance images. The same registration step can therefore be applied on Wide and Tele images captured by standard CFA sensors, as well as by any combination of CFAs or Clear sensor pixels disclosed herein. The registration process chooses either the Wide image or the Tele image to be a primary image. The other image is defined as an auxiliary image. The registration process considers the primary image as the baseline image and registers the overlap area in the auxiliary image to it, by finding for each pixel in the overlap area of the primary image its corresponding pixel in the auxiliary image. The output image point of view is determined according to the primary image point of view (camera angle). Various correspondence metrics could be used for this purpose, among which are a sum of absolute differences and correlation.

In an embodiment, the choice of the Wide image or the Tele image as the primary and auxiliary images is based on the ZF chosen for the output image. If the chosen ZF is larger than the ratio between the focal-lengths of the Tele and Wide cameras, the Tele image is set to be the primary image and the Wide image is set to be the auxiliary image. If the chosen ZF is smaller than or equal to the ratio between the focal-lengths of the Tele and Wide cameras, the Wide image is set to be the primary image and the Tele image is set to be the auxiliary image. In another embodiment independent of a zoom factor, the Wide image is always the primary image and the Tele image is always the auxiliary

image. The output of the registration stage is a map relating Wide image pixels indices to matching Tele image pixels indices.

4. Combination into a High Resolution Image

In this final step, the primary and auxiliary images are used to produce a high resolution image. One can distinguish between several cases:

a. If the Wide image is the primary image, and the Tele image was generated from a Clear sensor, $Luma_{Wide}$ is calculated and replaced or averaged with $Luma_{Tele}$ in the overlap area between the two images to create a luminance output image, matching corresponding pixels according to the registration map $Luma_{Out} = c1 * Luma_{Wide} + c2 * Luma_{Tele}$. The values of $c1$ and $c2$ may change between different pixels in the image. Then, RGB values of the output are calculated from $Luma_{Out}$ and R_{Wide} , G_{Wide} , and B_{Wide} .

b. If the Wide image is the primary image and the Tele image was generated from a CFA sensor, $Luma_{Tele}$ is calculated and is combined with $Luma_{Wide}$ in the overlap area between the two images, according to the flow described in 4a.

c. If the Tele image is the primary image generated from a Clear sensor, the RGB values of the output are calculated from the $Luma_{Tele}$ image and R_{Wide} , G_{Wide} , and B_{Wide} (matching pixels according to the registration map).

d. If the Tele image is the primary image generated from a CFA sensor, the RGB values of the output (matching pixels according to the registration map) are calculated either by using only the Tele image data, or by also combining data from the Wide image. The choice depends on the zoom factor.

Certain portions of the registered Wide and Tele images are used to generate the output image based on the ZF of the output image. In an embodiment, if the ZF of the output image defines a FOV smaller than the Tele FOV, the fused high resolution image is cropped to the required field of view and digital interpolation is applied to scale up the image to the required output image resolution.

Exemplary and Non-Limiting Pixel Interpolations Specifications for the Overlap Area
FIG. 2

B11	B12	R13
R21	B22	B23
R31	R32	B33

In order to reconstruct the missing R22 pixel, we perform $R22 = (R31 + R13) / 2$. The same operation is performed for all missing Blue pixels.

FIG. 3

R11	B12	R13
B21	R22	B23
R31	B32	R33

In order to reconstruct the missing B22 pixel, we perform $B22 = (B12 + B21 + B32 + B23) / 4$. The same operation is performed for all missing Red pixels.

FIG. 4

Y11	C12	Y13
C21	Y22	C23
Y31	C32	Y33

11

In order to reconstruct the missing C22 pixel, we perform $C22=(C12+C21+C32+C23)/4$. The same operation is performed for all missing Yellow pixels.

FIG. 5

Case 1: W is Center Pixel

R11	B12	B13
R21	W22	R23
B31	B32	R33

In order to reconstruct the missing 22 pixels, we perform the following:

$$B22=(B12+B32)/2$$

$$R22=(R21+R23)/2$$

$G22=(W22-R22-B22)$ (assuming that W includes the same amount of R, G and B colors).

Case 2: R22 is Center Pixel

B11	B12	R13	R14
W21	R22	B23	W24
B31	R32	B33	R34

$$B22=(B11+R33)/2$$

In order to reconstruct the missing 22 pixels, we perform the following:

$$W22=(2*W21+W24)/3$$

$G22=(W22-R22-B22)$ (assuming that W contains the same amount of R, G and B colors). The same operation is performed for Blue as the center pixel.

FIG. 6

B11	B12	G13	R14
R21	G22	R23	B24
G31	B32	R33	G34
R41	R42	G43	B44

In order to reconstruct the missing 22 pixels, we perform the following:

$$B22=(B12+B32)/2$$

$$R22=(R21+R23)/2$$

In order to reconstruct the missing 32 pixels, we perform the following:

$$G32=(2*G31+2*G22+G43)/5$$

$$R32=(R41+2*R42+2*R33+R23+R21)/7$$

FIG. 7

G11	B12	R13	G14
R21	G22	B23	R24
B31	R32	G33	B34
G41	B42	R43	G44

In order to reconstruct the missing 22 pixels, we perform the following:

$$B22=(2*B12+2*B23+B31)/5$$

$$R22=(2*R21+2*R32+R13)/5$$

and similarly for all other missing pixels.

FIG. 8

R11	B12	B13	R14
R21	G22	R23	B24
B31	B32	R33	B34

12

-continued

R41	R42	B43	R44
B51	G52	B53	R54

5

In order to reconstruct the missing 22 pixels, we perform the following:

$$B22=(2*B12+2*B32+B13)/5$$

$$R22=(2*R21+2*R23+R11)/5$$

10

In order to reconstruct the missing 32 pixels, we perform the following:

$$G32=(2*G22+G52)/3$$

$$R32=(2*R33+2*R42+R41+R21+R23)/7$$

FIG. 9

15

R11	B12	R13	B14
B21	G22	B23	R24
R31	B32	R33	B34
B41	R42	B43	R44
R51	G52	R53	B54

20

In order to reconstruct the missing 22 pixels, we perform the following:

$$B22=(B12+B32+B23+B21)/4$$

$$R22=(R11+R13+R31+R33)/4$$

25

In order to reconstruct the missing 32 pixels, we perform the following:

$$G32=(2*G22+G52)/3$$

$$R32=(R42+R31+R33)/3$$

30

Triple-Aperture Zoom Imaging System with Improved Color Resolution

As mentioned, a multi-aperture zoom or non-zoom imaging system disclosed herein may include more than two apertures. A non-limiting and exemplary embodiment 1100 of a triple-aperture imaging system is shown in FIGS.

35

11A-11B. System 1100 includes a first Wide subset camera 1102 (with exemplarily X1), a second Wide subset camera (with exemplarily X1.5, and referred to as a "Wide-Tele" subset) and a Tele subset camera (with exemplarily X2).

FIG. 11A shows exemplary images captured by imaging system 1100, while FIG. 11B illustrates schematically three sensors marked 1102, 1104 and 1106, which belong respectively to the Wide, Wide-Tele and Tele subsets. FIG. 11B

40

also shows the CFA arrangements in each sensor: sensors 1102 and 1104 are similar to Wide sensors described above with reference to any of FIGS. 2-9, in the sense that they include an overlap area and a non-overlap area. The overlap area includes a non-standard CFA. In both Wide sensors, the non-overlap area may have a Clear pattern or a standard CFA. Thus, neither Wide subset is solely a Clear channel camera. The Tele sensor may be Clear or have a standard Bayer CFA or a standard non-Bayer CFA. In use, an image is acquired with imaging system 1100 and processed as follows: demosaicing is performed on the overlap area pixels of the Wide and Wide-Tele sensors according to the specific CFA pattern in each overlap area. The overlap and non-overlap subsets of pixels in each of these sensors may need different demosaicing. Exemplary and non-limiting demosaicing specifications for the overlap area for Wide sensors shown in FIGS. 2-9 are given above. The aim is to reconstruct the missing colors in each and every pixel. In cases in which the Tele subset sensor is not Clear only, demosaicing is performed as well. The Wide and Wide-Tele subset color images acquired this way will have colors (in the overlap area) holding higher resolution than that of a standard CFA pattern. Then, the Tele image acquired with the Tele sensor is registered (mapped) into the respective Wide image. The data from the Wide, Wide-Tele and Tele

45

50

55

60

65

13

images is then processed to form a high quality zoom image. In cases where the Tele subset is Clear only, high Luma resolution is taken from the Tele sensor and color resolution is taken from the Wide sensor. In cases where the Tele subset includes a CFA, both color and Luma resolution is taken from the Tele subset. In addition, color resolution is taken from the Wide sensor. The resolution of the fused image may be higher than the resolution of both sensors.

While this disclosure has been described in terms of certain embodiments and generally associated methods, alterations and permutations of the embodiments and methods will be apparent to those skilled in the art. For example, multi-aperture imaging systems with more than two Wide or Wide-Tele subsets (and sensors) or with more than one Tele subset (and sensor) may be constructed and used according to principles set forth herein. Similarly, non-zoom multi-aperture imaging systems with more than two sensors, at least one of which has a non-standard CFA, may be constructed and used according to principles set forth herein. The disclosure is to be understood as not limited by the specific embodiments described herein, but only by the scope of the appended claims.

What is claimed is:

1. A multi-aperture imaging system comprising:

- a) a first camera that provides a first camera image, the first camera having a first sensor with a first plurality of sensor pixels covered at least in part with a [non-standard] first color filter array (CFA) used to increase a specific color sampling rate relative to a same color sampling rate in a standard CFA, wherein the [non-standard] first CFA includes a repetition of a $n \times n$ micro-cell where $n=4$ and wherein each micro-cell includes a BBRR-RBBR-RRBB-BRRB color filter order;
- b) a second camera that provides a second camera image, the second camera having a second sensor with a second plurality of sensor pixels, the second plurality of sensor pixels being either Clear or covered with a [standard] second CFA, wherein the second camera image has an overlap area with the first camera image, wherein the second CFA is one of RGB (Bayer), RGBE, CYYM, CYGM, RGBW#1, RGBW#2 or RGBW#3; and
- c) a processor configured to process the first and second camera images into a fused output image, wherein in the overlap area pixels of the second camera image are registered with corresponding pixels of the first camera image.

2. A multi-aperture imaging system comprising:

- a) a first camera that provides a first camera image, the first camera having a first sensor with a first plurality of sensor pixels covered at least in part with a [non-standard] first color filter array (CFA) used to increase a specific color sampling rate relative to a same color sampling rate in a standard CFA, wherein the [non-standard] first CFA includes a repetition of a $n \times n$ micro-cell where $n=6$ and wherein each micro-cell includes a color filter order selected from the group consisting of RBBRRB-RWRBWB-BBRBRR-RRBRBB-BWBRWR-BRRBBR, BBGRRG-RGRBGB-GBRGRB-RRGBBG-BGBRGR-GRBGBR, RBBRRB-RGRBGB-BBRBRR-RRBRBB-BGBRGR-BRRBBR and RBRBRB-BGBRGR-RBRBRB-BRBRBR-RGRBGB-BRBRBR;
- b) a second camera that provides a second camera image, the second camera having a second sensor with a second plurality of sensor pixels, the second plurality of sensor pixels being either Clear or covered with a

14

[standard] second CFA, wherein the second camera image has an overlap area with the first camera image, wherein the second CFA is one of RGB (Bayer), RGBE, CYYM, CYGM, RGBW#1, RGBW#2 or RGBW#3; and

- c) a processor configured to process the first and second camera images into a fused output image, wherein in the overlap area pixels of the second camera image are registered with corresponding pixels of the first camera image.

3. The multi-aperture imaging system of claim 1, wherein the first camera is a Wide camera with a field of view FOV_w and wherein the second camera is a Tele camera with a field of view FOV_T smaller than FOV_w .

4. A method of acquiring images by a multi-aperture imaging system, the method comprising:

- a) providing a first image generated by a first camera of the imaging system, the first camera having a first field of view (FOV_1);
- b) providing a second image generated by a second camera of the imaging system, the second camera having a second field of view (FOV_2) such that $FOV_2 < FOV_1$, the second image having an overlap area with the first image; and
- c) fusing the first and second images into a fused image, wherein the fusing includes applying a registration process between the first and second images, the registration process including:
 - i. extracting a first Luma image from the first image
 - ii. extracting a second Luma image from the second image,
 - iii. applying low-pass filtering on the second Luma image in order to match its spatial frequency content to that of the first Luma image and to generate a low-pass second Luma image, and
 - iv. applying registration on the low-pass second Luma image and the first Luma image,

wherein [the non-standard] a CFA includes a repetition of a $n \times n$ micro-cell where $n=4$ and wherein each micro-cell includes a BBRR-RBBR-RRBB-BRRB color filter order.

5. The method of claim 4, wherein $n=6$ instead of $n=4$ and wherein instead of each micro-cell including a BBRR-RBBR-RRBB-BRRB color filter order, each micro-cell includes a color filter order selected from the group consisting of RBBRRB-RWRBWB-BBRBRR-RRBRBB-BWBRWR-BRRBBR, BBGRRG-RGRBGB-GBRGRB-RRGBBG-BGBRGR-GRBGBR, RBBRRB-RGRBGB-BBRBRR-RRBRBB-BGBRGR-BRRBBR and RBRBRB-BGBRGR-RBRBRB-BRBRBR-RGRBGB-BRBRBR.

6. A multi-aperture imaging system comprising:

- a) a first camera that provides a first image, the first camera having a first field of view (FOV_1) and a first sensor with a first color filter array; and
- b) a second camera that provides a second image, the second camera having a second field of view (FOV_2) such that $FOV_2 < FOV_1$ and a second sensor with a second color filter array different from the first color filter array;

wherein the first color filter array has a first red color pixel and a second red color pixel adjacent to the first red color pixel, and a first blue color pixel and a second blue color pixel adjacent to the first blue color pixel.

7. The multi-aperture imaging system of claim 6, wherein the first red color pixel is disposed adjacent to the first blue color pixel in a diagonal direction.

15

8. The multi-aperture imaging system of claim 7, wherein the second color filter array is one of an RGB (Bayer), RGBE, CYYM, CYGM, RGBW#1, RGBW#2 or RGBW#3 color filter array.

9. The multi-aperture imaging system of claim 7, wherein the first color filter array is one of an RGBE, CYYM, CYGM, RGBW#1, RGBW#2 or RGBW#3 color filter array.

10. The multi-aperture imaging system of claim 9, wherein the first color filter array has a first 2x2 pixel group with three blue color pixels and a fourth pixel that is not a blue color pixel.

11. The multi-aperture imaging system of claim 10, wherein the first color filter array has a second 2x2 pixel group with three red color pixels and a fourth pixel that is not a red color pixel.

12. A multi-aperture imaging system comprising:

a) a first camera that provides a first image, the first camera having a first sensor with a first color filter array; and

b) a second camera that provides a second image, the second camera having a second sensor with a second color filter array different from the first color filter array,

wherein the first color filter array has a first red color pixel group comprising a first red color pixel and a second red color pixel adjacent to the first red color pixel in a first direction, and a first blue color pixel group comprising a first blue color pixel and a second blue color pixel adjacent to the first blue color pixel in a second direction perpendicular to the first direction.

13. The multi-aperture imaging system of claim 12, wherein the first camera has a first field of view (FOV_1) and wherein the second camera has a second field of view (FOV_2) such that $FOV_2 < FOV_1$.

14. The multi-aperture imaging system of claim 12, wherein the first red color pixel is disposed adjacent to the first blue color pixel in a diagonal direction.

15. The multi-aperture imaging system of claim 12, wherein the first color filter array has a first 2x2 pixel group with three blue color pixels and a fourth pixel that is not a blue pixel.

16

16. The multi-aperture imaging system of claim 12, wherein the first color filter array has a second 2x2 pixel group with three red color pixels and a fourth pixel that is not a red color pixel.

17. The multi-aperture imaging system of claim 12, wherein the first color filter array is a non-Bayer color filter array.

18. The multi-aperture imaging system of claim 17, wherein the second color filter array is a standard color filter array.

19. The multi-aperture imaging system of claim 12, wherein the first color filter array has a first red and green color pixel group with a first red color pixel and a first green color pixel adjacent to the first red color pixel in the first direction.

20. A multi-aperture imaging system comprising:

a) a first camera that provides a first image, the first camera having a sensor with a first color filter array and a first resolution; and

b) a second camera that provides a second image, the second camera having a second sensor with a second color filter array and a second resolution,

wherein the first color filter array has a first red color pixel and a second red color pixel adjacent to the first red color pixel, and wherein the output image has a third resolution higher than the first resolution.

21. The multi-aperture imaging system of claim 20, wherein the first sensor has a first blue color pixel group with a first blue color pixel and a second blue color pixel adjacent to the first blue color pixel.

22. The multi-aperture imaging system of claim 21, wherein the first red color pixel is disposed adjacent to the first blue color pixel in a diagonal direction.

23. The multi-aperture imaging system of claim 22, wherein the first camera has a first field of view (FOV_1) and the second camera has a second field of view (FOV_2) different from FOV_1 .

24. The multi-aperture imaging system of claim 23, wherein the FOV_1 is greater than the FOV_2 .

* * * * *